

MI981

**Intel® Q87 Based Mini-ITX board
Mini ITX Motherboard**

USER'S MANUAL

Version 1.0

Acknowledgments

AMI is a registered trademark of American Megatrends Inc.

PS/2 is a trademark of International Business Machines Corporation.

Intel and Intel® 4th Generation Core DC/QC Processor are registered trademarks of Intel Corporation.

Microsoft Windows is a registered trademark of Microsoft Corporation.

Fintek is a registered trademark of Fintek Electronics Corporation.

All other product names or trademarks are properties of their respective owners.

Table of Contents

Introduction	1
Product Description.....	1
Checklist.....	1
MI981 Specifications	2
Board Dimensions	4
Installations	5
Installing the Memory	6
Setting the Jumpers	7
Connectors on MI981	12
BIOS Setup	25
Drivers Installation	51
Intel Chipset Software Installation Utility	52
VGA Drivers Installation	53
Realtek HD Audio Driver Installation	54
LAN Drivers Installation.....	55
Intel® Management Engine Interface	56
Intel® USB 3.0 Drivers.....	57
Appendix.....	59
A. I/O Port Address Map	59
B. Interrupt Request Lines (IRQ).....	60
C. Watchdog Timer Configuration	61

This page is intentionally left blank.

Introduction

Product Description

The MI981 Mini ITX motherboard is based on the latest Intel® Q87 chipset. The platform supports Intel® 4th Generation Core™ DT i7/i5/i3 processors. The latest Intel® processors provide advanced performance in both computing and graphics quality. This meets the requirement of customers in the gaming, POS, digital signage and server market segment.

The platform supports two SO-DIMM sockets that can accommodate up to 16GB of DDR3-1600 Non ECC memory. The Intel® 4th Gen. Core™ DT processor integrated HD graphics supports 3 independent displays, Direct X 11.1, OpenGL 3.2, and Open CL 1.2. Display interfaces are for HDMI, DisplayPort and VGA CRT.

With two Gigabit Ethernet, the MI981 Mini ITX board utilizes the dramatic increase in performance provided Intel's latest cutting-edge technology. Expansion is provided by PCIe(16x), one full sized MiniPCIe and a half sized MiniPCIe. Onboard connectors support 4x SATA III, 4x or 6x USB 2.0 depending on the MI981 model and 6x COM ports. The board measures 170mm x 170mm.

Checklist

Your MI981 package should include the items listed below.


- The MI981 MINI ITX motherboard
- This User's Manual
- 1 CD containing chipset drivers and flash memory utility

MI981 Specifications

Model Name	MI981AF
Form Factor	Mini ITX
CPU Type	- Haswell Refresh 4th Generation Intel® Core™ i7/i5/i3/Pentium DT processor & FCLGA1150 package [37.5 mm x 37.5mm] - TDP: 35W ~ 84W
CPU Speed	Up to 4.0GHz
Cache Size	Up to 8MB
CPU Socket	LGA1150 (Socket H3)
Chipset	Intel® Q87 PCH Package =23 mm x 22 mm, 0.65 mm ball pitch
BIOS	AMI BIOS
Memory	Haswell Refresh 4th Generation Intel® Core™ DT processors integrated memory controller, - DDR3-1600 MHz@1.5V - SO-DIMM x 2, Max. 16GB (Non-ECC)
VGA	Haswell Refresh 4 th Generation Intel® DT processor integrated HD Gfx, supports 3 independent displays, Direct X 11.1, OpenGL 3.2, Open CL 1.2 - DVI-D x 1 (Thru port C, with level shifter ASM1442K) - DisplayPort x 1 (Thru port D) - LVDS (Thru port B, via NXP PTN3460) - VGA x 1 (Thru PCH)
LAN	1. Intel® I217LM PHY GbE 2. Intel® I211AT PCIe GbE as 2 nd LAN
USB	USB 2.0 host controller [Q87 Integrated], supports 8 ports - 6 ports via onboard pin header - 2 ports via MiniPCIe socket USB 3.0 host controller [Q87 Integrated], supports 6 ports - 6 ports via the rear panel I/O
Serial ATA	Intel® Q87 PCH built-in SATA controller, supports 4x SATA 3.0 (6Gbps)
Storage Device	mSATA x 1 thru Mini-PCIe slot [full-sized]
Audio	Intel® Q87 PCH built-in High Definition Audio controller + Realtek ALC892 w/ 7.1 channels
LPC I/O	Fintek F81866AD-1 (128-pin LQFP [14mm x 14 mm]) - COM #1 (RS232/422/485) support ring-in with power @500 mA (selectable for 5V or 12V) [EXAR SP339EER1 232/422/485 transceiver x 1 for jumper-less] - COM #2 (RS232 only), support ring-in with power @500 mA (selectable for 5V or 12V) - COM #3~COM #6 (RS232 only) Hardware Monitor (2 thermal inputs, 4 voltage monitor inputs & 2 Fan headers) - CPU FAN x 1(PWN Fan type, 4-pin connector) SYS fan x 1(PWM Fan type, 4-pin connector)]
Digital IO	4 in & 4 out
IAMT 9.1	Intel® Active Management Technology ver. 9.1
TPM 1.2	Infineon SLB9655

Expansion Slots	- PCI-Express (16x) x1 [Gen 3.0 PEG] - Mini PCI-Express x 2 port [1 x Full-sized, 1 x Half-sized] , both support USB 2.0 signal / supports mSATA thru full-size mini PCIe slot
Edge Connectors	Dual DB9 stack connector for COM #1 / #2 VGA + DVI-D stack connector x1 DisplayPort + dual USB (3.0) stack connector x1 RJ-45 + dual USB (3.0) stack connector x2 Triplet type Jack 3x1 for Audio port [Line-in / Line-out / Mic-in]
Onboard Header/Connector	4 ports x SATA III [Blue color] DF-11 2x4 header x 3 for 6 ports USB 2.0 DF-11 2x5 box header x 4 for COM2/3/4 (RS232 only) DF-20 20-pin connector x 2 for Dual channel LVDS 1x4 box header for LCD backlight control 2x5 header for Digital IO 2x5 header for front Audio 2x4 header for front panel I/O (2.54 pitch) 2x2 pin ATX power connector x1 1x ATX standard 24-pin type for power connector
Watchdog Timer	Yes (256 segments, 0, 1, 2...255 sec/min)
System Voltage	ATX standard 24-pins type 4 pin type (+12V only)
Other	- LAN Wakeup - iSMART 3.0
Environment	Operation Temperature: 0~60 degree C Storage Temperature: -20~80 degree C Relative humidity: 0~90%, non-condensing
Board Size	170mm x 170mm
Operation System	Windows 7, Windows 8, Linux

Board Dimensions



Installations

This section provides information on how to use the jumpers and connectors on the MI981 in order to set up a workable system. The topics covered are:

Installing the Memory	6
Setting the Jumpers	7
Connectors on MI981	12


Installing the Memory

The MI981 board supports two DDR3 memory modules for a maximum total of 16GB in DDR3 SODIMM memory type.

Installing and Removing Memory Modules

To install the DDR3 modules, locate the memory slot on the board and perform the following steps:

1. Hold the DDR3 module so that the key of the DDR3 module aligned with that on the memory slot.
2. Gently push the DDR3 module in an upright position until the clips of the slot close to hold the DDR3 module in place when the DDR3 module touches the bottom of the slot.
3. To remove the DDR3 module, press the clips with both hands.




Setting the Jumpers


Jumpers are used on MI981 to select various settings and features according to your needs and applications. Contact your supplier if you have doubts about the best configuration for your needs. The following lists the connectors on MI981 and their respective functions.


Jumper Locations on MI981	8
JP1: COM2 RS232 RI/+5V/+12V Power Setting.....	9
JP2: COM1 RS232 RI/+5V/+12V Power Setting.....	9
JP3: LVDS Panel Power Selection	10
JP4: Power Good Selection	10
JP5: Flash Descriptor Security Override (Factory use only).....	11
JBAT1: Clear CMOS Contents.....	11


Jumper Locations on MI981




Jumpers on MI981	Page
JP1: COM2 RS232 RI/+5V/+12V Power Setting	9
JP2: COM1 RS232 RI/+5V/+12V Power Setting	9
JP3: LVDS Panel Power Selection	10
JP4: Power Good Selection	10
JP5: Flash Descriptor Security Override (Factory use only)	11
JBAT1: Clear CMOS Contents	11


JP1: COM2 RS232 RI/+5V/+12V Power Setting




JP1	Setting	Function
	Pin 1-3 Short/Closed	+12V
	Pin 3-4 Short/Closed	RI
	Pin 3-5 Short/Closed	+5V

JP2: COM1 RS232 RI/+5V/+12V Power Setting



JP2	Setting	Function
	Pin 1-3 Short/Closed	+12V
	Pin 3-4 Short/Closed	RI
	Pin 3-5 Short/Closed	+5V

JP3: LVDS Panel Power Selection




JP3	Setting	Panel Voltage
	Pin 1-2 Short/Closed	3.3V (default)
	Pin 2-3 Short/Closed	5V

JP4: Power Good Selection




JP4	Function
Short	Factory use only
Open	Normal



JP5: Flash Descriptor Security Override (Factory use only)



JP5	Flash Descriptor Security Override
Open	Disabled (Default)
Close	Enabled

JBAT1: Clear CMOS Contents



JBAT1	Setting	Function
 1 2 3	Pin 1-2 Short/Closed	Normal
 1 2 3	Pin 2-3 Short/Closed	Clear CMOS


Connectors on MI981

Connector Locations on MI981	13
CN1: COM1 and COM2 Serial Ports.....	14
CN2: VGA and DVI-D Connector.....	14
CN3: USB3.0 Connector	15
CN4: DP Connector	15
CN5: Gigabit LAN (Intel I217LM) / USB3.0.....	15
CN6, CN7, CN8, CN9: SATA Connectors	15
CN10: Gigabit LAN (Intel I211AT) / USB3.0	15
CN11: HD Audio Connector.....	15
J1: ATX 12V Power Connector	16
J4: ATX Power Supply Connector.....	16
J5, J6: LVDS Connectors.....	17
J7: Digital I/O	17
J8: LCD Backlight Connector	18
J9: Mini PCIE/mSATA Connector	18
J10: Mini PCIE Connector	18
J11: SPI Flash Connector (Factory use only).....	19
J12: MCU Flash Connector (factory use only).....	19
J13: Debug 80 Port Connector (factory use only).....	19
J14: Front Panel Function Connector.....	20
J15, J16, J17, J18: COM3/COM4/COM5/COM6 Connector	21
J19, J20, J21: USB Connectors.....	21
J22: Audio Front Header.....	22
PCIE1: PCI-E X16 Slot	22
CPU_FAN1: CPU Fan Power Connector	23
SYS_FAN1: System Fan1 Power Connector	23




INSTALLATIONS

CN1: COM1 and COM2 Serial Ports




Pin #	Signal Name		
	RS-232	R2-422	RS-485
1	DCD	TX-	DATA-
2	RX	TX+	DATA+
3	TX	RX+	NC
4	DTR	RX-	NC
5	Ground	Ground	Ground
6	DSR	NC	NC
7	RTS	NC	NC
8	CTS	NC	NC
9	RI	NC	NC
10	NC	NC	NC

CN2: VGA and DVI-D Connector



Signal Name	Pin #	Pin #	Signal Name
Red	1	2	Green
Blue	3	4	N.C.
GND	5	6	GND
GND	7	8	GND
N.C.	9	10	GND
N.C.	11	12	DDCDATA
HSYNC	13	14	VSYNC
DDCCLK	15		



Signal Name	Pin #	Pin #	Signal Name
DATA 2-	1	16	HOT POWER
DATA 2+	2	17	DATA 0-
GROUND	3	18	DATA 0+
N.C.	4	19	GROUND
N.C.	5	20	N.C.
DDC CLOCK	6	21	N.C.
DDC DATA	7	22	GROUND
N.C	8	23	CLOCK +
DATA 1-	9	24	CLOCK -
DATA 1+	10		
GROUND	11		
N.C.	12		
N.C.	13		
DDC POWER	14		
GROUND	15		

CN3: USB3.0 Connector

CN4: DP Connector


CN5: Gigabit LAN (Intel I217LM) / USB3.0

CN6, CN7, CN8, CN9: SATA Connectors

CN10: Gigabit LAN (Intel I211AT) / USB3.0


CN11: HD Audio Connector

J1: ATX 12V Power Connector




Pin #	Signal Name
1	Ground
2	Ground
3	+12V
4	+12V


J4: ATX Power Supply Connector



Signal Name	Pin #	Pin #	Signal Name
3.3V	13	1	3.3V
-12V	14	2	3.3V
Ground	15	3	Ground
PS-ON	16	4	+5V
Ground	17	5	Ground
Ground	18	6	+5V
Ground	19	7	Ground
-5V	20	8	Power good
+5V	21	9	5VSB
+5V	22	10	+12V
+5V	23	11	+12V
Ground	24	12	+3.3V


J5, J6: LVDS Connectors


Signal Name	Pin #	Pin #	Signal Name
LCD_PWR	19	20	LCD_PWR
LD3+	17	18	LD3-
GND	15	16	GND
CLK+	13	14	CLK-
GND	11	12	GND
LD2+	9	10	LD2-
GND	7	8	GND
LD1+	5	6	LD1-
GND	3	4	GND
LD0+	1	2	LD0-

J7: Digital I/O



Signal Name	Pin	Pin	Signal Name
GND	1	2	VCC
OUT3	3	4	OUT1
OUT2	5	6	OUT0
IN3	7	8	IN1
IN2	9	10	IN0

J8: LCD Backlight Connector







Pin #	Signal Name
1	Backlight Power
2	Backlight Enable
3	Brightness Control
4	Ground

J9: Mini PCIE/mSATA Connector




J10: Mini PCIE Connector



J11: SPI Flash Connector (Factory use only)**J12: MCU Flash Connector (factory use only)****J13: Debug 80 Port Connector (factory use only)**

J14: Front Panel Function Connector



ATX Power ON Switch: Pins 1 and 2

This 2-pin connector is an “ATX Power Supply On/Off Switch” on the system that connects to the power switch on the case. When pressed, the power switch will force the system to power on. When pressed again, it will force the system to power off.

Hard Disk Drive LED Connector: Pins 3 and 4

This connector connects to the hard drive activity LED on control panel. This LED will flash when the HDD is being accessed.


Pin #	Signal Name
4	HDD Active
3	3.3V

Reset Switch: Pins 5 and 6


The reset switch allows the user to reset the system without turning the main power switch off and then on again. Orientation is not required when making a connection to this header.

Power LED: Pins 7 and 8

Pin #	Signal Name
7	+5V
8	GND


J15, J16, J17, J18: COM3/COM4/COM5/COM6 Connector


Signal Name	Pin #	Pin #	Signal Name
DCD, Data carrier detect	1	2	RXD, Receive data
TXD, Transmit data	3	4	DTR, Data terminal ready
GND, ground	5	6	DSR, Data set ready
RTS, Request to send	7	8	CTS, Clear to send
RI, Ring indicator	9	10	Not Used

J19, J20, J21: USB Connectors



Signal Name	Pin	Pin	Signal Name
VCC	1	2	GND
D0-	3	4	D1+
D0+	5	6	D1-
GND	7	8	VCC


J22: Audio Front Header




Signal Name	Pin #	Pin #	Signal Name
MIC2_L	1	2	Ground
MIC2_R	3	4	Presence#
Line2_R	5	6	MIC2_ID
Sense	7	8	NC
Line2_L	9	10	Line2_ID

PCIE1: PCI-E X16 Slot



CPU_FAN1: CPU Fan Power Connector


Pin #	Signal Name
1	Ground
2	+12V
3	Rotation detection
4	Control

SYS_FAN1: System Fan1 Power Connector


Pin #	Signal Name
1	Ground
2	+12V
3	Rotation detection
4	Control

This page is intentionally left blank.

BIOS Setup

This chapter describes the different settings available in the AMI BIOS that comes with the board. The topics covered in this chapter are as follows:

BIOS Introduction	26
BIOS Setup	26
Advanced Settings	27
Chipset Settings	42
Boot Settings.....	47
CSM parameters	48
Security Settings	49
Save & Exit Settings	50

BIOS Introduction

The BIOS (Basic Input/Output System) installed in your computer system's ROM supports Intel processors. The BIOS provides critical low-level support for a standard device such as disk drives, serial ports and parallel ports. It also has password protection as well as special support for detailed fine-tuning of the chipset controlling the entire system.

BIOS Setup

The BIOS provides a Setup utility program for specifying the system configurations and settings. The BIOS ROM of the system stores the Setup utility. When you turn on the computer, the BIOS is immediately activated. Pressing the key immediately allows you to enter the Setup utility. If you are a little bit late pressing the key, POST (Power On Self Test) will continue with its test routines, thus preventing you from invoking the Setup. If you still wish to enter Setup, restart the system by pressing the "Reset" button or simultaneously pressing the <Ctrl>, <Alt> and <Delete> keys. You can also restart by turning the system Off and back On again. The following message will appear on the screen:

Press to Enter Setup

In general, you press the arrow keys to highlight items, <Enter> to select, the <PgUp> and <PgDn> keys to change entries, <F1> for help and <Esc> to quit.

When you enter the Setup utility, the Main Menu screen will appear on the screen. The Main Menu allows you to select from various setup functions and exit choices.

Warning: *It is strongly recommended that you avoid making any changes to the chipset defaults. These defaults have been carefully chosen by both AMI and your system manufacturer to provide the absolute maximum performance and reliability. Changing the defaults could cause the system to become unstable and crash in some cases.*

Main Settings

Aprio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
System Language		[English]			Choose the system default language → ← Select Screen ↑ ↓ Select Item Enter: Select +- Change Field F1: General Help F2: Previous Values F3: Optimized Default F4: Save ESC: Exit
System Date		[Tue 01/20/2009]			
System Time		21:25:55			
Access Level		Administrator			

System Language

Choose the system default language.

System Date

Set the Date. Use Tab to switch between Date elements.

System Time

Set the Time. Use Tab to switch between Time elements.

Advanced Settings

This section allows you to configure and improve your system and allows you to set up some system features according to your preference.

Aprio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
	<ul style="list-style-type: none"> ▶ PCI Subsystem Settings ▶ ACPI Settings ▶ Trusted Computing ▶ Wake up event Configuration ▶ CPU Configuration ▶ SATA Configuration ▶ Shutdown Temperature Configuration ▶ LVDS (eDP/DP) Configuration ▶ iSmart Controller 3.1 ▶ AMT Configuration ▶ USB Configuration ▶ F81866 Super IO Configuration ▶ F81866 H/W Monitor 				→ ← Select Screen ↑ ↓ Select Item Enter: Select +- Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit

PCI Subsystem Settings

Aptio Setup Utility - Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
PCI Bus Driver Version			V 2.05.02		→ ← Select Screen
PCI Common Settings					↑ ↓ Select Item
PCI Latency Timer			32 PCI Bus Cycles		Enter: Select
VGA Palette Snoop			Disabled		+ - Change Opt.
PERR# Generation			Disabled		F1: General Help
SERR# Generation			Disabled		F2: Previous Values
▶ PCI Express Settings					F3: Optimized Defaults
					F4: Save & Exit
					ESC: Exit

PCI Latency Timer

Value to be programmed into PCI Latency Timer Register.

VGA Palette Snoop

Enables or disables VGA Palette Registers Snooping.

PERR# Generation

Enables or disables PCI device to generate PERR#.

SERR# Generation

Enables or disables PCI device to generate SERR#.

PCI Express Settings

Change PCI Express devices settings.

PCI Express Settings

Aptio Setup Utility

Main	Advanced	Chipset	Boot	Security	Save & Exit
PCI Express Device Register Settings					
Relaxed Ordering			Disabled		
Extended Tag			Disabled		
No Snoop			Enabled		
Maximum Payload			Auto		
Maximum Read Request			Auto		
PCI Express Link Register Settings					
ASPM Support			Disabled		
WARNING: Enabling ASPM may cause some PCI-E devices to fail					→ ← Select Screen
Extended Synch			Disabled		↑ ↓ Select Item
					Enter: Select
					+ - Change Field
Link Training Retry			5		F1: General Help
Link Training Timeout (uS)			100		F2: Previous Values
Unpopulated Links			Keep Link ON		F3: Optimized Default
Restore PCIe Registers			Disabled		F4: Save ESC: Exit

Relaxed Ordering

Enables or disables PCI Express Device Relaxed Ordering.

Extended Tag

If ENABLED allows device to use 8-bit Tag field as a requester.

No Snoop

Enables or disables PCI Express Device No Snoop option.

Maximum Payload

Set Maximum Payload of PCI Express Device or allow System BIOS to select the value.

Maximum Read Request

Set Maximum Read Request Size of PCI Express Device or allow System BIOS to select the value.

ASPM Support

Set the ASPM Level: Force L0s – Force all links to L0s State:
AUTO – BIOS auto configure: DISABLE – Disables ASPM.

Extended Synch

If ENABLED allows generation of Extended Synchronization patterns.

Link Training Retry

Defines number of Retry Attempts software will take to retrain the link if previous training attempt was unsuccessful.

Link Training Timeout (uS)

Defines number of Microseconds software will wait before polling 'Link Training' bit in Link Status register. Value range from 10 to 1000 uS.

Unpopulated Links

In order to save power, software will disable unpopulated PCI Express links, if this option set to 'Disable Link'.

Restore PCIE Registers

On non-PCI Express aware OS's (Pre Windows Vista) some devices may not be correctly reinitialized after S3. Enabling this restore PCI Express device configuration on S3 resume

Warning: Enabling this may cause issues with other hardware after S3 resume.

ACPI Settings

Aptio Setup Utility

Main	Advanced	Chipset	Boot	Security	Save & Exit
ACPI Settings					→ ← Select Screen
Enable Hibernation					↑ ↓ Select Item
ACPI Sleep State					Enter: Select
Lock Legacy Resources					+ - Change Field
S3 Video Repost					F1: General Help
					F2: Previous Values
					F3: Optimized Default
					F4: Save ESC: Exit

Enable Hibernation

Enables or Disables System ability to Hibernate (OS/S4 Sleep State). This option may be not effective with some OS.

ACPI Sleep State

Select ACPI sleep state the system will enter, when the *SUSPEND* button is pressed.

Lock Legacy Resources

Enabled or Disabled Lock of Legacy Resources.

S3 Video Repost

Enable or disable S3 Video Repost.

Trusted Computing

Aptio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
Configuration					
Security Device Support			Disabled		
Current Status Information					
SUPPORT TURNED OFF					
					→ ← Select Screen ↑ ↓ Select Item Enter: Select +- Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit

Security Device Support

This configuration is supported only with MI981AF. Enables or disables BIOS support for security device. O.S. will not show Security Device. TCG EFI protocol and INT1A interface will not be available.

TPM State

Enable/Disable Security Device. NOTE: Your Computer will reboot during restart in order to change State of the Device.

Pending operation

Schedule an Operation for the Security Device. NOTE: Your Computer will reboot during restart in order to change State of Security Device.

Wake up event settings

Aptio Setup Utility - Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
Wake on Ring			Disabled		→ ← Select Screen ↑ ↓ Select Item Enter: Select +- Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit
Wake on PCIE Wake Event			Disabled		

Wake up by Ring / Wake up by PCIE WAKE#

The options are Disabled and Enabled.

CPU Configuration

This section shows the CPU configuration parameters.

Aptio Setup Utility - Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
CPU Configuration					
Intel(R) CPU Core(TM)i3-4340TE @ 2.60GHz					
CPU Signature				306c3	
Processor Family				6	
Microcode Patch				17	
FSB Speed				100MHz	
Max CPU Speed				2600 MHz	
Min CPU Speed				800 MHz	
CPU Speed				2600 MHz	
Processor Cores				2	
Intel HT Technology				Supported	
Intel VT-x Technology				Supported	
Intel SMX Technology				Supported	
64-bit				Supported	
EIST				Supported	
Hyper-threading				Enabled	
Active Processor Cores				All	
Execute Disable Bit				Enabled	
Intel Virtualization Technology				Enabled	
Boot performance mode				Turbo performance	
EIST				Enabled	
					→ ←Select Screen
					↑↓ Select Item
					Enter: Select
					+ - Change Field
					F1: General Help
					F2: Previous Values
					F3: Optimized Default
					F4: Save ESC: Exit

Active Processor Cores

Number of cores to enable in each processor package.

Execute Disable Bit

XD can prevent certain classes of malicious buffer overflow attacks when combined with a supporting OS

Intel Virtualization Technology

When enabled, a VMM can utilize the additional hardware capabilities provided by Vanderpool Technology.

Boot Performance Mode

Select the performance state that the BIOS will set before OS handoff.

EIST

Enabled/Disabled Intel Speedstep.

SATA Configuration

SATA Devices Configuration.

Aptio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
SATA Controller(s)			Enabled		
SATA Mode Selection			AHCI		
SATA Controller Speed			Default		
SATA Port0			Empty		
Software Preserve			Unknown		
Hot Plug			Dissabled		
SATA Port1			Empty		
Software Preserve			Unknown		
Hot Plug			Dissabled		
SATA Port2			Empty		
Software Preserve			Unknown		
Hot Plug			Dissabled		
SATA Port3			Empty		
Software Preserve			Unknown		
Hot Plug			Dissabled		
SATA Port4			Empty		
Software Preserve			Unknown		
Hot Plug			Dissabled		
SATA Port5			Empty		
Software Preserve			Unknown		
Hot Plug			Dissabled		

→ ← Select Screen
 ↑ ↓ Select Item
 Enter: Select
 +- Change Opt.
 F1: General Help
 F2: Previous Values
 F3: Optimized Defaults
 F4: Save & Exit
 ESC: Exit

SATA Controller(s)

Enable or disable SATA Device.

SATA Mode Selection

Determines how SATA controller(s) operate.

- (1) IDE Mode.
- (2) AHCI Mode.
- (3) RAID Mode. (MI981AF only)

SATA Controller Speed

Indicates the maximum speed the SATA controller can support.

Hot Plug

Designates this port as Hot Pluggable.

Shutdown Temperature Configuration

Aptio Setup Utility - Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
ACPI Shutdown Temperature				Disabled	→ ← Select Screen ↑ ↓ Select Item Enter: Select +- Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save ESC: Exit

ACPI Shutdown Temperature

The default setting is Disabled.

LVDS (eDP/DP) Configuration

Aptio Setup Utility - Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
LVDS (eDP/DP) Configuration					
DP/eDP LVDS Control				Disable	→ ← Select Screen ↑ ↓ Select Item Enter: Select +- Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save ESC: Exit

DP/eDP LVDS Control

The default setting is Disabled.

iSmart Controller 3.1

Aptio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
iSmart Controller 3.1					→ ← Select Screen
Power-On after Power failure			Disable		↑ ↓ Select Item
Temperature Guardian			Disable		Enter: Select
Schedule Slot 1			None		+ - Change Opt.
Schedule Slot 2			None		F1: General Help
					F2: Previous Values
					F3: Optimized Defaults
					F4: Save & Exit
					ESC: Exit

Power-On after Power failure

This field sets the system power status whether *Disable* or *Enable* when power returns to the system from a power failure situation.

Temperature Guardian

Generate the reset signal when system hangs up on POST

Schedule Slot 1 / 2

Setup the hour/minute for system power on.

AMT Configuration

Aptio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
Intel AMT			Enabled		
BIOS Hotkey Pressed			Disabled		
MEBx Selection Screen			Disabled		
Hide Un-Configure ME Confirmation			Disabled		
Un-Configure ME			Disabled		→ ← Select Screen
Amt Wait Timer			0		↑ ↓ Select Item
Activate Remote Assistance Process			Disabled		Enter: Select
USB Configure			Enabled		+– Change Opt.
PET Progress			Enabled		F1: General Help
AMT CIRA Timeout			0		F2: Previous Values
Watchdog			Disabled		F3: Optimized Defaults
OS Timer			0		F4: Save & Exit
BIOS Timer			0		ESC: Exit

AMT configuration is supported only with MI981AF (with iAMT function).

Intel AMT

Enable/Disable Intel (R) Active Management Technology BIOS Extension.

Note: iAMT H/W is always enabled. This option just controls the BIOS extension execution. If enabled, this requires additional firmware in the SPI device.

BIOS Hotkey Pressed

OEMFLag Bit 1: Enable/Disable BIOS hotkey press.

AMT Configuration

OEMFLag Bit 2: Enable/Disable MEBx selection screen.

Hide Un-Configure ME Configuration

OEMFLag Bit 6: Hide Un-Configure ME without password Confirmation Prompt.

Un-Configure ME

OEMFLag Bit 15: Un-Configure ME without password.

Amt Wait Timer

Set timer to wait before sending ASF_GET_BOOT_OPTIONS.

Activate Remote Assistance Process

Trigger CIRA boot.

USB Configure

Enable/Disable USB Configure function.

PET Progress

User can Enable/Disable PET Events progress to receive PET.

Watchdog Timer

Enable/Disable Watchdog Timer.

USB Configuration

Aptio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
USB Configuration				<div>→ ← Select Screen</div> <div>↑ ↓ Select Item</div> <div>Enter: Select</div> <div>+ - Change Opt.</div> <div>F1: General Help</div> <div>F2: Previous Values</div> <div>F3: Optimized Defaults</div> <div>F4: Save & Exit</div> <div>ESC: Exit</div>	
USB Module Version		8.10.28			
USB Devices:					
2 Keyboards, 1 Mouse, 2 Hubs					
Legacy USB Support		Enabled			
USB3.0 Support		Enabled			
XHCI Hand-off		Enabled			
EHCI Hand-off		Enabled			
USB Mass Storage Driver Support		Enabled			
USB hardware delays and time-outs:					
USB Transfer time-out		20 sec			
Device reset time-out		20 sec			
Device power-up delay		Auto			

Legacy USB Support

Enables Legacy USB support.

AUTO option disables legacy support if no USB devices are connected.

DISABLE option will keep USB devices available only for EFI applications.

USB3.0 Support

Enable/Disable USB3.0 (XHCI) Controller support.

XHCI Hand-off

This is a workaround for OSes without XHCI hand-off support. The XHCI ownership change should be claimed by XHCI driver.

EHCI Hand-off

This is a workaround for OSes without EHCI hand-off support. The XHCI ownership change should be claimed by EHCI driver.

USB Mass Storage Driver Support

Enable/Disable USB Mass Storage Driver Support.

USB Transfer time-out

The time-out value for Control, Bulk, and Interrupt transfers.

Device reset time-out

USB mass Storage device start Unit command time-out.

Device power-up delay

Maximum time the device will take before it properly reports itself to the Host Controller. 'Auto' uses default value: for a Root port it is 100ms, for a Hub port the delay is taken from Hub descriptor.

F81866 Super IO Configuration

Aptio Setup Utility

Main	Advanced	Chipset	Boot	Security	Save & Exit
Super IO Configuration					
F81866 Super IO Chip		F81866			
<ul style="list-style-type: none">▶ Serial Port 1 Configuration▶ Serial Port 2 Configuration▶ Serial Port 3 Configuration▶ Serial Port 4 Configuration▶ Serial Port 5 Configuration▶ Serial Port 6 Configuration				<div>→ ← Select Screen</div> <div>↑ ↓ Select Item</div> <div>Enter: Select</div> <div>+ - Change Field</div> <div>F1: General Help</div> <div>F2: Previous Values</div> <div>F3: Optimized Default</div> <div>F4: Save ESC: Exit</div>	

Serial Port Configuration

Set Parameters of Serial Ports. User can Enable/Disable the serial port and Select an optimal settings for the Super IO Device.

F81866 H/W Monitor

Aptio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
PC Health Status					
CPU temperature			+33.0 C		
System temperature			+34.5 C		
CPU Fan Speed			4066 RPM		
System Fan Speed			N/A		→ ← Select Screen
Vcore			+1.704 V		↑ ↓ Select Item
+5V			+5.144 V		Enter: Select
+12V			+12.096V		+ - Change Opt.
+1.5V			+1.512V		F1: General Help
+3.3V			+3.424		F2: Previous Values
CPU smart fan control			Disabled		F3: Optimized Defaults
System smart fan control			Disabled		F4: Save & Exit
					ESC: Exit

CPU/System smart fan control

This field enables or disables the smart fan feature.

Disabled (default)

50 °C

60 °C

70 °C

80 °C

90 °C

Temperatures/Voltages

These fields are the parameters of the hardware monitoring function feature of the motherboard. The values are read-only values as monitored by the system and show the PC health status.

Chipset Settings

This section allows you to configure and improve your system and allows you to set up some system features according to your preference.

Aptio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
<ul style="list-style-type: none">▶ PCH-IO Configuration▶ System Agent (SA) Configuration					→ ← Select Screen ↑ ↓ Select Item Enter: Select +- Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit

PCH-IO Configuration

This section allows you to configure the North Bridge Chipset.

Aptio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
Intel PCH RC Version			1.8.0.0	→ ← Select Screen ↑ ↓ Select Item Enter: Select +- Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit	
Intel PCH SKU Name			Q87		
Intel PCH Rev ID			05/C2		
<ul style="list-style-type: none">▶ PCI Express Configuration▶ USB Configuration▶ PCH Azalia Configuration					
PCH LAN Controller			Enabled		
Wake on LAN			Enabled		
SLP_S4 Assertion Width			4-5 Seconds		

PCH LAN Controller

Enable or disable onboard NIC.

Wake on LAN

Enable or disable integrated LAN to wake the system. (The Wake On LAN cannot be disabled if ME is on at Sx state.)

SLP_S4 Assertion Width

Select a minimum assertion width of the SLP_S4# signal.

PCI Express Configuration

Aptio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
PCI Express Configuration DMI Link ASPM Control Disabled DMI Link Extended Synch Control Disabled PCIe-USB Glitch W/A Disabled Subtractive Decode Disabled ▶ PCI Express Root Port 1 ▶ PCI Express Root Port 2 ▶ PCI Express Root Port 3 ▶ PCI Express Root Port 4 ▶ PCI Express Root Port 5 PCI-E Port 6 is assigned to LAN ▶ PCI Express Root Port 7 ▶ PCI Express Root Port 8					→ ← Select Screen ↑ ↓ Select Item Enter: Select +- Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit

DMI Link ASPM Control

The control of Active State Power Management on both NB side and SB side of the DMI Link.

DMI Link Extended Synch Control

The control of Extended Synch on SB side of the DMI Link.

PCIe-USB Glitch W/A

PCIe-USB Glitch W/A for bad USB device(s) connected behind PCIe/PEG port.

Subtractive Decode

Enable or disable PCI Express Subtractive Decode.

USB Configuration

Main	Advanced	Chipset	Boot	Security	Save & Exit
USB Configuration				<div>→ ← Select Screen</div> <div>↑ ↓ Select Item</div> <div>Enter: Select</div> <div>+ - Change Field</div> <div>F1: General Help</div> <div>F2: Previous Values</div> <div>F3: Optimized Default</div> <div>F4: Save ESC: Exit</div>	
USB Precondition		Disabled			
xHCI Mode		Auto			
USB Ports Per-Port Disable Control		Disabled			

USB Precondition

Precondition work on USB host controller and root ports for faster enumeration.

PCH Azalia Configuration

Aptio Setup Utility - Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
PCH Azalia Configuration				<div>→ ← Select Screen</div> <div>↑ ↓ Select Item</div> <div>Enter: Select</div> <div>+ - Change Opt.</div> <div>F1: General Help</div> <div>F2: Previous Values</div> <div>F3: Optimized Defaults</div> <div>F4: Save & Exit</div> <div>ESC: Exit</div>	
Azalia		Auto			

Azalia

Control Detection of the Azalia device.

Disabled = Azalia will be unconditionally disabled.

Enabled Azalia will be unconditionally Enabled.

Auto = Azalia will be enabled if present, disabled otherwise.

System Agent (SA) Configuration

Aptio Setup Utility

Main	Advanced	Chipset	Boot	Security	Save & Exit
System Agent Bridge Name			Haswell		
System Agent RC Version			1.8.0.0		
VT-d Capability			Unsupported		
CHAP Device (B0:D7:F0)			Disabled		→ ← Select Screen
Thermal Device (B0:D4:F0)			Disabled		↑ ↓ Select Item
CPU SA Audio Device (B0:D3:F0)			Enabled		Enter: Select
Enable NB CRID			Disabled		+ - Change Field
▶ Graphics Configuration					F1: General Help
▶ Memory Configuration					F2: Previous Values
					F3: Optimized Defaults
					F4: Save ESC: Exit

VT-d

Check to enable VT-d function on MCH.

Enable NB CRID

Enable or disable NB CRID WorkAround.

Graphics Configuration

Aptio Setup Utility - Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
Graphics Configuration					
IGFX VBIOS Version			2179		
IGfx Frequency			700 MHz		→ ← Select Screen
Primary Display			Auto		↑ ↓ Select Item
Primary PEG			Auto		Enter: Select
Primary PCIe			Auto		+ - Change Opt.
Internal Graphics			Auto		F1: General Help
Aperture Size			256MB		F2: Previous Values
DVMT Pre-Allocated			32M		F3: Optimized Defaults
DVMT Total Gfx Mem			256MB		F4: Save & Exit
					ESC: Exit

Primary Display

Select which of IGFX/PEG/PCI graphics device should be Primary Display or select SG for switchable Gfx.

Primary PEG

Select PEG0/PEG1/PEG2/PEG3 Graphics device should be Primary PEG.

Primary PCIE

Select PCIE0/PCIE1/PCIE2/PCIE3/PCIE4/PCIE5/PCIE6/PCIE7
Graphics device should be Primary PCIE.

Internal Graphics

Keep IGD enabled based on the setup options.

Aperture Size

Select the Aperture Size.

DVMT Pre-Allocated

Select DVMT 5.0 Pre-Allocated (Fixed) Graphics Memory Size used by the Internal Graphics Device.

DVMT Total Gfx Mem

Select DVMT 5.0 Total Graphics Memory Size used by the Internal Graphics Device.

Memory Configuration

Aptio Setup Utility

Main	Advanced	Chipset	Boot	Security	Save & Exit
Memory Information					
Memory Frequency		1333 MHz			
Total Memory		4096 MB (DDR3)			
DIMM#0		2048 MB (DDR3)			
DIMM#1		Not Present			→ ← Select Screen
DIMM#2		2048 MB (DDR3)			↑ ↓ Select Item
DIMM#3		Not Present			Enter: Select
CAS Latency (tCL)		11			+ - Change Field
Minimum delay time					F1: General Help
CAS to RAS (tRCDmin)		11			F2: Previous Values
Row Precharge (tRPmin)		11			F3: Optimized Default
Active to Precharge (tRASmin)		28			F4: Save ESC: Exit

Boot Settings

This section allows you to configure the boot settings.

Aptio Setup Utility					
Main	Advanced	Chipset	Boot	Security	Save & Exit
Boot Configuration					
Setup Prompt Timeout			1		
Bootup NumLock State			On		
Quiet Boot			Disabled		
Fast Boot			Disabled		
Boot mode Select			LEGACY		
FIXED BOOT ORDER Priorities					
Boot Option #1			Hard Disk		
Boot Option #2			CD/DVD		
Boot Option #3			USB Hard Disk		
Boot Option #4			USB CD/DVD		
Boot Option #5			USB Key		
Boot Option #6			USB Floppy		
Boot Option #7			Network		
► CSM16 Parameters					
CSM Parameters					
				→ ← Select Screen ↑ ↓ Select Item Enter: Select +- Change Field F1: General Help F2: Previous Values F3: Optimized Default F4: Save ESC: Exit	

Setup Prompt Timeout

Number of seconds to wait for setup activation key.

65535(0xFFFF) means indefinite waiting.

Bootup NumLock State

Select the keyboard NumLock state.

Quiet Boot

Enables/Disables Quiet Boot option.

Fast Boot

Enables/Disables boot with initialization of a minimal set of devices required to launch active boot option. Has no effect for BBS boot options.

FIXED BOOT ORDER Priorities

Sets the system boot order.

CSM parameters

This section allows you to configure the boot settings.

Aptio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
Launch CSM			Enabled		
Boot option filter			UEFI and Legacy		→ ← Select Screen
Launch PXE OpROM policy			Do not launch		↑ ↓ Select Item
Launch Storage OpROM policy			Legacy only		Enter: Select
Launch Video OpROM policy			Legacy only		+ - Change Opt.
					F1: General Help
					F2: Previous Values
					F3: Optimized Defaults
					F4: Save & Exit
					ESC: Exit
Other PCI device ROM priority			Legacy OpROM		

Launch CSM

This option controls if CSM will be launched.

Boot option filter

This option controls what devices system can boot to.

Launch PXE OpROM policy

Controls the execution of UEFI and Legacy PXE OpROM.

Launch Storage OpROM policy

Controls the execution of UEFI and Legacy Storage OpROM.

Launch Video OpROM policy

Controls the execution of UEFI and Legacy Video OpROM.

Other PCI device ROM priority

For PCI devices other than Network, Mass storage or Video defines which OpROM to launch.

Security Settings

This section allows you to configure and improve your system and allows you to set up some system features according to your preference.

Aptio Setup Utility					
Main	Advanced	Chipset	Boot	Security	Save & Exit
Password Description					
If ONLY the Administrator's password is set, then this only limit access to Setup and is only asked for when entering Setup.					
If ONLY the User's password is set, then this is a power on password and must be entered to boot or enter Setup. In Setup the User will have Administrator rights					
The password length must be				→ ← Select Screen	
in the following range:				↑ ↓ Select Item	
Minimum length				Enter: Select	
Maximum length				+- Change Field	
				F1: General Help	
Administrator Password				F2: Previous Values	
User Password				F3: Optimized Default	
				F4: Save ESC: Exit	

Administrator Password

Set Setup Administrator Password.

User Password

Set User Password.

Save & Exit Settings

Aptio Setup Utility – Copyright © 2012 American Megatrends, Inc.

Main	Advanced	Chipset	Boot	Security	Save & Exit
Save Changes and Exit Discard Changes and Exit Save Changes and Reset Discard Changes and Reset Save Options Save Changes Discard Changes Restore Defaults Save as User Defaults Restore User Defaults					→ ← Select Screen ↑ ↓ Select Item Enter: Select +- Change Opt. F1: General Help F2: Previous Values F3: Optimized Defaults F4: Save & Exit ESC: Exit

Save Changes and Exit

Exit system setup after saving the changes.

Discard Changes and Exit

Exit system setup without saving any changes.

Save Changes and Reset

Reset the system after saving the changes.

Discard Changes and Reset

Reset system setup without saving any changes.

Save Changes

Save Changes done so far to any of the setup options.

Discard Changes

Discard Changes done so far to any of the setup options.

Restore Defaults

Restore/Load Defaults values for all the setup options.

Save as User Defaults

Save the changes done so far as User Defaults.

Restore User Defaults

Restore the User Defaults to all the setup options.

Drivers Installation

This section describes the installation procedures for software and drivers. The software and drivers are included with the motherboard. If you find the items missing, please contact the vendor where you made the purchase. The contents of this section include the following:

Intel Chipset Software Installation Utility	52
VGA Drivers Installation.....	53
Realtek HD Audio Driver Installation	54
LAN Drivers Installation	55
Intel® Management Engine Interface	56
Intel® USB 3.0 Drivers	57

IMPORTANT NOTE:

After installing your Windows operating system, you must install first the Intel Chipset Software Installation Utility before proceeding with the drivers installation.

Intel Chipset Software Installation Utility

The Intel Chipset Drivers should be installed first before the software drivers to enable Plug & Play INF support for Intel chipset components. Follow the instructions below to complete the installation.

1. Insert the DVD that comes with the board. Click **Intel** and then **Intel(R) 8 Series Chipset Drivers**.



2. Click **Intel(R) Chipset Software Installation Utility**.





3. When the Welcome screen to the Intel® Chipset Device Software appears, click **Next** to continue.
4. Click **Yes** to accept the software license agreement and proceed with the installation process.
5. On the Readme File Information screen, click **Next** to continue the installation.
6. The Setup process is now complete. Click **Finish** to restart the computer and for changes to take effect.

VGA Drivers Installation

1. Insert the DVD that comes with the board. Click **Intel** and then **Intel(R) 8 Series Chipset Drivers**. Click **Intel(R) Graphics Driver**.



2. When the Welcome screen appears, click **Next** to continue.
3. Click **Yes** to agree with the license agreement and continue the installation.
4. On the Readme File Information screen, click **Next** to continue the installation of the Intel® HD Graphics Driver.
5. On the screen shown below, click **Install** to continue.



6. On the Setup Progress screen, click **Next** to continue.
7. Setup complete. Click **Finish** to restart the computer and for changes to take effect.

Realtek HD Audio Driver Installation

1. Insert the DVD that comes with the board. Click **Intel** and then **Intel(R) 8 Series Chipset Drivers**. Click **Realtek High Definition Audio Driver**.



2. On the Welcome to the InstallShield Wizard screen, click **Next** to proceed with and complete the installation process.

3. The InstallShield Wizard Complete. Click **Finish** to restart the computer and for changes to take effect.

LAN Drivers Installation

1. Insert the DVD that comes with the board. Click **Intel** and then **Intel(R) 8 Series Chipset Drivers**. Click **Intel(R) PRO LAN Network Drivers**.



2. Click **Install Drivers and Software**.

4. When the Welcome screen appears, click **Next**.

5. Click **Next** to agree with the license agreement.

6. Click the checkbox for **Drivers** in the Setup Options screen to select it and click **Next** to continue.

7. The wizard is ready to begin installation. Click **Install** to begin the installation.

8. When InstallShield Wizard is complete, click **Finish**.

Intel® Management Engine Interface



The following application requires Microsoft .NET Framework 3.5 or later: Intel® Management Engine Components. Please install the latest version of Microsoft .NET Framework from Microsoft Download Center to run this application correctly.

Follow the steps below to install the Intel Management Engine.

1. Insert the DVD that comes with the board. Click **Intel** and then **Intel(R) 8 Series Chipset Drivers** and then **Intel(R) ME 9.0 Drivers**.



2. When the Welcome screen to the InstallShield Wizard for Intel® Management Engine Components, click the checkbox for **Install Intel® Control Center** & click **Next**.
3. Click **Yes** to agree with the license agreement.
4. When the Setup Progress screen appears, click **Next**. Then, click **Finish** when the setup progress has been successfully installed.

Intel® USB 3.0 Drivers

1. Insert the DVD that comes with the board. Click **Intel** and then **Intel(R) 8 Series Chipset Drivers**. Click **Intel(R) USB 3.0 Drivers**.



2. When the Welcome screen to the InstallShield Wizard for Intel® USB 3.0 eXtensible Host Controller Driver, click **Next**.

3. Click **Yes** to agree with the license agreement and continue the installation.

4. On the Readme File Information screen, click **Next** to continue the installation of the Intel® USB 3.0 eXtensible Host Controller Driver.

5. When the Setup Progress screen appears, click **Next**. Setup complete. Click **Finish** to restart the computer and for changes to take effect.

This page is intentionally set blank.

Appendix

A. I/O Port Address Map

Each peripheral device in the system is assigned a set of I/O port addresses which also becomes the identity of the device. The following table lists the I/O port addresses used.

Address	Device Description
0000h-001Fh	Direct memory access controller
0000h-001Fh	PCI bus
0040h-0043h	System timer
0050h-0053h	System timer
0070h-0077h	System CMOS/real time clock
0081h-0091h	Direct memory access controller
0093h-009Fh	Direct memory access controller
00C0h-00DFh	Direct memory access controller
00F0h-00F0h	Numeric data processor
02E0h-02E7h	Communications Port (COM6)
02E8h-02EFh	Communications Port (COM4)
02F0h-02F7h	Communications Port (COM5)
02F8h-02FFh	Communications Port (COM2)
03B0h-03BBh	Intel(R) HD Graphics 4600
03C0h-03DFh	Intel(R) HD Graphics 4600
03E8h-03EFh	Communications Port (COM3)
03F8h-03FFh	Communications Port (COM1)
0D00h-FFFFh	PCI bus
E000h-EFFFh	Intel(R) 8 Series/C220 Series PCI Express Root Port #7 - 8C1C
F000h-F03Fh	Intel(R) HD Graphics 4600
F040h-F05Fh	Intel(R) 8 Series/C220 Series SMBus Controller - 8C22
F060h-F07Fh	Intel(R) 8 Series/C220 Series SATA AHCI Controller - 8C02
F0A0h-F0A3h	Intel(R) 8 Series/C220 Series SATA AHCI Controller - 8C02
F0B0h-F0B7h	Intel(R) 8 Series/C220 Series SATA AHCI Controller - 8C02
F0C0h-F0C3h	Intel(R) 8 Series/C220 Series SATA AHCI Controller - 8C02
F0D0h-F0D7h	Intel(R) 8 Series/C220 Series SATA AHCI Controller - 8C02
F0E0h-F0E7h	Intel(R) Active Management Technology - SOL (COM7)

B. Interrupt Request Lines (IRQ)

Peripheral devices use interrupt request lines to notify CPU for the service required. The following table shows the IRQ used by the devices on board.

Level	Function
IRQ0	System Timer
IRQ3	Serial Port #2
IRQ4	Serial Port #1
IRQ5	Serial Port #3
IRQ5	Serial Port #4
IRQ7	Serial Port #5
IRQ7	Serial Port #6
IRQ8	Real Time Clock
IRQ 10	Intel(R) 8 Series/C220 Series SMBus Controller - 8C22
IRQ 13	Numeric data processor
IRQ 16	High Definition Audio Controller
IRQ 16	Intel(R) 8 Series/C220 Series USB EHCI #2 - 8C2D
IRQ 16	Intel(R) Management Engine Interface
IRQ 16	Intel(R) 8 Series/C220 PCI-Express Root Port #1 - 8C10
IRQ 16	Intel(R) Xeon(R) processor E3-1200 v3/4th Gen Core processor PCI Express x16 Controller - 0C01
IRQ 19	Intel(R) 8 Series/C220 Series SATA AHCI Controller - 8C02
IRQ 19	Intel(R) Active Management Technology - SOL (COM7)
IRQ 22	High Definition Audio Controller
IRQ 23	Intel(R) 8 Series/C220 Series USB EHCI #1 - 8C26

C. Watchdog Timer Configuration

The WDT is used to generate a variety of output signals after a user programmable count. The WDT is suitable for use in the prevention of system lock-up, such as when software becomes trapped in a deadlock. Under these sorts of circumstances, the timer will count to zero and the selected outputs will be driven. Under normal circumstance, the user will restart the WDT at regular intervals before the timer counts to zero.

SAMPLE CODE:

```
//-----
//
// THIS CODE AND INFORMATION IS PROVIDED "AS IS" WITHOUT WARRANTY OF ANY
// KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE
// IMPLIED WARRANTIES OF MERCHANTABILITY AND/OR FITNESS FOR A PARTICULAR
// PURPOSE.
//
//-----
#include <dos.h>
#include <conio.h>
#include <stdio.h>
#include <stdlib.h>
#include "F81866.H"
//-----
int main (int argc, char *argv[]);
void EnableWDT(int);
void DisableWDT(void);
//-----
int main (int argc, char *argv[])
{
    unsigned char bBuf;
    unsigned char bTime;
    char **endptr;

    char SIO;

    printf("Fintek 81866 watch dog program\n");

    SIO = Init_F81866();
    if (SIO == 0)
    {
        printf("Can not detect Fintek 81866, program abort.\n");
        return(1);
    }
    if (SIO == 0)

    if (argc != 2)
    {
        printf(" Parameter incorrect!!\n");
        return (1);
    }

    bTime = strtol(argv[1], endptr, 10);
    printf("System will reset after %d seconds\n", bTime);

    if (bTime)
    {
        EnableWDT(bTime); }
    else
    {
        DisableWDT(); }

    return 0;
}
```

```
}
//-----
void EnableWDT(int interval)
{
    unsigned char bBuf;

    bBuf = Get_F81866_Reg(0x2B);
    bBuf &= (~0x20);
    Set_F81866_Reg(0x2B, bBuf);                                //Enable WDTO

    Set_F81866_LD(0x07);                                       //switch to logic device 7
    Set_F81866_Reg(0x30, 0x01);                                //enable timer

    bBuf = Get_F81866_Reg(0xF5);
    bBuf &= (~0x0F);
    bBuf |= 0x52;
    Set_F81866_Reg(0xF5, bBuf);                                //count mode is second

    Set_F81866_Reg(0xF6, interval);                             //set timer

    bBuf = Get_F81866_Reg(0xFA);
    bBuf |= 0x01;
    Set_F81866_Reg(0xFA, bBuf);                                //enable WDTO output

    bBuf = Get_F81866_Reg(0xF5);
    bBuf |= 0x20;
    Set_F81866_Reg(0xF5, bBuf);                                //start counting
}
//-----
void DisableWDT(void)
{
    unsigned char bBuf;

    Set_F81866_LD(0x07);                                       //switch to logic device 7

    bBuf = Get_F81866_Reg(0xFA);
    bBuf &= ~0x01;
    Set_F81866_Reg(0xFA, bBuf);                                //disable WDTO output

    bBuf = Get_F81866_Reg(0xF5);
    bBuf &= ~0x20;
    bBuf |= 0x40;
    Set_F81866_Reg(0xF5, bBuf);                                //disable WDT
}
//-----
```

```

//-----
//
// THIS CODE AND INFORMATION IS PROVIDED "AS IS" WITHOUT WARRANTY OF ANY
// KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE
// IMPLIED WARRANTIES OF MERCHANTABILITY AND/OR FITNESS FOR A PARTICULAR
// PURPOSE.
//
//-----
#include "F81866.H"
#include <dos.h>
//-----
unsigned int F81866_BASE;
void Unlock_F81866 (void);
void Lock_F81866 (void);
//-----
unsigned int Init_F81866(void)
{
    unsigned int result;
    unsigned char ucDid;

    F81866_BASE = 0x4E;
    result = F81866_BASE;

    ucDid = Get_F81866_Reg(0x20);
    if (ucDid == 0x07)                                //Fintek 81866
    {
        goto Init_Finish;
    }

    F81866_BASE = 0x2E;
    result = F81866_BASE;

    ucDid = Get_F81866_Reg(0x20);
    if (ucDid == 0x07)                                //Fintek 81866
    {
        goto Init_Finish;
    }

    F81866_BASE = 0x00;
    result = F81866_BASE;

Init_Finish:
    return (result);
}
//-----
void Unlock_F81866 (void)
{
    outportb(F81866_INDEX_PORT, F81866_UNLOCK);
    outportb(F81866_INDEX_PORT, F81866_UNLOCK);
}
//-----
void Lock_F81866 (void)
{
    outportb(F81866_INDEX_PORT, F81866_LOCK);
}
//-----
void Set_F81866_LD( unsigned char LD)
{
    Unlock_F81866();
    outportb(F81866_INDEX_PORT, F81866_REG_LD);
    outportb(F81866_DATA_PORT, LD);
    Lock_F81866();
}
//-----
void Set_F81866_Reg( unsigned char REG, unsigned char DATA)
{
    Unlock_F81866();
    outportb(F81866_INDEX_PORT, REG);
    outportb(F81866_DATA_PORT, DATA);
    Lock_F81866();
}
//-----

```

```
unsigned char Get_F81866_Reg(unsigned char REG)
```

```
{
    unsigned char Result;
    Unlock_F81866();
    outportb(F81866_INDEX_PORT, REG);
    Result = inportb(F81866_DATA_PORT);
    Lock_F81866();
    return Result;
}
//-----
```

```
//-----
//
// THIS CODE AND INFORMATION IS PROVIDED "AS IS" WITHOUT WARRANTY OF ANY
// KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE
// IMPLIED WARRANTIES OF MERCHANTABILITY AND/OR FITNESS FOR A PARTICULAR
// PURPOSE.
//
```

```
//-----
#ifndef __F81866_H
#define __F81866_H                1
//-----
#define F81866_INDEX_PORT        (F81866_BASE)
#define F81866_DATA_PORT        (F81866_BASE+1)
//-----
#define F81866_REG_LD            0x07
//-----
#define F81866_UNLOCK            0x87
#define F81866_LOCK              0xAA
//-----
unsigned int Init_F81866(void);
void Set_F81866_LD( unsigned char);
void Set_F81866_Reg( unsigned char, unsigned char);
unsigned char Get_F81866_Reg( unsigned char);
//-----
#endif //__F81866_H
```