

SPECIFICATION



Date:2024-04-24 16:53



**Specification
VITA-550BD
9PA550AN00**



Content

1、General	4
2、Input Specification	4
2.1、AC Input.....	4
2.2、Input over Current Protection.....	4
2.3、Inrush Current Limiting	4
3、DC Output	5
3.1、Voltage Regulation	5
3.2、+5V DC / +3.3V DC Power Sequencing	5
3.3、Power Distribution	5
3.4、Cross Load Regulation	6
3.5、Efficiency.....	6
3.6、Energy Star & ErP.....	6
3.7、Ripple Noise.....	7
3.8、Transient Response.....	7
3.9、Capacitive Load.....	8
3.10、Hold Up Time	8
3.11、Over Voltage Protection.....	8
3.12、Short Circuit Protection	8
3.13、No Load Operation	9
3.14、Over Current Protection.....	9
3.15、Over Power Protection	9
3.16、Over Temperature Protection	9
4.0、System specification.....	9
4.1、Power Good Signal PWR_OK.....	9
4.2、PS_ON #.....	10
4.3、+5Vsb.....	11
4.4、Power-on Time	12
4.5、Rise Time	12
4.6、Over Shoot at Turn-on / Turn-off	12
4.7、Reset after Shutdown.....	12
4.8、+5V _{SB} at AC Power-down	12
4.9、Power Excursion.....	13
5.0、Mechanical	13
5.1、Dimension	13
5.2、Airflow / Fan / Fan Speed Control	14
5.3、DC Cables	14
6.0、Environmental	14
6.1、MTBF	14
6.2、Operation Temperature& Altitude	14
7.0、Regulatory	15
7.1、GROUND LEAKAGE CURRENT	15
7.2、DIELECTRIC STRENGTH	15
7.3、INSULATION RESISTANCE	15
7.4、Lightning surge.....	15
7.5、E.M.I	15
7.6、Electrostatic Discharge – ESD	15
8.0、Safety Requirement :	16



Reversion History

Ver.	Description	Date	Author
1.0	Original	2023/10/02	Maksim
1.01	3.5、 Del Efficiency 2% >62% 、 add 10% test load 、 Revise 20% 、 50% 、 100% Load 5.2 Typical load Noise < 27db 3.1 Voltage Regulation: + 5VSB± 5% 7.0 Regulatory add 7.5 、 Electrostatic Discharge – ESD	2023/11/29	Anne
1.02	Del: 2.4 、 Input Under Voltage Revise: 3.7 、 Ripple Noise: +3.3V&5V&5Vsb:30mv to 40mv 、 +12V R/N: 80 to 100mv Revise: 6.2 to Operation Temperature & Altitude 6.4 to 6.3 、 Mechanical Shock 6.5 to 6.4 、 Random Vibration Revise: add 7.5 EMI 7.5 to 7.6 、 Electrostatic Discharge – ESD	2024/03/20	Anne
1.03	Revise 3.1: + 3.3V &+5V&+12V 由 3% 改± 5% ADD 4.9: Power Excursion	2024/03/29	Anne
1.04	Revise : General	2024/04/18	Maksim



1. General

This document is defined for VITA-550BD specification that complies with newest ATX 12V V3.x and EPS 12V V2.92 standards. Regarding to energy saving purpose, the PSU shall meet energy star 8.0 and ErP 2013 requirement. and 80PLUS 230V EU Bronze Level.

2. Input Specification

2.1 AC Input

Table 1 lists AC input voltage and frequency requirements for continuous operation. The power supply shall be capable of supplying full-rated output power from voltage ranges rated 200 to 240 VAC RMS nominal. The power supply shall automatically recover from AC power loss.

Table 1: AC Input Requirements

Parameter	Minimum	Nominal	Maximum	Unit
Vin	180	200~240	265	Vrms
Vin Frequency	47	50 or 60	63	Hz
lin	4A @230V _{AC}		Arms	
PFC	PF ≥ 0.95@ Full Load			

2.2 Input over Current Protection

The power supply shall incorporate primary fusing for input over-current protection to prevent damage to the power supply and meet product safety requirements. Fuses should be slow-blow-type or equivalent to prevent nuisance trips

2.3 Inrush Current Limiting

Maximum inrush current from power-on (with power-on at any point on the AC sine) and including, but not limited to, three line cycles, shall be limited to a level below the surge rating of the AC switch if present, bridge rectifier, and fuse components. Repetitive ON/OFF cycling of the AC input voltage should not damage the power supply or cause the input fuse to blow.



3. DC Output

3.1 Voltage Regulation

The DC output voltages shall remain within the regulation ranges shown in Table 2 when measured at the load end of the output connectors under all line, load, and environmental conditions.

Table 2: DC Output Voltage Regulation

Output	Range	Minimum	Nominal	Maximum	Units
+ 3.3V	± 5%	+ 3.135	+ 3.30	+ 3.465	Volts
+ 5V	± 5%	+ 4.75	+ 5.00	+ 5.25	Volts
+ 12V	± 5%	+ 11.4	+ 12.00	+ 12.6	Volts
- 12V	± 10%	- 13.20	- 12.00	- 10.80	Volts
+ 5V _{SB}	± 5%	+ 4.75	+ 5.00	+ 5.25	Volts

3.2 +5V DC / +3.3V DC Power Sequencing

The +12 VDC and +5 VDC output levels must be equal to or greater than the +3.3 VDC output at all times during power-up and normal operation.

The time between any output of +12 VDC and +5 VDC reaching its minimum in regulation level and +3.3 VDC reaching its minimum in-regulation level must be ≤ 20ms.

3.3 Power Distribution

It should not be inferred that those three models must conform to these tables.

The power supply designed to meet the information in the tables will work for all system configurations under total power consumption.

AC INPUT	200-240V~ 4A 50-60Hz				
DC OUTPUT	+3.3V	+5V	+12V	-12V	+5Vsb
MAX CURRENT	20A	20A	45.8A	0.3A	2.5A
MAX COMBINED	100W		550W	3.6W	12.5W
TOTAL	550W				

Note: The PSU shall deliver total power output wattages continuously when ambient temperature is under 40°C without damage and the maximum fan speed shall be controlled by fan curve chart.



3.4 Cross Load Regulation

The DC load voltages shall remain within the regulation ranges shown in the following tables when measured at the load end of the output connector.

LOAD	+3.3V	+5V	+12V	-12V	+5Vsb	PS-ON
Condition_1	X	X	X	X	2.5A	Off
Condition_2	0.1A	0.2A	0.15A	0A	0A	On
Condition_3	0A	0A	2A	0.3A	0A	On
Condition_4	20A	6.8A	36.15A	0.3A	2.5A	On
Condition_5	0A	20A	36.15A	0.3A	2.5A	On
Condition_6	0A	0A	45.83A	0A	0A	On

Minimum load : +3.3V: 0.1A / +5V: 0.2A / +12V: 0.15A

3.5 Efficiency

The power supply required minimum is 85% efficient under “Full” load, 88% under “typical” load, and 85% in a “light” load or idle condition. The efficiency of the power supply should be tested at nominal input voltage of 230vac input. The loading condition for testing efficiency shown in table below represents a fully loaded system, a ~50% (typical) loaded system, and a ~20% (light) loaded system.

Specification	2%	10%	20%	50%	100%
Efficiency	60%	80%	85%	88%	85%

550W (loading shown in Amps)					
Load	+3.3V	+5V	+12V	-12V	+5Vsb
10%	0.995	0.995	3.785	0.026	0.206
20%(Light)	1.990	1.990	7.569	0.050	0.413
50%(Typical)	4.974	4.974	18.922	0.124	1.032
100%(Full)	9.948	9.948	37.845	0.248	2.064

3.6 Energy Star & ErP


The PSU shall meet ENERGY STAR 8.0 and ErP 2013 requirements, and other low Power system demands, It is recommended that the +5 VSB standby supply efficiency should be as high as possible. Standby efficiency is measured with the main outputs off (PS_ON# high state). Standby efficiency should be as shown in Table below.

Vac	230Vac input					
Load	45mA	90mA	550mA	1A	1.5A	2.5A
Efficiency	>45%	>55%	>75%	>75%	>75%	>75%
Version	Lot 3/6		Lot 3/6		Lot 3	

3.7 Ripple Noise

The output ripple noise requirements listed in Table below should be met throughout the load ranges specified for the appropriate form factor and under all input voltage conditions as specified in Table 1. Ripple and noise are defined as periodic or random signals over a frequency band of 10 Hz to 20MHz. Measurements shall be made with an oscilloscope with 20 MHz of bandwidth. Outputs should be bypassed at the connector with a $0.1\mu\text{F}$ ceramic disk capacitor and a $10\mu\text{F}$ electrolytic capacitor to simulate system loading. See Figure 1 for the differential noise measurement setup.

Parameter	+3.3V	+5V	+12V	-12V	+5Vsb	PWR_OK	PS_ON
Maximum(mV _{p-p})	40 mV	40 mV	100 mV	100 mV	40 mV	400mV	400mV



3.8 Transient Response

The table summarizes the expected output transient step sizes for each output. The 12V transient load slew rate is = 5.0 A/us.

Output	Max. Step size (% of rated output amps)	Max. Step Size (amps)
+ 12V	80%	
+ 5V	30%	
+ 3.3V	30%	
- 12V		0.1 A
+ 5V _{sb}		0.5 A

Output voltage should remain within the regulation limits of DC voltage regulation, and the power supply should be stable when subjected to load transients from any steady state load, including any or all of the following conditions.



3.9 Capacitive Load

The power supply should be able to power up and operate normally with the following capacitances simultaneously present on the DC outputs.

This capacitive loading should be used to check stability and should not be included for noise testing.

Output Voltage	+ 3.3V	+ 5V	+ 12V ₁	- 12V	+ 5V _{SB}
Capacitive Load	3300µF	3300µF	3300µF	330µF	3300µF

3.10 Hold Up Time

The power supply should maintain output regulation per Section 3.1 despite a loss of input power at the low-end nominal range 230 VAC / 47 Hz—at 100% continuous output load as applicable for a minimum of 12ms(T5+T6).

3.11 Over Voltage Protection

The over voltage sense circuitry and reference shall reside in packages that are separate and distinct from the regulator control circuitry and reference. No single point fault shall be able to cause a sustained over voltage condition on any or all outputs.

The PSU shall provide latch-mode Over Voltage Protection for the main outputs only. A remote power OFF/ON cycle is permitted to restore normal operation but is not required. For the 5Vsb a Main AC power OFF/ON cycle is permitted to restore normal operation but is not required.

Output Voltage	Protection Range	Unit
+ 3.3V	<4.3	Volts
+ 5V	<7.0	Volts
+ 12V	<15.6	Volts

3.12 Short Circuit Protection

An output short circuit is defined as any output impedance of less than 0.1 ohms. The PSU shall shut down and latch off for shorting the +3.3V, +5V, or +12V rails to return or any other rails.

Short between main output rails and +5Vsb shall not cause any damage to the PSU. The PSU shall either shut down and latch off or fold back for shorting the negative rails. +5Vsb must be capable of being shorted indefinitely, but when the short is removed, the PSU shall recover automatically or by cycling PS_ON#.

The PSU shall be capable of withstanding a continuous short-circuit to the output without damage or overstress to the unit (for example, to components, PCB traces, connectors) under the input conditions specified in Section 2.1.



3.13 ◀ No Load Operation

No damage or hazardous condition should occur with all the DC output connectors disconnected from the load. The power supply may latch into the shut down state.

3.14 ◀ Over Current Protection

Basically, the OCP is defined by vendor but the trigger point shall be 140% of maximum current at least each rail. And the PSU can't be damaged when OCP occur. Current protection should be designed to limit the current to operate within safe operating conditions.

Over current protection schemes where only the voltage output that experiences the over current event is shut off may be adequate to maintain safe operation of the power supply and the system; however, damage to the motherboard or other system components may occur. The recommended over current protection scheme is for the power supply to latch into the shutdown state.

Output voltage	Over current limit
+3.3V	22A~38A
+5V	22A~38A
+12V	50A~65A

3.15 ◀ Over Power Protection

The power supply shall be shut down and latch off

Test: Full load

3.16 ◀ Over Temperature Protection

The power supply shall include an over-temperature protection sensor, which can trip and shut down the power supply at a preset temperature point. Such an overheated condition is typically the result of internal current overloading or a cooling fan failure. If the protection circuit is non-latching, then it should have hysteresis built in to avoid intermittent tripping.


4.0 ◀ System specification

4.1 ◀ Power Good Signal PWR_OK

PWR_OK is a “power good” signal. It should be asserted high by the power supply to indicate that the +12 VDC, +5VDC, and +3.3VDC outputs are above the under-voltage thresholds listed and that sufficient mains energy is stored by the converter to guarantee continuous power operation.



Conversely, PWR_OK should be deasserted to a low state when any of the +12 VDC, +5 VDC, or +3.3 VDC output voltages falls below its under-voltage threshold, or when mains power has been removed for a time sufficiently long such that power supply operation cannot be guaranteed beyond the power down warning time. The electrical and timing characteristics of the PWR_OK signal are given in table.



Parameter	Description	Required
T0	AC power on time	< 2 S
T1	Powe-on time	< 200 ms
T2	Rise time	0.2 – 20 ms
T3	PWR_OK delay	100 ms* - 250 ms
T4	PWR_OK rise time	< 10 ms
T5	AC loss to PWR_OK hold-up time	> 11 ms
T6	PWR_OK inactive to DC loss delay	> 1 ms

4.2、PS_ON

PS_ON# is an active-low, TTL-compatible signal that allows a motherboard to remotely control the power supply in conjunction with features such as soft on/off, Wake on LAN*, or wake-on-modem. When PS_ON# is pulled to TTL low, the power supply should turn on the four main DC output rails: +12 VDC, +5 VDC, +3.3 VDC, and -12 VDC. When PS_ON# is pulled to TTL high or open-circuited, the DC output rails should not deliver current and should be held at zero potential with respect to ground. PS_ON# has no effect on the +5 VSB output, which is always enabled whenever the AC power is present. Below table lists PS_ON# signal characteristics.



The power supply shall provide an internal pull-up to TTL high. The power supply shall also provide de-bounce circuitry on PS_ON# to prevent it from oscillating on/off at startup when activated by a mechanical switch. The DC output enable circuitry must be SELV-compliant.


The power supply shall not latch into a shutdown state when PS_ON# is driven active by pulses between 10ms to 100ms during the decay of the power rails.

Parameter	Minimum	Maximum
V_{IL}	0	0.8 V
I_{IL} ($V_{IN} = 0.4$ V)	-	-1.6 mA ¹
V_{IH} ($I_{IN} = 200$ uA)	2.0 V	-
V_{IH} open circuit	-	-5.25 V
Ripple / Noise		400 mV p-p

NOTES:

1. Negative current indicates that the current is flowing from the power supply to the motherboard.
2. Due to PS_ON# toggle on/off frequently, system and PSU component's reliability should be considered based on the days, months, or years of claimed warranty listed on product specification. Refer to Section 10.2 for more details about PSU design considerations for S0ix mode.

PS_ON# Signal Characteristics



4.3 +5Vsb

+5Vsb is a standby supply output that is active whenever the AC power is present. This output provides a power source for circuits that must remain operational when the five main DC output rails are in a disabled state. Example uses include soft power control, Wake on LAN, wake-on-modem, intrusion detection, or suspend state activities.

The power supply must be able to provide the required power during a “wake up” event. If an external USB device generates the event, there may be peak currents as high as 3.5A, lasting no more than 500ms.

Over current protection is required on the +5Vsb output regardless of the output current rating. This ensures the power supply will not be damaged if external circuits draw more current than the supply can provide.



4.4 ◀ Power-on Time

The power-on time is defined as the time from when PS_ON# is pulled low to when the +12 VDC, +5 VDC, and +3.3 VDC outputs are within the regulation ranges specified in Section 3.1. The power-on time shall be less than 200ms ($T_1 < 200\text{ms}$). +5V_{SB} shall have a power-on time of two seconds maximum after application of valid AC voltages.

4.5 ◀ Rise Time

The output voltages shall rise from $\leq 10\%$ of nominal to within the regulation ranges specified in Section 3.1 within 0.2 ms to 20 ms ($0.2\text{ ms} \leq T_2 \leq 20\text{ ms}$).

There must be a smooth and continuous ramp of each DC output voltage from 10% to 95% of its final set-point within the regulation band, while loaded as specified in the Section 3.4. The smooth turn-on requires that, during the 10% to 95% portion of the rise time, the slope of the turn-on waveform must be positive and have a value of between 0 V/ms and $[\text{Vout, nominal} / 0.1] \text{ V/ms}$. Also, for any 5 ms segment of the 10% to 95% risetime waveform, a straight line drawn between the end points of the waveform segment must have a slope $\geq [\text{Vout, nominal} / 20] \text{ V/ms}$.

4.6 ◀ Over Shoot at Turn-on / Turn-off

The output voltage overshoot upon the application or removal of the input voltage, or the assertion/desertion of PS_ON#, under the conditions specified in Section 2.1, shall be less than 10% above the nominal voltage.

No voltage of opposite polarity shall be present on any output during turn-on or turn-off.

4.7 ◀ Reset after Shutdown


If the power supply latches into a shutdown status because of a fault condition on its outputs, the power supply shall return to normal operation only after the fault has been removed and the PS_ON# (or AC input) has been cycled OFF/ON with a minimum OFF time of 1 second.

4.8 ◀ +5V_{SB} at AC Power-down

After AC power is removed, the +5V_{SB} standby voltage output should remain at its steady state value for the minimum hold-up time specified in Section 3.10 until the output begins to decrease in voltage. The decrease shall be monotonic in nature, dropping to 0.0V. There shall be no other perturbations of this voltage at or following removal of AC power.

4.9 ◆ Power Excursion

Based on the power budgets and peak power of both the Processor detailed and the PCIe* Add-in Cards, the following Peak Power Requirements are defined for the Power Supply.



Duty cycle	Tc	Te	Power @Tc	Power @Te
5%	1900 us	100 us	531.6	825
8%	11.5 ms	1 ms	523.0	798
12.5%	70 ms	10 ms	516.7	743
25%	300 ms	100 ms	530.4	605

output voltages shall remain within the regulation ranges

Output	Range	Minimum	Nominal	Maximum	Units
+ 3.3V	$\pm 5\%$	+ 3.135	+ 3.30	+ 3.465	Volts
+ 5V	$\pm 5\%$	+ 4.75	+ 5.00	+ 5.25	Volts
+ 12V	+ 5%/-7%	+ 11.16	+ 12.00	+ 12.6	Volts
- 12V	$\pm 10\%$	- 13.20	- 12.00	- 10.80	Volts
+ 5V _{SB}	$\pm 5\%$	+ 4.75	+ 5.00	+ 5.25	Volts

5.0 ◆ Mechanical

5.1 ◆ Dimension

Mechanical specifications are to be the standard ATX12V (150mm x 140mm x 86mm).
Base on the OAD drawing define.



5.2、Airflow / Fan / Fan Speed Control

Exact CFM requirements vary by application and end-use environment, but 82-94 CFM is typical for the fan itself. The noise-sensitive applications, it is recommended that a thermally sensitive fan speed control circuit be used to balance system-level thermal and acoustic performance. The circuit typically senses the temperature of an internal heatsink and/or incoming ambient air and adjusts the fan speed as necessary to keep power supply and system component temperatures within specification.

The power supply fan should be turned off when PS_ON# is de-asserted (high). In this status, any remaining active power supply circuitry must rely only on passive convection for cooling. In general, more venting in a power supply case yields reduced airflow impedance and improved cooling performance. Intake and exhaust vents should be as large, open, and unobstructed as possible so as not to impede airflow or generate excessive acoustic noise.

5.3、DC Cables

Base on the OAD drawing define.

6.0、Environmental

The following subsections define recommended environmental specifications and test parameters, based on the typical conditions to which an ATX12V power supply may be subjected during operation or shipment.

6.1、MTBF

FSP requires the MTBF shall be meet 100,000 hours at full load condition.

The vendor shall provide test report after MP for a while.

6.2、Operation Temperature& Altitude

Temperature/Humidity	Operating	0°C / 0%RH 40°C / 90%RH
Temperature/Humidity	Storage	-20°C / 0%RH 70°C / 95%RH

- Operation Altitude: 2000 meters or 6660 ft
- Storage Altitude: 15000 meters or 50000 ft



6.3 、Mechanical Shock

Operation:

10G, 11 mS. Half-sine wave pulse in both directions on three mutually perpendicular axes.

Storage:

40G, 7 mS. Half-sine wave pulse in both directions on three mutually perpendicular axes

6.4 、Random Vibration

0.01g²/ Hz at 5 Hz, sloping to 0.02g²/ Hz at 20 Hz, and maintaining 0.02g²/ Hz from 20Hz to 500Hz. The area under the PSD curve is 3.13gRMS.

The duration shall be 10 minutes per axis for all three axes on all samples. (non-operating)

7.0 、Regulatory

7.1 、GROUND LEAKAGE CURRENT

The power supply ground leakage current shall be less than 3.5 mA.

7.2 、DIELECTRIC STRENGTH

Primary to Frame Ground : 1500Vac / 3 sec.

Primary to Secondary : 3000Vac / 60 sec.

7.3 、INSULATION RESISTANCE

Primary to Frame Ground : 20M ohm , Minimum

Primary to Secondary : 20M ohm , Minimum

7.4 、Lightning surge

Line to line: 1KV; Line to ground: 2KV

7.5 、E.M.I

EN 55032 CLASS B

7.6 、Electrostatic Discharge – ESD

8kV air discharge, 4kV Contact discharge, Performance Criterion A



8.0 Safety Requirement :

@CB

IEC 62368:2014

@TUV

EN 62368-1: 2014+A11

@KC

KC62368-1(2021-08)

@RoHs

IEC62474