

**ZIPPY TECHNOLOGY CORP.****Global Service  
Headquarter**

10F, No. 50, Minquan Rd., Xindian Dist., New Taipei City 231, TAIWAN  
 TEL : +886-2-2918-8512 FAX : +886-2-2913-4969  
 Power Division e-mail : powersales@zippy.com.tw  
 e-RMA: <http://erma.zippy.com.tw>  
 Open between 8:30 a.m. and 6:00 p.m. Local Time, Monday - Friday.

**Germany**

Zippy Technology Europe GmbH  
 Giesenheide 23, 40724 Hilden, Germany  
 TEL : +49-(0)2103-57601-00 FAX : +49-(0)2103-57601-29  
 e-mail : info@zippy-europe.com

**USA West**

Zippy USA Inc. (Pacific)  
 1 Morgan, Irvine CA 92618, USA  
 TEL : + 1-949-3669525 FAX : + 1-949-3669526  
 e-mail : powerusa@zippy.com

**USA East**

Zippy USA Inc. (Atlantic)  
 670 N. Beers Street, Bldg 2, Unit 6, Holmdel, NJ 07733, USA  
 TEL : +1-732-203-6988 FAX : +1-732-203-6989  
 E-mail : powerusa@zippy.com

**Canada**

Canada Region  
 TEL : +1-877-809-4779 ext. 132

**China**

G-Brim International Inc. 巨曜贸易（深圳）有限公司  
 深圳市宝安区西乡街道后瑞社区新瑞工业区C栋5层  
 5F Building-C, Xinrui Industry Park Hourui Community, Xixiang Street, Baoan District Shenzhen City 518128, China  
 TEL : +86-755-29778708-29778712 FAX : +86-755-29778713  
 e-mail : g-brim@zippy.com.tw

Beijing Representative Office 巨曜贸易（深圳）有限公司·北京分公司  
 北京市海淀区上地三街9号嘉华大厦E504  
 E-504 Jiahua Building, No.9 Shangdi 3 St., Haidian District, Beijing, 100085, China  
 TEL : +86-010-82743850 FAX : +86-010-82743851  
 e-mail : g-brim@zippy.com.tw

SERVER GRADE POWER GUIDE BOOK V.7

ZIPPY TECHNOLOGY CORP.

# Server Grade Power Guide Book

For the Future of Our Planet





## ***SERVER GRADE POWER***




**ZIPPY TECHNOLOGY CORP.**



## ***ZIPPY WORLDWIDE SERVICE***

**ZIPPY USA Inc.**  
New Jersey



**ZIPPY Europe GmbH**  
Germany




**G-BRIM International Corp.**  
Beijing Branch  
Beijing, China



**Headquater**  
Taiwan




**ZIPPY (Suzhou)**  
Electronics Co., Ltd.  
Suzhou, China



**Wugu Factory**  
Taiwan



**ZIPPY USA Inc.**  
California



**G-BRIM International Corp.**  
Shenzhen, China



**ZIPPY TECHNOLOGY CORP.**



## Profile

ZIPPY TECHNOLOGY CORPORATION, POWER DIVISION manufactures the well-known EMACS brand of high quality POWER SUPPLIES for file servers, industrial PC's (IPC), storage systems, workstations, blade servers, communications, and networking equipment. We are both an innovator in technology and design, creating high efficiency power supplies to substantially reduce energy costs. We continuously push ourselves to improve the functionality and the design of our power supplies for a more compact and higher output product.

## Factory

Zippy has invested a tremendous amount of time and effort in our manufacturing facility and computerized testing equipment. Our goal is to develop the highest quality products and establish the most efficient manufacturing process all while reducing production costs and meeting the demands of an ever-changing market. Our flexible production schedule allows us to make various adjustments to accommodate our customer's most urgent needs. We have achieved this by integrating our production process into a company-wide network, which allows us to meet the requirements of our customers. Our factory is located in Taipei, Taiwan, with a capacity of approximately 100,000 units per month. Zippy Technology has always emphasized its flexibility, customization, and quality.

## R&D

Our power division is particularly well known for manufacturing highly reliable and high-power redundant power supplies with outstanding quality. More than 30 professional engineers devote themselves to design and develop products with the latest equipment and testing tools. Our expertise and experience allow us to reduce the time to market for new designs, achieving lead times three to six months faster than our competitors.

## CORE TECHNOLOGY

### Passive Backplane Design

Many redundant systems utilize passive backplanes, where the components on the backplane perform monitoring and voltage compensation functions only. In the rare event of backplane failure, it is likely the supply will continue to operate.

### Modular Technology

Modular power supply units provide great flexibility in dimensionally challenged applications, when designed into today's common and custom server chassis designs.

### Load Sharing

Our redundant power supplies are all based on load sharing technology, which provide a more reliable operation and a longer life for each individual module.

### True Wattage

Our power supplies are designed to work at 100% of their specified load, indefinitely, over their lifetime. Unlike other manufacturers who often specify peak wattage which is only available in short bursts.

### Quality Control

Zippy has received EMACS' ISO-9001 Quality Certification in 1994. We strictly follow these guidelines in every aspect of our operation and also work hard to continuously improve our production system, bringing it in line with the highest of standards. We have dramatically reduced the occurrence of reworked and scrapped product as well as other production issues. All our products are tested and meet numerous international safety and EMI standards before shipping.

*Our strict quality management begins with product design, through the development and onto service and support. Our goal is always to build the safest and the most reliable product with the best professional service available. This has allowed our brand name to become a synonym for Quality throughout the world.*



ZIPPY TECHNOLOGY CORP.





## CATEGORY SPECIFICATION

EMACS, is one of the leading server-grade SMPS manufacturers, we provide instant technical support response and full scale power supply solutions for servers, cloud computing, industrial computing and various applications.

## ECO FRIENDLY

### Enabling High Efficiency Power Solutions

As an industry leading provider of OEM/ODM high efficiency power supply solutions, Zippy manufactures a broad range of green solutions for the rapidly growing green market. No matter what your sustainable objectives are, you can count on us for energy efficient and recyclable solutions.

### GO GREEN with us!

Quality Standard Certification and Compliances

1. IECQ QC080000 - Quality Assessment for Electronic Components (Electrical and Electronic Components and Products Hazardous Substance Free Standard and Requirements)
2. RoHS - 6/6 since March 2008

### Our Initiatives

- High-Efficiency Power Supplies - 84%-86% efficient compared to industry average of 65% (Gold+ compliant design in progress)
- High-Efficiency VRM designs on backplane - 85%-93% compared to industry average of 70%-80%
- 6/6 RoHS - both EU and China standards
- Maximize Packaging recyclability - separate EPE foam and cardboard to minimize contaminations
- Fan speed control design - minimizes power consumption and noise from the fan



### Cloud Power Series

Cloud computing technology ready. Zippy announced cloud computing technology for some high efficiency PSU. This technology can monitor and control cloud computing power operations anywhere via the Internet.



### Micro Redundant Power Supply

Micro redundant Power Series also can be used in 1U chassis; moreover, it is also suitable for MINI ATX and 1U Servers. Compact size with redundancy advantage.



### PMBus Solution

A smart option, to let you monitor power supply operating conditions through analog-to-digital interface.



### High Efficiency Power Supply

There are many 80 PLUS Certified Power Supply in our product lines are ready for your energy saving needs. Zippy is still in progress to develop new power-supplies with high-efficiency ratings.



### Medical Power Series

Meets Medical Power Supply requirements UL, TUV, IEC 60601. We are specialized in customized design so we could meet most updated medical application and standard quickly.



### True Redundant Power Supply

With over 20 years of design experience, EMACS Power Series delivers superior performance. Multiple outputs per module can withstand the most rigorous systems with unsurpassed reliability.



### Open Frame Power Supply

Silent and Fanless, Zippy (EMACS) Open Frame Solutions set a new industry standard in design and performance.



### Telecom Power Series

Telecom power series utilizes DC-DC power and it can be applied to all types of communications systems.

The content available in this catalog, including but not limited to all text, graphics, drawings, diagrams, photographs and compilation of data or other materials are subject to copyright owned by Zippy Technology Corp, and Zippy Technology Corp reserves the right to modify, update and change the content from time to time. Except as expressly permitted herein or where prior written authorization is obtained from Zippy Technology Corp, any reproduction, adaptation, distribution, dissemination or making available of such copyright works to the public is strictly prohibited.



## CERTIFICATE



**ISO/TS 16949**



**ERP EN62075**



**ISO 9001**



**IECQ QC 08000**



**ISO 14001**



# EFFICIENCY

EMACS introduces a wide range of high efficiency power supplies, which will further our reputation for manufacturing superior quality power supplies and reduce energy costs. Most of our newly developed power supplies have now received 80PLUS certification. For further information, please contact your nearest ZIPPY Sales Representative.



## 115V

| Model Number | Form Factor   | Wattage | Rating   |
|--------------|---------------|---------|----------|
| V2H-5435V    | 2U            | 435     | Standard |
| V2H-5350V    | 2U            | 350     | Standard |
| V2H-5400V    | 2U            | 400     | Standard |
| P1D-5600V    | ATX12V        | 600     | Standard |
| P1D-5700V    | ATX12V/ETX12V | 700     | Standard |
| PSM-5860V    | ATX12V/EP512V | 860     | Standard |
| HU2-5860V    | ATX12V/EP512V | 860     | Standard |
| V1E-5300V    | EP51U         | 300     | Standard |
| V1E-5350V    | EP51U         | 350     | Standard |
| HG2-5400V    | ATX12V        | 400     | Standard |
| GP2-5500V    | ATX12V        | 500     | Standard |
| HG2-5500V    | ATX12V        | 500     | Standard |
| HU2-5560V    | ATX12V/EP512V | 560     | Standard |
| P1H-5400V    | EP51U         | 400     | Standard |
| P1S-5300V    | EP51U         | 300     | Standard |
| P2G-5650V    | EP52U         | 650     | Standard |
| P2G-5500V    | EP52U         | 500     | Standard |
| P2H-5400V    | EP52U         | 400     | Standard |
| P2M-5600V    | EP52U         | 600     | Standard |
| P2M-5700V    | EP52U         | 700     | Standard |
| P2M-5800V    | EP52U         | 800     | Standard |
| H1U-5320V    | EP51U         | 320     | Standard |
| P1S-6300V    | 1U            | 300     | Standard |
| PSM-5760V    | ATX12V/EP512V | 760     | Bronze   |
| PSM-5660V    | ATX12V/EP512V | 660     | Bronze   |
| HU2-5760V    | ATX12V/EP512V | 760     | Bronze   |
| V1E-5250V    | EP51U         | 250     | Bronze   |
| GP2-5600V    | ATX12V        | 600     | Bronze   |
| HG2-5600V    | ATX12V        | 600     | Bronze   |
| H1U-5300V    | 1U            | 300     | Bronze   |
| HU2-5660V    | ATX12V/EP512V | 660     | Bronze   |
| P1H-5500V    | EP51U         | 500     | Bronze   |
| P1H-5550V    | EP51U         | 550     | Bronze   |
| P2G-5600V    | EP52U         | 600     | Bronze   |
| P2H-5550V    | EP52U         | 550     | Bronze   |
| P2H-5500V    | EP52U         | 500     | Bronze   |
| Y1U-5650V    | ATX12V        | 650     | Bronze   |
| PSL-6A00V    | ATX12V        | 1000    | Bronze   |
| H1M-5607V    | EP512V 1U     | 600     | Bronze   |
| H1M-5707V    | EP512V 1U     | 700     | Bronze   |
| PSL-6C00V    | ATX12V        | 1200    | Silver   |
| P1H-5500G    | 1U            | 500     | Gold     |
| P2G-5600G    | 2U            | 600     | Gold     |
| P2G-5500G    | 2U            | 500     | Gold     |
| P1H-5420E    | 1U            | 420     | Gold     |
| P1H-5420G    | 1U            | 420     | Gold     |
| P1H-5500K    | 1U            | 500     | Platinum |
| P1U-5520K    | 1U            | 520     | Platinum |

## 230V

| Model Number | Form Factor         | Wattage | Rating   |
|--------------|---------------------|---------|----------|
| MTW-5660V    | 1U 230V EU Internal | 660     | Standard |
| C2W-3620V-R  | 1U 230V Internal    | 620     | Bronze   |
| R1S-1120V    | 1U 230V Internal    | 120     | Bronze   |
| MRW-3500V-R  | Custom              | 500     | Bronze   |
| M1Y-2152V    | 1U 230V Internal    | 150     | Bronze   |
| P1S-2400V    | 1U 230V Internal    | 400     | Silver   |
| GIN-3800V    | 1U 230V Internal    | 800     | Silver   |
| GIN-3600V    | 1U 230V Internal    | 600     | Silver   |
| GIN-3500V    | 1U 230V Internal    | 500     | Silver   |
| M1W-2810V    | 1U 230V Internal    | 810     | Silver   |
| G1W-3660V    | 1U 230V Internal    | 660     | Silver   |
| MRW-3600V-R  | Custom              | 600     | Silver   |
| P1S-2500V    | 1U 230V Internal    | 500     | Silver   |
| M1P-2500V    | 1U 230V Internal    | 500     | Silver   |
| T1W-3A10V    | 1U 230V Internal    | 1010    | Silver   |
| G1W-3760V    | 1U 230V Internal    | 760     | Silver   |
| M1S-3501V    | 1U 230V Internal    | 500     | Silver   |
| KIN-2800V    | 1U 230V Internal    | 800     | Gold     |
| PSG-2A00V    | 1U 230V Internal    | 1000    | Gold     |
| PSS-2A00V    | 1U 230V Internal    | 1000    | Gold     |
| G1W-3960V    | 1U 230V Internal    | 960     | Gold     |
| G1W-3A10V    | 1U 230V Internal    | 1010    | Gold     |
| M1W-2A10V    | 1U 230V Internal    | 1010    | Gold     |
| M1W-2C00V    | 1U 230V Internal    | 1200    | Gold     |
| M1W-2E00V    | 1U 230V Internal    | 1400    | Gold     |
| C2W-3820V-R  | 1U 230V Internal    | 820     | Gold     |
| PSS-2E00V    | 1U 230V Internal    | 1400    | Gold     |
| PSS-2C00V    | 1U 230V Internal    | 1200    | Gold     |
| M1W-2600G    | 1U 230V Internal    | 600     | Gold     |
| M1W-2650G    | 1U 230V Internal    | 650     | Gold     |
| M1W-2700G    | 1U 230V Internal    | 700     | Gold     |
| M1K-2C00V    | 1U 230V Internal    | 1200    | Gold     |
| M1U-2750V    | 1U 230V Internal    | 750     | Gold     |
| MRT-2320G-R  | Custom              | 320     | Gold     |
| MRT-2450G-R  | Custom              | 450     | Gold     |
| MRW-3600G-R  | Custom              | 600     | Gold     |
| G1W-3762V    | 1U 230V Internal    | 760     | Gold     |
| G1W-3862V    | 1U 230V Internal    | 860     | Gold     |
| M1Y-2302G    | 1U 230V Internal    | 300     | Gold     |
| M1Y-2222G    | 1U 230V Internal    | 220     | Gold     |
| M1W-2700K    | 1U 230V Internal    | 700     | Platinum |
| P1P-2600K    | 1U 230V Internal    | 600     | Platinum |
| Q1N-2400K    | 1U 230V Internal    | 400     | Platinum |
| M1R-2500G    | 1U 230V Internal    | 500     | Platinum |
| M1Y-2302K    | 1U 230V Internal    | 300     | Platinum |
| M1D-2500G    | 1U 230V Internal    | 500     | Platinum |
| M1D-2800V    | 1U 230V Internal    | 800     | Platinum |

# Power index

How to use this guide book

01

Use the simplified index from **Page 10** to find the desirable form factor, wattage and dimensions. Then follow the page number indicated to check the specification details.

02

If you do not find what you are looking for from the simplified index, please turn to **Page 190** where you will find a detailed index from **Page 190-197**. If you are already our client and need a replacement for a redundant module, please turn to **Page 200 <Module Details>** for the relevant information.

03

Alternatively you can either visit our website **www.zippy.com** to look for your desired power supply, or email us your enquiry via **powersales@zippy.com.tw**. We welcome any feedback or advice on our products or guidebook, which you can share with us by email.



| FORM FACTOR | MODEL NAME    | WATTAGE | INPUT     | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) | Page |
|-------------|---------------|---------|-----------|----------------|----------------|----------------|------|
| 1U          | MQ1G-1035V-40 | 35W     | AC90-240V | 101.6 / 4      | 50.8 / 2       | 30 / 1.18      | 18   |
| 1U          | MQ1G-1050V-5  | 50W     | AC90-240V | 101.6 / 4      | 50.8 / 2       | 30 / 1.18      | 19   |
| 1U          | MQ1G-1060V-12 | 60W     | AC90-240V | 101.6 / 4      | 50.8 / 2       | 30 / 1.18      | 20   |
| 1U          | MQ1G-1060V-24 | 60W     | AC90-240V | 101.6 / 4      | 50.8 / 2       | 30 / 1.18      | 20   |
| 1U          | MQ1G-1060V-40 | 60W     | AC90-240V | 101.6 / 4      | 50.8 / 2       | 30 / 1.18      | 20   |
| 1U          | MQ1G-1060V-48 | 60W     | AC90-240V | 101.6 / 4      | 50.8 / 2       | 30 / 1.18      | 20   |
| 1U          | MQ1D-5120V    | 120W    | PFC       | 190 / 7.48     | 83.8 / 3.3     | 40 / 1.57      | 21   |
| Mini 1U     | MP1S-5220V    | 220W    | PFC       | 190 / 7.48     | 81.5 / 3.21    | 40.3 / 1.59    | 22   |
| Mini 1U     | MP1S-5300V    | 300W    | PFC       | 190 / 7.48     | 81.5 / 3.21    | 40.3 / 1.59    | 22   |
| Mini 1U     | MP1S-6400V    | 400W    | PFC       | 250 / 9.84     | 81.5 / 3.21    | 40.3 / 1.59    | 23   |
| 1U          | MV1E-5350V    | 350W    | PFC       | 260 / 10.24    | 100 / 3.94     | 40.5 / 1.59    | 24   |
| 2U          | MP2M-5435V    | 435W    | PFC       | 270 / 10.63    | 100 / 3.94     | 70 / 2.76      | 25   |
| PS2         | MHG2-6300P    | 300W    | PFC       | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 26   |
| PS2         | MHG2-6350P    | 350W    | PFC       | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 26   |
| PS2         | MHG2-6400P    | 400W    | PFC       | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 26   |
| PS2         | MHU2-5400V    | 400W    | PFC       | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 27   |
| PS2         | MPSM-5500V    | 500W    | PFC       | 160 / 6.3      | 150 / 5.91     | 86 / 3.39      | 28   |
| PS2         | MPSM-5600V    | 600W    | PFC       | 160 / 6.3      | 150 / 5.91     | 86 / 3.39      | 28   |
| 1U          | Q1P-1052V19   | 50W     | AC90-240V | 94.5 / 3.72    | 39.5 / 1.56    | 32 / 1.26      | 29   |
| 1U          | Q1L-5060V     | 60W     | AC90-240V | 176 / 6.93     | 39 / 1.54      | 39 / 1.54      | 30   |
| 1U          | Q1J-1050V-5   | 50W     | AC90-240V | 103 / 4.06     | 52 / 2.05      | 39 / 1.54      | 31   |
| 1U          | Q1J-1060V-12  | 60W     | AC90-240V | 103 / 4.06     | 52 / 2.05      | 39 / 1.54      | 31   |
| 1U          | Q1J-1060V-24  | 60W     | AC90-240V | 103 / 4.06     | 52 / 2.05      | 39 / 1.54      | 31   |
| 1U          | Q1J-1060V-48  | 60W     | AC90-240V | 103 / 4.06     | 52 / 2.05      | 39 / 1.54      | 31   |
| 1U          | Q1I-1060V12   | 60W     | AC90-240V | 114.5 / 4.51   | 50.8 / 2       | 38 / 1.5       | 32   |
| 1U          | Q1I-2050V53   | 50W     | AC90-240V | 114.5 / 4.51   | 50.8 / 2       | 38 / 1.5       | 32   |
| 1U          | Q1I-2060V123  | 60W     | AC90-240V | 114.5 / 4.51   | 50.8 / 2       | 38 / 1.5       | 32   |
| 1U          | Q1I-2060V125  | 60W     | AC90-240V | 114.5 / 4.51   | 50.8 / 2       | 38 / 1.5       | 32   |
| 1U          | Q1H-5060V     | 60W     | AC90-240V | 126 / 4.96     | 55 / 2.17      | 39 / 1.54      | 33   |
| 1U          | Q1Q-1060V12   | 60W     | AC90-240V | 137 / 5.4      | 50 / 1.97      | 32 / 1.26      | 34   |
| 1U          | Q1O-1060V12   | 60W     | AC90-240V | 127.5 / 5.02   | 56 / 2.2       | 32 / 1.26      | 35   |
| 1U          | Q1F-1150V12   | 150W    | PFC       | 125 / 4.92     | 76.2 / 3       | 39 / 1.54      | 36   |
| 1U          | Q1F-1150V24   | 150W    | PFC       | 125 / 4.92     | 76.2 / 3       | 39 / 1.54      | 36   |
| 1U          | Q1F-1150V48   | 150W    | PFC       | 125 / 4.92     | 76.2 / 3       | 39 / 1.54      | 36   |
| 1U          | Q1F-2150V123  | 150W    | PFC       | 125 / 4.92     | 76.2 / 3       | 39 / 1.54      | 37   |
| 1U          | Q1F-2150V125  | 150W    | PFC       | 125 / 4.92     | 76.2 / 3       | 39 / 1.54      | 37   |
| 1U          | Q1F-3150V     | 150W    | PFC       | 127 / 5        | 76.2 / 3       | 39 / 1.54      | 38   |
| 1U          | Q1D-5120V     | 120W    | PFC       | 165 / 6.5      | 83.8 / 3.3     | 39 / 1.54      | 39   |
| 1U          | Q1K-5150V     | 150W    | PFC       | 186 / 7.32     | 100 / 3.94     | 39.5 / 1.56    | 40   |
| 1U          | Q1K-5200V     | 200W    | PFC       | 186 / 7.32     | 100 / 3.94     | 39.5 / 1.56    | 40   |
| 1U          | Q1N-2400K     | 400W    | PFC       | 199 / 7.83     | 92 / 3.62      | 43 / 1.69      | 41   |
| 1U          | Q1N-3400K     | 400W    | PFC       | 199 / 7.83     | 92 / 3.62      | 43 / 1.69      | 41   |

| FORM FACTOR  | MODEL NAME    | WATTAGE | INPUT    | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) | Page |
|--------------|---------------|---------|----------|----------------|----------------|----------------|------|
| 1U           | Q1S-1150V12   | 150W    | PFC      | 127 / 5        | 76.2 / 3       | 39.6 / 1.56    | 42   |
| 1U           | Q1S-1150V24   | 150W    | PFC      | 127 / 5        | 76.2 / 3       | 39.6 / 1.56    | 42   |
| 1U           | Q1S-1150V48   | 150W    | PFC      | 127 / 5        | 76.2 / 3       | 39.6 / 1.56    | 42   |
| 1U Module    | G1X-1060V12   | 60W     | PFC      | 135 / 5.31     | 50.5 / 1.99    | 38 / 1.5       | 43   |
| 1U Redundant | G1X2-1060V12  | 60W     | PFC      | 190 / 7.48     | 106 / 4.17     | 39.5 / 1.56    | 44   |
| 1U Redundant | G1X2-5060V    | 60W     | PFC      | 190 / 7.48     | 106 / 4.17     | 39.5 / 1.56    | 45   |
| 1U Redundant | DG1X-1060V12  | 60W     | PFC      | 135 / 5.31     | 50.5 / 1.99    | 38 / 1.5       | 46   |
| 1U Redundant | DG1X2-1060V12 | 60W     | PFC      | 190 / 7.48     | 106 / 4.17     | 39.5 / 1.56    | 47   |
| 1U Redundant | DG1X2-5060V   | 60W     | PFC      | 190 / 7.48     | 106 / 4.17     | 39.5 / 1.56    | 48   |
| 1U Redundant | RH1E-1060V    | 60W     | PFC      | 147 / 5.79     | 96 / 3.78      | 36 / 1.42      | 49   |
| DC 1U        | AN1U-5150V    | 150W    | DC 12V   | 40.5 / 1.59    | 100 / 3.94     | 20.6 / 0.81    | 50   |
| DC 1U        | AN1P-5400V    | 400W    | DC 12V   | 70 / 2.76      | 81.5 / 3.21    | 40 / 1.57      | 51   |
| DC 1U        | AB1U-5120V    | 120W    | DC10~36V | 152 / 5.98     | 83.8 / 3.3     | 38 / 1.5       | 52   |
| DC 1U        | BB1U-6150V    | 150W    | DC18~36V | 152 / 5.98     | 83.8 / 3.3     | 38 / 1.5       | 53   |
| Mini 1U      | P1S-5300G     | 300W    | PFC      | 150 / 5.91     | 81.5 / 3.21    | 40.3 / 1.59    | 54   |
| Mini 1U      | P1S-2300V19   | 300W    | PFC      | 150 / 5.91     | 81.5 / 3.21    | 40.3 / 1.59    | 55   |
| Mini 1U      | P1S-2300V     | 300W    | PFC      | 150 / 5.91     | 81.5 / 3.21    | 40.3 / 1.59    | 56   |
| Mini 1U      | P1S-2400V     | 400W    | PFC      | 150 / 5.91     | 81.5 / 3.21    | 40.3 / 1.59    | 56   |
| Mini 1U      | P1S-2500V     | 500W    | PFC      | 150 / 5.91     | 81.5 / 3.21    | 40.3 / 1.59    | 56   |
| Mini 1U      | P1P-5400V     | 400W    | PFC      | 170 / 6.69     | 81.5 / 3.21    | 40.3 / 1.59    | 57   |
| Mini 1U      | P1P-5401V     | 400W    | PFC      | 170 / 6.69     | 81.5 / 3.21    | 40.3 / 1.59    | 57   |
| Mini 1U      | P1P-2600K     | 600W    | PFC      | 170 / 6.69     | 81.5 / 3.21    | 40.3 / 1.59    | 58   |
| Mini 1U      | P1P-2600G     | 600W    | PFC      | 170 / 6.69     | 81.5 / 3.21    | 40.3 / 1.59    | 59   |
| Mini 1U      | P1P-2600K     | 600W    | PFC      | 170 / 6.69     | 81.5 / 3.21    | 40.3 / 1.59    | 59   |
| 1U           | H1U-5300V     | 300W    | PFC      | 155 / 6.1      | 100 / 3.94     | 40 / 1.57      | 60   |
| 1U           | H1U-5320V     | 320W    | PFC      | 155 / 6.1      | 100 / 3.94     | 40 / 1.57      | 60   |
| 1U           | P1U-5400E     | 400W    | PFC      | 190 / 7.48     | 100 / 3.94     | 40 / 1.57      | 61   |
| 1U           | P1U-5520K     | 520W    | PFC      | 190 / 7.48     | 100 / 3.94     | 40 / 1.57      | 62   |
| 1U           | P1H-5400V     | 400W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 63   |
| 1U           | P1H-5500V     | 500W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 63   |
| 1U           | P1H-5550V     | 550W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 63   |
| 1U           | P1H-5501V     | 500W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 63   |
| 1U           | P1H-5551V     | 550W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 63   |
| 1U           | P1H-5407V     | 400W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 64   |
| 1U           | P1H-5507V     | 500W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 64   |
| 1U           | P1H-5557V     | 550W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 64   |
| 1U           | P1H-5420G     | 420W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 65   |
| 1U           | P1H-5500G     | 500W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 65   |
| 1U           | P1H-5420E     | 420W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 66   |
| 1U           | P1H-5500E     | 500W    | PFC      | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 66   |
| 1U           | V1E-5250V     | 250W    | PFC      | 210 / 8.27     | 100 / 3.94     | 40.5 / 1.59    | 67   |
| 1U           | V1E-5300V     | 300W    | PFC      | 210 / 8.27     | 100 / 3.94     | 40.5 / 1.59    | 67   |



| FORM FACTOR     | MODEL NAME   | WATTAGE | INPUT | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) | Page |
|-----------------|--------------|---------|-------|----------------|----------------|----------------|------|
| 1U              | V1E-5350V    | 350W    | PFC   | 210 / 8.27     | 100 / 3.94     | 40.5 / 1.59    | 67   |
| 1U              | H1M-5350V    | 350W    | PFC   | 242 / 9.53     | 100 / 3.94     | 40.5 / 1.59    | 68   |
| 1U              | H1M-5600V    | 600W    | PFC   | 250 / 9.84     | 100 / 3.94     | 40.5 / 1.59    | 69   |
| 1U              | H1M-5700V    | 700W    | PFC   | 250 / 9.84     | 100 / 3.94     | 40.5 / 1.59    | 69   |
| 1U              | H1M-5800V    | 800W    | PFC   | 250 / 9.84     | 100 / 3.94     | 40.5 / 1.59    | 69   |
| 1U              | H1M-5607V    | 600W    | PFC   | 275 / 10.83    | 100 / 3.94     | 40.5 / 1.59    | 70   |
| 1U              | H1M-5707V    | 700W    | PFC   | 275 / 10.83    | 100 / 3.94     | 40.5 / 1.59    | 70   |
| 1U              | H1M-5807V    | 800W    | PFC   | 275 / 10.83    | 100 / 3.94     | 40.5 / 1.59    | 70   |
| 1U              | P1D-5400V    | 400W    | PFC   | 300 / 11.81    | 100 / 3.94     | 40.5 / 1.59    | 71   |
| 1U              | P1D-5600V    | 600W    | PFC   | 300 / 11.81    | 100 / 3.94     | 40.5 / 1.59    | 71   |
| 1U              | P1D-5700V    | 700W    | PFC   | 300 / 11.81    | 100 / 3.94     | 40.5 / 1.59    | 71   |
| 1U              | P1D-3940V    | 940W    | PFC   | 300 / 11.81    | 100 / 3.94     | 40.5 / 1.59    | 72   |
| 1U              | H1W-5AD0V    | 1400W   | PFC   | 295 / 11.61    | 100 / 3.94     | 40 / 1.57      | 73   |
| 2U              | P2H-5400V    | 400W    | PFC   | 215 / 8.46     | 100 / 3.94     | 70 / 2.76      | 74   |
| 2U              | P2H-5500V    | 500W    | PFC   | 215 / 8.46     | 100 / 3.94     | 70 / 2.76      | 74   |
| 2U              | P2H-5550V    | 550W    | PFC   | 215 / 8.46     | 100 / 3.94     | 70 / 2.76      | 74   |
| 2U              | P2H-5501V    | 500W    | PFC   | 215 / 8.46     | 100 / 3.94     | 70 / 2.76      | 74   |
| 2U              | P2G-5500G    | 500W    | PFC   | 240 / 9.45     | 100/3.94       | 70/2.76        | 75   |
| 2U              | P2G-5600G    | 600W    | PFC   | 240 / 9.45     | 100/3.94       | 70/2.76        | 75   |
| 2U              | P2G-5650G    | 650W    | PFC   | 240 / 9.45     | 100/3.94       | 70/2.76        | 75   |
| 2U              | P2M-5600V    | 600W    | PFC   | 280 / 11.02    | 100 / 3.94     | 70 / 2.76      | 76   |
| 2U              | P2M-5700V    | 700W    | PFC   | 280 / 11.02    | 100 / 3.94     | 70 / 2.76      | 76   |
| 2U              | P2M-5800V    | 800W    | PFC   | 280 / 11.02    | 100 / 3.94     | 70 / 2.76      | 76   |
| PS2             | HG2-5400V    | 400W    | PFC   | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 77   |
| PS2             | HG2-5500V    | 500W    | PFC   | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 77   |
| PS2             | HG2-5600V    | 600W    | PFC   | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 77   |
| PS2             | HG2-5400E    | 400W    | PFC   | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 78   |
| PS2             | HG2-5500E    | 500W    | PFC   | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 78   |
| PS2             | HG2-5600E    | 600W    | PFC   | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 78   |
| PS2             | HU2-5560V    | 560W    | PFC   | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 79   |
| PS2             | HU2-5660V    | 660W    | PFC   | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 79   |
| PS2             | HU2-5760V    | 760W    | PFC   | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 79   |
| PS2             | HU2-5860V    | 860W    | PFC   | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 79   |
| PS2+            | PSM-5660V    | 660W    | PFC   | 160 / 6.3      | 150 / 5.91     | 86 / 3.39      | 80   |
| PS2+            | PSM-5760V    | 760W    | PFC   | 160 / 6.3      | 150 / 5.91     | 86 / 3.39      | 80   |
| PS2+            | PSM-5860V    | 860W    | PFC   | 160 / 6.3      | 150 / 5.91     | 86 / 3.39      | 80   |
| PS2+            | PSL-6A00V    | 1000W   | PFC   | 220 / 8.66     | 150 / 5.91     | 86 / 3.39      | 81   |
| PS2+            | PSL-6C00V    | 1200W   | PFC   | 220 / 8.66     | 150 / 5.91     | 86 / 3.39      | 81   |
| Micro Redundant | R1T2-5120V0H | 120W    | PFC   | 215 / 8.46     | 106 / 4.17     | 41.5 / 1.63    | 82   |
| Micro Redundant | R1T2-5120VFH | 120W    | PFC   | 215 / 8.46     | 106 / 4.17     | 41.5 / 1.63    | 83   |
| Micro Redundant | R1U2-5220V4H | 220W    | PFC   | 260 / 10.24    | 106 / 4.17     | 41.3 / 1.63    | 84   |
| Micro Redundant | R1V2-5275V4H | 275W    | PFC   | 295 / 11.61    | 106 / 4.17     | 41.3 / 1.63    | 85   |

| FORM FACTOR     | MODEL NAME   | WATTAGE | INPUT | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) | Page |
|-----------------|--------------|---------|-------|----------------|----------------|----------------|------|
| Micro Redundant | M1Y2-5300G2H | 300W    | PFC   | 275 / 10.83    | 106 / 4.17     | 41.3 / 1.63    | 86   |
| Micro Redundant | M1Y2-5300K2H | 300W    | PFC   | 275 / 10.83    | 106 / 4.17     | 41.3 / 1.63    | 86   |
| Micro Redundant | M1R2-5300V0H | 300W    | PFC   | 295 / 11.61    | 106 / 4.17     | 41.3 / 1.63    | 87   |
| Micro Redundant | M1R2-5400V0H | 400W    | PFC   | 295 / 11.61    | 106 / 4.17     | 41.3 / 1.63    | 87   |
| Micro Redundant | M1R2-5500G0H | 500W    | PFC   | 295 / 11.61    | 106 / 4.17     | 41.3 / 1.63    | 88   |
| Micro Redundant | M1S2-5600G2H | 600W    | PFC   | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 89   |
| Micro Redundant | M1V2-5800V4H | 800W    | PFC   | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 90   |
| Micro Redundant | M1V2-5801V4H | 800W    | PFC   | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 90   |
| Micro Redundant | M1U2-5650V4H | 650W    | PFC   | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 91   |
| Micro Redundant | M1U2-5750V4H | 750W    | PFC   | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 91   |
| Micro Redundant | M1U2-5651V4H | 650W    | PFC   | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 91   |
| Micro Redundant | M1U2-5751V4H | 750W    | PFC   | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 91   |
| Micro Redundant | M1K2-5A00V4H | 1000W   | PFC   | 400 / 15.75    | 106 / 4.17     | 41.3 / 1.63    | 92   |
| Micro Redundant | M1K2-5C00V4H | 1200W   | PFC   | 400 / 15.75    | 106 / 4.17     | 41.3 / 1.63    | 92   |
| Micro Redundant | M1K2-5A01V4H | 1000W   | PFC   | 400 / 15.75    | 106 / 4.17     | 41.3 / 1.63    | 92   |
| Micro Redundant | M1K2-5C01V4H | 1200W   | PFC   | 400 / 15.75    | 106 / 4.17     | 41.3 / 1.63    | 92   |
| 1U Redundant    | M1P2-5300V4H | 300W    | PFC   | 230 / 9.06     | 176 / 6.93     | 41.8 / 1.65    | 93   |
| 1U Redundant    | M1P2-5420V4H | 420W    | PFC   | 230 / 9.06     | 176 / 6.93     | 41.8 / 1.65    | 93   |
| 1U Redundant    | M1P2-5500V4H | 500W    | PFC   | 230 / 9.06     | 176 / 6.93     | 41.8 / 1.65    | 93   |
| 1U Redundant    | R1S2-5120V0H | 120W    | PFC   | 150 / 5.91     | 176 / 6.93     | 41.8 / 1.65    | 94   |
| 1U Redundant    | R1S2-5180V4H | 180W    | PFC   | 230 / 9.06     | 176 / 6.93     | 41.8 / 1.65    | 95   |
| 1U Redundant    | R1S2-5300V4H | 300W    | PFC   | 230 / 9.06     | 176 / 6.93     | 41.8 / 1.65    | 95   |
| 1U Redundant    | R1S2-5380V4H | 380W    | PFC   | 230 / 9.06     | 176 / 6.93     | 41.8 / 1.65    | 95   |
| 1U Redundant    | G1W2-5760V3H | 760W    | PFC   | 330 / 12.99    | 206 / 8.11     | 41.5 / 1.63    | 96   |
| 1U Redundant    | RP1U-5240V   | 240W    | PFC   | 270 / 10.63    | 100 / 3.94     | 40.5 / 1.59    | 97   |
| 2U Redundant    | M1V2-5800V4V | 800W    | PFC   | 400 / 15.75    | 54.5 / 2.15    | 84.6 / 3.33    | 98   |
| 2U Redundant    | M1V2-5801V4V | 800W    | PFC   | 400 / 15.75    | 54.5 / 2.15    | 84.6 / 3.33    | 98   |
| 2U Redundant    | M1V2-5807V4D | 800W    | PFC   | 450 / 17.72    | 54.5 / 2.15    | 84.6 / 3.33    | 99   |
| 2U Redundant    | M1V2-5807V4D | 800W    | PFC   | 450 / 17.72    | 54.5 / 2.15    | 84.6 / 3.33    | 99   |
| 2U Redundant    | M1U2-5650V4V | 650W    | PFC   | 400 / 15.75    | 54.5 / 2.15    | 84.6 / 3.33    | 100  |
| 2U Redundant    | M1U2-5750V4V | 750W    | PFC   | 400 / 15.75    | 54.5 / 2.15    | 84.6 / 3.33    | 100  |
| 2U Redundant    | M1U2-5651V4V | 650W    | PFC   | 400 / 15.75    | 54.5 / 2.15    | 84.6 / 3.33    | 100  |
| 2U Redundant    | M1U2-5751V4V | 750W    | PFC   | 400 / 15.75    | 54.5 / 2.15    | 84.6 / 3.33    | 100  |
| 2U Redundant    | M1K2-5A00V4V | 1000W   | PFC   | 425 / 16.73    | 54.5 / 2.15    | 84.6 / 3.33    | 101  |
| 2U Redundant    | M1K2-5C00V4V | 1200W   | PFC   | 425 / 16.73    | 54.5 / 2.15    | 84.6 / 3.33    | 101  |
| 2U Redundant    | M1K2-5A01V4V | 1000W   | PFC   | 425 / 16.73    | 54.5 / 2.15    | 84.6 / 3.33    | 101  |
| 2U Redundant    | M1K2-5C01V4V | 1200W   | PFC   | 425 / 16.73    | 54.5 / 2.15    | 84.6 / 3.33    | 101  |
| 2U Redundant    | M1K2-2C00V4D | 1200W   | PFC   | 450 / 17.72    | 54.5 / 2.15    | 84.6 / 3.33    | 102  |
| 2U Redundant    | M1K2-2C00V4Q | 1200W   | PFC   | 450 / 19.69    | 54.5 / 2.15    | 84.6 / 3.33    | 103  |
| 2U Redundant    | M1H2-5AD0V0V | 1400W   | PFC   | 442 / 17.4     | 54.5 / 2.15    | 84.6 / 3.33    | 104  |
| 2U Redundant    | M1K2-2A07V4D | 1000W   | PFC   | 485 / 19.69    | 54.5 / 2.15    | 84.6 / 3.33    | 105  |
| 2U Redundant    | PSS2-5A00V3V | 1000W   | PFC   | 385 / 15.16    | 65 / 2.56      | 84 / 3.31      | 106  |



| FORM FACTOR  | MODEL NAME   | WATTAGE | INPUT   | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) | Page |
|--------------|--------------|---------|---------|----------------|----------------|----------------|------|
| 2U Redundant | R1S2-5120V0V | 120W    | PFC     | 150 / 5.91     | 85 / 3.35      | 84 / 3.31      | 107  |
| 2U Redundant | R1S2-5300V4V | 300W    | PFC     | 207 / 8.15     | 85 / 3.35      | 84 / 3.31      | 108  |
| 2U Redundant | R1S2-5380V4V | 380W    | PFC     | 207 / 8.15     | 85 / 3.35      | 84 / 3.31      | 108  |
| 2U Redundant | R1S2-5507V4V | 500W    | PFC     | 217 / 8.54     | 85 / 3.35      | 84 / 3.31      | 109  |
| 2U Redundant | M1P2-5300V4V | 300W    | PFC     | 217 / 8.54     | 85 / 3.35      | 84 / 3.31      | 110  |
| 2U Redundant | M1P2-5420V4V | 420W    | PFC     | 217 / 8.54     | 85 / 3.35      | 84 / 3.31      | 110  |
| 2U Redundant | M1P2-5500V4V | 500W    | PFC     | 217 / 8.54     | 85 / 3.35      | 84 / 3.31      | 110  |
| 2U Redundant | M1D2-5300V0V | 300W    | PFC     | 170 / 6.69     | 101.2 / 3.98   | 84 / 3.31      | 111  |
| 2U Redundant | M1D2-5400V0V | 400W    | PFC     | 170 / 6.69     | 101.2 / 3.98   | 84 / 3.31      | 111  |
| 2U Redundant | M1D2-5500G0V | 500W    | PFC     | 170 / 6.69     | 101.2 / 3.98   | 84 / 3.31      | 111  |
| 2U Redundant | M1D2-5600V0V | 600W    | PFC     | 200 / 7.87     | 101.2 / 3.98   | 84 / 3.31      | 112  |
| 2U Redundant | M1D2-5700V0V | 700W    | PFC     | 200 / 7.87     | 101.2 / 3.98   | 84 / 3.31      | 112  |
| 2U Redundant | M1D2-5800V0V | 800W    | PFC     | 200 / 7.87     | 101.2 / 3.98   | 84 / 3.31      | 112  |
| 2U Redundant | M1W2-5600G0V | 600W    | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 113  |
| 2U Redundant | M1W2-5700G0V | 700W    | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 113  |
| 2U Redundant | M1W2-5700K0V | 700W    | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 114  |
| 2U Redundant | M1W2-5810V3V | 810W    | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 115  |
| 2U Redundant | M1W2-5910V3V | 910W    | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 115  |
| 2U Redundant | M1W2-5A10V3V | 1010W   | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 115  |
| 2U Redundant | M1W2-5E00V3V | 1400W   | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 115  |
| 2U Redundant | M1W2-5E01V3V | 1400W   | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 115  |
| 2U Redundant | M1W2-5911V3V | 910W    | PFC     | 320 / 11.27    | 101.2 / 3.98   | 84 / 3.31      | 116  |
| 2U Redundant | M1W2-7AG0V0V | 1700W   | PFC     | 330 / 12.2     | 101.2 / 3.98   | 84 / 3.31      | 117  |
| 2U Redundant | G1W2-5660V3V | 660W    | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 118  |
| 2U Redundant | G1W2-5760V3V | 760W    | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 118  |
| 2U Redundant | G1W2-5860V3V | 860W    | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 118  |
| 2U Redundant | G1W2-5960V3V | 960W    | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 118  |
| 2U Redundant | G1W2-5760V2V | 760W    | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 119  |
| 2U Redundant | G1W2-5860V2V | 860W    | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 119  |
| 2U Redundant | G1W2-5A10V2V | 1010W   | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 119  |
| 2U Redundant | G1W2-5C00V2V | 1200W   | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 119  |
| 2U Redundant | G1W2-5A10V3V | 1010W   | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 120  |
| 2U Redundant | G1W2-5C00V3V | 1200W   | PFC     | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 120  |
| 2U Redundant | G1W2-5AE0G2V | 1500W   | PFC     | 300 / 11.81    | 101 / 3.98     | 84 / 3.31      | 121  |
| 2U Redundant | MTW2-5960V2V | 960W    | PFC     | 300 / 11.81    | 101 / 3.98     | 84 / 3.31      | 122  |
| 2U Redundant | MTW2-5AD0B2V | 1400W   | PFC     | 300 / 11.81    | 101 / 3.98     | 84 / 3.31      | 123  |
| 2U Redundant | R2K-5800V    | 800W    | PFC     | 340 / 13.39    | 101 / 3.98     | 82 / 3.23      | 124  |
| 2U Redundant | R2K-5A00V    | 1000W   | AC 240V | 340 / 13.39    | 101 / 3.98     | 82 / 3.23      | 124  |
| 2U Redundant | R2K-5C00V    | 1200W   | PFC     | 340 / 13.39    | 101 / 3.98     | 82 / 3.23      | 124  |
| 2U Redundant | R2K-5800V4D  | 800W    | PFC     | 397 / 15.63    | 101 / 3.98     | 82 / 3.23      | 125  |
| 2U Redundant | PRP-5560G0V  | 560W    | PFC     | 217 / 8.54     | 85 / 3.35      | 84 / 3.31      | 126  |
| 2U Redundant | S1Z2-5800K2V | 800W    | PFC     | 240 / 9.45     | 85 / 3.35      | 83 / 3.27      | 127  |

| FORM FACTOR     | MODEL NAME   | WATTAGE | INPUT | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) | Page |
|-----------------|--------------|---------|-------|----------------|----------------|----------------|------|
| 2U Redundant    | S1Z2-5700K2V | 700W    | PFC   | 240 / 9.45     | 85 / 3.35      | 83 / 3.27      | 127  |
| 2U Redundant    | S1Z2-5600K2V | 600W    | PFC   | 240 / 9.45     | 85 / 3.35      | 83 / 3.27      | 127  |
| Mini Redundant  | MRT-5320G0V  | 320W    | PFC   | 185 / 7.28     | 150 / 5.91     | 86 / 3.39      | 128  |
| Mini Redundant  | MRT-5450G0V  | 450W    | PFC   | 185 / 7.28     | 150 / 5.91     | 86 / 3.39      | 128  |
| Mini Redundant  | MRW-5450V4V  | 450W    | PFC   | 185 / 7.28     | 150 / 5.91     | 86 / 3.39      | 128  |
| Mini Redundant  | MRW-5500V4V  | 500W    | PFC   | 185 / 7.28     | 150 / 5.91     | 86 / 3.39      | 129  |
| Mini Redundant  | MRW-5600V4V  | 600W    | PFC   | 185 / 7.28     | 150 / 5.91     | 86 / 3.39      | 129  |
| Mini Redundant  | MRG-5700V4V  | 700W    | PFC   | 200 / 7.87     | 150 / 5.91     | 86 / 3.39      | 130  |
| Mini Redundant  | MRG-5800V4V  | 800W    | PFC   | 200 / 7.87     | 150 / 5.91     | 86 / 3.39      | 130  |
| Mini Redundant  | MRH2-5930V0H | 930W    | PFC   | 280 / 11.02    | 150 / 5.91     | 86 / 3.39      | 131  |
| Mini Redundant  | MRH2-5AD0V0H | 1400W   | PFC   | 280 / 11.02    | 150 / 5.91     | 86 / 3.39      | 131  |
| N + 1 Redundant | M1Z3-5950V3V | 950W    | PFC   | 265 / 10.43    | 101.2 / 3.98   | 125 / 4.92     | 132  |
| N + 1 Redundant | M1Z3-5A45V3V | 1045W   | PFC   | 265 / 10.43    | 101.2 / 3.98   | 125 / 4.92     | 132  |
| N + 1 Redundant | M1Z3-5950V3H | 950W    | PFC   | 310 / 12.2     | 331 / 13.03    | 43 / 1.69      | 133  |
| N + 1 Redundant | MTW3-5C50V3V | 1250W   | PFC   | 300 / 11.81    | 101 / 3.98     | 125 / 4.92     | 134  |
| N + 1 Redundant | MTW3-5H00V3V | 1700W   | PFC   | 300 / 11.81    | 101 / 3.98     | 125 / 4.92     | 134  |
| N + 1 Redundant | MTW4-5H80V3V | 1780W   | PFC   | 300 / 11.81    | 101.2 / 3.98   | 166 / 6.54     | 135  |
| N + 1 Redundant | R3G-5500V4V  | 500W    | PFC   | 276 / 10.87    | 83 / 3.27      | 127 / 5        | 136  |
| N + 1 Redundant | R3G-5800V4V  | 800W    | PFC   | 276 / 10.87    | 83 / 3.27      | 127 / 5        | 136  |
| N + 1 Redundant | R3G-5950V4V  | 950W    | PFC   | 276 / 10.87    | 83 / 3.27      | 127 / 5        | 136  |
| N + 1 Redundant | R3G-5B40V4V  | 1140W   | PFC   | 276 / 10.87    | 83 / 3.27      | 127 / 5        | 136  |
| N + 1 Redundant | SPH2-5A00V4H | 1000W   | PFC   | 404 / 15.91    | 127 / 5        | 49 / 1.93      | 137  |
| N + 1 Redundant | SPH2-5C00V4H | 1200W   | PFC   | 404 / 15.91    | 127 / 5        | 49 / 1.93      | 137  |
| N + 1 Redundant | M1P4-6950V4H | 950W    | PFC   | 260 / 10.24    | 359 / 14.13    | 41.8 / 1.65    | 138  |
| N + 1 Redundant | M1P4-6D50V4H | 1350W   | PFC   | 260 / 10.24    | 359 / 14.13    | 41.8 / 1.65    | 138  |
| N + 1 Redundant | M1Z4-5A80V3H | 1080W   | PFC   | 310 / 12.2     | 422 / 16.61    | 43 / 1.69      | 139  |
| N + 1 Redundant | M1Z4-5C40V3H | 1240W   | PFC   | 310 / 12.2     | 422 / 16.61    | 43 / 1.69      | 139  |
| N + 1 Redundant | M1Z4-5D50V3H | 1350W   | PFC   | 310 / 12.2     | 422 / 16.61    | 43 / 1.69      | 139  |
| N + 1 Redundant | M1Z4-5E85V3H | 1485W   | PFC   | 310 / 12.2     | 422 / 16.61    | 43 / 1.69      | 139  |
| N + 1 Redundant | M1W4-5L80V3H | 2180W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 140  |
| N + 1 Redundant | M1W4-5O50V3H | 2450W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 140  |
| N + 1 Redundant | M1W4-5R20V3H | 2720W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 140  |
| N + 1 Redundant | M1W4-5W40V3H | 3240W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 140  |
| N + 1 Redundant | M1W4-5CH0V0H | 3300W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 140  |
| N + 1 Redundant | MTW4-5C50V3H | 1250W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 141  |
| N + 1 Redundant | MTW4-5F50V3H | 1550W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 141  |
| N + 1 Redundant | MTW4-5H10V3H | 1710W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 141  |
| N + 1 Redundant | MTW4-5H80V3H | 1780W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 141  |
| N + 1 Redundant | MTW4-5K50V3H | 2050W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 141  |
| N + 1 Redundant | MTW4-5M10V3H | 2210W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 141  |
| N + 1 Redundant | MTW4-5O30V3H | 2430W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 141  |
| N + 1 Redundant | G1W4-5BG0V0H | 2700W   | PFC   | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 142  |

| FORM FACTOR        | MODEL NAME    | WATTAGE | INPUT   | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) | Page |
|--------------------|---------------|---------|---------|----------------|----------------|----------------|------|
| N + 1 Redundant    | PSS2-5A00V3H  | 1000W   | PFC     | 360 / 14.17    | 127 / 5        | 44 / 1.73      | 143  |
| N + 1 Redundant    | PSS2-5C00V3H  | 1200W   | PFC     | 360 / 14.17    | 127 / 5        | 44 / 1.73      | 143  |
| N + 1 Redundant    | M1K6-6CB0V0H  | 3200W   | PFC     | 470 / 18.5     | 425 / 16.73    | 43 / 1.69      | 144  |
| N + 1 Redundant    | M1K6-5DH0V0H  | 4800W   | PFC     | 470 / 18.5     | 425 / 16.73    | 43 / 1.69      | 145  |
| N + 1 Redundant    | M1K6-6DH0V0H  | 4800W   | PFC     | 470 / 18.5     | 425 / 16.73    | 43 / 1.69      | 146  |
| DC 1U              | BP1P-5220V    | 220W    | DC +24V | 170 / 6.69     | 81.5 / 3.21    | 40.3 / 1.59    | 147  |
| DC 1U              | DP1P-5300V    | 300W    | DC -48V | 170 / 6.69     | 81.5 / 3.21    | 40.3 / 1.59    | 148  |
| DC 1U              | DP1P-5320V    | 320W    | DC -48V | 170 / 6.69     | 81.5 / 3.21    | 40.3 / 1.59    | 148  |
| DC 1U              | BP1H-5420V    | 420W    | DC 24V  | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 149  |
| DC 1U              | BP1H-5460V    | 460W    | DC 24V  | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 149  |
| DC 1U              | DP1H-5460V    | 460W    | DC -48V | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 150  |
| DC 1U              | DP1H-5550V    | 500W    | DC -48V | 225 / 8.86     | 100 / 3.94     | 40.5 / 1.59    | 150  |
| DC 2U              | BP2H-5420V    | 420W    | DC 24V  | 215 / 8.46     | 100 / 3.94     | 70 / 2.76      | 151  |
| DC 2U              | BP2H-5460V    | 460W    | DC 24V  | 215 / 8.46     | 100 / 3.94     | 70 / 2.76      | 151  |
| DC 2U              | DP2H-5460V    | 460W    | DC -48V | 215 / 8.46     | 100 / 3.94     | 70 / 2.76      | 152  |
| DC 2U              | DP2H-5500V    | 500W    | DC -48V | 215 / 8.46     | 100 / 3.94     | 70 / 2.76      | 152  |
| DC 2U              | DP2H-5550V    | 550W    | DC -48V | 215 / 8.46     | 100 / 3.94     | 70 / 2.76      | 152  |
| DC PS2             | BHG2-5300V    | 300W    | DC 24V  | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 153  |
| DC PS2             | BHG2-5350V    | 350W    | DC 24V  | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 153  |
| DC PS2             | BHG2-5400V    | 400W    | DC 24V  | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 153  |
| DC PS2             | DHG2-5400V    | 400W    | DC -48V | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 154  |
| DC PS2             | DHG2-5500V    | 500W    | DC -48V | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 154  |
| DC PS2             | DHG2-5600V    | 600W    | DC -48V | 140 / 5.51     | 150 / 5.91     | 86 / 3.39      | 154  |
| DC Micro Redundant | DR1U2-5200V4H | 200W    | DC -48V | 260 / 10.24    | 106 / 4.17     | 41.8 / 1.65    | 155  |
| DC Micro Redundant | DR1V2-5250V4H | 250W    | DC -48V | 295 / 11.61    | 106 / 4.17     | 41.8 / 1.65    | 156  |
| DC Micro Redundant | DM1R2-5500V0H | 500W    | DC -48V | 295 / 11.61    | 106 / 4.17     | 41.3 / 1.63    | 157  |
| DC Micro Redundant | DM1Y2-5150V2H | 150W    | DC -48V | 275 / 10.83    | 106 / 4.17     | 41.3 / 1.63    | 158  |
| DC Micro Redundant | DM1Y2-5300V2H | 300W    | DC -48V | 275 / 10.83    | 106 / 4.17     | 41.3 / 1.63    | 158  |
| DC Micro Redundant | BM1U2-5500V4H | 500W    | DC 24V  | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 159  |
| DC Micro Redundant | BM1U2-5501V4H | 500W    | DC 24V  | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 159  |
| DC Micro Redundant | DM1S2-5400V4H | 400W    | DC -48V | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 160  |
| DC Micro Redundant | DM1S2-5401V4H | 400W    | DC -48V | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 160  |
| DC Micro Redundant | DM1S2-5500V4H | 500W    | DC -48V | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 160  |
| DC Micro Redundant | DM1S2-5501V4H | 500W    | DC -48V | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 160  |
| DC Micro Redundant | DM1S2-5551V4H | 550W    | DC -48V | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 160  |
| DC Micro Redundant | DM1U2-2650V4H | 650W    | DC -48V | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 161  |
| DC Micro Redundant | DM1U2-5650V4H | 650W    | DC -48V | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 162  |
| DC Micro Redundant | DM1U2-5750V4H | 750W    | DC -48V | 355 / 13.98    | 106 / 4.17     | 41.3 / 1.63    | 162  |
| DC Micro Redundant | DM1K2-5A00V0H | 1000W   | DC -48V | 400 / 15.75    | 106 / 4.17     | 41.3 / 1.63    | 163  |
| DC 1U Redundant    | DR1S2-5300V4H | 300W    | DC -48V | 230 / 9.06     | 176 / 6.93     | 41.8 / 1.65    | 164  |

| FORM FACTOR       | MODEL NAME    | WATTAGE | INPUT   | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) | Page |
|-------------------|---------------|---------|---------|----------------|----------------|----------------|------|
| DC 1U Redundant   | DR1S2-5380V4H | 380W    | DC -48V | 230 / 9.06     | 176 / 6.93     | 41.8 / 1.65    | 164  |
| DC Mini Redundant | BMRW-5360V4V  | 360W    | DC 24V  | 185 / 7.28     | 150 / 5.91     | 86 / 3.39      | 165  |
| DC Mini Redundant | DMRW-5500V4V  | 500W    | DC -48V | 185 / 7.28     | 150 / 5.91     | 86 / 3.39      | 166  |
| DC Mini Redundant | DMRW-5600V4V  | 600W    | DC -48V | 185 / 7.28     | 150 / 5.91     | 86 / 3.39      | 166  |
| DC 2U Redundant   | BM1U2-5500V4V | 500W    | DC 24V  | 400 / 15.75    | 54.5 / 2.15    | 84.6 / 3.33    | 167  |
| DC 2U Redundant   | BM1U2-5501V4V | 500W    | DC 24V  | 400 / 15.75    | 54.5 / 2.15    | 84.6 / 3.33    | 167  |
| DC 2U Redundant   | DM1U2-5650V4V | 650W    | DC -48V | 400 / 15.75    | 54.5 / 2.15    | 86 / 3.39      | 168  |
| DC 2U Redundant   | DM1U2-5750V4V | 750W    | DC -48V | 400 / 15.75    | 54.5 / 2.15    | 86 / 3.39      | 168  |
| DC 2U Redundant   | DPSS2-5A00V3V | 1000W   | DC -48V | 385 / 15.16    | 65 / 2.56      | 84 / 3.31      | 169  |
| DC 2U Redundant   | DR1S2-5300V4V | 300W    | DC -48V | 207 / 8.15     | 85 / 3.35      | 84 / 3.31      | 170  |
| DC 2U Redundant   | DR1S2-5380V4V | 380W    | DC -48V | 207 / 8.15     | 85 / 3.35      | 84 / 3.31      | 170  |
| DC 2U Redundant   | BM1P2-5250V4V | 250W    | DC 24V  | 217 / 8.54     | 85 / 3.35      | 84 / 3.31      | 171  |
| DC 2U Redundant   | DM1P2-5500V4V | 500W    | DC -48V | 217 / 8.54     | 85 / 3.35      | 84 / 3.31      | 172  |
| DC 2U Redundant   | DM1X2-5700V0V | 700W    | DC -48V | 240 / 9.45     | 101 / 3.98     | 84 / 3.31      | 173  |
| DC 2U Redundant   | BM1Z2-5360V3V | 360W    | DC 24V  | 265 / 10.43    | 101 / 3.98     | 84 / 3.31      | 174  |
| DC 2U Redundant   | DM1Z2-5500V3V | 500W    | DC -48V | 265 / 10.43    | 101 / 3.98     | 84 / 3.31      | 175  |
| DC 2U Redundant   | DM1Z2-5550V3V | 550W    | DC -48V | 265 / 10.43    | 101 / 3.98     | 84 / 3.31      | 175  |
| DC 2U Redundant   | BR2G-5420V4V  | 420W    | DC 24V  | 276 / 10.87    | 101 / 3.98     | 82 / 3.23      | 176  |
| DC 2U Redundant   | BR2G-5460V4V  | 460W    | DC 24V  | 276 / 10.87    | 101 / 3.98     | 82 / 3.23      | 176  |
| DC 2U Redundant   | DR2G-5500V4V  | 500W    | DC -48V | 276 / 10.87    | 101 / 3.98     | 82 / 3.23      | 177  |
| DC 2U Redundant   | DR2G-5600V4V  | 600W    | DC -48V | 276 / 10.87    | 101 / 3.98     | 82 / 3.23      | 177  |
| DC 2U Redundant   | DR2G-5800V    | 800W    | DC -48V | 340 / 13.39    | 101 / 3.98     | 82 / 3.23      | 178  |
| DC 2U Redundant   | BMTW2-5600V3V | 600W    | DC 24V  | 300 / 11.81    | 101 / 3.98     | 84 / 3.31      | 179  |
| DC 2U Redundant   | DM1W2-5600V3V | 600W    | DC -48V | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 180  |
| DC 2U Redundant   | DM1W2-5650V3V | 650W    | DC -48V | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 180  |
| DC 2U Redundant   | DM1W2-5700V3V | 700W    | DC -48V | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 180  |
| DC 2U Redundant   | BG1W2-5600V3V | 600W    | DC 24V  | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 181  |
| DC 2U Redundant   | DG1W2-5660V3V | 660W    | DC -48V | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 182  |
| DC 2U Redundant   | DG1W2-5760V3V | 760W    | DC -48V | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 182  |
| DC 2U Redundant   | DG1W2-5860V3V | 860W    | DC -48V | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 182  |
| DC 2U Redundant   | DG1W2-5960V3V | 960W    | DC -48V | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 182  |
| DC 2U Redundant   | DG1W2-5A10V3V | 1010W   | DC -48V | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 182  |
| DC 2U Redundant   | DMTW2-5660V3V | 660W    | DC -48V | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 183  |
| DC 2U Redundant   | DMTW2-5820V3V | 820W    | DC -48V | 300 / 11.81    | 101.2 / 3.98   | 84 / 3.31      | 183  |
| DC 2U Redundant   | DM1L2-5600V3V | 600W    | DC -48V | 330 / 12.99    | 101.2 / 3.98   | 84 / 3.31      | 184  |
| DC 2U Redundant   | DM1L2-5650V3V | 650W    | DC -48V | 330 / 12.99    | 101.2 / 3.98   | 84 / 3.31      | 184  |
| DC 2U Redundant   | DM1L2-5700V3V | 700W    | DC -48V | 330 / 12.99    | 101.2 / 3.98   | 84 / 3.31      | 184  |
| DC N+1 Redundant  | DPSS2-5A00V3H | 1000W   | DC -48V | 360 / 14.17    | 127 / 5        | 44 / 1.73      | 185  |
| DC N+1 Redundant  | DMTW4-5M10V3H | 2210W   | DC -48V | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 186  |
| DC N+1 Redundant  | DG1W4-5BG0V0H | 2700W   | DC -48V | 340 / 13.39    | 422 / 16.61    | 43 / 1.69      | 187  |





**HIGH EFFICIENCY**  
AC INPUT TO DC OUTPUT



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |   |   |   |   |   |
|------------------|---------|--------|---|---|---|---|---|
|                  |         | +40V   | X | X | X | X | X |
| MQ1G-1035V-40    | 35W     | 0.9A   | X | X | X | X | X |
| REGULATION LOAD  |         | ±5%    | X | X | X | X | X |
| RIPPLE AND NOISE |         | 400mV  | X | X | X | X | X |

## MQ1G-1035V-40

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN AC SOURCE SHUTDOWN DC OUTPUT MUST BE MAINTAIN 16ms IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE(AC115V AT 80% OF FULL LOAD)

EFFICIENCY : 83% (+/-2%) AT 230VAC AND LOAD CONDITION : 40V/0.9A

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 101.5mm (D) × 50.5mm (W) × 30mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

1/0.5 AMPS @ ANY LOW/HIGH RANGE INPUT

##### INRUSH CURRENT :

35/70 AMPS @ 115/230V

##### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE


##### SAFETY :

TO MEET UL, CUL, TUV, CCC





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### MQ1G-1050V-5

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

1.5/1 AMPS @ ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

35/70 AMPS @ 115/230VAC

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL CSA, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |   |   |   |   |   |
|------------------|---------|--------|---|---|---|---|---|
|                  |         | +5V    | X | X | X | X | X |
| MQ1G-1050V-5     | 50W     | 10A    | X | X | X | X | X |
| REGULATION LOAD  |         | ±5%    | X | X | X | X | X |
| RIPPLE AND NOISE |         | 50mV   | X | X | X | X | X |

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN AC SOURCE SHUTDOWN DC OUTPUT MUST BE MAINTAIN 16ms IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE(AC115V AT 80% OF FULL LOAD)


EFFICIENCY : 81% (+/-2%) AT 115VAC/230VAC AND LOAD CONDITION : 5V/10A

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 101.5mm (D) × 50.5mm (W) × 30mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## **HIGH EFFICIENCY** AC INPUT TO DC OUTPUT



**MQ1G-1060V-12**  
**MQ1G-1060V-24**  
**MQ1G-1060V-40**  
**MQ1G-1060V-48**

MEDICAL OPEN FRAME

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

1.5/1 AMPS @ ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

35/70 AMPS @ 115/230VAC

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |       |   |   |
|------------------|---------|--------|-------|-------|-------|---|---|
|                  |         | +12V   | +24V  | +40V  | +48V  | X | X |
| MQ1G-1060V-12    | 60W     | 5A     | X     | X     | X     | X | X |
| MQ1G-1060V-24    | 60W     | X      | 2.5A  | X     | X     | X | X |
| MQ1G-1060V-40    | 60W     | X      | X     | 1.5A  | X     | X | X |
| MQ1G-1060V-48    | 60W     | X      | X     | X     | 1.25A | X | X |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | ±5%   | X | X |
| RIPPLE AND NOISE |         | 120mV  | 240mV | 400mV | 480mV | X | X |

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN AC SOURCE SHUTDOWN DC OUTPUT MUST BE MAINTAIN 16ms IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE(AC115V AT 80% OF FULL LOAD)


EFFICIENCY : 85% (+/-2%) AT 230VAC AND LOAD CONDITION : 40V/1.5A

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 101.5mm (D) × 50.5 mm (W) × 30mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| MQ1D-5120V       | 120W    | 14A    | 8A    | 12A   | X   | 0.5A  | 1.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V and +3.3V TOTAL OUTPUT MAX : 70W ( WITH 20 CFM )

+5V and +3.3V TOTAL OUTPUT MAX : 50W ( WITHOUT FAN )

## MQ1D-5120V

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

2/1 AMPS @ ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

35/70 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

HOLD UP TIME : 41mS MINIMUM AT 115V FULL LOAD

EFFICIENCY : 82%±2% TYPICAL @ 230V FULL LOAD




POWER GOOD SIGNAL : ON DELAY 100mS TO 550mS · OFF DELAY 1mS

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 190mm (D) × 83.8mm (W) × 39mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| MP1S-5220V       | 220W    | 12A    | 16A   | 10A   | X   | 0.3A  | 2A    |
| MP1S-5300V       | 300W    | 18A    | 24A   | 17A   | X   | 0.3A  | 2.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 60mV  | X   | 120mV | 60mV  |

REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 80W / 120W

## MP1S-5220V MP1S-5300V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~40°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V FULL LOAD

EFFICIENCY : 80%±2% TYPICAL @ 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1mS

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

LEAKAGE CURRENT : 0.3mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 190mm (D) × 81.5mm (W) × 40.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 220W    | 3.5A | 2A   |
| 300W    | 4.5A | 2A   |

#### INRUSH CURRENT :

70/140 AMPS @ 115/230 VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD)

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL60601-1, CUL CSA C22.2 NO. 60601-1, TUV EN 60601-1, CCC GB4943-1995, GB9254-1998, GB17625.1-1998





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### MP1S-6400V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

6/3A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

70/140 AMPS @ 115/230 VAC

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL60601-1, CUL CSA C22.2 NO. 60601-1, TUV EN 60601-1, CCC GB4943-1995, GB9254-1998, GB17625.1-1998



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |       |       |       |
|------------------|---------|--------|-------|-------|-------|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | +24V  | -12V  | +5VSB |
| MP1S-6400V       | 400W    | 12A    | 16A   | 10A   | 6A    | 0.3A  | 2.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | ±5%   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 60mV  | 240mV | 120mV | 60mV  |

##### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 90W

+5V&+12V&-12V&+3.3V&5VSB TOTAL OUTPUT MAX : 260W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20°C ~80°C

HOLD UP TIME : 10mS MINIMUM AT 115V FULL LOAD

EFFICIENCY : 80%±2% TYPICAL @ 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1mS


OUTPUT PROTECTION : OPP / OVP / OCP / SCP

LEAKAGE CURRENT : 0.3mA MAX. AT NOMINAL VOLTAGE 264VAC

REMOTE ON/OFF CONTROL

DIMENSION : 250mm (D) × 81.5mm (W) × 40.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |            |       |
|------------------|---------|--------|-------|-------|-----|------------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V       | +5VSB |
| MV1E-5350V       | 350W    | 20A    | 25A   | 20A   | X   | 0.7A       | 2A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | +13% / -7% | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV      | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 130W

## MV1E-5350V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , OPERATING : -20°C ~80

HOLD UP TIME : 16mS MINIMUM AT 115V LOAD <300W & 24mS MINIMUM AT 230V FULL LOAD

EFFICIENCY : 81-84% TYPICAL @ 110V FULL LOAD

OUTPUT PROTECTION : OPP / OVP / SCP

POWER GOOD SIGNAL : ON DELAY 100mS TO 550mS · OFF DELAY 1mS

REMOTE ON/OFF CONTROL

LEAKAGE CURRENT : 0.2mA MAX. AT NOMINAL VOLTAGE 240VAC

DIMENSION : 260mm (D) × 100mm (W) × 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

6/3 AMPS @ ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

15/30 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL60601-1, CUL CSA C22.2 NO. 60601-1, TUV EN 60601-1, CCC GB4943-1995, GB9254-1998, GB17625.1-1998





HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



MP2M-5435V

INPUT CHARACTERISTICS

- VOLTAGE :  
90~264VAC FULL RANGE
- FREQUENCY :  
47~63HZ
- INPUT CURRENT :  
7/3 AMPS @ ANY LOW/HIGH RANGE INPUT VOLTAGE
- INRUSH CURRENT :  
15/30 AMPS @ 115/230 VAC
- POWER FACTOR CORRECTION :  
PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL60601-1, CUL CSA C22.2 NO. 60601-1, TUV EN 60601-1, CCC GB4943-1995, GB9254-1998, GB17625.1-1998




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |         |       |
|------------------|---------|--------|-------|-------|-----|---------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V    | +5VSB |
| MP2M-5435V       | 435W    | 20A    | 32A   | 20A   | X   | 0.7A    | 2.0A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | +13/-7% | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV   | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 130W

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~ 80°C
- HOLD UP TIME : 16ms MINIMUM AT 115V FULL LOAD
- EFFICIENCY : TYPICAL 80-83% @ 110V FULL LOAD
- OUTPUT PROTECTION OPP / OVP / SCP
- LEAKAGE CURRENT : 0.2mA MAX. AT NOMINAL VOLTAGE 240VAC
- DIMENSION : 270mm (D) x 100mm (W) x 70mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





**MHG2-6300P**  
**MHG2-6350P**  
**MHG2-6400P**

## INPUT CHARACTERISTICS

VOLTAGE :

90~264VAC FULL RANGE

FREQUENCY :

47~63HZ

INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 300W    | 7A   | 3.5A |
| 350W    | 7A   | 3.5A |
| 400W    | 8A   | 4A   |

INRUSH CURRENT :

65/125 AMPS @ 115/230VAC

POWER FACTOR CORRECTION :

## PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

**SAFETY :**

TO MEET UL60601-1, CUL CSA C22.2 NO. 60601-1,  
TUV EN 60601-1, CCC GB4943-1995, GB9254-1998,  
GB17625.1-1998



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |        |       |       |       |       |
|------------------|---------|--------|--------|-------|-------|-------|-------|
|                  |         | +5V    | +12V   | +3.3V | -5V   | -12V  | +5VSB |
| MHG2-6300P       | 300W    | 35A    | 22A    | 28A   | 0.5A  | 0.8A  | 2.0A  |
| MHG2-6350P       | 350W    | 35A    | 26A    | 28A   | 0.5A  | 0.8A  | 2.0A  |
| MHG2-6400P       | 400W    | 35A    | 30A    | 28A   | 0.5A  | 0.8A  | 2.0A  |
| REGULATION LOAD  |         | ±5%    | +7/-5% | ±5%   | ±5%   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV  | 50mV  | 150mV | 150mV | 50mV  |

## REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 45A

**SPECIFICATION :**

TEMPERATURE RANGE : OPERATING -10°C ~50°C , STORAGE -40°C ~80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : 70% TYPICAL @ FULL LOAD


POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 0.3mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 140mm (D) x 150mm (W) x 86 mm (H) (PS/2)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### MHU2-5400V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

6/3 AMPS @ ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

20/40 AMPS @ 115/230VAC

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL60601-1, CUL CSA C22.2 NO. 60601-1, TUV EN 60601-1, CCC GB4943-1995, GB9254-1998, GB17625.1-1998



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| MHU2-5400V       | 400W    | 18A    | 32A   | 18A   | X   | 0.5A  | 2A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 30A

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~40°C

HOLD UP TIME : 16mS MINIMUM AT 115V LOAD

EFFICIENCY : 80-85% TYPICAL @ 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1Ms


OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON/OFF CONTROL

LEAKAGE CURRENT : 0.3mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 140mm (D) × 150mm (W) × 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



## MPSM-5500V MPSM-5600V

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| MPSM-5500V       | 500W    | 20A    | 36A   | 20A   | X   | 0.8A  | 3.5A  |
| MPSM-5600V       | 600W    | 25A    | 45A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL MAX : 40A

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 16ms IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 80-85% @ FULL LOAD

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 0.3mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 160mm (D) x 150mm (W) x 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

8/4 AMPS @ ANY LOW/HIGH RANGE INPUT VOLTAGE

10/5 AMPS @ ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

20/40 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL60601-1, CUL CSA C22.2 NO. 60601-1, TUV EN 60601-1, CCC GB4943-1995, GB9254-1998, GB17625.1-1998





## AC INPUT TO DC OUTPUT

HIGH EFFICIENCY



### Q1P-1052V19

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

1.3/0.8A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

70AMPS @230 VAC

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |      |       |
|------------------|---------|--------|-------|-------|-----|------|-------|
|                  |         | +5V    | +19V  | +3.3V | -5V | -12V | +5VSB |
| Q1P-1052V19      | 50W     | X      | 2.63A | X     | X   | X    | X     |
| REGULATION LOAD  |         | X      | ±5%   | X     | X   | X    | X     |
| RIPPLE AND NOISE |         | X      | 190mV | X     | X   | X    | X     |

##### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 50W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 60°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V 80% OF FULL LOAD


EFFICIENCY : 83% AT 115/230VAC AND LOAD CONDITION:12V/5A

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 94.5mm (D) × 39.5mm (W) × 32mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| Q1L-5060V        | 60W     | 7A     | 5A    | 6A    | X   | 0.3A  | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 40W

## Q1L-5060V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 70°C , STORAGE-20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V @80% OF FULL LOAD

EFFICIENCY : 80%±2% TYPICAL @ 115VAC IN

POWER GOOD SIGNAL : ON DELAY 100mS TO 550mS · OFF DELAY 1mS

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC

REMOTE ON/OFF CONTROL

DIMENSION : 176mm (D) × 39mm (W) × 39mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

1.5/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

35/70 AMPS @115/230 VAC

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |       |
|------------------|---------|--------|-------|-------|-------|
|                  |         | +5V    | +12V  | +24V  | +48V  |
| Q1J-1050V-5      | 50W     | 10A    | X     | X     | X     |
| Q1J-1060V-12     | 60W     | X      | 5A    | X     | X     |
| Q1J-1060V-24     | 60W     | X      | X     | 2.5A  | X     |
| Q1J-1060V-48     | 60W     | X      | X     | X     | 1.25A |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 70mV   | 120mV | 240mV | 480mV |

**Q1J-1050V-5**  
**Q1J-1060V-12**  
**Q1J-1060V-24**  
**Q1J-1060V-48**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

1.5/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

35/70 AMPS @ 115/230V

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V 80% OF FULL LOAD


EFFICIENCY : TYPICAL 87%(+/-2%) for 48V, 85%(+/-2%) for 24V , 85%(+/-2%) for 12V , 80%(+/-2%) for 5V AT 115VAC/230VAC AND FULL LOAD CONDITION

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 103mm (D) × 52mm (W) × 39mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**Q1I-1060V12**  
**Q1I-2050V53**  
**Q1I-2060V123**  
**Q1I-2060V125**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

1.5/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

35/70 AMPS @115/230 VAC

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |      |       |
|------------------|---------|--------|-------|-------|-----|------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V | +5VSB |
| Q1I-1060V12      | 60W     | X      | 5A    | X     | X   | X    | X     |
| REGULATION LOAD  |         | X      | ±5%   | X     | X   | X    | X     |
| RIPPLE AND NOISE |         | X      | 120mV | X     | X   | X    | X     |
| Q1I-2050V53      | 50W     | 10A    | X     | 6A    | X   | X    | X     |
| REGULATION LOAD  |         | ±5%    | X     | ±5%   | X   | X    | X     |
| RIPPLE AND NOISE |         | 50mV   | X     | 50mV  | X   | X    | X     |
| Q1I-2060V123     | 60W     | X      | 5A    | 6A    | X   | X    | X     |
| REGULATION LOAD  |         | X      | ±5%   | ±5%   | X   | X    | X     |
| RIPPLE AND NOISE |         | X      | 120mV | 50mV  | X   | X    | X     |
| Q1I-2060V125     | 60W     | 6A     | 5A    | X     | X   | X    | X     |
| REGULATION LOAD  |         | ±5%    | ±5%   | X     | X   | X    | X     |
| RIPPLE AND NOISE |         | 50mV   | 120mV | X     | X   | X    | X     |

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 70°C , STORAGE-20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V 80% OF FULL LOAD



EFFICIENCY : 79% (+/-2%)-Q1I-2050V53, 230VAC AND LOAD CONDITION 81% (+/-2%)-Q1I-2060V123/Q1I-2060V125/Q1I-1060V12/@ 115/230VAC AND LOAD CONDITION : 5V/6.04A, 3.3V/6A- Q1I-2050V53, 12V/3.35A, 3.3V/6A- Q1I-2060V123, 12V/2.5A 5V/6A -Q1I-2060V125

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 114.3mm (D) × 50.5mm (W) × 38mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## AC INPUT TO DC OUTPUT



### Q1H-5060V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

1.5/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

35/70 AMPS @115/230 VAC

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| Q1H-5060V        | 60W     | 7A     | 5A    | 6A    | X   | 0.3A  | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 40W (WITH 8 CFM)

+5V AND +3.3V TOTAL OUTPUT MAX : 30W (WITHOUT FAN)

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V 80% OF FULL LOAD

EFFICIENCY : 80%±2% TYPICAL · AT FULL LOAD 115VAC




POWER GOOD SIGNAL : ON DELAY 100mS TO 550mS · OFF DELAY 1mS

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 126mm (D) × 55mm (W) × 39mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





**HIGH EFFICIENCY**  
AC INPUT TO DC OUTPUT



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |      |       |
|------------------|---------|--------|-------|-------|-----|------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V | +5VSB |
| Q1Q-1060V12      | 60W     | X      | 5A    | X     | X   | X    | X     |
| REGULATION LOAD  |         | X      | ±5%   | X     | X   | X    | X     |
| RIPPLE AND NOISE |         | X      | 120mV | X     | X   | X    | X     |

REMARKS :  
TOTAL POWER:60W (MAX)

## Q1Q-1060V12

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING -40°C ~ 70°C , STORAGE -40°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V 80% OF FULL LOAD

EFFICIENCY : 82% AT 115/230VAC FULL LOAD

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 240VAC

DIMENSION : 137mm (D) × 50mm (W) × 32mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

2/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

35/70A AMPS @115/230 VAC

##### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC





## AC INPUT TO DC OUTPUT



### Q10-1060V12

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

2/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

30 AMPS @230 VAC

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE  | OUTPUT |       |       |     |      |       |
|------------------|----------|--------|-------|-------|-----|------|-------|
|                  |          | +5V    | +12V  | +3.3V | -5V | -12V | +5VSB |
| Q10-1060V-12     | 60W      | X      | 5A    | X     | X   | X    | X     |
|                  | 75W peak | X      | 6.25A | X     | X   | X    | X     |
| REGULATION LOAD  |          | X      | ±5%   | X     | X   | X    | X     |
| RIPPLE AND NOISE |          | X      | 120mV | X     | X   | X    | X     |

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 60°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V 80% OF FULL LOAD


EFFICIENCY : 82% AT 115/230VAC FULL LOAD

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 240VAC

DIMENSION : 127mm (D) × 56mm (W) × 32mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







**HIGH EFFICIENCY**  
AC INPUT TO DC OUTPUT



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |        |
|------------------|---------|--------|-------|--------|
|                  |         | +12V   | +24V  | +48V   |
| Q1F-1150V12      | 150W    | 12.5A  | X     | X      |
| Q1F-1150V24      | 150W    | X      | 6.25A | X      |
| Q1F-1150V48      | 150W    | X      | X     | 3.125A |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%    |
| RIPPLE AND NOISE |         | 120mV  | 240mV | 480mV  |

**Q1F-1150V12**  
**Q1F-1150V24**  
**Q1F-1150V48**

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C

HOLD UP TIME : 32mS MINIMUM AT 115V OF FULL LOAD

EFFICIENCY : 82%±2% TYPICAL · AT FULL LOAD 115VAC/230VAC AND LOAD  
CONDITION 12V/12.5A-Q1F-1150V12 · 83%±2% TYPICAL · AT 115Vin AND LOAD  
CONDITION 24V/6.25A-Q1F-1150V24 ; 82%±2% TYPICAL · AT 115Vin AND LOAD  
48V/3.125A-Q1F-1150V48

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 125mm (D) × 76.2mm(W) × 39mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.

## INPUT CHARACTERISTICS

### VOLTAGE :

90~264VAC FULL RANGE

### FREQUENCY :

47~63HZ

### INPUT CURRENT :

2.5/1A AT ANY LOW/HIGH RANGE INPUT  
VOLTAGE ; 2/1A AT ANY LOW/HIGH RANGE INPUT  
VOLTAGE (Q1F-1150V48)

### INRUSH CURRENT :

35/70 AMPS @115/230 VAC

### POWER FACTOR CORRECTION

PFC CAN REACH THE TARGET OF 95% AT  
115/230VAC, FULL LOAD

### EMI :



IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

### SAFETY :

TO MEET UL&CUL, TUV, CCC





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### Q1F-2150V123 Q1F-2150V125

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

2.5/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

35/70 AMPS @115/230 VAC

##### POWER FACTOR CORRECTION

PFC CAN REACH THE TARGET OF 95% AT  
115/230VAC, FULL LOAD

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |
|------------------|---------|--------|-------|-------|
|                  |         | +5V    | +12V  | +3.3V |
| Q1F-2150V123     | 150W    | X      | 12.5A | 8A    |
| Q1F-2150V125     | 150W    | 8A     | 12.5A | X     |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  |

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C

HOLD UP TIME : 32mS MINIMUM AT 115V FULL LOAD


EFFICIENCY : 82%±2% TYPICAL · AT FULL LOAD 115VAC/230VAC AND LOAD  
CONDITIOIN : 12V/12.5A

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT:3mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 125mm (D) × 76.2mm (W) × 39mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |
|------------------|---------|--------|-------|-------|
|                  |         | +5V    | +12V  | +24V  |
| Q1F-3150V        | 150W    | 2A     | 12.5A | 1.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 240mV |

## Q1F-3150V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 70°C , STORAGE -20°C ~80°C

HOLD UP TIME : 32mS MINIMUM AT 115V FULL LOAD

EFFICIENCY : 82%±2% TYPICAL · AT FULL LOAD 115VAC/230VAC AND LOAD  
CONDITIOIN : 12V/8.6A, 5V/2A, 24V/1.5A

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 125mm (D) × 76.2mm (W) × 39mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

2/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

35/70 AMPS @115/230 VAC

#### POWER FACTOR CORRECTION

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD.

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| Q1D-5120V        | 120W    | 14A    | 8A    | 12A   | X   | 0.5A  | 1.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 70W ( WITH 20 CFM )

+5V AND +3.3V TOTAL OUTPUT MAX : 50W ( WITHOUT FAN )

## Q1D-5120V

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

2/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

35/70 AMPS @115/230 VAC

#### POWER FACTOR CORRECTION

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD.

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

HOLD UP TIME : 41mS MINIMUM AT 115V FULL LOAD


EFFICIENCY : 82%(±2%) TYPICAL @ FULL LOAD 230VAC IN AND LOAD CONDITION:1 2V/4.46A;5V/4.98A;3.3V/4.27A;-12V/0.39A;5VSB/0.56A

OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON/OFF CONTROL

DIMENSION : 165mm (D) x 83.8mm (W) x 39mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### Q1K-5150V Q1K-5200V

#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| Q1K-5150V        | 150W    | 14A    | 12A   | 12A   | X   | 0.5A  | 3A    |
| Q1K-5200V        | 200W    | 14A    | 15.5A | 12A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 70W ( WITH 10 CFM )

+5V AND +3.3V TOTAL OUTPUT MAX : 50W ( WITHOUT FAN )

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C

HOLD UP TIME : 100mS MINIMUM AT 115V FULL LOAD -Q1K-5150V,  
100mS MINIMUM AT 115V 80% LOAD -Q1K-5200V

EFFICIENCY : 83% (+/-2%) - Q1K-5150V ; 83% (+/-2%) - Q1K-5200V @ 230VACin AND  
LOAD CONDITION : 12V/7.78A; 5V/5.57A; 3.3V/4.77A; -12V/0.31A; 5VSB/1.87A -Q1K-  
5150V 12V/11.18A;5V/6.47A;3.3V/5.53A;-12V/0.36A;5Vsb/2.17A-Q1K-5200V

POWER GOOD SIGNAL : ON DELAY 100mS TO 550mS

OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 186mm (D) × 100mm (W) × 39.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC - AND SAFETY-REGULATIONS.

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 150W    | 2.5A | 1A   |
| 200W    | 3A   | 1.5A |

##### INRUSH CURRENT :

35/80 AMPS @115/230 VAC

##### POWER FACTOR CORRECTION

PFC CAN REACH THE TARGET OF 95% AT  
115/230VAC, FULL LOAD.

##### EMI :




IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC





## AC INPUT TO DC OUTPUT



**Q1N-2400K**  
**Q1N-3400K**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

6/3A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

30 AMPS @230 VAC (AT 25 DEGREES AMBIENT COLD START)

#### POWER FACTOR CORRECTION

PFC CAN REACH THE TARGET OF 90% AT 230VAC, FULL LOAD.

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |        |       |     |      |       |
|------------------|---------|--------|--------|-------|-----|------|-------|
|                  |         | +5V    | +12V   | +3.3V | -5V | -12V | +5VSB |
| Q1N-2400K        | 400W    | X      | 33.33A | X     | X   | X    | 2A    |
| Q1N-3400K        | 400W    | 5A     | 33A    | X     | X   | X    | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%    | X     | X   | X    | ±5%   |
| RIPPLE AND NOISE |         | X      | 120mV  | X     | X   | X    | 50mV  |

#### REMARKS :

TOTAL OUTPUT POWER : 400W WITH 10CFM AIR FLOW; 250W W/O AIR FLOW

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V 80% OF FULL LOAD

EFFICIENCY : 90% @ 230VACin AND LOAD CONDITION : 12V/32.95A; 5VSB/0.2A

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS


OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON/OFF CONTROL

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC


DIMENSION : 199mm (D) × 92mm (W) × 43mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |        |
|------------------|---------|--------|-------|--------|
|                  |         | +12V   | +24V  | +48V   |
| Q1S-1150         | 150W    | 12.5A  | 6.25A | 3.125A |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%    |
| RIPPLE AND NOISE |         | 120mV  | 240mV | 480mV  |

REMARKS :  
TOTAL OUTPUT POWER : 150W

**Q1S-1150V12**  
**Q1S-1150V24**  
**Q1S-1150V48**

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V FULL LOAD

EFFICIENCY : TYPICAL 86% AT 115V, TYPICAL 87% AT 230V

OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON/OFF CONTROL

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC

DIMENSION : 127mm (D) × 76.2mm (W) × 39.6mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

2A/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

40/80 AMPS @115/230 VAC (AT 25 DEGREES AMBIENT COLD START)

#### POWER FACTOR CORRECTION

PFC CAN REACH THE TARGET OF 95% AT 110VAC, FULL LOAD.

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



G1X-1060V12

INPUT CHARACTERISTICS

- VOLTAGE :  
90~264VAC FULL RANGE
- FREQUENCY :  
47~63HZ
- INPUT CURRENT :  
2A @ 115 VAC, 1A @ 230 VAC
- INRUSH CURRENT :  
35A MAX.@115 VAC PER MODULE, 70A MAX. @ 230 VAC
- PER MODULE
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV, CCC




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |
|------------------|---------|--------|
|                  |         | +12V   |
| G1X-1060V12      | 60W     | 5A     |
| REGULATION LOAD  |         | ±5%    |
| RIPPLE AND NOISE |         | 120mV  |

REMARKS :  
OUTPUT MAX : 60W

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C
- HOLD UP TIME : 16mS MINIMUM AT 115V 80% OF FULL LOAD
- EFFICIENCY : 80%±2% TYPICAL · AT FULL LOAD 115VAC/230VAC
- LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC
- OUTPUT PROTECTION : OPP / OVP / SCP
- DIMENSION : 135mm (D) × 50.5mm (W) × 38mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT

OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |
|------------------|---------|--------|
|                  |         | +12V   |
| G1X2-1060V12     | 60W     | 5A     |
| REGULATION LOAD  |         | ±5%    |
| RIPPLE AND NOISE |         | 120mV  |

REMARKS :  
OUTPUT MAX : 60W




G1X2-1060V12

INPUT CHARACTERISTICS

- VOLTAGE :  
90~264VAC FULL RANGE
- FREQUENCY :  
47~63HZ
- INPUT CURRENT :  
2A @ 115 VAC, 1A @ 230 VAC
- INRUSH CURRENT :  
35A MAX.@115 VAC PER MODULE, 70A MAX. @ 230 VAC
- PER MODULE
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV, CCC

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C
- HOLD UP TIME : 16mS MINIMUM AT 115V 80% OF FULL LOAD
- EFFICIENCY : 78%±2% TYPICAL · AT FULL LOAD 115VAC/230VAC
- OUTPUT PROTECTION : OPP / OVP / SCP
- LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC
- WARNING METHOD : AUDIO ALARM (BUZZER SOUND, RESETABLE), FALUT LED, TTL
- DIMENSION : 190mm (D) × 106mm (W) × 39.5mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### G1X2-5060V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

2A @115 VAC, 1A @230 VAC

##### INRUSH CURRENT :

35A MAX.@115 VAC PER MODULE, 70A MAX. @ 230 VAC

##### PER MODULE

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| G1X2-5060V       | 60W     | 6A     | 5A    | 6A    | X   | 0.3A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 30W; TOTAL OUTPUT MAX : 60W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 70°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V 75% OF FULL LOAD

EFFICIENCY : TYPICAL 76%±2% AT FULL LOAD 115VAC/230VAC


OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5 mA. MAX. AT NOMINAL VOLTAGE 264VAC

WARNING METHOD : AUDIO ALARM (BUZZER SOUND, RESETABLE), FALUT LED, TTL

DIMENSION : 190mm (D) × 106mm (W) × 39.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### DG1X-1060V12

#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |
|------------------|---------|--------|
|                  |         | +12V   |
| DG1X-1060V12     | 60W     | 5A     |
| REGULATION LOAD  |         | ±5%    |
| RIPPLE AND NOISE |         | 120mV  |

REMARKS :  
OUTPUT MAX : 60W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 70°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT 115V 80% OF FULL LOAD

EFFICIENCY : 80%±2% TYPICAL · AT FULL LOAD -48VDC AND LOAD CONDITION : 12V/5A

OUTPUT PROTECTION : OPP / OVP / SCP

WARNING METHOD : AUDIO ALARM (BUZZER SOUND, RESETABLE), FALUT LED, TTL

DIMENSION : 135mm (D) × 50.5mm (W) × 38mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

#### INPUT CHARACTERISTICS

##### VOLTAGE :

39-72VDC FULL RANGE

##### FREQUENCY :

0HZ(DC)

##### STEADY-STATE CURRENT

2/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

3AMPS @ 48VDC HIGH FREQUENCY PEAK  
AMPLITUDES LASTING LESS THAN 100US (AT 25  
DEGREES AMBIENT COLD START)

##### EMI :



IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |      |       |
|------------------|---------|--------|-------|-------|-----|------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V | +5VSB |
| DG1X2-1060V12    | 60W     | X      | 5A    | X     | X   | X    | X     |
| REGULATION LOAD  |         | X      | ±5%   | X     | X   | X    | X     |
| RIPPLE AND NOISE |         | X      | 120mV | X     | X   | X    | X     |

REMARKS :  
MAXIMUM OUTPUT POWER : 60W

## DG1X2-1060V12

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 70°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 1mS IN REGULATION LIMIT AT -48V

EFFICIENCY : 78%±2% TYPICAL · AT FULL LOAD -48VDC

OUTPUT PROTECTION : OPP / OVP / SCP

WARNING METHOD : AUDIO ALARM (BUZZER SOUND, RESETABLE), FALUT LED, TTL

DIMENSION : 190mm (D) × 106mm (W) × 39.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

39-72VDC FULL RANGE

#### STEADY-STATE CURRENT

2/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

3AMPS @ 48VDC HIGH FREQUENCY PEAK  
AMPLITUDES LASTING LESS THAN 100US (AT 25  
DEGREES AMBIENT COLD START)

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

#### SAFETY :

UL&CUL, TUV, CCC







## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DG1X2-5060V      | 60W     | 6A     | 5A    | 6A    | X   | 0.3A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 30W  
MAXIMUM OUTPUT POWER : 60W

## DG1X2-5060V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 70°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN, DC OUTPUT MUST BE MAINTAIN 1mS IN REGULATION LIMIT AT -48V

EFFICIENCY : 78%±2% TYPICAL · AT FULL LOAD -48VDC

OUTPUT PROTECTION : OPP / OVP / SCP

WARNING METHOD : AUDIO ALARM (BUZZER SOUND, RESETABLE), FALUT LED, TTL

DIMENSION : 190mm (D) × 106mm (W) × 39.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

39-72VDC FULL RANGE

#### FREQUENCY :

0HZ(DC)

#### STEADY-STATE CURRENT

2/1A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

3AMPS @ 48VDC HIGH FREQUENCY PEAK AMPLITUDES LASTING LESS THAN 100US (AT 25 DEGREES AMBIENT COLD START)

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



RH1E-1060V

INPUT CHARACTERISTICS


- VOLTAGE :  
90 ~ 264VAC FULL RANGE
- FREQUENCY :  
47 ~ 63HZ
- INPUT CURRENT :  
1.5/1A @ ANY LOW/HIGH RANGE INPUT VOLTAGE
- INRUSH CURRENT :  
35/70AMPS @ 115/230 VAC
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
MEET UL&CUL, TUV, CCC



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |
|------------------|---------|--------|
|                  |         | +12V   |
| RH1E-1060V       | 60W     | 5A     |
| REGULATION LOAD  |         | ±5%    |
| RIPPLE AND NOISE |         | 120mV  |

- SPECIFICATION :  
TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -10°C ~85°C
- HOLD UP TIME : WHEN AC SOURCE SHUTDOWN DC OUTPUT MUST BE MAINTAIN 20mSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE(AC115V AT 80% OF FULL LOAD)
- EFFICIENCY : TYPICAL 80% AT 115VIN AND LOAD CONDITION
- OUTPUT PROTECTION : OPP / OVP / SCP
- LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC
- I WARNING METHOD : AUDIO ALARM (BUZZER SOUND, RESETABLE), FALUT LED, TTL
- DIMENSION : 147 (D) × 96 (W) × 36 (H) mm;
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## DC INPUT TO DC OUTPUT



### AN1U-5150V

#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| AN1U-5150V       | 150W    | 8A     | 12.5A | 8A    | X   | 0.3A  | 2A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
PEAK : +5V → 12A, +3.3V → 12A, +5VSB → 3A; LOAD SHOULD NOT EXCEED 20SECONDS.  
+5V AND +3.3V TOTAL OUTPUT : 65W MAX  
TOTAL OUTPUT POWER : 150W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING -20°C ~40°C , STORAGE -20°C ~80°C

EFFICIENCY : 96% (+/-2%) AT 12VDC AND LOAD CONDITION : 5V/5.39A, 12V/8.01A, +3.3V/5.39A, -12V/0.2A, 5VSB/1.34A

OUTPUT PROTECTION : OPP / OVP / SCP

DIMENSION : 39mm (D) × 99mm (W) × 20.6mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

#### INPUT CHARACTERISTICS

##### VOLTAGE :

12VDC FULL RANGE (11.4~12.6V)

##### STEADY-STATE CURRENT :

15A

##### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### AN1P-5400V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

DC 12V (11.4V~12.6V)

##### STEADY-STATE CURRENT :

12V/40A AND 5VSB/3A

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| AN1P-5400V       | 400W    | 35A    | 33A   | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

WITHOUT AIR-FLO : +5V/21.54A AND +3.3V/18A TOTAL OUTPUT MAX : 170W.

+5V ,+3.3V ,+12V,-12V TOTAL OUTPUT MAX : 400W

EXTERNAL FORCED AIR COOLING FAN CFM : 9.53,

+3.3V AND +5V MAXIMUM POWER : 210W,

MAXIMUM OUTPUT POWER :400W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C




HOLD UP TIME : 16mS MINIMUM AT 115V 80% OF FULL LOAD

EFFICIENCY : 96% (+/-2%) AT 12VDC AND LOAD CONDITION : 5V/21.54A ,12V/14.5A, +3.3V/31 A, -12V/0.5A, 5VSB/3A

OUTPUT PROTECTION : OPP / OVP / SCP

DIMENSION : 70mm (D) × 81.5mm (W) × 40mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### AB1U-5120V

#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| AB1U-5120V       | 120W    | 14A    | 8A    | 12A   | X   | 0.5A  | 1.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 70W(WITH 10CFM); +5V AND +3.3V TOTAL OUTPUT MAX : 50W(WITHOUT FAN)

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C

HOLD UP TIME : 2ms MINIMUM AT 10V FULL LOAD

EFFICIENCY : 80%(±2%) TYPICAL @ FULL LOAD 12VDC/24VDC IN AND LOAD CONDITION:12V/4.46A;5V/4.98A;3.3V/4.27A;-12V/0.39A;5VSB/0.56A

OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON/OFF CONTROL

DIMENSION : 152.4mm (D) x 83.8mm (W) x 38mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

#### INPUT CHARACTERISTICS

##### VOLTAGE :

10 ~ 36VDC

##### INPUT CURRENT :

14.5/4A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

15AMPS MAX. @ 36 VDC (AT 25 DEGREES AMBIENT COLD START )

##### EMI :





IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC







## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### BB1U-6150V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

18 ~ 36VDC

##### INPUT CURRENT :

10/5A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

15AMPS @ 36 VDC (AT 25 DEGREES AMBIENT COLD START )

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |       |       |       |
|------------------|---------|--------|-------|-------|-------|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V   | -12V  | +5VSB |
| BB1U-6150V       | 150W    | 14A    | 12A   | 12A   | 0.3A  | 0.5A  | 1.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | ±5%   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | 100mV | 120mV | 50mV  |

##### REMARKS :

-5V IS OPTION AND WE DID NOT PUT -5V IN OUT STANDARD MODEL; +5V AND +3.3V TOTAL OUTPUT MAX : 50W(WITHOUT FAN)

+5V AN +3.3V TOTAL OUTPUT MAX : 70W(WITH 10CFM)

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~70°C , STORAGE -20°C ~80°C


HOLD UP TIME : 2ms MINIMUM AT 18V FULL LOAD

EFFICIENCY : 82%(+/-2%) AT 18VDC/24VDC IN AND LOAD CONDITION; 12V/6.12A; 5V/4.98A; 3.3V/4.27A; -12V/0.39A; 5VSB/0.56A

OUTPUT PROTECTION : OPP / OVP / SCP

DIMENSION : 152.4mm (D) × 83.8mm (W) × 38mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



# HIGH EFFICIENCY AC INPUT TO DC OUTPUT



## P1S-5300G

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V1 | +12V2 | +3.3V | -5V | -12V  | +5VSB |
| P1S-5300G        | 300W    | 14A    | 25A   | X     | 14A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | X     | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | X     | 60mV  | X   | 120mV | 60mV  |

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C

EFFICIENCY : 80%-84% TYPICAL @ 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100ms TO 500ms · OFF DELAY 1ms

HOLD UP TIME : 12ms MINIMUM AT 115V FULL LOAD

OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON/OFF CONTROL

DIMENSION : 150mm (D) × 81.5mm (W) × 40.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90 ~ 264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

5 / 2.5 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

15/50 AMPS @110/220VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115/230V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :



IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

UL&CUL, TUV, CCC



# HIGH EFFICIENCY AC INPUT TO DC OUTPUT



## P1S-2300V19

### INPUT CHARACTERISTICS

#### VOLTAGE :

90 ~ 264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

4.5 / 2 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

60 / 80 AMPS @115/230 VAC (AT 25 DEGREES AMBIENT COLD START FOR EACH POWER UNIT)

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |      |       |
|------------------|---------|--------|-------|-------|-----|------|-------|
|                  |         | +5V    | +19V  | +3.3V | -5V | -12V | +5VSB |
| P1S-2300V19      | 300W    | X      | 15.8A | X     | X   | X    | 2.5A  |
| REGULATION LOAD  |         | X      | ±5%   | X     | X   | X    | ±5%   |
| RIPPLE AND NOISE |         | X      | 190mV | X     | X   | X    | 50mV  |

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 19V MUST BE MAINTAIN 16mS IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : >80% AT 115VAC, 40%~100% MAX LOAD

REMOTE ON/OFF CONTROL


LEAKAGE CURRENT : 3.5MA. MAX. AT NOMINAL VOLTAGE 250VAC

POWER GOOD SIGNAL : ON DELAY 100mS TO 550mS · OFF DELAY 1Ms

OUTPUT PROTECTION : OPP / OVP / SCP

DIMENSION : 150(D)×81.5(W)×40.3(H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



# HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**P1S-2300V**

**80 PLUS P1S-2400V**

**80 PLUS P1S-2500V**

## INPUT CHARACTERISTICS

### VOLTAGE :

90 ~ 264VAC FULL RANGE (300W , 400W)

180 ~ 264VAC FULL RANGE (500W)

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 300W    | 4.5A | 2A   |
| 400W    | 5.5A | 2.5A |
| 500W    | 6.5A | 3A   |

### INRUSH CURRENT :

15/30 AMPS @ 115/230 VAC

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL&CUL, TUV, CCC



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |       |     |       |
|------------------|---------|--------|-------|-------|-------|-----|-------|
|                  |         | +5V    | +12V1 | +12V2 | +3.3V | -5V | +5VSB |
| P1S-2300V        | 300W    | X      | 24A   | X     | X     | X   | 2.5A  |
| P1S-2400V        | 400W    | X      | 33A   | X     | X     | X   | 2.5A  |
| P1S-2500V        | 500W    | X      | 41A   | X     | X     | X   | 2.5A  |
| REGULATION LOAD  |         | X      | ±5%   | X     | X     | X   | ±5%   |
| RIPPLE AND NOISE |         | X      | 120mV | X     | X     | X   | 50mV  |

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~40°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 16MS ( 300W , 400W ) / 12MS (500W) IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : > 80% AT 115VAC, 40%~100% MAX LOAD ( 300W , 400W )

> 86% AT 115VAC, 40%~100% MAX LOAD ( 500W )


LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 250VAC

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1Ms

OUTPUT PROTECTION : OPP / OVP / SCP

DIMENSION : 150mm (D) × 81.5mm (W) × 40.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



# **HIGH EFFICIENCY** AC INPUT TO DC OUTPUT



## **P1P-5400V** **P1P-5401V**

### **INPUT CHARACTERISTICS**

#### **VOLTAGE :**

90~264VAC FULL RANGE

#### **FREQUENCY :**

47 ~ 63HZ

#### **INPUT CURRENT :**

6/3 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE

#### **INRUSH CURRENT :**

30/60 AMPS @ 115/230VAC

#### **POWER FACTOR CORRECTION :**

PFC CAN REACH THE TARGET OF 95% AT  
115/230VAC, FULL LOAD

#### **EMI :**

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### **EMS :**

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

#### **SAFETY :**

TO MEET UL&CUL, TUV, CCC



### **OUTPUT CHARACTERISTICS**

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| P1P-5400V        | 400W    | 12A    | 32A   | 10A   | X   | 0.5A  | 2.5A  |
| P1P-5401V        | 400W    | 18A    | 32A   | 10A   | X   | 0.5A  | 2.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 60mV  | X   | 120mV | 60mV  |

#### **REMARKS :**

+5 AND +3.3V TOTAL OUTPUT MAX : 90W

### **SPECIFICATION :**

TEMPERATURE RANGE : OPERATING 0°C ~40°C , OPERATING -20°C ~80°C

EFFICIENCY : TYPICAL 80-84% (5401V : 78~83%) AT 25°C 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100ms TO 500ms · OFF DELAY 1Ms

HOLD UP TIME : 12ms MINIMUM AT FULL LOAD & NOMINAL INPUT VOLTAGE


OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

3.3V & 5V REMOTE SENSING DESIGN

DIMENSION : 170mm (D) × 81.5mm (W) × 40.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





# HIGH EFFICIENCY AC INPUT TO DC OUTPUT



## P1P-2600K

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |      |       |
|------------------|---------|--------|-------|-------|-----|------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V | +5VSB |
| P1P-2600K        | 600W    | X      | 50A   | X     | X   | X    | 3A    |
| REGULATION LOAD  |         | X      | ±5%   | X     | X   | X    | ±5%   |
| RIPPLE AND NOISE |         | X      | 120mA | X     | X   | X    | 50mA  |

REMARKS :  
TOTAL POWER : 600W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , OPERATING -20°C ~80°C

EFFICIENCY : TYPICAL 93% AT 230V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100ms TO 500ms · OFF DELAY 1Ms

HOLD UP TIME : 12ms MINIMUM AT FULL LOAD & NOMINAL INPUT VOLTAGE

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE VAC

DIMENSION : 170mm (D) × 81.5mm (W) × 40.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

8.5/4.5 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

35/80 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



P1P-2600G  
P1P-2600K

OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |      |       |
|------------------|---------|--------|-------|-------|-----|------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V | +5VSB |
| P1P-2600G        | 600W    | X      | 50A   | X     | X   | X    | 3A    |
| REGULATION LOAD  |         | X      | ±5%   | X     | X   | X    | ±5%   |
| RIPPLE AND NOISE |         | X      | 120mA | X     | X   | X    | 50mA  |

REMARKS :  
TOTAL POWER : 600W

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , OPERATING -20°C ~80°C

EFFICIENCY : TYPICAL 87% AT 230V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1mS

HOLD UP TIME : 12mS MINIMUM AT FULL LOAD & NOMINAL INPUT VOLTAGE

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE VAC

DIMENSION : 170mm (D) × 81.5mm (W) × 40.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

INPUT CHARACTERISTICS

VOLTAGE :

90~264VAC FULL RANGE

FREQUENCY :

47 ~ 63HZ

INPUT CURRENT :

8.5/4.5 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

INRUSH CURRENT :

35/80 AMPS @ 115/230VAC

POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

SAFETY :

TO MEET UL&CUL, TUV, CCC



# **HIGH EFFICIENCY** AC INPUT TO DC OUTPUT



**H1U-5300V**  
**H1U-5320V**

## **OUTPUT CHARACTERISTICS**

| MODEL            | WATTAGE | OUTPUT |       |       |      |       |       |
|------------------|---------|--------|-------|-------|------|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V* | -12V  | +5VSB |
| H1U-5300V        | 300W    | 18A    | 22A   | 16A   | X    | 0.5A  | 2A    |
| H1U-5320V        | 320W    | 18A    | 22A   | 16A   | X    | 0.5A  | 2A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X    | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X    | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 25A

## **SPECIFICATION :**

TEMPERATURE RANGE : OPERATING 0°C ~40°C , STORAGE -20°C ~80°C

EFFICIENCY : TYPICAL 80-84% @ 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

HOLD UP TIME : 16 ms MINIMUM AT 115AC INPUT; 20ms MINIMUM AT 230 AC INPUT

OUTPUT PROTECTION : OPP / OVP / SCP

3.3V REMOTE SENSING DESIGN

DIMENSION : 155mm (D) x 100mm (W) x 40mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

## **INPUT CHARACTERISTICS**

### **VOLTAGE :**

90~264VAC FULL RANGE

### **FREQUENCY :**

47 ~ 63HZ

### **INPUT CURRENT :**

4/2 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE

### **INRUSH CURRENT :**

20/40 AMPS @ 115/230VAC

### **POWER FACTOR CORRECTION :**

PFC CAN REACH THE TARGET OF 95% AT  
115/230VAC, FULL LOAD

### **EMI :**


IEC61000-3-2, FCC, CISPR 22(EN 55022)

### **EMS :**

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

### **SAFETY :**

TO MEET UL&CUL, TUV, CCC





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| P1U-5400E        | 400W    | 0~18   | 2~32  | 0~18  | X   | 0~0.5 | 0.1~3 |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 105W

## P1U-5400E

Erp ready

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

8/4 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE

#### INRUSH CURRENT :

15/30 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL  
LOAD, FOLLOWING THE STANDARD OF IEC 61000-  
3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

#### SAFETY :

TO MEET UL, CUL, TUV

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~ 80°C

EFFICIENCY : 85%±2 TYPICAL AT 115V, FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE


OUTPUT PROTECTION : OPP / OVP / SCP

LEAKAGE CURRENT : 3.5MA MAX. AT NOMINAL VOLTAGE 264VAC

REMOTE ON/OFF CONTROL

DIMENSION : 190mm (D) x 100mm (W) x 40mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



P1U-5520K

INPUT CHARACTERISTICS

- VOLTAGE :**  
90~264VAC FULL RANGE
- FREQUENCY :**  
47 ~ 63HZ
- INPUT CURRENT :**  
8/4 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE
- INRUSH CURRENT :**  
15/30 AMPS @ 115/230VAC
- POWER FACTOR CORRECTION :**  
PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2
- EMI :**  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :**  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :**  
TO MEET UL, CUL, TUV



OUTPUT CHARACTERISTICS


| MODEL            | WATTAGE | OUTPUT |       |       |      |      |       |
|------------------|---------|--------|-------|-------|------|------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V* | -12V | +5VSB |
| P1U-5520K        | 520W    | 14A    | 43A   | 14A   | X    | 0.3A | 2A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X    | ±5%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X    | 50mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 70W

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~ 80°C
- EFFICIENCY : 89%±2 TYPICAL AT 115V, FULL LOAD
- POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms
- HOLD UP TIME : 16ms MINIMUM AT 80% OF FULL LOAD & NORMAL INPUT VOLTAGE
- OUTPUT PROTECTION : OPP / OVP / SCP
- LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC
- REMOTE ON/OFF CONTROL
- DIMENSION : 190 (D) x 100 (W) x 40 (H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**80 PLUS P1H-5400V**  
**80 PLUS P1H-5500V**  
**80 PLUS P1H-5550V**  
**P1H-5501V**  
**P1H-5551V**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

6~10/3~5 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

20/40 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| P1H-5400V        | 400W    | 22A    | 32A   | 22A   | X   | 0.8A  | 3.5A  |
| P1H-5500V        | 500W    | 25A    | 40A   | 25A   | X   | 0.8A  | 3.5A  |
| P1H-5550V        | 550W    | 25A    | 40A   | 25A   | X   | 0.8A  | 3.5A  |
| P1H-5501V        | 500W    | 25A    | 40A   | 25A   | X   | 0.8A  | 4A    |
| P1H-5551V        | 550W    | 25A    | 40A   | 25A   | X   | 0.8A  | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 60mV  | X   | 120mV | 60mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 35A

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 16ms IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : 80% TYPICAL @ 115V FULL LOAD


LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 250VAC

POWER GOOD SIGNAL : ON DELAY 100ms TO 500ms · OFF DELAY 1ms

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

DIMENSION : 225mm (D) × 100mm (W) × 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS



| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| P1H-5407V        | 400W    | 22A    | 32A   | 22A   | X   | 0.8A  | 3.5A  |
| P1H-5507V        | 500W    | 25A    | 40A   | 25A   | X   | 0.8A  | 3.5A  |
| P1H-5557V        | 550W    | 25A    | 40A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 60mV  | X   | 120mV | 60mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 35A

## P1H-5407V P1H-5507V P1H-5557V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS MINIMUM AT FULL LOAD & NOMINAL INPUT VOLTAGE

EFFICIENCY : TYPICAL >80% @ 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

DIMENSION : 225mm (D) × 100mm (W) × 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

6~10/3~5 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

20/40 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115/230VAC, FULL LOAD

FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| P1H-5420G        | 420W    | 12A    | 32A   | 12A   | X   | 0.5A  | 3A    |
| P1H-5500G        | 500W    | 18A    | 40A   | 18A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
THE OUTPUT CURRENT OF +5V AND +3.3V NOT EXCEED 90W / 100W



## P1H-5420G P1H-5500G

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 16MSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : >87% TYPICAL @ 115V FULL LOAD

LEAKAGE CURRENT : 3.5MA. MAX. AT NOMINAL VOLTAGE 250VAC

POWER GOOD SIGNAL : ON DELAY 100mS TO 550mS · OFF DELAY 1Ms

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

DIMENSION : 225mm (D) × 100mm (W) × 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC - AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

5.5/2.5A AT ANY LOW/HIGH RANGE INPUT VOLTAGE (420W)

7/3A AT ANY LOW/HIGH RANGE INPUT VOLTAGE (500W)

#### INRUSH CURRENT :

50/100 AMPS @ 115/230VAC (420W)

40/60 AMPS @ 115/230VAC (500W)

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022), , CLASS B

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| P1H-5420E        | 420W    | 12A    | 32A   | 12A   | X   | 0.5A  | 3A    |
| P1H-5500E        | 500W    | 18A    | 40A   | 18A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
THE OUTPUT CURRENT OF +5V AND +3.3V NOT EXCEED 90W/100W ;  
TOTAL POWER MAX 420W/500W



## P1H-5420E P1H-5500E

ErPready

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 16MSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : >87% TYPICAL @ 115V FULL LOAD

5VSB EFFICIENCY : 5VSB EFFICIENCY IS MEASURED WITH THE MAIN OUTPUTS OFF (REMOTE OFF) @ 115/230VAC

| LOAD  | EFFICIENCY |
|-------|------------|
| 90mA  | ≥ 50%      |
| 250mA | ≥ 60%      |
| ≥ 1A  | ≥ 70%      |

LEAKAGE CURRENT : 3.5MA. MAX. AT NOMINAL VOLTAGE 240VAC

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1Ms

REMOTE ON/OFF CONTROL

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

DIMENSION : 225mm (D) × 100mm (W) × 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

6/3 AT ANY LOW/HIGH RANGE INPUT VOLTAGE(420W)

7/3 AT ANY LOW/HIGH RANGE INPUT VOLTAGE(500W)

#### INRUSH CURRENT :

50/100 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022), , CLASS B

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



- V1E-5250V**
- V1E-5300V**
- V1E-5350V**

INPUT CHARACTERISTICS

VOLTAGE :  
90~264VAC FULL RANGE

FREQUENCY :  
47 ~ 63HZ

INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 250W    | 4A   | 2A   |
| 300W    | 6A   | 3A   |
| 350W    | 6A   | 3A   |

INRUSH CURRENT :  
15/30 AMPS @115/230 VAC

POWER FACTOR CORRECTION :  
PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)

EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

SAFETY :  
TO MEET UL&CUL, TUV, CCC



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |      |                                |       |
|------------------|---------|--------|-------|-------|------|--------------------------------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V* | -12V                           | +5VSB |
| V1E-5250V        | 250W    | 15A    | 18A   | 10A   | X    | 1A                             | 2A    |
| V1E-5300V        | 300W    | 20A    | 20A   | 20A   | X    | 1A                             | 2A    |
| V1E-5350V        | 350W    | 20A    | 25A   | 20A   | X    | 1A                             | 2A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X    | 250W/300W:±10%<br>350W +13%-7% | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X    | 120mV                          | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 80W / 130W / 130W

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C ; STORAGE -20°C ~80°C

HOLD UP TIME : 16 ms MINIMUM AT 115AC INPUT; 24ms MINIMUM AT 230 AC INPUT


EFFICIENCY : 81-84% AT 100V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 550 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / SCP

DIMENSION : 210mm (D) x 100mm (W) x 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





# HIGH EFFICIENCY AC INPUT TO DC OUTPUT



## H1M-5350V

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

6/2.5 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

30 AMPS@230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 90% @ 230V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |       |      |       |       |
|------------------|---------|--------|-------|-------|-------|------|-------|-------|
|                  |         | +5V    | +12V1 | +12V2 | +3.3V | -5V* | -12V  | +5VSB |
| H1M-5350V        | 350W    | 14A    | 15A   | 14A   | 14A   | X    | 0.3A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | ±5%   | X    | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 120mV | 50mV  | X    | 120mV | 50mV  |

#### REMARKS :

TOTAL POWER:350W (MAX)

+5V AND +3.3V TOTAL OUTPUT MAX : 85W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20°C ~ 80°C

EFFICIENCY : TYPICAL >90% @ 230V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

HOLD UP TIME : 16 ms MINIMUM AT 80% LOAD


OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON/OFF CONTROL

LEAKAGE CURRENT : INPUT LEAKAGE CURRENT FROM LINE TO GROUND WILL BE LESS THAN 3.5MA RMS. MEASUREMENT WILL BE MADE AT 240 VAC AND 60Hz.

DIMENSION : 242mm (D) x 100mm (W) x 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**H1M-5600V**  
**H1M-5700V**  
**H1M-5800V**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 600W    | 10A  | 5A   |
| 700W    | 10A  | 5A   |
| 800W    | 12A  | 6A   |

#### INRUSH CURRENT :

40/60 AMPS@115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| H1M-5600V        | 600W    | 25A    | 48A   | 25A   | X   | 0.8A  | 3.5A  |
| H1M-5700V        | 700W    | 25A    | 48A   | 25A   | X   | 0.8A  | 3.5A  |
| H1M-5800V        | 800W    | 25A    | 57A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 60mV  | X   | 120mV | 60mV  |

#### REMARKS :

THE OUTPUT CURRENT OF +5V AND +3.3V NOT EXCEED : 40A

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

EFFICIENCY : TYPICAL >80% @ 115V FULL LOAD

PFC CAN REACH THE TARGET OF 95% AT 115V/230VAC, FULL LOAD


POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

HOLD UP TIME : 16 ms MINIMUM AT 115AC INPUT; 20ms MINIMUM AT 230 AC INPUT

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

DIMENSION : 250mm (D) x 100mm (W) x 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## H1M-5607V H1M-5707V H1M-5807V

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 600W    | 10A  | 5A   |
| 700W    | 10A  | 5A   |
| 800W    | 12A  | 6A   |

#### INRUSH CURRENT :

40/60 AMPS@115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| H1M-5607V        | 600W    | 25A    | 48A   | 25A   | X   | 0.8A  | 3.5A  |
| H1M-5707V        | 700W    | 25A    | 48A   | 25A   | X   | 0.8A  | 3.5A  |
| H1M-5807V        | 800W    | 25A    | 57A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 60mV  | X   | 120mV | 60mV  |

#### REMARKS :

THE OUTPUT CURRENT OF +5V AND +3.3V NOT EXCEED : 40A

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

EFFICIENCY : TYPICAL >80% @ 115V FULL LOAD


POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

HOLD UP TIME : 16 ms MINIMUM AT 115AC INPUT; 20ms MINIMUM AT 230 AC INPUT

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

DIMENSION : 275mm (D) x 100mm (W) x 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



# **HIGH EFFICIENCY** AC INPUT TO DC OUTPUT



**P1D-5400V**

**80 PLUS P1D-5600V**

**80 PLUS P1D-5700V**

## **INPUT CHARACTERISTICS**

### **VOLTAGE :**

90~264VAC FULL RANGE

### **FREQUENCY :**

47 ~ 63HZ

### **INPUT CURRENT :**

| WATTAGE | 115V | 230V |
|---------|------|------|
| 400W    | 6A   | 3A   |
| 700W    | 10A  | 5A   |
| 800W    | 10A  | 5A   |

### **INRUSH CURRENT :**

30/60 AMPS @115/230VAC

### **POWER FACTOR CORRECTION :**

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD,FOLLOWING THE STANDARD OF IEC 61000-3-2

### **EMI :**

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### **EMS :**

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### **SAFETY :**

TO MEET UL, CUL, TUV, CCC



## **OUTPUT CHARACTERISTICS**

| MODEL            | WATTAGE | OUTPUT |       |        |     |       |        |
|------------------|---------|--------|-------|--------|-----|-------|--------|
|                  |         | +5V1   | +12V1 | +3.3V1 | -5V | -12V1 | +5VSB1 |
|                  |         | +5V2   | +12V2 | +3.3V2 |     | -12V2 | +5VSB2 |
| P1D-5400V        | 400W    | 20A    | 30A   | 20A    | X   | 0.8A  | 3.5A   |
| P1D-5600V        | 600W    | 25A    | 45A   | 25A    | X   | 0.8A  | 3.5A   |
| P1D-5700V        | 700W    | 25A    | 50A   | 25A    | X   | 0.8A  | 3.5A   |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%    | X   | ±5%   | ±5%    |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV   | X   | 50mV  | 50mV   |

### **REMARKS :**

TOTAL OUTPUT POWER OF V1 AND V2 NOT EXCEED 400W / 600W / 700W  
THE OUTPUT CURRENT OF 5V AND 3.3V NOT EXCEED 40A

### **SPECIFICATION :**

TEMPERATURE RANGE : OPERATING 0°C ~50°C

EFFICIENCY : TYPICAL 80-83% AT 25°C 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100ms TO 500ms · OFF DELAY 1ms

HOLD UP TIME : 16ms MINIMUM AT FULL LOAD & NOMINAL INPUT VOLTAGE


OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON/OFF CONTROL

3.3V & 5V REMOTE SENSING

DIMENSION : 300mm(D) × 100mm (W) × 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



# **HIGH EFFICIENCY** AC INPUT TO DC OUTPUT



## **P1D-3940V**

### **INPUT CHARACTERISTICS**

#### **VOLTAGE :**

90~264VAC FULL RANGE

#### **FREQUENCY :**

47 ~ 63HZ

#### **INPUT CURRENT :**

15/7.5 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### **INRUSH CURRENT :**

30/60 AMPS @115/230VAC

#### **POWER FACTOR CORRECTION :**

PFC CAN REACH THE TARGET OF 95% @ 230V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### **EMI :**

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### **EMS :**

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### **SAFETY :**

TO MEET UL, CUL, TUV



### **OUTPUT CHARACTERISTICS**

| MODEL            | WATTAGE | OUTPUT |       |       |     |      |        |
|------------------|---------|--------|-------|-------|-----|------|--------|
|                  |         | +5V1   | +12V1 | +3.3V | -5V | -12V | +5VSB1 |
| P1D-3940V        | 940W    | 25A    | 70A   | X     | X   | X    | 2.5A   |
| REGULATION LOAD  |         | ±5%    | ±5%   | X     | X   | X    | ±5%    |
| RIPPLE AND NOISE |         | 50mV   | 120mV | X     | X   | X    | 50mV   |

#### **REMARKS :**

TOTAL CURRENT OF V1 AND V2 NOT EXCEED EACH MAX LOAD

( FOR EXAMPLE : +12V1 & +12V2 NOT EXCEED 70A )

TOTAL OUTPUT POWER OF V1 AND V2 NOT EXCEED 940W

### **SPECIFICATION :**

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C

EFFICIENCY : TYPICAL 80% AT 25°C 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100ms TO 500ms · OFF DELAY 1Ms

HOLD UP TIME : 16ms MINIMUM AT FULL LOAD & NOMINAL INPUT VOLTAGE


OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON/OFF CONTROL

REMOTE SENSING

DIMENSION : 300mm (D) × 100mm (W) × 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



H1W-5AD0V

INPUT CHARACTERISTICS

- VOLTAGE :  
115 - 240 VAC FULL RANGE
- FREQUENCY :  
47 ~ 63HZ
- INPUT CURRENT :  
15/10 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE
- INRUSH CURRENT :  
15/30 AMPS @ 110/230VAC
- POWER FACTOR CORRECTION :  
PFC CAN REACH THE TARGET OF 95% @ 230V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL&CUL, TUV




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| H1W-5AD0V        | 1200W   | 36A    |       | 31A   | X   | 0.5A  | 4A    |
|                  | 1400W   | 36A    | 116A  | 31A   | X   | 0.5A  | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

- REMARKS :
1. TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 210W.
  2. TOTAL OUTPUT POWER NOT EXCEED 1400W FOR 180~264VAC.
  3. TOTAL OUTPUT POWER NOT EXCEED 1200W FOR 103~132VAC.

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C
- EFFICIENCY:84% TYPICAL @ 230V FULL LOAD
- POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms
- HOLD UP TIME : 17mS MINIMUM AT 800W & NOMINAL INPUT VOLTAGE
- OUTPUT PROTECTION : OPP / OVP / SCP
- 3.3V/5V REMOTE SENSING
- DIMENSION : 295mm (D) × 100mm (W) × 40mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**80 PLUS P2H-5400V**  
**80 PLUS P2H-5500V**  
**80 PLUS P2H-5550V**  
**P2H-5501V**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

10/5 AMPS AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

40/60 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| P2H-5400V        | 400W    | 22A    | 32A   | 22A   | X   | 0.8A  | 3.5A  |
| P2H-5500V        | 500W    | 25A    | 40A   | 25A   | X   | 0.8A  | 3.5A  |
| P2H-5550V        | 550W    | 25A    | 40A   | 25A   | X   | 0.8A  | 3.5A  |
| P2H-5501V        | 500W    | 40A    | 40A   | 40A   | X   | 3A    | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 60mV  | X   | 120mV | 60mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 35A

+5V AND +3.3V TOTAL OUTPUT MAX : 200W (92H-550H)

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

HOLD UP TIME:16mS MINIMUM AT FULL LOAD & NOMINAL INPUT VOLTAGE

EFFICIENCY : 80% TYPICAL @ FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1mS


OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

3.3V & 5V REMOTE SENSING DESIGN

DIMENSION : 215mm (D) x 100mm (W) x 70mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



P2G-5500G  
P2G-5600G  
P2G-5650G

INPUT CHARACTERISTICS

- VOLTAGE :  
90~264 VAC FULL RANGE
- FREQUENCY :  
47 ~ 63HZ
- INPUT CURRENT :  
7/3.5A AT ANY LOW/HIGH RANGE INPUT VOLTAGE  
10/5A AT ANY LOW/HIGH RANGE INPUT VOLTAGE
- INRUSH CURRENT :  
50/100 AMPS @ 115/230VAC
- POWER FACTOR CORRECTION :  
PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL&CUL, TUV, CCC




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| P2G-5500G        | 500W    | 20A    | 40A   | 20A   | X   | 0.5A  | 3A    |
| P2G-5600G        | 600W    | 25A    | 48A   | 25A   | X   | 0.5A  | 3A    |
| P2G-5650G        | 650W    | 25A    | 53A   | 25A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 60mV  | X   | 120mV | 60mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 140W/160W ;  
+5V, +3.3V AND +12V TOTAL MAX : 480/581.5W/630W  
TOTAL POWER 500W/600W

- SPECIFICATION :
- TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C
- HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE
- EFFICIENCY : 87-90% TYPICAL @ 115V FULL LOAD
- POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms
- OUTPUT PROTECTION : OPP / OVP / OCP / SCP
- LEAKAGE CURRENT : 3.5mA. MAX. AT NOMINAL VOLTAGE 250VAC
- DIMENSION : 240mm (D) x 100mm (W) x 70mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



P2M-5600V  
P2M-5700V  
P2M-5800V

INPUT CHARACTERISTICS

VOLTAGE :  
90~264 VAC FULL RANGE  
FREQUENCY :  
47 ~ 63HZ  
INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 600W    | 9A   | 4A   |
| 700W    | 11A  | 5A   |
| 800W    | 12A  | 6A   |

INRUSH CURRENT :  
35/70 AMPS @ 115/230VAC  
POWER FACTOR CORRECTION :  
PFC CAN REACH THE TARGET OF 95% AT  
115/230VAC, FULL LOAD  
EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)  
EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE  
SAFETY :  
TO MEET UL&CUL, TUV, CCC




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| P2M-5600V        | 600W    | 25A    | 46A   | 25A   | X   | 0.8A  | 3.0A  |
| P2M-5700V        | 700W    | 25A    | 50A   | 25A   | X   | 0.8A  | 3.0A  |
| P2M-5800V        | 800W    | 25A    | 62A   | 25A   | X   | 0.8A  | 3.0A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 60mV  | X   | 120mV | 60mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 170W

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~ 80°C  
HUMIDITY : OPERATING :20%-80%, NON-OPERATING :10%-90%  
HOLD UP TIME : 16ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE  
EFFICIENCY : TYPICAL 80~84% @ FULL LOAD  
OUTPUT PROTECTION : OPP / OVP / OCP / SCP  
LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC  
REMOTE ON/OFF CONTROL  
DIMENSION : 280mm (D) X 100mm (W) X 70mm (H)  
THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**80 PLUS HG2-5400V**  
**80 PLUS HG2-5500V**  
**80 PLUS HG2-5600V**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 400W    | 6A   | 3A   |
| 500W    | 8A   | 4A   |
| 600W    | 10A  | 5A   |

#### INRUSH CURRENT :

20/40AMPS @ 115/30VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| HG2-5400V        | 400W    | 20A    | 30A   | 20A   | X   | 0.8A  | 3.5A  |
| HG2-5500V        | 500W    | 20A    | 38A   | 20A   | X   | 0.8A  | 3.5A  |
| HG2-5600V        | 600W    | 25A    | 45A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

THE OUTPUT CURRENT OF +5V & +3.3V NOT EXCEED 40A

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 80-85% @115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms


OUTPUT PROTECTION : OPP / OVP / SCP, RESTART AFTER PROTECTION

LEAKAGE CURRENT : 1.5mA MAX. AT NOMINAL VOLTAGE VAC

REMOTE ON/OFF CONTROL

DIMENSION : 140mm (D) x150mm (W) x 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



# HG2-5400E HG2-5500E HG2-5600E

Erp ready

## INPUT CHARACTERISTICS

### VOLTAGE :

90~264 VAC FULL RANGE

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 400W    | 5.5A | 3A   |
| 500W    | 7A   | 3.5A |
| 600W    | 8.5A | 4.5A |

### INRUSH CURRENT :

35/80 MAX. FOR 115/230VAC

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL, CUL, TUV, CCC



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| HG2-5400E        | 400W    | 21A    | 33A   | 15A   | X   | 0.5A  | 3A    |
| HG2-5500E        | 500W    | 23A    | 41A   | 18A   | X   | 0.5A  | 3A    |
| HG2-5600E        | 600W    | 25A    | 50A   | 20A   | X   | 0.5A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

### REMARKS :

TOTAL OUTPUT CURRENT OF +5V AND +3.3V NOT EXCEED 110W / 125W / 135W  
TOTAL POWER : 400W / 500W / 600W

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C ; STORAGE -20°C ~ 80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 87% @115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / SCP, RESTART AFTER PROTECTION


LEAKAGE CURRENT : 3.5MA MAX. AT NOMINAL VOLTAGE VAC

REMOTE ON/OFF CONTROL

ErP READY

DIMENSION : 140mm (D) x150mm (W) x 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





# **HIGH EFFICIENCY** AC INPUT TO DC OUTPUT



**80 PLUS** HU2-5560V  
**80 PLUS** HU2-5660V  
**80 PLUS** HU2-5760V  
**80 PLUS** HU2-5860V

## INPUT CHARACTERISTICS

### VOLTAGE :

90~264 VAC FULL RANGE

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 560W    | 8A   | 4A   |
| 660W    | 10A  | 5A   |
| 760W    | 12A  | 6A   |
| 860W    | 13A  | 7A   |

### INRUSH CURRENT :

20/40 AMPS @ 115/230VAC

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL&CUL, TUV, CCC



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| HU2-5560V        | 560W    | 22A    | 40A   | 22A   | X   | 0.8A  | 3.5A  |
| HU2-5660V        | 660W    | 25A    | 50A   | 25A   | X   | 0.8A  | 3.5A  |
| HU2-5760V        | 760W    | 25A    | 55A   | 25A   | X   | 0.8A  | 3.5A  |
| HU2-5860V        | 860W    | 25A    | 60A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

### REMARKS :

THE OUTPUT CURRENT OF 5V & 3.3V NOT EXCEED 40A WITH 12CM FAN

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C

HOLD UP TIME : 16mS MINIMUM AT FULL LOAD & NOMINAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 80-85% @ 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1mS


OUTPUT PROTECTION : OPP / OVP / OCP / SCP, RESTART AFTER PROTECTION

LEAKAGE CURRENT : 1.5mA MAX. AT NOMINAL VOLTAGE VAC

REMOTE ON/OFF CONTROL

DIMENSION : 140mm (D) X 150mm (W) X 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



# HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**PSM-5660V**  
**PSM-5760V**  
**PSM-5860V**

## INPUT CHARACTERISTICS

### VOLTAGE :

90~264 VAC FULL RANGE

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 600W    | 10A  | 5A   |
| 760W    | 12A  | 6A   |
| 860W    | 13A  | 7A   |

### INRUSH CURRENT :

20/40 AMPS @ 120/230VAC

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL&CUL, TUV, CCC



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| PSM-5660V        | 660W    | 25A    | 50A   | 25A   | X   | 0.8A  | 3.5A  |
| PSM-5760V        | 760W    | 25A    | 55A   | 25A   | X   | 0.8A  | 3.5A  |
| PSM-5860V        | 860W    | 25A    | 60A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

### REMARKS :

+5V AND +3.3V TOTAL MAX : 40A

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 16ms IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 80-85% @ 115V FULL LOAD


OUTPUT PROTECTION : OPP / OVP / SCP, RESTART AFTER PROTECTION

LEAKAGE CURRENT : 1.5mA MAX. AT NOMINAL VOLTAGE VAC

REMOTE ON/OFF CONTROL

DIMENSION : 160mm (D) x 150mm (W) x 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



# HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**PSL-6A00V**  
**PSL-6C00V**

## INPUT CHARACTERISTICS

### VOLTAGE :

90~264 VAC FULL RANGE

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 1000W   | 14A  | 7A   |
| 1200W   | 15A  | 7.5A |

### INRUSH CURRENT :

20/40 AMPS @ 110/220VAC

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL&CUL, TUV, CCC



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |       |       |       |
|------------------|---------|--------|-------|-------|-------|-------|-------|
|                  |         | +5V    | +12V1 | +12V2 | +3.3V | -12V  | +5VSB |
| PSL-6A00V        | 1000W   | 25A    | 50A   | 50A   | 25A   | 0.8A  | 3.5A  |
| PSL-6C00V        | 1200W   | 25A    | 50A   | 50A   | 25A   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | ±5%   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 120mV | 60mV  | 120mV | 60mV  |

### REMARKS :

+5V AND +3.3V TOTAL MAX. POWER : 170W

+3.3V & +5V AND +12V2 MAX. POWER : 600W

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~40°C ; STORAGE TEMPERATURE : -20°C ~80°C

HOLD UP TIME : 18mS MINIMUM AT 90V FULL LOAD & NOMINAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 81%-86% (1000W) / 83%-88% (1200W) @ 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / SCP / OCP , RESTART AFTER PROTECTION


LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE VAC

REMOTE ON/OFF CONTROL

12C FEATURES (OPTIONAL)

DIMENSION : 220mm (D) x 150mm (W) x 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## R1T2-5120V0H

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| R1T2-5120V0H     | 120W    | 10A    | 10A   | 10A   | X   | 0.3A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V MAX. POWER : 80W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 17ms MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL 86% AT 230V, FULL LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100ms TO 700ms · OFF DELAY 1ms

OUTPUT PROTECTION : OPP / OVP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

Leakage current : Input leakage current from line to ground will be less than 3.5mA rms. Measurement

will be made at 240 VAC and 60Hz.

DIMENSION : 215mm(D) x 106mm(W) x 41.5mm(H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

2/1 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

35/70 AMPS @115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC





## R1T2-5120VFH

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### STEADY-STATE CURRENT :

2/1 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE

#### INRUSH CURRENT :

35/70 AMPS @115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL  
LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| R1T2-5120VFH     | 120W    | 10A    | 10A   | 10A   | X   | 0.3A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V MAX. POWER : 80W. TOTAL POWER:120W (MAX)

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 17mS MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE

EFFICIENCY : THE MAXIMUM POWER SUPPLY SYSTEM EFFICIENCY SHALL BE 86%,  
MEASURED AT NOMINAL input voltage 230 V and full loading(+12V:10A).

POWER GOOD SIGNAL : ON DELAY 100mS TO 700mS · OFF DELAY 1mS

OUTPUT PROTECTION : OPP / OVP / SCP


REMOTE ON/OFF CONTROL

LEAKAGE CURRENT : INPUT LEAKAGE CURRENT FROM LINE TO GROUND WILL BE  
LESS THAN 3.5MA RMS. MEASUREMENT WILL BE MADE AT 240 VAC AND 60HZ.

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

DIMENSION : 215mm (D) x 106mm (W) x 41.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.





**HIGH EFFICIENCY**  
AC INPUT TO DC OUTPUT



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| R1U2-5220V4H     | 220W    | 16A    | 17.5A | 16A   | X   | 0.3A  | 2A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 120W

# R1U2-5220V4H

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 20mS MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL 78% ±2 TYPICAL @230VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 600mS

OUTPUT PROTECTION : OPP / OVP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

DIMENSION : 260mm (D) x 106mm (W) x 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

## INPUT CHARACTERISTICS

### VOLTAGE :

90~264 VAC FULL RANGE

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

2A ( RMS ) FOR 230VAC, 4A ( RMS ) FOR 115VAC

### INRUSH CURRENT :

35/70 AMPS @ 115/230V

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL, CUL, TUV






**OUTPUT CHARACTERISTICS**

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| R1V2-5275V4H     | 275W    | 20A    | 22A   | 20A   | X   | 0.3A  | 2.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
 +5V AND +3.3V TOTAL OUTPUT MAX : 150W  
 +5V, +3.3V, +12V, -12V TOTAL OUTPUT MAX : 263W  
 TOTAL POWER : 275W

## R1V2-5275V4H

**INPUT CHARACTERISTICS**
**VOLTAGE :**

90~264 VAC FULL RANGE

**FREQUENCY :**

47 ~ 63HZ

**INPUT CURRENT :**

2A ( RMS ) FOR 230VAC, 4A ( RMS ) FOR 115VAC

**INRUSH CURRENT :**

15/30 AMPS AT 115/230 VAC

**POWER FACTOR CORRECTION :**

PFC CAN REACH THE TARGET OF 95% AT 115V AND 90% AT 230V, FULL LOAD

**EMI :**

IEC61000-3-2, FCC, CISPR 22(EN 55022)

**EMS :**

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

**SAFETY :**

TO MEET UL, CUL, TUV, CCC

**SPECIFICATION :**

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 16mS MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL 84% AT 230V, FULL LOAD (PER SET)


POWER GOOD SIGNAL : ON DELAY 100mS TO 600mS

OUTPUT PROTECTION : OPP / OVP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

DIMENSION : 295mm (D) x 106mm (W) x 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





M1Y2-5300G2H

M1Y2-5300K2H

OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1Y2-5300G2H     | 300W    | 18A    | 24A   | 18A   | X   | 0.3A  | 3A    |
| M1Y2-5300K2H     | 300W    | 18A    | 24A   | 18A   | X   | 0.3A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V MAX. POWER:120W; TOTAL POWER:300W (MAX)

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 20MSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : THE MAXMUM POWER SUPPLY SYSTEM EFFICIENCY SHALL BE ≥ 86%, MEASURED AT NOMINAL INPUT VOLTAGE 115 V OR 230 V AND FULL LOADING.

LEAKAGE CURRENT : INPUT LEAKAGE CURRENT FROM LINE TO GROUND WILL BE LESS THAN 3.5MA RMS. MEASUREMENT WILL BE MADE AT 240 VAC AND 60HZ.

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1mS

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

WARNING METHOD : AUDIO ALARM (BUZZER SOUND, RESETABLE), FALUT LED, TTL

DIMENSION : 275(D) × 106(W) × 41.3(H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

INPUT CHARACTERISTICS

VOLTAGE :

90~264 VAC FULL RANGE

FREQUENCY :

47 ~ 63HZ

INPUT CURRENT :

5/2.5A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

INRUSH CURRENT :

15/30A @115/230VAC

POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5 SURGE

SAFETY :

TO MEET UL, CUL, TUV, CCC





M1R2-5300V0H  
M1R2-5400V0H

INPUT CHARACTERISTICS

VOLTAGE :

90~264 VAC FULL RANGE

FREQUENCY :

47 ~ 63HZ

INPUT CURRENT :

7A/3A(400W) 6A/3A(300W) AT ANY LOW/HIGH RANGE INPUT VOLTAGE

INRUSH CURRENT :

15/30A @115/230VAC

POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5 SURGE

SAFETY :

TO MEET UL, CUL, TUV, CCC



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1R2-5300V0H     | 300W    | 22A    | 25A   | 22A   | X   | 0.5A  | 3A    |
| M1R2-5400V0H     | 400W    | 22A    | 33A   | 22A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 120mV | X   | 120mV | 120mV |

REMARKS :

+5V AND +3.3V NOT EXCEED 150W; TOTAL POWER NOT EXCEED 400W(M1R2-5400V0H)  
+5V AND +3.3V NOT EXCEED 150W; TOTAL POWER NOT EXCEED 300W(M1R2-5300V0H)

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 11MSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : 88% TYPICAL · AT FULL LOAD 230VAC


LEAKAGE CURRENT : 3.5 mA. MAX. AT NOMINAL VOLTAGE 250VAC

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

WARNING METHOD : AUDIO ALARM (BUZZER SOUND, RESETABLE), FALUT LED, TTL

DIMENSION : 295mm (D) × 106mm (W) × 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## M1R2-5500G0H

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

8/4A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

15/30A @115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1R2-5500G0H     | 500W    | 22A    | 41A   | 22A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V NOT EXCEED 150W; TOTAL POWER NOT EXCEED 500W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 9MSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : 88% TYPICAL · AT FULL LOAD 230VAC

LEAKAGE CURRENT : 3.5 mA. MAX. AT NOMINAL VOLTAGE 240VAC


POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

WARNING METHOD : AUDIO ALARM (BUZZER SOUND, RESETABLE), FALUT LED, TTL

DIMENSION : 295mm (D) × 106mm (W) × 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





# M1S2-5600G2H

## INPUT CHARACTERISTICS

### VOLTAGE :

90~264 VAC FULL RANGE

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

8.5/4.5A AT ANY LOW/HIGH RANGE INPUT VOLTAGE

### INRUSH CURRENT :

35/65 AMPS @ 132/264VAC PER POWER MODULE

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL&CUL, TUV, CCC

## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1S2-5600G2H     | 600W    | 25A    | 50A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

### REMARKS :

TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED 170W, TOTAL POWER 600W

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 16mS MIN. TESTED AT 90% MAXIMUM LOAD AND OVER 100~240VAC INPUT

EFFICIENCY : TYPICAL 86% AT 25°C 230VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1mS

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION


ISOLATION : BUILT-IN THE POWER MODULE

REMOTE SENSING DESIGN

LEAKAGE CURRENT : INPUT LEAKAGE CURRENT FROM LINE TO GROUND WILL BE LESS THAN 3.5MA RMS. MEASUREMENT WILL BE MADE AT 240 VAC AND 60HZ.

DIMENSION : 355mm (D) x 106mm (W) x 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## M1V2-5800V4H M1V2-5801V4H

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

6A ( RMS ) FOR 230VAC, 12A ( RMS ) FOR 115VAC

#### INRUSH CURRENT :

15A MAX. FOR 115 VAC PER MODULE, 30A MAX.  
FOR 230 VAC PER MODULE

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 98% AT 110VAC,  
FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

#### SAFETY :

TO MEET UL, CUL, TUV

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1V2-5800V4H     | 800W    | 22A    | 66A   | 22A   | X   | 0.5A  | 3A    |
| M1V2-5801V4H     | 800W    | 35A    | 66A   | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 150W  
(M1V2-5800V4H); +5V AND +3.3V NOT EXCEED 210W(M1V2-5801V4H)

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C · STORAGE -20°C ~80°C

HOLD UP TIME : 11mS MIN. AT FULL LOAD & 90 VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL 85% AT 115V, TYPICAL 88% AT 230V, FULL LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS


OUTPUT PROTECTION : OPP / OVP / SCP

WARNING METHOD : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

DIMENSION : 355mm (D) x 106mm (W) x 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.







**M1U2-5650V4H**  
**M1U2-5750V4H**  
**M1U2-5651V4H**  
**M1U2-5751V4H**

## INPUT CHARACTERISTICS

### VOLTAGE :

90~264 VAC FULL RANGE

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 650W    | 10A  | 5A   |
| 750W    | 12A  | 6A   |

### INRUSH CURRENT :

15/30A @ 115V/230VAC

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 98% AT 110VAC, FULL LOAD

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL&CUL, TUV, CCC



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1U2-5650V4H     | 650W    | 22A    | 54A   | 22A   | X   | 0.5A  | 3A    |
| M1U2-5750V4H     | 750W    | 22A    | 62A   | 22A   | X   | 0.5A  | 3A    |
| M1U2-5651V4H     | 650W    | 35A    | 54A   | 31A   | X   | 0.5A  | 3A    |
| M1U2-5751V4H     | 750W    | 35A    | 62A   | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

### REMARKS :

+5V AND +3.3V NOT EXCEED 150W : M1U2-5650V4H / M1U2-5750V4H  
+5V AND +3.3V NOT EXCEED 210W : M1U2-5651V4H / M1U2-5751V4H

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C · STORAGE -20°C ~80°C

HOLD UP TIME : 11mS MIN. AT FULL LOAD & 90 VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL 85% AT 115V, 88% AT 230V, FULL LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100ms TO 500ms


OUTPUT PROTECTION : OPP / OVP / SCP

WARNING METHOD : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

DIMENSION : 355mm (D) x 106mm (W) x 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





# M1K2-5A00V4H M1K2-5C00V4H M1K2-5A01V4H M1K2-5C01V4H

## INPUT CHARACTERISTICS

### VOLTAGE :

90~264 VAC FULL RANGE

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

15/7.5 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

### INRUSH CURRENT :

15/30 AMPS @115/230VAC

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 110V , FULL LOAD

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL&CUL, TUV



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1K2-5A00V4H     | 1000W   | 22A    | 83A   | 22A   | X   | 0.5A  | 3A    |
| M1K2-5C00V4H     | 1200W   | 22A    | 100A  | 22A   | X   | 0.5A  | 3A    |
| M1K2-5A01V4H     | 1000W   | 36A    | 83A   | 31A   | X   | 0.5A  | 3A    |
| M1K2-5C01V4H     | 1200W   | 36A    | 100A  | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

### REMARKS :

POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 150W (M1K2-5A00V4H / M1K25C00V4H) 210W (M1K2-5A01V4H / M1K2-5C01V4H)

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C · STORAGE -20°C ~80°C

HOLD UP TIME : 10mS MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL 83% AT 115V, TYPICAL 86% AT 230V, FULL LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS


OUTPUT PROTECTION : OPP / OVP / SCP

WARNING METHOD : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

DIMENSION : 400mm (D) x 106mm (W) x 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### M1P2-5300V4H M1P2-5420V4H M1P2-5500V4H

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264 VAC FULL RANGE

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

5 / 3 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE (300W)

7 / 3 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE (420W)

8 / 4 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE (500W)

##### INRUSH CURRENT :

40/60A @ 115/230VAC (25°C)

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 230V, FULL  
LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1P2-5300V4H     | 300W    | 20A    | 25A   | 20A   | X   | 0.5A  | 3.5A  |
| M1P2-5420V4H     | 420W    | 32A    | 35A   | 25A   | X   | 0.5A  | 3.5A  |
| M1P2-5500V4H     | 500W    | 32A    | 41A   | 25A   | X   | 0.5A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

+5V AND 3.5V TOTAL MAX 140W/170W/170W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~ 40°C , STORAGE : -20°C ~ 80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD IN REGULATION LIMIT AT 90 VAC  
INPUT VOLTAGE

EFFICIENCY : >80% TYPICAL AT 230 VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

REMOTE SENSING DESIGN

DIMENSION : 230mm (D) x 176mm (W) x 41.8mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.



1U REDUNDANT

# HIGH EFFICIENCY AC INPUT TO DC OUTPUT



## R1S2-5120V0H

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| R1S2-5120V0H     | 120W    | 10A    | 10A   | 10A   | X   | 0.3A  | 3.0A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 80W;  
POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 120W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN ALL DC OUTPUT MUST BE MAINTAIN 17MSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 85% AT 230V, 50% OF FULL LOAD

LEAKAGE CURRENT : 3.5 mA. MAX. AT NOMINAL VOLTAGE 250VAC

POWER GOOD SIGNAL : ON DELAY 100mS TO 700mS · OFF DELAY 1mS

OUTPUT PROTECTION : OPP / OVP / SCP

WARNING METHOD : AUDIO ALARM(BUZZER SOUND, RESETABLE), FALUT LED, TTL

DIMENSION : 150mm (D) × 176mm (W) × 41.8mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

2/1 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE

#### INRUSH CURRENT :

35/70 AMPS @115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 110V, FULL  
LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

#### SAFETY :

TO MEET UL, CUL, TUV



HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



R1S2-5180V4H  
R1S2-5300V4H  
R1S2-5380V4H

INPUT CHARACTERISTICS

VOLTAGE :  
90~264 VAC FULL RANGE  
FREQUENCY :  
47 ~ 63HZ  
INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 180W    | 3A   | 1.5A |
| 300W    | 4.5  | 2A   |
| 380W    | 5.5A | 2.5A |

INRUSH CURRENT :  
15/30 AMPS @115/230VAC  
POWER FACTOR CORRECTION :  
PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD  
EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)  
EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE  
SAFETY :  
TO MEET UL&CUL, TUV




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| R1S2-5180V4H     | 180W    | 14A    | 14A   | 12A   | X   | 0.3A  | 2.5A  |
| R1S2-5300V4H     | 300W    | 20A    | 24A   | 20A   | X   | 0.5A  | 2.5A  |
| R1S2-5380V4H     | 380W    | 20A    | 30A   | 20A   | X   | 0.5A  | 2.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 140W  
R1S2-5180V4H : +5V AND +3.3V TOTAL 70W

SPECIFICATION :  
TEMPERATURE RANGE : OPERATING 0°C ~40°C , STORAGE -20°C ~80°C  
HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 16ms IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE  
EFFICIENCY : 78% ±2% TYPICAL AT FULL LOAD 230V (180W) , 84% TYPICAL · AT FULL LOAD 115VAC (300W,380W)  
LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 250VAC  
POWER GOOD SIGNAL : ON DELAY 100mS TO 550mS · OFF DELAY 1Ms  
OUTPUT PROTECTION : OPP / OVP / SCP  
WARNING METHOD : AUDIO ALARM(BUZZER SOUND, RESETABLE), FAULT LED, TTL  
HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION  
DIMENSION : 230(D)×176(W)×41.8(H) mm  
THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



1U REDUNDANT



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| G1W2-5760V3H     | 760W    | 32A    | 62A   | 32A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 190W; TOTAL OUTPUT MAX : 760W

## G1W2-5760V3H

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~ 40°C , STORAGE : -20°C ~ 80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : >80% TYPICAL AT 230 VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

LEAKAGE CURRENT : 3.5 mA. MAX. AT NOMINAL VOLTAGE 250VAC

REMOTE SENSING DESIGN

DIMENSION : 330mm (D) x 206mm (W) x 41.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE

#### FREQUENCY :

47 ~ 63Hz

#### INPUT CURRENT :

11/5.5A MAX AT ANY LOW/HIGH INPUT VOLTAGE

#### INRUSH CURRENT :

60/80 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV





HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



RP1U-5240V

INPUT CHARACTERISTICS

- VOLTAGE :  
90~264 VAC FULL RANGE
- FREQUENCY :  
47 ~ 63HZ
- INPUT CURRENT :  
4/2A @ ANY LOW/HIGH RANGE INPUT VOLTAGE
- INRUSH CURRENT :  
35/70A MAX. @ 115/230 VAC
- POWER FACTOR CORRECTION :  
PFC CAN REACH THE TARGET OF 95% AT 115VAC  
90%@230VAC, FULL LOAD
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL&CUL, TUV, CCC




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| RP1U-5240V       | 240W    | 20A    | 20A   | 20A   | X   | 0.3A  | 2.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
THE OUTPUT CURRENT OF +5V & +3.3V NOT EXCEED 150 WATTS

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C
- HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE
- EFFICIENCY : TYPICAL 78%±2 @ 230V FULL LOAD; EFFICIENCY CALCULATION : WHEN CALCULATING OUTPUT POWER, INTERNAL FAN CURRENT SHALL BE INCLUDED WITH 12V OUTPUT.
- POWER GOOD SIGNALON DELAY 100 ms TO 600 ms, OFF DELAY 1 ms
- OUTPUT PROTECTION : OPP / OVP / SCP
- LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 264VAC
- DIMENSION : 270mm (D) x 100mm (W) x 40.5mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



1U REDUNDANT



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### M1V2-5800V4V M1V2-5801V4V

#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1V2-5800V4V     | 800W    | 22A    | 66A   | 22A   | X   | 0.5A  | 3A    |
| M1V2-5801V4V     | 800W    | 35A    | 66A   | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 150W (M1V2-5800V4V); +5V AND +3.3V NOT EXCEED 210W (M1V2-5801V4V)

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 11mS MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL 85% AT 115V, TYPICAL 88% AT 230V, FULL LOAD (PER SET)

OUTPUT PROTECTION : OPP / OVP / SCP

WARNING METHOD : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

REMOTE SENSING DESIGN

DIMENSION : 400mm (D) X 54.5mm (W) X 84.6mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264 VAC FULL RANGE

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

12/6A MAX AT ANY LOW/HIGH INPUT VOLTAGE

##### INRUSH CURRENT :

15/30A @ 115/230VAC

##### POWER FACTOR CORRECTION :

POWER FACTOR CORRECTIONPFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

##### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### M1V2-5807V4D

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264 VAC FULL RANGE

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

12/6A MAX AT ANY LOW/HIGH INPUT VOLTAGE

##### INRUSH CURRENT :

15/30A @ 115/230VAC

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT       |                |                  |            |                |                  |
|------------------|---------|--------------|----------------|------------------|------------|----------------|------------------|
|                  |         | +5V1<br>+5V2 | +12V1<br>+12V2 | +3.3V1<br>+3.3V2 | -5V<br>-5V | -12V1<br>-12V2 | +5VSB1<br>+5VSB2 |
| M1V2-5807V4D     | 800W    | 20A          | 32A            | 20A              | X          | 0.5A           | 2A               |
| REGULATION LOAD  |         | ±5%          | ±5%            | ±5%              | X          | ±5%            | ±5%              |
| RIPPLE AND NOISE |         | 50mV         | 120m           | 50v              | X          | 120mV          | 50mV             |

##### REMARKS :

TOTAL MAX OUTPUT OF +5V1 AND +3.3V1 NOT EXCEED 135W

TOTAL MAX OUTPUT OF +12V1, +5V1, +3.3V1, -12V1, +5VSB1 NOT EXCEED 400W

TOTAL MAX OUTPUT OF +5V2 AND +3.3V2 NOT EXCEED 135W

TOTAL MAX OUTPUT OF +12V2, +5V2, +3.3V2, -12V2, +5VSB2 NOT EXCEED 400W

TOTAL MAX OUTPUT OF +5VSB1 AND +5VSB2 NOT EXCEED 15W

TOTAL MAX OUTPUT NO EXCEED 800W

##### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 11ms MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL 85% AT 115V, TYPICAL 88% AT 230V, FULL LOAD (PER SET)

OUTPUT PROTECTION : OPP / OVP / SCP / OCP


FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

LEAKAGE CURRENT : INPUT LEAKAGE CURRENT FROM LINE TO GROUND WILL BE LESS THAN 3.5MA RMS. MEASUREMENT WILL BE MADE AT 240 VAC AND 60HZ.

DIMENSION : 450(D) X 54.5(W) X 84.6(H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**M1U2-5650V4V**  
**M1U2-5750V4V**  
**M1U2-5651V4V**  
**M1U2-5751V4V**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 650W    | 10A  | 5A   |
| 750W    | 12A  | 6A   |

#### INRUSH CURRENT :

15/30 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 98% AT 110V, FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1U2-5650V4V     | 650W    | 22A    | 54A   | 22A   | X   | 0.5A  | 3A    |
| M1U2-5750V4V     | 750W    | 22A    | 62A   | 22A   | X   | 0.5A  | 3A    |
| M1U2-5651V4V     | 650W    | 35A    | 54A   | 31A   | X   | 0.5A  | 3A    |
| M1U2-5751V4V     | 750W    | 35A    | 62A   | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 150W (M1U2-5650V4V / M1U2-5750V4V) 210W (M1U2-5651V4V / M1U2-5751V4V)

#### SPECIFICATION :

TEMPERATURE RANGE:OPERATING 0°C ~50°C · STORAGE -20°C ~80°C

HOLD UP TIME : 11mS MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL 85% @ 115V, 88% @ 230V, FULL LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS

OUTPUT PROTECTION : OPP / OVP / SCP


WARNING METHOD : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

REMOTE SENSING DESIGN

DIMENSION : 400mm (D) x 54.5mm (W) x 84.6mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**M1K2-5A00V4V**  
**M1K2-5C00V4V**  
**M1K2-5A01V4V**  
**M1K2-5C01V4V**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

7.5A ( RMS ) FOR 230VAC, 15A ( RMS ) FOR 115VAC

#### INRUSH CURRENT :

15A MAX. FOR 115 VAC PER MODULE, 30A MAX. FOR 230 VAC PER MODULE

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 98% AT 110V, FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1K2-5A00V4V     | 1000W   | 22A    | 83A   | 22A   | X   | 0.5A  | 3A    |
| M1K2-5C00V4V     | 1200W   | 22A    | 100A  | 22A   | X   | 0.5A  | 3A    |
| M1K2-5A01V4V     | 1000W   | 36A    | 83A   | 31A   | X   | 0.5A  | 3A    |
| M1K2-5C01V4V     | 1200W   | 36A    | 100A  | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 150W (M1K2-5A00V4V / M1K2-5C00V4V) 210W (M1K2-5A01V4V / M1K2-5C01V4V)

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C · STORAGE -20°C ~80°C

HOLD UP TIME : 10mS MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL 83% AT 115V, TYPICAL 86% AT 230V, FULL LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS


OUTPUT PROTECTION : OPP / OVP / SCP

WARNING METHOD : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

DIMENSION : 425mm (D) x 54.5mm(W) x 84.6mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |                |       |     |      |                  |
|------------------|---------|--------|----------------|-------|-----|------|------------------|
|                  |         | +5V    | +12V1<br>+12V2 | +3.3V | -5V | -12V | +5VSB1<br>+5VSB2 |
| M1K2-2C00V4D     | 1200W   | X      | 42             | X     | X   | X    | 2                |
| REGULATION LOAD  |         | X      | ±5%            | X     | X   | X    | ±5%              |
| RIPPLE AND NOISE |         | X      | 120mV          | X     | X   | X    | 50mV             |

REMARKS :  
TOTAL OUTPUT POWER NOT EXCEED : 1200W (MAX)  
5VSB1, 5VSB2 TOTAL OUTPUT MAX : 15W

## M1K2-2C00V4D

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C · STORAGE -20°C ~80°C  
HOLD UP TIME : 17mS MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE  
EFFICIENCY : TYPICAL 83% AT 115V, TYPICAL 86% AT 230V, FULL LOAD (PER SET)  
POWER GOOD SIGNAL : ON DELAY 100mS TO 600mS  
OUTPUT PROTECTION : OPP / OVP / SCP / OCP  
WARNING METHOD : LED, BUZZER, TTL SIGNAL  
HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION  
DIMENSION : 450mm (D) x 54.5mm (W) x 84.6mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

**VOLTAGE :**  
90~264 VAC FULL RANGE

**FREQUENCY :**  
47 ~ 63HZ

**INPUT CURRENT :**  
7.5A ( RMS ) FOR 230VAC, 15A ( RMS ) FOR 115VAC


**INRUSH CURRENT :**  
15A MAX. FOR 115 VAC PER MODULE, 30A MAX. FOR 230 VAC PER MODULE

**POWER FACTOR CORRECTION :**  
PFC CAN REACH THE TARGET OF 95% AT 110V, FULL LOAD

**EMI :**  
IEC61000-3-2, FCC, CISPR 22(EN 55022)

**EMS :**  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

**SAFETY :**  
TO MEET UL&CUL, TUV, CCC







## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### M1K2-2C00V4Q

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90 - 264 VAC FULL RANGE

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT (PER POWER MODULE) :

15/8A FOR 115/230VAC

##### INRUSH CURRENT (PER POWER MODULE) :

15/30A MAX. FOR 115/230VAC (25°C)

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |                 |       |     |      |                   |
|------------------|---------|--------|-----------------|-------|-----|------|-------------------|
|                  |         | +5V    | +12V1<br>~+12V4 | +3.3V | -5V | -12V | +5VSB1<br>~+5VSB4 |
| M1K2-2C00V4Q     | 1200W   | X      | 25A             | X     | X   | X    | 1A                |
| REGULATION LOAD  |         | X      | ±5%             | X     | X   | X    | ±5%               |
| RIPPLE AND NOISE |         | X      | 120mV           | X     | X   | X    | 50mV              |

##### REMARKS :

+5VSB1,+5VSB2,+5VSB3,+5VSB4 TOTAL MAX : 15W  
TOTAL OUTPUT POWER NOT EXCEED : 1200W (MAX)

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C

POWER SUPPLY EFFICIENCY TYPICAL 83% AT 115V,12V/100A,5VSB/0.1A(PES SET)

POWER SUPPLY EFFICIENCY TYPICAL 86% AT 230V · 12V/100A,5VSB/0.1A(PES SET)

POWER GOOD SIGNAL : ON DELAY 100 mS TO 600 mS


HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 12V MUST BE MAINTAIN 10MSEC IN REGULATION LIMIT AT 115 VAC INPUT VOLTAGE AND 1000W OUTPUT LOAD

LEAKAGE CURRENT : 3.5mA MAX. AT FULL LOAD 240VAC AND 60HZ

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

DIMENSION : 450(D) × 54.5(W) × 84.6(H) MM

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



2U REDUNDANT



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1H2-5AD0V0V     | 1400W   | 36A    | 116A  | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V NOT EXCEED 210W; TOTAL POWER NOT EXCEED 1000W AT 90~264V, 1200W AT 115~264V, 1400W AT 180~264V

## M1H2-5AD0V0V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : TEST AT 1000W OUTPUT AND INPUT >115VAC, 11ms AT 80% LOAD

EFFICIENCY : TYPICAL 83% AT 115V, MAX LOAD (PER SET)  
TYPICAL 86% AT 230V, MAX LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100ms TO 500ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

LEAKAGE CURRENT : 3.5 mA. MAX. AT NOMINAL VOLTAGE 240VAC

REMOTE ON/OFF CONTROL

DIMENSION : 450mm (D) x 54.5mm (W) x 84.6mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

15/10A MAX AT ANY LOW/HIGH INPUT VOLTAGE

#### INRUSH CURRENT :

15/30 AMPS @ 115/230 VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V AND 90% @230V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |                 |       |     |      |                  |
|------------------|---------|--------|-----------------|-------|-----|------|------------------|
|                  |         | +5V    | +12V1<br>~+12V2 | +3.3V | -5V | -12V | +5VSB<br>~+5VSB2 |
| M1K2-2A07V4D     | 1400W   | X      | 42A             | X     | X   | X    | 1.5A             |
| REGULATION LOAD  |         | X      | ±5%             | X     | X   | X    | ±5%              |
| RIPPLE AND NOISE |         | X      | 120mV           | X     | X   | X    | 50mV             |


REMARKS :  
TOTAL OUTPUT POWER NOT EXCEED : 1000W (MAX).

M1K2-2A07V4D

INPUT CHARACTERISTICS

- VOLTAGE :**  
90 - 264 VAC FULL RANGE
- FREQUENCY :**  
47 ~ 63HZ
- INPUT CURRENT (PER POWER MODULE) :**  
15/7.5 FOR 115/230VAC
- INRUSH CURRENT (PER POWER MODULE) :**  
15/30A MAX. FOR 115/230VAC (25°C)
- POWER FACTOR CORRECTION :**  
PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2
- EMI :**  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :**  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :**  
TO MEET UL, CUL, TUV

- SPECIFICATION :**
- TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C
- POWER SUPPLY EFFICIENCY TYPICAL 83% AT 115V,12V/83A,5VSB/0.1A(PER SET)
- POWER SUPPLY EFFICIENCY TYPICAL 86% AT 230V · 12V/83A,5VSB/0.1A(PER SET)
- POWER GOOD SIGNAL : ON DELAY 100 mS TO 500 mS
- HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 12V MUST BE MAINTAIN 17MSEC IN REGULATION LIMIT AT 115 VAC INPUT VOLTAGE AND 1000W OUTPUT LOAD
- OUTPUT PROTECTION : OCP
- DIMENSION : 485(D) × 54.5(W) × 84.6(H) MM
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



2U REDUNDANT



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### PSS2-5A00V3V

2U REDUNDANT

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264 VAC FULL RANGE

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

15A/7.5A @ ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

15/30AMPS @ 115/230 VAC

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL&CUL, TUV

#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| PSS2-5A00V3V     | 1000W   | 22A    | 83A   | 22A   | X   | 0.5A  | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

POWER MODULE TOTAL OUTPUT POWER OF +5V & +3.3V NOT EXCEED 150W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~ 50°C ; STORAGE : -20°C ~ 80°C

HOLD UP TIME : 5V MUST MAINTAIN 10 mS IN REGULATION LIMIT AT 90V INPUT VOLTAGE

EFFICIENCY : TYPICAL 83% AT 115V, TYPICAL 86% AT 230V, FULL LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms

OUTPUT PROTECTION : OPP / OVP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

REMOTE SENSING DESIGN

DIMENSION : 385mm (D) x 65mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| R1S2-5120V0V     | 120W    | 10A    | 10A   | 10A   | X   | 0.3A  | 3.0A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |


REMARKS :  
POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 80W;  
POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 120W

R1S2-5120V0V

INPUT CHARACTERISTICS

- VOLTAGE :  
90~264 VAC FULL RANGE
- FREQUENCY :  
47 ~ 63HZ
- INPUT CURRENT :  
2/1 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE
- INRUSH CURRENT :  
35/70 AMPS @115/230VAC
- POWER FACTOR CORRECTION :  
PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL&CUL, TUV

- SPECIFICATION :
- TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C
- HOLD UP TIME : WHEN POWER SHUTDOWN ALL DC OUTPUT MUST BE MAINTAIN 17MSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE
- EFFICIENCY : TYPICAL 85% AT 230V, 50% OF FULL LOAD (PER SET)
- LEAKAGE CURRENT : 3.5 MA. MAX. AT NOMINAL VOLTAGE 250VAC
- POWER GOOD SIGNAL : ON DELAY 100ms TO 700ms
- OUTPUT PROTECTION : OPP / OVP / SCP
- WARNING METHOD : AUDIO ALARM(BUZZER SOUND, RESETABLE), FALUT LED, TTL
- DIMENSION : 150mm (D) × 85mm (W) × 84mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



R1S2-5300V4V  
R1S2-5380V4V

INPUT CHARACTERISTICS

**VOLTAGE :**  
90~264 VAC FULL RANGE  
**FREQUENCY :**  
47 ~ 63HZ  
**INPUT CURRENT :**

| WATTAGE | 115V | 230V |
|---------|------|------|
| 300W    | 4.5  | 2    |
| 380W    | 5.5  | 2.5  |

**INRUSH CURRENT :**  
15/30 AMPS @115/230VAC  
**POWER FACTOR CORRECTION :**  
PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2  
**EMI :**  
IEC61000-3-2, FCC, CISPR 22(EN 55022)  
**EMS :**  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE  
**SAFETY :**  
TO MEET UL, CUL, TUV, CCC




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| R1S2-5300V4V     | 300W    | 20     | 24    | 20    | X   | 0.5   | 2.5   |
| R1S2-5380V4V     | 380W    | 20     | 30    | 20    | X   | 0.5   | 2.5   |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 140W

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20°C ~80°C  
HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 16MSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE  
EFFICIENCY : 84% TYPICAL · AT FULL LOAD 115VAC  
POWER GOOD SIGNAL : ON DELAY 100ms TO 550ms · OFF DELAY 1Ms  
OUTPUT PROTECTION : OPP / OVP / SCP  
FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL  
HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION  
ISOLATION : BUILT-IN THE POWER MODULE  
LEAKAGE CURRENT : 3.5 MA. MAX. AT NOMINAL VOLTAGE 250VAC  
REMOTE SENSING DESIGN  
DIMENSION : 207mm (D) × 85mm (W) × 84mm (H)  
THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





HIGH EFFICIENCY  
AC INPUT TO DC OUTPUT



R1S2-5507V4V

INPUT CHARACTERISTICS

- VOLTAGE :  
110 ~ 240 VAC (WITH ± 10% TOLERANCE)
- FREQUENCY :  
47 ~ 63HZ
- INPUT CURRENT :  
15 / 30 AMPS @115/230 VAC (AT 25 DEGREES AMBIENT COLD START FOR EACH POWER UNIT)
- INRUSH CURRENT :  
60/80 AMPS @115/230VAC
- POWER FACTOR CORRECTION :  
PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV, CCC




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| R1S2-5507V4V     | 500W    | 20     | 37.5  | 20    | X   | 0.5   | 2.5   |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 140W  
TOTAL OUTPUT MAX : 500W

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20°C ~80°C
- HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 16MSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE
- EFFICIENCY : 82% TYPICAL · AT FULL LOAD 115VAC
- POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1ms
- OUTPUT PROTECTION : OPP / OVP / SCP
- FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL
- HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION
- ISOLATION : BUILT-IN THE POWER MODULE
- LEAKAGE CURRENT : 3.5 MA. MAX. AT NOMINAL VOLTAGE 250VAC
- REMOTE ON/OFF CONTROL
- DIMENSION : 217mm (D) x 85mm (W) x 84mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



2U REDUNDANT



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**M1P2-5300V4V**

**80 PLUS M1P2-5420V4V**

**80 PLUS M1P2-5500V4V**

2U REDUNDANT

### INPUT CHARACTERISTICS

#### VOLTAGE :

90V ~ 264VAC (WITH  $\pm 10\%$  TOLERANCE)

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

5/3 MAX AT ANY LOW/HIGH INPUT VOLTAGE (300W) ; 8/4A MAX AT ANY LOW/HIGH INPUT VOLTAGE(420W,500W)

#### INRUSH CURRENT :

40/60A @ 115/230VAC (25°C)

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT    |           |           |     |            |           |
|------------------|---------|-----------|-----------|-----------|-----|------------|-----------|
|                  |         | +5V       | +12V      | +3.3V     | -5V | -12V       | +5VSB     |
| M1P2-5300V4V     | 300W    | 20A       | 25A       | 20A       | X   | 0.5A       | 3.5A      |
| M1P2-5420V4V     | 420W    | 32A       | 35A       | 25A       | X   | 0.5A       | 3.5A      |
| M1P2-5500V4V     | 500W    | 32A       | 41A       | 25A       | X   | 0.5A       | 3.5A      |
| REGULATION LOAD  |         | $\pm 5\%$ | $\pm 5\%$ | $\pm 5\%$ | X   | $\pm 10\%$ | $\pm 5\%$ |
| RIPPLE AND NOISE |         | 50mV      | 120mV     | 50mV      | X   | 120mV      | 50mV      |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 140W / 170W / 170W ; TOTAL OUTPUT MAX 300W / 420W / 500W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C --- 40°C, STORAGE : -20°C --- 80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : >80% TYPICAL AT 230 VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

REMOTE SENSING DESIGN

DIMENSION : 217mm (D) x 85mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**M1D2-5300V0V**  
**M1D2-5400V0V**  
**M1D2-5500G0V**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90V ~ 264VAC (WITH  $\pm 10\%$  TOLERANCE)

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 300W    | 6    | 3    |
| 400W    | 7    | 3    |
| 500W    | 8    | 4    |

#### INRUSH CURRENT :

15/30A @115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT    |           |           |     |           |           |
|------------------|---------|-----------|-----------|-----------|-----|-----------|-----------|
|                  |         | +5V       | +12V      | +3.3V     | -5V | -12V      | +5VSB     |
| M1D2-5300V0V     | 300W    | 22A       | 25A       | 22A       | X   | 0.5A      | 3A        |
| M1D2-5400V0V     | 400W    | 22A       | 33A       | 22A       | X   | 0.5A      | 3A        |
| M1D2-5500G0V     | 500W    | 22A       | 41A       | 22A       | X   | 0.5A      | 3A        |
| REGULATION LOAD  |         | $\pm 5\%$ | $\pm 5\%$ | $\pm 5\%$ | X   | $\pm 5\%$ | $\pm 5\%$ |
| RIPPLE AND NOISE |         | 50mV      | 120mV     | 50mV      | X   | 120mV     | 50mV      |

#### REMARKS :

1. TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED 150W.
2. POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 300W/400W/500W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING  $0^{\circ}\text{C} \sim 50^{\circ}\text{C}$  , STORAGE  $-20^{\circ}\text{C} \sim 80^{\circ}\text{C}$

HOLD UP TIME : 8ms MINIMUM AT 80% MAX. LOAD & NOMINAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 88% AT 230V, FULL LOAD (PER SET)

INPUT LEAKAGE CURRENT FROM LINE TO GROUND WILL BE LESS THAN 3.5MA RMS. MEASUREMENT WILL BE MADE AT 240 VAC AND 60HZ.

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

REMOTE ON/OFF CONTROL

BALANCE LOAD SHARING DESIGN


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

DIMENSION : 170(D)  $\times$  101.2(W)  $\times$  84(H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



2U REDUNDANT



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### M1D2-5600V0V M1D2-5700V0V M1D2-5800V0V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90 ~ 264VAC FULL RANGE

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 600     | 10   | 5    |
| 700     | 11   | 5.5  |
| 800     | 12   | 6    |

15/30A @115/230VAC

##### INRUSH CURRENT :

15/30A @ 115/230VAC (25°C)

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 230V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1D2-5600V0V     | 600W    | 36A    | 50A   | 31A   | X   | 0.5A  | 3A    |
| M1D2-5700V0V     | 700W    | 36A    | 58A   | 31A   | X   | 0.5A  | 3A    |
| M1D2-5800V0V     | 800W    | 36A    | 66A   | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

1. TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED210W.
2. POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 600W/700W/800W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C

HOLD UP TIME : 11ms MINIMUM AT 80% MAX. LOAD & NOMINAL INPUT VOLTAGE

EFFICIENCY : (PER SET) : POWER SUPPLY EFFICIENCY TYPICAL 85 % AT 115V · FULL LOAD / POWER SUPPLY EFFICIENCY TYPICAL 88 % AT 230V · FULL LOAD.


INPUT LEAKAGE CURRENT FROM LINE TO GROUND WILL BE LESS THAN 3.5MA RMS. MEASUREMENT WILL BE MADE AT 240 VAC AND 60HZ.

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

WARNING METHOD : AUDIO ALARM (BUZZER SOUND, RESETABLE), FALUT LED, TTL

DIMENSION : 200(D) × 101.2(W) × 84(H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### M1W2-5600G0V M1W2-5700G0V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90 ~ 264VAC FULL RANGE

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

8/4A MAX AT ANY LOW/HIGH INPUT VOLTAGE (600W)

9.5/5A MAX AT ANY LOW/HIGH INPUT VOLTAGE (700W)

##### INRUSH CURRENT :

60A MAX. FOR 115 VAC PER MODULE ; 80A MAX. FOR 230 VAC PER MODULE

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V AND 90% @ 230V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |      |       |     |       |       |
|------------------|---------|--------|------|-------|-----|-------|-------|
|                  |         | +5V    | +12V | +3.3V | -5V | -12V  | +5VSB |
| M1W2-5600G0V     | 600W    | 32A    | 50A  | 25A   | X   | 0.8A  | 3A    |
| M1W2-5700G0V     | 700W    | 36A    | 58A  | 25A   | X   | 0.8A  | 3A    |
| RIPPLE AND NOISE |         | 50mV   | 50mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX 170W/190W; TOTAL OUTPUT MAX:600W/700W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 16mS MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE (TESTED AT 90% OF MAXIMUM LOAD AND OVER 100-240VAC INPUT)

EFFICIENCY : TYPICAL >86% AT 230V, 20%~100% MAX LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1mS

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION


ISOLATION : BUILT-IN THE POWER MODULE

LEAKAGE CURRENT : 3.5 mA. MAX. AT NOMINAL VOLTAGE 250VAC

REMOTE ON/OFF CONTROL

DIMENSION : 300mm (D) x 101.2mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## M1W2-5700K0V

2U REDUNDANT

### INPUT CHARACTERISTICS

#### VOLTAGE :

90 ~ 264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

9.5/5A MAX AT ANY LOW/HIGH INPUT VOLTAGE (700W)

#### INRUSH CURRENT :

60A MAX. FOR 115 VAC PER MODULE ; 80A MAX. FOR 230 VAC PER MODULE

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V AND 90% @230V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |      |       |     |       |       |
|------------------|---------|--------|------|-------|-----|-------|-------|
|                  |         | +5V    | +12V | +3.3V | -5V | -12V  | +5VSB |
| M1W2-5700K0V     | 700W    | 36A    | 58A  | 25A   | X   | 0.8A  | 3A    |
| RIPPLE AND NOISE |         | 50mV   | 50mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX 170W/190W; TOTAL OUTPUT MAX : 700W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 16mS MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE (TESTED AT 90% OF MAXIMUM LOAD AND OVER 100-240VAC INPUT)

EFFICIENCY : TYPICAL >86% AT 230V, 20%~100% MAX LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1mS

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION


ISOLATION : BUILT-IN THE POWER MODULE

LEAKAGE CURRENT : 3.5 mA. MAX. AT NOMINAL VOLTAGE 250VAC

REMOTE ON/OFF CONTROL

DIMENSION : 300mm (D) x 101.2mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



- M1W2-5810V3V**
- M1W2-5910V3V**
- M1W2-5A10V3V**
- M1W2-5E00V3V**
- M1W2-5E01V3V**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90V ~ 264VAC (WITH  $\pm 10\%$  TOLERANCE)

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 810W    | 12A  | 6A   |
| 910W    | 14A  | 7A   |
| 1010W   | 15A  | 7.5A |
| 1400W   | 15A  | 10A  |

#### INRUSH CURRENT :

15/30 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT    |           |           |     |           |           |
|------------------|---------|-----------|-----------|-----------|-----|-----------|-----------|
|                  |         | +5V       | +12V      | +3.3V     | -5V | -12V      | +5VSB     |
| M1W2-5810V3V     | 810W    | 24A       | 66A       | 24A       | X   | 1.5A      | 4A        |
| M1W2-5910V3V     | 910W    | 24A       | 75A       | 24A       | X   | 1.5A      | 4A        |
| M1W2-5A10V3V     | 1010W   | 24A       | 83A       | 24A       | X   | 1.5A      | 4A        |
| M1W2-5E00V3V     | 1400W   | 24A       | 116A      | 24A       | X   | 1.5A      | 4A        |
| M1W2-5E01V3V     | 1400W   | 35A       | 116A      | 31A       | X   | 0.5A      | 4A        |
| REGULATION LOAD  |         | $\pm 5\%$ | $\pm 5\%$ | $\pm 5\%$ | X   | $\pm 5\%$ | $\pm 5\%$ |
| RIPPLE AND NOISE |         | 50mV      | 120mV     | 50mV      | X   | 120mV     | 50mV      |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 135W / 210W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~ 80°C

EFFICIENCY : TYPICAL 84% AT 115VAC, 86% AT 230V, FULL LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100 mS TO 500 mS

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

WARNING METHOD : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION


ISOLATION : BUILT-IN THE POWER MODULE

REMOTE SENSING DESIGN

DIMENSION : 300mm (D) x 101.2mm (W) x 84mm (H)

M1W2-5E01V3V : 320mm (D) x 101.2mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



2U REDUNDANT



## M1W2-5911V3V

2U REDUNDANT

### INPUT CHARACTERISTICS

#### VOLTAGE :

90 ~ 264 VAC FULL RANGE.

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

14/7 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE

#### INRUSH CURRENT :

15/30 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL  
LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

#### SAFETY :

TO MEET UL, CUL, TUV



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1W2-5911V3V     | 910W    | 35A    | 75A   | 31A   | X   | 0.5A  | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 210W.  
POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 910W.

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~ 80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 12V MUST BE MAINTAIN  
16MSEC IN REGULATION LIMIT AT 90 VAC INPUT VOLTAGE.

EFFICIENCY : TYPICAL 84% AT 115VAC, 86% AT 230V, FULL LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100 mS TO 500 mS

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

REMOTE SENSING DESIGN

DIMENSION : 320 (D) x 101.2 (W) x 84 (H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### M1W2-7AG0VFB

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90V ~ 264VAC (WITH  $\pm 10\%$  TOLERANCE)

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

15/12A MAX AT ANY LOW/HIGH INPUT VOLTAGE

##### INRUSH CURRENT :

15A MAX. FOR 115 VAC PER MODULE ; 30A MAX. FOR 230 VAC PER MODULE

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V AND 90% @230V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

UL&CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT               |           |           |     |            |           |
|------------------|---------|----------------------|-----------|-----------|-----|------------|-----------|
|                  |         | +5V1<br>+5V2<br>+5V3 | +12V      | +3.3V     | -5V | -12V       | +5VSB     |
| M1W2-7AG0VFB     | 1700W   | 36A<br>25A<br>25A    | 141A      | 31A       | X   | 0.5A       | 4A        |
| REGULATION LOAD  |         | $\pm 5\%$            | $\pm 5\%$ | $\pm 5\%$ | X   | $\pm 10\%$ | $\pm 5\%$ |
| RIPPLE AND NOISE |         | 50mV                 | 120mV     | 50mV      | X   | 120mV      | 50mV      |

##### REMARKS :

+5V1 AND +3.3V MAX. POWER:210W; +5V2 AND +5V3 MAX. POWER:250W;  
1000W AT 90-264  
1200W AT 115-264  
1700W AT 180-264

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 9ms MIN. AT FULL LOAD & 115 VAC INPUT VOLTAGE (TESTED AT 90% OF MAXIMUM LOAD AND OVER 100-240VAC INPUT)(PER SET)

EFFICIENCY : THE MAXIMUM POWER SUPPLY SYSTEM EFFICIENCY SHALL BE 82%, MEASURED AT NOMINAL INPUT VOLTAGE 115V@ 12V/100A, 5VSB/0.1A. 84%, MEASURED AT NOMINAL INPUT VOLTAGE 230V@ 12V/142A, 5VSB/0.1A.

POWER GOOD SIGNAL : ON DELAY 100ms TO 500ms · OFF DELAY 1ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION


ISOLATION : BUILT-IN THE POWER MODULE

LEAKAGE CURRENT : 3.5 mA. MAX. AT NOMINAL VOLTAGE 250VAC

REMOTE ON/OFF CONTROL

DIMENSION : 310mm (D) x 101.2mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC - AND SAFETY-REGULATIONS.





**G1W2-5660V3V**

**G1W2-5760V3V**

**G1W2-5860V3V**

**G1W2-5960V3V**

2U REDUNDANT

## INPUT CHARACTERISTICS

### VOLTAGE :

90V ~ 264VAC (WITH  $\pm 10\%$  TOLERANCE)

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 660W    | 10A  | 5A   |
| 760W    | 11A  | 5.5A |
| 880W    | 13A  | 6.5A |
| 960W    | 14A  | 7A   |

### INRUSH CURRENT :

60/80 AMPS @ 115/230VAC

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL, CUL, TUV, CCC



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT    |           |           |     |           |           |
|------------------|---------|-----------|-----------|-----------|-----|-----------|-----------|
|                  |         | +5V       | +12V      | +3.3V     | -5V | -12V      | +5VSB     |
| G1W2-5660V3V     | 660W    | 25A       | 55A       | 25A       | X   | 0.8A      | 3.5A      |
| G1W2-5760V3V     | 760W    | 32A       | 62A       | 32A       | X   | 0.8A      | 3.5A      |
| G1W2-5860V3V     | 860W    | 32A       | 70A       | 32A       | X   | 0.8A      | 3.5A      |
| G1W2-5960V3V     | 960W    | 32A       | 78A       | 32A       | X   | 0.8A      | 3.5A      |
| REGULATION LOAD  |         | $\pm 5\%$ | $\pm 5\%$ | $\pm 5\%$ | X   | $\pm 5\%$ | $\pm 5\%$ |
| RIPPLE AND NOISE |         | 50mV      | 120mV     | 50mV      | X   | 120mV     | 50mV      |

### REMARKS :

\* +5V AND +3.3V TOTAL OUTPUT MAX : 190W

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING :  $0^{\circ}\text{C} \sim 40^{\circ}\text{C}$ , STORAGE :  $-20^{\circ}\text{C} \sim 80^{\circ}\text{C}$

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY :  $> 80\%$  TYPICAL AT 230 VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP


WARNING METHOD : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

REMOTE SENSING DESIGN

DIMENSION : 300mm (D) x 101.2mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





**G1W2-5760V2V**  
**G1W2-5860V2V**  
**G1W2-5A10V2V**  
**G1W2-5C00V2V**

## INPUT CHARACTERISTICS

### VOLTAGE :

90 ~ 264VAC FULL RANGE

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 760W    | 11A  | 5.5A |
| 860W    | 13A  | 6.5A |
| 1010W   | 15A  | 7A   |
| 1200W   | 15A  | 7A   |

### INRUSH CURRENT :

40/60 AMPS @ 115/230VAC

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL, CUL, TUV, CCC



**HIGH EFFICIENCY**  
**AC INPUT TO DC OUTPUT**

## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| G1W2-5760V2V     | 760W    | 32A    | 62A   | 32A   | X   | 0.8A  | 3.5A  |
| G1W2-5860V2V     | 860W    | 32A    | 70A   | 32A   | X   | 0.8A  | 3.5A  |
| G1W2-5A10V2V     | 1010W   | 32A    | 83A   | 32A   | X   | 0.8A  | 3.5A  |
| G1W2-5C00V2V     | 1200W   | 36A    | 98A   | 36A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

### REMARKS :

\* +5V AND +3.3V TOTAL OUTPUT MAX : 190W; TOTAL POWER 860W MAX.

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~40°C , STORAGE : -20°C ~80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : >85% TYPICAL AT 230 VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION


ISOLATION : BUILT-IN THE POWER MODULE

REMOTE ON/OFF CONTROL

LEAKAGE CURRENT:INPUT LEAKAGE CURRENT FROM LINE GROUND BE LESS THAN 3.5mA RMS. MEASUREMENT MADE AT 240 VAC AND 60HZ

DIMENSION : 300mm (D) x 101.2mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



2U REDUNDANT



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### **G1W2-5A10V3V** **G1W2-5C00V3V**

2U REDUNDANT

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90 ~ 264VAC FULL RANGE  
200 ~ 264VAC (OUTPUT : 1200W)

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

15/7A MAX AT ANY LOW/HIGH INPUT VOLTAGE

##### INRUSH CURRENT :

60/80 AMPS @ 115/230VAC

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115V, FULL LOAD

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| G1W2-5A10V3V     | 1010W   | 32A    | 83A   | 32A   | X   | 0.8A  | 3.5A  |
| G1W2-5C00V3V     | 1200W   | 36A    | 98A   | 36A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 190W (G1W2-5A10V3V) 210W (G1W2-5C00V3V)  
TOTEL OUTPUT MAX. 1010W/1200W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~40°C , STORAGE : -20°C ~80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE  
(G1W2-5A10V3V)  
12 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE  
(G1W2-5C00V3V)

EFFICIENCY : >80% TYPICAL AT 230 VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

WARNING METHOD : LED, BUZZER, TTL SIGNAL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

REMOTE SENSING DESIGN

DIMENSION : 300mm (D) x 101.2mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## AC INPUT TO DC OUTPUT



### G1W2-5AE0G2V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90 ~ 264VAC FULL RANGE

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

15/7.5A MAX AT ANY LOW/HIGH INPUT VOLTAGE

##### INRUSH CURRENT :

40/60 AMPS @ 115/230VAC

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| G1W2-5AE0G2V     | 1500W   | 36A    | 124A  | 36A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

\* +5V AND +3.3V TOTAL OUTPUT MAX : 190W; TOTAL POWER 1500W MAX.  
115VAC ONLY : 1200W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~40°C , STORAGE : -20°C ~80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : >80% TYPICAL AT 230 VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

REMOTE SENSING DESIGN

DIMENSION : 300mm (D) x 101.2mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



2U REDUNDANT



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| MTW2-5960V2V     | 960W    | 32     | 77    | 36    | X   | 0.8   | 3.5   |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 200W; TOTAL OUTPUT MAX : 960W

## MTW2-5960V2V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~45°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS IN REGULATOR LIMIT AT 90VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL >80% AT 25°C 115VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

REMOTE ON/OFF CONTROL

COOLING : TWO 38mm DC FANS (EACH MODULE)

DIMENSION : 300mm (D) x 101mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90 ~ 264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

15/8AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

40/60 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| MTW2-5AD0V2V     | 1400W   | 50     | 100   | 12    | X   | 0.8   | 3     |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 310W; TOTAL OUTPUT MAX : 1400W

## MTW2-5AD0B2V

### INPUT CHARACTERISTICS

#### VOLTAGE :

115 ~ 264VAC FULL RANGE (90V ONLY 1000W)

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

15/10AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

40/80 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

HOLD UP TIME : 10mS IN REGULATOR LIMIT AT 90VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL >82% AT 25°C 230VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION


ISOLATION : BUILT-IN THE POWER MODULE

REMOTE ON/OFF CONTROL

COOLING : TWO 38mm DC FANS (EACH MODULE)

DIMENSION : 300mm (D) x 101mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### 80 PLUS R2K-5800V R2K-5A00V R2K-5C00V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

100~240±10%VAC(OUTPUT 1000W);  
200~240±10%VAC (OUTPUT 1200W)

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 800W    | 12A  | 6A   |
| 1000W   | 15A  | 7A   |
| 1200W   | X    | 9A   |

##### INRUSH CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 800W    | 18A  | 36A  |
| 1000W   | 25A  | 50A  |
| 1200W   | X    | 50A  |

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT  
115/230VAC, FULL LOAD

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| R2K-5800V4V      | 800W    | 32A    | 65A   | 32A   | X   | 0.5A  | 3.5A  |
| R2K-5A00V4V      | 1000W   | 32A    | 83A   | 32A   | X   | 0.5A  | 3.5A  |
| R2K-5C00V4V      | 1200W   | 32A    | 100A  | 32A   | X   | 0.5A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT 190W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~40°C ,STORAGE -20°C ~80°C

HOLD UP TIME : POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 16mSEC IN  
REGULATION LITMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 86% MAX @ 230V (ANY DIFFERENCE EITHER ON THE DC  
OUTPUT CABLE(I.E., LENGTH, WIRE GAUGE) OR ON THE ACCURATE OF INSTRUMENTS  
WILL CONCLUDE DIFFERENT TEST RESULT.

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

WARNING METHOD : LED, BUZZER, TTL SIGNAL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

LEAKAGE CURRENT 3.5mA MAX. AT NOMINAL VOLTAGE 250VAC

REMOTE ON/OFF CONTROL

DIMENSION : 340mm (D) x 101mm (W) x 82mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### 80 PLUS R2K-5800V4D

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90 ~ 264VAC FULL RANGE

##### FREQUENCY :

47~63HZ

##### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 800W    | 12A  | 6A   |

##### INRUSH CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 800W    | 18A  | 36A  |

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 230V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET, UL, CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| R2K-5800V4D      | 800W    | 32A    | 65A   | 32A   | X   | 0.5A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARK :

+5V AND +3.3V TOTAL OUTPUT 190W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C ,STORAGE -20°C ~ 80°C

HOLD UP TIME : POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 16mSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 86% MAX @ 230V (ANY DIFFERENCE EITHER ON THE DC OUTPUT CABLE(I.E., LENGTH, WIRE GAUGE) OR ON THE ACCURATE OF INSTRUMENTS WILL CONCLUDE DIFFERENT TEST RESULT.

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

LEAKAGE CURRENT : 3.5mA. MAX. AT NOMINAL VOLTAGE 250VAC

REMOTE ON/OFF CONTROL

DIMENSION : 397mm (D) x 101mm (W) x 82mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS



2U REDUNDANT



## PRP-5560G0V

### INPUT CHARACTERISTICS

#### VOLTAGE :

90 ~ 264VAC FULL RANGE

#### FREQUENCY :

47~63HZ

#### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 560W    | 8.5A | 4.5A |

#### INRUSH CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 560W    | 35A  | 80A  |

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 230V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET, UL, CUL, TUV, CCC



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| PRP-5560G0V      | 560W    | 20A    | 46A   | 20A   | X   | 0.5A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARK :

+5V AND +3.3V TOTAL OUTPUT 140W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C ,STORAGE -20°C ~ 80°C

HOLD UP TIME : POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 13mSEC IN REGULATION LITMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 86% MAX @ 230V (ANY DIFFERENCE EITHER ON THE DC OUTPUT CABLE(I.E., LENGTH, WIRE GAUGE) OR ON THE ACCURATE OF INSTRUMENTS WILL CONCLUDE DIFFERENT TEST RESULT.

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

LEAKAGE CURRENT : 3.5mA. MAX. AT NOMINAL VOLTAGE 250VAC

REMOTE ON/OFF CONTROL

DIMENSION : 217mm (D) x 85mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS







## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### S1Z2-5800K2V S1Z2-5700K2V S1Z2-5600K2V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90 ~ 264VAC FULL RANGE

##### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 600W    | 11   | 5.5  |
| 700W    | 11   | 5.5  |
| 800W    | 12   | 6    |

##### INRUSH CURRENT :

15A MAX. FOR 115 VAC PER MODULE ; 30A MAX.  
FOR 230 VAC PER MODULE

##### POWER FACTOR CORRECTION :

PFC CAN UP TO THE TARGET OF 95% @230V,  
FULL LOAD, FOLLOWING THE STANDARD OF  
EN 61000-3-2

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5  
SURGE

##### SAFETY :

UL&CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| S1Z2-5800K2V     | 800W    | 36A    | 66A   | 31A   | X   | 0.5A  | 3A    |
| S1Z2-5700K2V     | 700W    | 36A    | 58A   | 31A   | X   | 0.5A  | 3A    |
| S1Z2-5600K2V     | 600W    | 36A    | 50A   | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

+5V AND +3.3V MAX. POWER: 210W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 10mS MIN. AT FULL LOAD (TESTED AT 80% OF MAXIMUM LOAD

EFFICIENCY : THE MAXIMUM POWER SUPPLY SYSTEM EFFICIENCY SHALL BE 88%,  
MEASURED AT NOMINAL INPUT VOLTAGE 230V@ FULL LOAD.

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION


ISOLATION : BUILT-IN THE POWER MODULE

LEAKAGE CURRENT : INPUT LEAKAGE CURRENT FROM LINE TO GROUND WILL BE  
LESS THAN 3.5mA RMS. MEASUREMENT WILL BE MADE AT 240 VAC AND 60HZ.

REMOTE ON/OFF CONTROL

DIMENSION : 240mm (D) x 85mm (W) x 83mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



## MRT-5320G0V MRT-5450G0V

MINI REDUNDANT

### INPUT CHARACTERISTICS

#### VOLTAGE :

90 ~ 264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

5/3A @115/230VAC (320W)

7/3A @115/230VAC (450W)

#### INRUSH CURRENT :

25 / 50A @ 115 / 230 VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| MRT-5320G0V      | 320W    | 25A    | 26A   | 20A   | X   | 0.5A  | 3A    |
| MRT-5450G0V      | 450W    | 25A    | 37A   | 20A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±7%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT CURRENT : 150W  
TOTAL POWER : 320W/450W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~ 80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & 90 VAC INPUT VOLTAGE

EFFICIENCY : THE MAXIMUM POWER SUPPLY SYSTEM EFFICIENCY SHALL BE 87.8%, MEASURED AT NOMINAL INPUT VOLTAGE 230 V AND FULL LOADING.

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE / HOT-PLUGGABLE REDUNDANCY FUNCTION

BALANCE LOAD SHARING DESIGN


REMOTE ON/OFF CONTROL

LEAKAGE CURRENT : 3.5mA. RMS. MEASUREMENT WILL BE MADE AT 240VAC AND 60HZ.

ISOLATION : BUILT-IN IN THE POWER MODULE

DIMENSION : 185mm (D) x 150mm (W) x 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### MRW-5450V4V MRW-5500V4V MRW-5600V4V



#### INPUT CHARACTERISTICS

##### VOLTAGE :

90 ~ 264VAC FULL RANGE

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

| WATTAGE | 110V | 220V |
|---------|------|------|
| 450W    | 7A   | 3A   |
| 500W    | 8A   | 4A   |
| 600W    | 9A   | 4A   |

##### INRUSH CURRENT :

25 / 50 AMPS @ 110 / 220 VAC

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT  
115/230VAC, FULL LOAD

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| MRW-5450V4V      | 450W    | 25A    | 37A   | 25A   | X   | 0.8A  | 3.5A  |
| MRW-5500V4V      | 500W    | 25A    | 41A   | 25A   | X   | 0.8A  | 3.5A  |
| MRW-5600V4V      | 600W    | 25A    | 49A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

+5V AND +3.3V TOTAL MAX. POWER : 170W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C ; STORAGE TEMPERATURE : -20°C ~ 80°C

HOLD UP TIME : 16mS MINIMUM AT NOMINAL INPUT VOLTAGE

EFFICIENCY : TYPICAL >80% @ 115V, 25%~100% MAX LOAD

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 250VAC

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms


OUTPUT PROTECTION : OPP / OVP / OVP / SCP

HOT-SWAPPABLE / HOT-PLUGGABLE REDUNDANCY FUNCTION

12C FEATURES (OPTIONAL)

DIMENSION : 185mm (D) x 150mm (W) x 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |       |      |       |
|------------------|---------|--------|-------|-------|-------|------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V   | -12V | +5VSB |
| MRG-5700V4V      | 700W    | 32A    | 57A   | 32A   | X     | 0.8A | 3.5A  |
| MRG-5800V4V      | 800W    | 32A    | 65A   | 32A   | X     | X    | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X     | ±5%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | 100mV | 50mV | 50mV  |

REMARKS :  
TOTAL OUTPUT OF +5V & +3.3V NOT EXCEED 190W

## MRG-5700V4V MRG-5800V4V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~40°C , STORAGE -20°C ~80°C

HOLD UP TIME : DC OUTPUT 12V MUST BE MAINTAIN 16 ms IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL >80% AT 115V, 25%~100% MAX LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE / HOT-PLUGGABLE REDUNDANCY FUNCTION

REMOTE ON/OFF CONTROL

DIMENSION : 200mm (D) x 150mm (W) x 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90 ~ 264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

| WATTAGE | 110V | 220V |
|---------|------|------|
| 700W    | 9A   | 5A   |
| 800W    | 11A  | 5A   |

#### INRUSH CURRENT :

35/40A @ 115V; 75/80A @230 VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC





## MRH2-5930V0H MRH2-5AD0V0H

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264 VAC FULL RANGE (930W)  
180 ~ 264 VAC (1400W)  
90 ~ 132 VAC FULL RANGE (1200W)

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

| WATTAGE     | 115V | 230V |
|-------------|------|------|
| 930W        | 14   | 7    |
| 1200W/1400W | 15   | 10   |

#### INRUSH CURRENT :

15/30 AMPS @115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 110V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| MRH2-5930V0H     | 930W    | 36A    | 77.5A | 31A   | X   | 0.5A  | 3A    |
| MRH2-5AD0V0H     | 1400W   | 36A    | 116A  | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

\* TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED 210W

\* POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 1400W FOR 180~264VAC

\* POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 1200W FOR 103~132VAC

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C ; STORAGE : -20°C ~ 80°C

HOLD UP TIME : 12mS MINIMUM AT NOMINAL INPUT VOLTAGE (930W); TEST AT 1000W OUTPUT AND INPUT >115VAC 17mS (1400W)

EFFICIENCY : TYPICAL 82% @ 115V, TYPICAL 84% @ 230V (930W)  
TYPICAL 84% @ 115V, TYPICAL 86% @ 230V (1400W)

LEAKAGE CURRENT : 3.5 mA. MAX. AT NOMINAL VOLTAGE 240VAC


POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms

OUTPUT PROTECTION : OPP / OVP / OVP / SCP

REMOTE ON/OFF CONTROL

DIMENSION : 280mm (D) x 150mm (W) x 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



MINI REDUNDANT



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1Z3-5950V3V     | 950W    | 43A    | 76A   | 43A   | X   | 1A    | 5A    |
| M1Z3-5A45V3V     | 1045W   | 43A    | 84A   | 43A   | X   | 1A    | 5A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 70mV   | 120mV | 70mV  | X   | 120mV | 70mV  |



## M1Z3-5950V3V M1Z3-5A45V3V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : 78% TYPICAL @ FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

WARNING METHOD : BUZZER, TTL

DIMENSION : 265mm (D) x 101.2mm (W) x 125mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90 ~ 264 VAC FULL RANGE.

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

6A/6A (RMS) FOR 230 VAC, 15A/16A (RMS) FOR 115 VAC

#### INRUSH CURRENT :

35A MAX. FOR 115 VAC PER MODULE, 40A MAX. FOR 230 VAC PER MODULE

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC







## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS



| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1Z3-5950V3H     | 950W    | 43A    | 76A   | 43A   | X   | 1A    | 5A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 70mV   | 120mV | 70mV  | X   | 120mV | 70mV  |

## M1Z3-5950V3H

### INPUT CHARACTERISTICS

#### VOLTAGE :

90 ~ 264 VAC FULL RANGE.

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

6A (RMS) FOR 230 VAC, 15A (RMS) FOR 115 VAC

#### INRUSH CURRENT :

35A MAX. FOR 115 VAC PER MODULE, 40A MAX. FOR 230 VAC PER MODULE

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : 78% TYPICAL @ FULL LOAD


REMOTE ON/OFF CONTROL

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

WARNING METHOD : BUZZER, TTL

DIMENSION : 310mm (D) x 331mm (W) x 43mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| MTW3-5C50V3V     | 1250W   | 60A    | 95A   | 68A   | X   | 1.2A  | 5A    |
| MTW3-5H00V3V     | 1700W   | 60A    | 136A  | 68A   | X   | 1.2A  | 5A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX 380W

## MTW3-5C50V3V MTW3-5H00V3V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~ 45°C , STORAGE : -20°C ~ 80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL >80% AT 115V, 30~100% MAX LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

WARMING METHOD : BUZZER SOUND, TTL

REMOTE ON/OFF CONTROL

DIMENSION : 300mm (D) x 101mm (W) x 125mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90V ~ 264VAC (WITH ± 10% TOLERANCE)

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

MTW3-5C50V3V  
19A/8A MAX AT ANY LOW/HIGH INPUT VOLTAGE  
MTW3-5H00V3V  
27A/12A MAX AT ANY LOW/HIGH INPUT VOLTAGE

#### INRUSH CURRENT :

40A MAX. FOR 115 VAC PER MODULE; 60A MAX.  
FOR 230 VAC PER MODULE

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL  
LOAD, FOLLOWING THE STANDARD OF IEC 61000-  
3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

#### SAFETY :

TO MEET UL, CUL, TUV





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| MTW4-5H80V3V     | 1780W   | 86A    | 135A  | 97A   | X   | 1.6A  | 7A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX 540W

## MTW4-5H80V3V

### INPUT CHARACTERISTICS

#### VOLTAGE :

90V ~ 264VAC (WITH ± 10% TOLERANCE)

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

27/12A MAX AT ANY LOW/HIGH INPUT VOLTAGE

#### INRUSH CURRENT :

40A MAX. FOR 115 VAC PER MODULE; 60A MAX. FOR 230 VAC PER MODULE

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~ 45°C , STORAGE : -20°C ~ 80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL >80% AT 115V, 30~100% MAX LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms


OUTPUT PROTECTION : OPP / OVP / OCP / SCP

WARMING METHOD : BUZZER SOUND, TTL

REMOTE ON/OFF CONTROL

DIMENSION : 300mm (D) x 101.2mm (W) x 166mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**R3G-5500V4V**  
**R3G-5800V4V**  
**R3G-5950V4V**  
**R3G-5B40V4V**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 500W    | 8A   | 3A   |
| 800W    | 8A   | 3A   |
| 950W    | 8A   | 3A   |
| 1140W   | 9A   | 4A   |

#### INRUSH CURRENT :

35A/70A MAX. FOR 115/230 VAC POWER MODULE

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |      |       |
|------------------|---------|--------|-------|-------|-----|------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V | +5VSB |
| R3G-5500V4V      | 500W    | 25A    | 40A   | 25A   | X   | 0.8A | 3.5A  |
| R3G-5800V4V      | 800W    | 32A    | 63A   | 32A   | X   | 1.2A | 4A    |
| R3G-5950V4V      | 950W    | 32A    | 76A   | 32A   | X   | 1.2A | 4A    |
| R3G-5B40V4V      | 1140W   | 32A    | 90A   | 32A   | X   | 1.2A | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10% | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 50mV | 50mV  |

#### REMARKS :

THE OUTPUT CURRENT OF +5V AND +3.3V NOT EXCEED 170W / 190W / 190W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~ 40°C , STORAGE : -20°C ~ 80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL >80% AT 115V, 20~100% MAX LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms


OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 250VAC

DIMENSION : 276mm (D)×83mm (W)×127mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### SPH2-5A00V4H SPH2-5C00V4H

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

15/7.5 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE

##### INRUSH CURRENT :

15/30 AMPS @ 115/230 VAC

##### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL  
LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| SPH2-5A00V4H     | 1000W   | 22A    | 83A   | 22A   | X   | 0.5A  | 4A    |
| SPH2-5C00V4H     | 1200W   | 22A    | 100A  | 22A   | X   | 0.5A  | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 150W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~ 80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 12V MUST BE MAINTAIN  
10mS (SPH2-5A00V4H)/ 9mS (SPH2-SC00V4H) IN REGULATION LIMIT AT 90VAC INPUT  
VOLTAGE

EFFICIENCY : TYPICAL 83% AT115V, FULL LOAD. (PER SET)  
TYPICAL 86% AT230V, FULL LOAD. (PER SET)

POWER GOOD SIGNAL : ON DELAY 100ms TO 500ms

OUTPUT PROTECTION : OPP / OVP / SCP


REMOTE ON / OFF CONTROL

BALANCE LOAD SHARING DESIGN

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

DIMENSION : 404mm (D) x 127mm (W) x 49mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.



N+1 REDUNDANT



## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT       |       |       |     |       |       |
|------------------|---------|--------------|-------|-------|-----|-------|-------|
|                  |         | +5V1<br>+5V2 | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1P4-6950V4H     | 950W    | 32A          | 79A   | 25A   | X   | 0.5A  | 5A    |
| M1P4-6D50V4H     | 1350W   | 32A          | 112A  | 25A   | X   | 0.5A  | 6A    |
| REGULATION LOAD  |         | ±5%          | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV         | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V1, +5V2 AND +3.3V TOTAL OUTPUT MAX : 350W; TOTAL OUTPUT MAX : 950W/1350W

## M1P4-6950V4H M1P4-6D50V4H

N+1 REDUNDANT

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

15/8A MAX AT ANY LOW/HIGH INPUT VOLTAGE (950W)

21/10A MAX AT ANY LOW/HIGH INPUT VOLTAGE (1350W)

#### INRUSH CURRENT :

40/60A @ 115/230VAC (25°C)

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~ 40°C , STORAGE : -20°C ~ 80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : 80% TYPICAL AT 115VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

REMOTE SENSING DESIGN

DIMENSION : 260mm (D) x 359mm (W) x 41.8mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1Z4-5A80V3H     | 1080W   | 64A    | 88A   | 64A   | X   | 1.2A  | 6A    |
| M1Z4-5C40V3H     | 1240W   | 64A    | 100A  | 64A   | X   | 1.2A  | 6A    |
| M1Z4-5D50V3H     | 1350W   | 64A    | 110A  | 64A   | X   | 1.2A  | 6A    |
| M1Z4-5E85V3H     | 1485W   | 64A    | 120A  | 64A   | X   | 1.2A  | 6A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 70mV   | 120mV | 70mV  | X   | 120mV | 70mV  |

**M1Z4-5A80V3H**  
**M1Z4-5C40V3H**  
**M1Z4-5D50V3H**  
**M1Z4-5E85V3H**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 1080W   | 16A  | 6A   |
| 1240W   | 19A  | 7A   |
| 1350W   | 20A  | 8A   |
| 1485W   | 22A  | 9A   |

#### INRUSH CURRENT :

35/40AMPS @ 115/230 VAC

#### POWER FACTOR CORRECTION :

POWER FACTOR CORRECTIONPFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD,

FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : 80% TYPICAL @ 115V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION: : OPP / OVP / OVP / SCP

WARNING METHOD : AUDIO ALARM, TTL


2 + 1, HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

N + 1 BALANCE LOAD SHARING DESIGN 5/12/3.3V CHANNEL

REMOTE SENSING DESIGN

DIMENSION : 310mm (D) x 422mm (W) x 43mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



N+1 REDUNDANT



**HIGH EFFICIENCY**  
AC INPUT TO DC OUTPUT



**M1W4-5L80V3H**

**M1W4-5O50V3H**

 **M1W4-5R20V3H**

 **M1W4-5W40V3H**

**M1W4-5CH0V0H**

N+1 REDUNDANT

## INPUT CHARACTERISTICS

### VOLTAGE :

90~264VAC FULL RANGE

### FREQUENCY :

47 ~ 63HZ

### INPUT CURRENT :

| WATTAGE | 115V | 230V  |
|---------|------|-------|
| 2180W   | 30A  | 15A   |
| 2450W   | 42A  | 21A   |
| 2720W   | 45A  | 22.5A |
| 3240W   | 45A  | 23A   |
| 3300W   | 45A  | 24A   |
| 3800W   | X    | 26A   |

### INRUSH CURRENT :

15/30 AMPS @ 115/230VAC

### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% AT 115/230VAC, FULL LOAD

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL&CUL, TUV, CCC



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| M1W4-5L80V3H     | 2180W   | 24A    | 178A  | 24A   | X   | 1.5A  | 4A    |
| M1W4-5O50V3H     | 2450W   | 24A    | 201A  | 24A   | X   | 1.5A  | 4A    |
| M1W4-5R20V3H     | 2720W   | 24A    | 223A  | 24A   | X   | 1.5A  | 4A    |
| M1W4-5W40V3H     | 3240W   | 24A    | 270A  | 24A   | X   | 1.5A  | 4A    |
| M1W4-5CH0V0H * 2 | 3800W   | 24A    | 316A  | 24A   | X   | 1.5A  | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

### REMARKS :

TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED 135W.

\* 1 INPUT VOLTAGE IS 103 ~ 264 VAC (3300W)

\* 2 INPUT VOLTAGE IS 180 ~ 264 VAC (3800W)

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C · STORAGE -20°C ~80°C

HOLD UP TIME : 16mS IN REGULATION LIMIT AT 90 VAC INPUT VOLTAGE

EFFICIENCY : TYPICAL 84% AT FULL LOAD 115VAC (PER SET)

POWER GOOD SIGNAL : ON DELAY 100mS TO 550mS

OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON/OFF CONTROL


REMOTE SENSING DESIGN

BALANCE LOAD SHARING DESIGN

WARNING METHOD : LED, BUZZER, TTL SIGNAL

DIMENSION : 340mm (D) x 422mm (W) x 43mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



**MTW4-5C50V3H**  
**MTW4-5F50V3H**  
**MTW4-5H10V3H**  
**MTW4-5H80V3H**  
**MTW4-5K50V3H**  
**MTW4-5M10V3H**  
**MTW4-5O30V3H**

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

| WATTAGE | 115V | 230V |
|---------|------|------|
| 1250W   | 19A  | 8A   |
| 1550W   | 24A  | 11A  |
| 1710W   | 26A  | 11A  |
| 1780W   | 27A  | 12A  |
| 2050W   | 31A  | 13A  |
| 2210W   | 33A  | 14A  |
| 2430W   | 36A  | 16A  |

#### INRUSH CURRENT :

40/60 AMPS @115/230V

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |      |       |
|------------------|---------|--------|-------|-------|-----|------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V | +5VSB |
| MTW4-5C50V3H     | 1250W   | 60A    | 95A   | 68A   | X   | 1.2A | 5A    |
| MTW4-5F50V3H     | 1550W   | 60A    | 127A  | 68A   | X   | 1.2A | 5A    |
| MTW4-5H10V3H     | 1710W   | 60A    | 136A  | 68A   | X   | 1.2A | 5A    |
| MTW4-5H80V3H     | 1780W   | 86A    | 135A  | 97A   | X   | 1.6A | 7A    |
| MTW4-5K50V3H     | 2050W   | 86A    | 167A  | 97A   | X   | 1.6A | 7A    |
| MTW4-5M10V3H     | 2210W   | 86A    | 180A  | 97A   | X   | 1.6A | 7A    |
| MTW4-5O30V3H     | 2430W   | 86A    | 194A  | 97A   | X   | 1.6A | 7A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 50mV | 50mV  |

#### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 380W / 380W / 380W / 540W / 540W / 540W / 540W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~45°C , STORAGE -20°C ~80°C

HOLD UP TIME : 16mS IN REGULATOR LIMIT AT 90VAC INPUT VOLTAGE

EFFICIENCY : >80% AT 115VAC, 30%~100% MAX LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500Ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE SENSING DESIGN

BALANCE LOAD SHARING DESIGN


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

WARNING METHOD : LED, BUZZER, TTL SIGNAL

DIMENSION : 340mm (D) x 422mm (W) x 43mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



N+1 REDUNDANT

# HIGH EFFICIENCY AC INPUT TO DC OUTPUT

## OUTPUT CHARACTERISTICS



| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| G1W4-5BG0V0H     | 2700W   | 32A    | 225A  | 32A   | X   | 1A    | 6A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
THE OUTPUT CURRENT OF +5V AND +3.3V NOT EXCEED 190W  
TOTAL POWER:2700W (MAX)

## G1W4-5BG0V0H

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~ 40°C , STORAGE : -20°C --- 80°C

HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE

EFFICIENCY : >80% TYPICAL AT 230 VAC FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

REMOTE SENSING DESIGN

LEAKAGE CURRENT : INPUT LEAKAGE CURRENT FROM LINE TO GROUND WILL BE LESS THAN 3.5MA RMS. MEASUREMENT WILL BE MADE AT 240 VAC AND 60HZ.

DIMENSION : 340mm (D) x 422mm (W) x 43mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

38/19A MAX AT ANY LOW/HIGH INPUT VOLTAGE

#### INRUSH CURRENT :

60/80 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 1000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT



### PSS2-5A00V3H PSS2-5C00V3H

#### INPUT CHARACTERISTICS

##### VOLTAGE :

90~264VAC FULL RANGE

##### FREQUENCY :

47 ~ 63HZ

##### INPUT CURRENT :

15A/7.5A @ ANY LOW/HIGH RANGE INPUT VOLTAGE

##### INRUSH CURRENT :

15/30AMPS @ 115/230 VAC

##### POWER FACTOR CORRECTION :

POWER FACTOR CORRECTION PFC CAN REACH THE TARGET OF 95% @ 110V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| PSS2-5A00V3H     | 1000W   | 22A    | 83A   | 22A   | X   | 0.5A  | 4A    |
| PSS2-5C00V3H     | 1200W   | 22A    | 100A  | 22A   | X   | 0.5A  | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

THE OUTPUT CURRENT OF +5V & +3.3V NOT EXCEED 150W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~50°C ; STORAGE : -20°C ~80°C

HOLD UP TIME : 5V MUST BE MAINTAIN 10mS (PSS2-5A00V3H) / 9mS (PSS2-5C00V3H) IN REGULATION LIMIT AT 90V INPUT VOLTAGE

EFFICIENCY : TYPICAL 83% AT 115V, TYPICAL 86% AT 230V, FULL LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms,

OUTPUT PROTECTION : OPP / OVP / SCP

WARNING METHOD : LED, BUZZER, TTL SIGNAL


2 + 1, HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

N + 1 BALANCE LOAD SHARING DESIGN 5/12/3.3V CHANNEL

REMOTE SENSING DESIGN

DIMENSION : 360mm (D) x 127mm (W) x 44mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



N+1 REDUNDANT



## AC INPUT TO DC OUTPUT

HIGH EFFICIENCY

### OUTPUT CHARACTERISTICS



| MODEL            | WATTAGE | OUTPUT |       |        |      |       |                 |                   |
|------------------|---------|--------|-------|--------|------|-------|-----------------|-------------------|
|                  |         | +5V5   | +12V5 | +3.3V5 | +9V5 | -12V5 | +12V1<br>~+12V4 | +5VSB1<br>~+5VSB5 |
| M1K6-6CB0V0H     | 3200W   | 36A    | 37A   | 31A    | 2A   | 0.5A  | 42A             | 3A                |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%    | ±5%  | ±5%   | ±5%             | ±5%               |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 120mV  | 50mV | 120mV | 120mV           | 50mV              |

REMARKS :  
+12V5,+5V5,+3.3V5,+9V5,-12V5 TOTAL MAX 500W  
TOTAL MAX OUTPUT 3200W

## M1K6-6CB0V0H

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 15mS MIN. AT FULL LOAD

EFFICIENCY : TYPICAL 87% AT 230V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 5mS TO 500mS

REMOTE ON/OFF CONTROL

OUTPUT PROTECTION : OPP / OCP / SCP / OVP

BALANCE LOAD SHARING DESIGN

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 240VAC

WARNING METHODS : LED, BUZZER, TTL SIGNAL

DIMENSION : 470(D) X 425(W) X 43(H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

45/23 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE

#### INRUSH CURRENT :

15/30 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL  
LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC







**M1K6-5DH0V0H**

## INPUT CHARACTERISTICS

VOLTAGE :

90~264VAC FULL RANGE

FREQUENCY :

47 ~ 63HZ

INPUT CURRENT :

75/38 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE

INRUSH CURRENT :

15/30 AMPS @ 115/230VAC

POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

## EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

**SAFETY :**

TO MEET UL&CUL, TUV, CCC



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |        |      |                     |       |
|------------------|---------|--------|-------|--------|------|---------------------|-------|
|                  |         | +5V9   | +12V9 | +3.3V9 | +9V9 | +12V1<br>~<br>+12V8 | +5VSB |
| M1K6-5DH0V0H     | 4800W   | 4A     | 37A   | 4A     | 2A   | 42A                 | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%    | ±5%  | ±5%                 | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV   | 50mV | 120mV               | 50mV  |

REMARKS :

+12V9, +5V9, +3.3V9, +9V9 TOTAL MAX 500W

+12V1~+12V9 TOTAL MAX 400A

TOTAL MAX OUTOT 4800W

**SPECIFICATION :**

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 10mS MIN. AT FULL LOAD

EFFICIENCY : TYPICAL 87% @230V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 5mS TO 500mS

## REMOTE ON/OFF CONTROL

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

## BALANCE LOAD SHARING DESIGN


## HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

LEAKAGE CURRENT : 3.5mA MAX. AT NOMINAL VOLTAGE 240VAC

## WARNING METHODS : LED, BUZZER, TTL SIGNAL

DIMENSION : 470mm (D) x 425mm (W) x 43mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY AC INPUT TO DC OUTPUT

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |        |      |                 |                   |
|------------------|---------|--------|-------|-------|--------|------|-----------------|-------------------|
|                  |         | +5V9   | +12V9 | -12V9 | +3.3V9 | +9V9 | +12V1<br>~+12V8 | +5VSB1<br>~+5VSB9 |
| M1K6-6DH0V0H     | 4800W   | 36A    | 21A   | 0.5A  | 31A    | 2A   | 42A             | 3A                |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | ±5%    | ±5%  | ±5%             | ±5%               |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 120mV | 120mV  | 50mV | 120mV           | 50mV              |

REMARKS :  
+5V9 AND +3.3V9 TOTAL MAX: 210W  
+5VSB9, +12V9, +5V9, +3.3V9, +9V9, -12V9 TOTAL MAX 500W  
TOTAL MAX OUTOT 4800W

## M1K6-6DH0V0H

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

HOLD UP TIME : 15mS MIN. AT FULL LOAD

EFFICIENCY : TYPICAL 87% @230V FULL LOAD

POWER GOOD SIGNAL : ON DELAY 5mS TO 500mS · OFF DELAY 1mS

REMOTE ON/OFF CONTROL

OUTPUT PROTECTION: OPP / OCP / SCP / OVP

BALANCE LOAD SHARING DESIGN

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

LEAKAGE CURRENT: 3.5mA MAX. AT NOMINAL VOLTAGE 240VAC

WARNING METHODS: LED, BUZZER, TTL SIGNAL

DIMENSION : 470(D) X 425(W) X 43(H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

90~264VAC FULL RANGE

#### FREQUENCY :

47 ~ 63HZ

#### INPUT CURRENT :

75/38 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE(4800W)

#### INRUSH CURRENT :

15/30 AMPS @ 115/230VAC

#### POWER FACTOR CORRECTION :

PFC CAN REACH THE TARGET OF 95% @ 115V, FULL  
LOAD, FOLLOWING THE STANDARD OF IEC 61000-3-2

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| BP1P-5220V       | 220W    | 18A    | 17A   | 17A   | X   | 0.3A  | 2A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
TOTAL POWER : 220W(MAX)

BP1P-5220V


INPUT CHARACTERISTICS

- VOLTAGE :  
20~ 36 VDC
- FREQUENCY :  
DC
- INPUT CURRENT :  
20~ 36 VDC / 15~8A (12AMP@24VDC)
- INRUSH CURRENT :  
28A AT 24VDC (AT 25 DEGREES AMBIENT COLD START)
- EMI :  
FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , OPERATING -20°C ~80°C
- HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 1.6 mS AT 24V
- EFFICIENCY : TYPICAL >80% AT 24VDC, FULL LOAD
- OUTPUT PROTECTION : OPP / OVP / OCP / SCP
- POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1Ms
- REMOTE ON/OFF CONTROL
- DIMENSION : 170mm (D)×81.5mm (W)×40.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC - AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DP1P-5300V       | 300W    | 18A    | 24A   | 17A   | X   | 0.3A  | 2.5A  |
| DP1P-5320V       | 320W    | 18A    | 26A   | 17A   | X   | 0.3A  | 2.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 120W

DP1P-5300V  
DP1P-5320V

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , OPERATING -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 1.6 mS AT -48V

EFFICIENCY : TYPICAL >80% AT -48V, FULL LOAD

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1Ms

DIMENSION : 170mm (D)×81.5mm (W)×40.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

INPUT CHARACTERISTICS

VOLTAGE :

-36~ -72 VDC

FREQUENCY :

DC

INPUT CURRENT :

-36 ~ -72VDC / 12~6A ( 7 / 8.5AMP AT -48VDC )

INRUSH CURRENT :

28/30A AT -48VDC (AT 25 DEGREES AMBIENT COLD START)

EMI :


FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

SAFETY :

TO MEET UL, CUL, TUV



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



BP1H-5420V  
BP1H-5460V

INPUT CHARACTERISTICS

- VOLTAGE :
- 18~ 36 VDC
- INPUT CURRENT :
- BP1H-5420V
- 18-36VDC / 33-16AMP (24AMP AT 24VDC)
- BP1H-5460V
- 18-36VDC / 35-18AMP (26AMP AT 24VDC)
- INRUSH CURRENT :
- 50A@ 24VDC (AT 25 DEGREES AMBIENT COLD START)
- EMI :
- FCC, CISPR 22(EN 55022)
- EMS :
- EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :
- TO MEET UL, CUL, TUV




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |      |       |       |
|------------------|---------|--------|-------|-------|------|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V  | -12V  | +5VSB |
| BP1H-5420V       | 420W    | 25A    | 33A   | 25A   | X    | 0.8A  | 3A    |
| BP1H-5460V       | 460W    | 25A    | 37A   | 25A   | X    | 0.8A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | ±5%  | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | 50mV | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 170W

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 40°C STORAGE -20°C ~80°C
- HOLD UP TIME : 1.6ms MINIMUM AT 24V FULL LOAD
- EFFICIENCY : >80% TYPICAL AT 24V FULL LOAD
- POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms
- OUTPUT PROTECTION : OPP / OVP / OCP / SCP
- DIMENSION : 225mm (D) x 100mm (W) x 40.5mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DP1H-5460V       | 460W    | 25A    | 37A   | 25A   | X   | 0.8A  | 3A    |
| DP1H-5550V       | 550W    | 25A    | 45A   | 25A   | X   | 0.8A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :

+5 V AND +3.3V TOTAL OUTPUT MAX. 170 WATTS

**DP1H-5460V**  
**DP1H-5550V**

## INPUT CHARACTERISTICS

VOLTAGE :

DC – 36 V ~ –72 V

INPUT CURRENT :

DP1H-5460V

-36 ~ -72 VDC / 16~8AMP (12AMP AT -48VDC)

DP1H-5550V

-36 ~ -72 VDC / 25~10AMP (16AMP AT -48VDC)

INRUSH CURRENT :

50 A @-48VDC(AT 25 DEGREES AMBIENT COLD  
START)

EMI :

FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

**SAFETY :**

TO MEET UL, CUL, TUV

**SPECIFICATION :**

TEMPERATURE RANGE : OPERATING 0°C ~40°C , STORAGE -20°C ~80°C

HOLD UP TIME : DC OUTPUT 12V MUST BE MAINTAIN 1.6 ms AT -48V


EFFICIENCY : >80% AT -48V, FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

DIMENSION : 225mm (D) x 100mm (W) x 40.5mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



BP2H-5420V  
BP2H-5460V

INPUT CHARACTERISTICS

- VOLTAGE :  
DC 18V ~ 36V
- INPUT CURRENT :  
BP2H-5420V  
18~36VDC / 33~16AMP (24AMPS AT 24 VDC)  
BP2H-5460V  
18~36VDC / 35~18AMP (26A (RMS) AT 24 VDC)
- INRUSH CURRENT :  
50 AMPS @24VDC(AT 25 DEGREES AMBIENT COLD START)
- EMI :  
FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| BP2H-5420V       | 420W    | 25A    | 34A   | 25A   | X   | 0.8A  | 3A    |
| BP2H-5460V       | 460W    | 25A    | 37A   | 25A   | X   | 0.8A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 170W

- SPECIFICATION :
- TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20~80°C
- HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 12V MUST BE MAINTAIN 1.6 ms AT 24V
- EFFICIENCY : >80% TYPICAL AT 24V, FULL LOAD
- POWER GOOD SIGNAL : ON DELAY 100mS TO 500mS · OFF DELAY 1mS
- OUTPUT PROTECTION : OPP / OVP / OCP / SCP
- DIMENSION : 215mm (D)×100mm (W)×70mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### DP2H-5460V DP2H-5500V DP2H-5550V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

-36 ~ -72 VDC

##### INPUT CURRENT :

DP2H-5460V

-36~-72VDC / 16~8AMP (12 AMP AT -48VDC)

DP2H-5500V

-36~-72VDC / 19~9AMP (14 AMP AT -48VDC)

DP2H-5550V

-36~-72VDC / 25~10AMP (16 AMP AT -48VDC)

##### INRUSH CURRENT :

50AMPS @ -48VDC (AT 25DEGREES AMBIENT COLD START)

##### EMI :

FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DP2H-5460V       | 460W    | 25A    | 37A   | 25A   | X   | 0.8A  | 3A    |
| DP2H-5500V       | 500W    | 25A    | 41A   | 25A   | X   | 0.8A  | 3A    |
| DP2H-5550V       | 550W    | 25A    | 45A   | 25A   | X   | 0.8A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 170W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~40°C , STORAGE -20~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 12V MUST BE MAINTAIN 1.6ms AT -48V


EFFICIENCY : >80% TYPICAL AT DC-48 INPUT, FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

DIMENSION : 215mm (D) x 100mm (W) x 70mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



BHG2-5300V  
BHG2-5350V  
BHG2-5400V

INPUT CHARACTERISTICS

- VOLTAGE :
- 18~36VDC(300W.350W) / 20~36VDC (400W)
- INPUT CURRENT :
- 300W     22~11 AMP (16 AMP AT 24VDC)
- 350W     25~13 AMP (19 AMP AT 24VDC)
- 400W     30~15 AMP (22 AMP AT 24VDC)
- INRUSH CURRENT :
- 50/50/60 AMPS @ 24VDC
- EMI :
- FCC, CISPR 22(EN 55022)
- EMS :
- EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :
- TO MEET UL, CUL, TUV




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| BHG2-5300V       | 300W    | 25A    | 25A   | 25A   | X   | 0.8A  | 2.5A  |
| BHG2-5350V       | 350W    | 25A    | 28A   | 25A   | X   | 0.8A  | 2.5A  |
| BHG2-5400V       | 400W    | 25A    | 30A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
THE OUTPUT CURRENT OF +5V & +3.3V NOT EXCEED 30A/30A/40A

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20°C ~80°C
- HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 12V MUST BE MAINTAIN 1mSEC AT 24V
- EFFICIENCY : >80% TYPICAL AT 24V, FULL LOAD
- POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms
- OUTPUT PROTECTION : OPP / OVP / OCP / SCP
- DIMENSION : 140mm (D) x 150mm (W) x 86mm (H) (PS/2)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



DHG2-5400V  
DHG2-5500V  
DHG2-5600V

INPUT CHARACTERISTICS

- VOLTAGE :  
-36 ~ -72VDC
- INPUT CURRENT :
- 400W    15~8 AMP (11 AMP AT -48VDC)  
500W    18~9 AMP (13 AMP AT -48VDC)  
600W    21~11 AMP (16 AMP AT -48VDC)
- INRUSH CURRENT :  
50AMPS @ -48VDC
- EMI :  
FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DHG2-5400V       | 400W    | 25A    | 32A   | 25A   | X   | 0.8A  | 3.5A  |
| DHG2-5500V       | 500W    | 25A    | 41A   | 25A   | X   | 0.8A  | 3.5A  |
| DHG2-5600V       | 600W    | 25A    | 45A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
THE OUTPUT CURRENT OF +5V & +3.3V NOT EXCEED 40A

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20°C ~ 80°C
- HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 12V MUST BE MAINTAIN 1.6ms AT -48V
- EFFICIENCY : >80% TYPICAL AT -48V, FULL LOAD
- POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms
- OUTPUT PROTECTION : OPP / OVP / OCP / SCP
- DIMENSION : 140mm (D) x 150mm (W) x 86mm (H) (PS/2)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DR1U2-5200V4H    | 200W    | 14A    | 16A   | 14A   | X   | 0.3A  | 2A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
 POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 100W.  
 POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 200W

# DR1U2-5200V4H

10AMPS @ -48VDC HIGH FREQUENCY PEAK AMPLITUDES LASTING LESS THAN 50ms (AT 25 DEGREES AMBIENT COLD START)

## INPUT CHARACTERISTICS

### VOLTAGE :

-40 ~ -72VDC

### FREQUENCY :

DC

### STEADY-STATE CURRENT :

10/5A MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

### INRUSH CURRENT :

10A MAX. @-48VDC HIGH FREQUENCY PEAK AMPLITUDES LASTING LESS THAN 50ms (AT 25 DEGREES AMBIENT COLD START)

### START UP CURRENT :

13A MAX. @-48VDC INPUT

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL, CUL, TUV, CCC

## SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STOREAGE -20°C ~80°C

HOLD UP TIME : 1ms MIN. IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE (DC-48V)

EFFICIENCY(PER SET) : TYPICAL 76-80% AT -48V, 12V/16A 5VSB/1.6A

OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON / OFF CONTROL

REMOTE SENSING DESIGN


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

DIMENSION : 260mm (D) x 106mm (W) x 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



## DR1V2-5250V4H

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DR1V2-5250V4H    | 250W    | 20A    | 20A   | 20A   | X   | 0.3A  | 2.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 150W;  
POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 250W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~ 80°C

HOLD UP TIME : 1 mSEC IN REGULATION LIMIT AT NORMAL INPUT VOLTAGE

EFFICIENCY : TYPICAL 78%(+/-2%) AT -48VDC, 12V/20A 5VSB/2A

POWER GOOD SIGNAL : ON DELAY 100 ms TO 600 ms, OFF DELAY 1 ms

OUTPUT PROTECTION : OPP / OVP / SCP

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

REMOTE ON/OFF CONTROL

DIMENSION : 295mm (D) x 106mm (W) x 41.3mm(H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

-40 ~ -72VDC, NORMAL -48VDC

#### STEADY-STATE CURRENT :

10/5 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE

#### INRUSH CURRENT :

10AMPS @ -48VDC HIGH FREQUENCY PEAK AMPLITUDES LASTING LESS THAN 50ms (AT 25 DEGREES AMBIENT COLD START)

#### START UP CURRENT :

13AMPS MAX. @ -48VDC INPUT (AT 25 DEGREES AMBIENT COLD STAR)

#### EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL&CUL, TUV, CCC









DM1Y2-5150V2H

DM1Y2-5300V2H

INPUT CHARACTERISTICS

VOLTAGE :

-36 ~ -72VDC

STEADY-STATE CURRENT :

| WATTAGE | LOW | HIGH |
|---------|-----|------|
| 150W    | 6A  | 3A   |
| 300W    | 11A | 6A   |

INRUSH CURRENT :

40A MAX. FOR EACH POWER UNIT

EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

SAFETY :

TO MEET UL, CUL, TUV, CCC



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT       |       |       |     |       |       |
|------------------|---------|--------------|-------|-------|-----|-------|-------|
|                  |         | +5V1<br>+5V2 | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DM1Y2-5150V2H    | 150W    | 10A          | 12A   | 10A   | X   | 0.3A  | 2A    |
| DM1Y2-5300V2H    | 300W    | 18A          | 24A   | 18A   | X   | 0.3A  | 3A    |
| REGULATION LOAD  |         | ±5%          | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV         | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :

TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED 120W

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STOREAGE -20°C ~80°C

HOLD UP TIME : 1.6ms MIN. AT FULL LOAD & NOMINAL INPUT VOLTAGE

EFFICIENCY : 80% TYPICAL · AT FULL LOAD

OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON / OFF CONTROL

REMOTE SENSING DESIGN

BALANCE LOAD SHARING DESIGN

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION


N +1 BALANCE LOAD SHARING DESIGN ON 5/12/3.3V CHANNEL

ISOLATION : BUILT-IN THE POWER MODULE

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

DIMENSION : 275(D) \* 106(W) \* 41.3 (H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





**BM1U2-5500V4H**  
**BM1U2-5501V4H**

## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| BM1U2-5500V4H    | 500W    | 22A    | 41A   | 22A   | X   | 0.5A  | 3A    |
| BM1U2-5501V4H    | 500W    | 36A    | 41A   | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED150W (BMIV2-5500V4H)  
+5V AND +3.3V NOT EXCEED210W (BMIV2-5501V4H)

**SPECIFICATION :**

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~ 80°C

HOLD UP TIME : 1mS IN REGULATOIN LIMIT AT NORMAL INPUT VOLTAGE (DC 28V)

EFFICIENCY(PER SET) : POWER SUPPLY EFFICIENCY TYPICAL 80% AT 28VDCin, FULL LOAD

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

## REMOTE ON/OFF CONTROL

## BALANCE LOAD SHARING DESIGN

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

## ISOLATION BUILT-IN THE POWER MODULE

WARNING METHOD : BUZZER, TTL SIGNAL

DIMENSION : 355mm (D) x 106mm (W) x 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

VOLTAGE :

19 ~ 36VDC

INPUT CURRENT :

30 / 18A MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE

INRUSH CURRENT :

10A MAX. @28VDC INPUT (AT 25DEGREES  
AMBIENT COLD START)

START UP CURRENT :

24AMPS MAX.@28VDC INPUT (AT 25 DEGREES  
AMBIENT COLD START)

## EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

**SAFETY :**

TO MEET UL, CUL, TUV





**DM1S2-5400V4H**  
**DM1S2-5401V4H**  
**DM1S2-5500V4H**  
**DM1S2-5501V4H**  
**DM1S2-5551V4H**

DC MICRO REDUNDANT

## INPUT CHARACTERISTICS

### VOLTAGE :

-36 ~ -72VDC, NORMAL : -48VDC

### STEADY-STATE CURRENT :

400W → -36 ~ -72VDC / 15~7 AMP (11 AMP AT -48VDC);

500W → -36 ~ -72VDC / 19~9 AMP (14 AMP AT -48VDC)

550W → -36 ~ -72VDC / 21~10 AMP (15 AMP AT -48VDC)

### INRUSH CURRENT :

40 AMPS @ -48VDC (AT 25 DEGREES AMBIENT COLD START)

### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

### SAFETY :

TO MEET UL, CUL, TUV, CCC



## OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DM1S2-5400V4H    | 400W    | 25A    | 33A   | 25A   | X   | 0.8A  | 3.5A  |
| DM1S2-5401V4H    | 400W    | 25A    | 33A   | 25A   | X   | 0.8A  | 3.5A  |
| DM1S2-5500V4H    | 500W    | 25A    | 41A   | 25A   | X   | 0.8A  | 3.5A  |
| DM1S2-5501V4H    | 500W    | 25A    | 41A   | 25A   | X   | 0.8A  | 3.5A  |
| DM1S2-5551V4H    | 550W    | 25A    | 45A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

### REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 170W

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20°C ~80°C ; OPERATING EMPEURATE FROM 0°C SHOULD START FROM DC-48V

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 1.6mS IN REGULATION LIMIT AT -48V

EFFICIENCY : >80% AT -48V · FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100ms TO 500Ms

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

REMOTE ON/OFF CONTROL


BALANCE LOAD SHARING DESIGN

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION BUILT-IN THE POWER MODULE

DIMENSION : 355mm (D) x 106mm (W) x 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





# DM1U2-2650V4H

## INPUT CHARACTERISTICS

- VOLTAGE :
- 40 ~ -72VDC
- FREQUENCY :
- 0HZ (DC)
- STEADY-STATE CURRENT :
- 20/10 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT VOLTAGE
- INRUSH CURRENT :
- 10A MAX. @-48VDC INPUT (AT 25DEGREES AMBIENT COLD START)
- START UP CURRENT :
- 20 AMPS MAX. @ -48VDC INPUT (AT 25DEGREES AMBIENT COLD START)
- EMI :
- IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :
- EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :
- TO MEET UL, CUL, TUV, CCC



## OUTPUT CHARACTERISTICS


| MODEL            | WATTAGE | OUTPUT |       |       |     |      |       |
|------------------|---------|--------|-------|-------|-----|------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V | +5VSB |
| DM1U2-2650V4H    | 650W    | X      | 54A   | X     | X   | X    | 3A    |
| REGULATION LOAD  |         | X      | ±5%   | X     | X   | X    | ±5%   |
| RIPPLE AND NOISE |         | X      | 120mV | X     | X   | X    | 50mV  |

REMARKS :

POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 650W

## SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STOREAGE -20°C ~80°C
- HOLD UP TIME : 1ms IN REGULATION LIMIT AT NORMA INPUT VOLTAGE (DC-48V)
- EFFICIENCY(PER SET) : TYPICAL 85% AT -48VDC , FULL LOAD
- OUTPUT PROTECTION : OPP / OVP / OCP / SCP
- REMOTE ON / OFF CONTROL
- REMOTE SENSING DESIGN
- BALANCE LOAD SHARING DESIGN
- HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION
- ISOLATION : BUILT-IN THE POWER MODULE
- FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL
- DIMENSION : 355mm (D) x 106mm (W) x 41.3mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## DM1U2-5650V4H DM1U2-5750V4H

### INPUT CHARACTERISTICS

**VOLTAGE :**

-40 ~ -72VDC

**FREQUENCY :**

DC

**STEADY-STATE CURRENT :**

| WATTAGE | LOW | HIGH |
|---------|-----|------|
| 650W    | 20A | 10A  |
| 750W    | 24A | 14A  |

**INRUSH CURRENT :**

10A MAX. @-48VDC INPUT(AT 25DEGREES  
AMBIENT COLD START)

**EMI :**

FCC, CISPR 22(EN 55022)

**EMS :**

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

**SAFETY :**

TO MEET UL, CUL, TUV, CCC



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DM1U2-5650V4H    | 650W    | 22A    | 54A   | 22A   | X   | 0.5A  | 3A    |
| DM1U2-5750V4H    | 750W    | 22A    | 62A   | 22A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

**REMARKS :**

TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED150W.

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STOREAGE -20°C ~80°C

HOLD UP TIME : 1mS MIN.

EFFICIENCY : TYPICAL 85% AT -48V (650W) FULL LOAD (PER SET)  
TYPICAL 85% AT -48V (750W) FULL LOAD (PER SET)

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

REMOTE SENSING DESIGN DESIGN

BALANCE LOAD SHARING DESIGN


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION BUILT-IN THE POWER MODULE

WARNING METHOD : LED, BUZZER, TTL SIGNAL

DIMENSION : 355mm (D) x 106mm (W) x 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## DM1K2-5A00V0H

### INPUT CHARACTERISTICS

#### VOLTAGE :

-36 ~ -72VDC

#### STEADY-STATE CURRENT :

30A @ -48VDC

#### INRUSH CURRENT :

25A MAX. @-48VDC INPUT (AT 25DEGREES AMBIENT COLD START)

#### START UP CURRENT :

30 AMPS MAX.@48VDC INPUT (AT 25 DEGREES AMBIENT COLD START)

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC

### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DM1K2-5A00V0H    | 1000W   | 22A    | 83A   | 22A   | X   | 0.5A  | 3.0A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED170W.

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STOREAGE -20°C ~80°C

HOLD UP TIME : 1ms IN REGULATOIN LIMIT AT NORMAL INPUT VOLTAGE (DC-48V)

EFFICIENCY(PER SET) : POWER SUPPLY EFFICIENCY MAX. 88% AT 48VDCin.

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

REMOTE ON / OFF CONTROL

BALANCE LOAD SHARING DESIGN


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

FAULTY ALARM METHODS : BUZZER, TTL SIGNAL

DIMENSION : 400mm (D) x 106mm (W) x 41.3mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



DR1S2-5300V4H  
DR1S2-5380V4H

INPUT CHARACTERISTICS

VOLTAGE :

-36 ~ -72VDC, NORMAL : -48VDC

STEADY-STATE CURRENT :

| WATTAGE | -36~72VDC                   |
|---------|-----------------------------|
| 300W    | 12~6 AMP (9 AMP AT -48VDC)  |
| 380W    | 12~6 AMP (11 AMP AT -48VDC) |

INRUSH CURRENT :

70 AMPS @-48VDC (AT 25 DEGREES AMBIENT COLD START)

EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

SAFETY :

TO MEET UL, CUL, TUV, CCC



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DR1S2-5300V4H    | 300W    | 20A    | 24A   | 20A   | X   | 0.5A  | 2.5A  |
| DR1S2-5380V4H    | 380W    | 20A    | 30A   | 20A   | X   | 0.5A  | 2.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 140W; TOTAL OUTPUT MAX : 300W/380W

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C ; OPERATING EMPERATURE FROM 0°C SHOULD START FROM DC-48V

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 1.6mS IN REGULATION LIMIT AT -48V

EFFICIENCY : >80% AT -48V · FULL LOAD

POWER GOOD SIGNAL : ON DELAY 100mS TO 500Ms

OUTPUT PROTECTION : OPP / OVP / SCP

REMOTE ON/OFF CONTROL


BALANCE LOAD SHARING DESIGN

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

DIMENSION : 230mm (D) x 176mm (W) x 41.8mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| BMRW-5360V4V     | 360W    | 25A    | 28A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 170W;  
TOTAL OUTPUT POWER NOT EXCEED 360W


BMRW-5360V4V

INPUT CHARACTERISTICS

- VOLTAGE :  
18 ~ 36 VDC
- STEADY-STATE CURRENT :  
18-36VDC/28-13AMP(19AMP AT 24VDC)
- INRUSH CURRENT :  
60A @24VDC AT 25 DEGREES AMBIENT COLD START
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV, CCC

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~ 80°C
- HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 1mS IN 24V
- EFFICIENCY : TYPICAL >80% AT 24VDC, 25%~100% MAX LOAD
- POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms
- OUTPUT PROTECTION : OPP / OVP / OCP / SCP
- REMOTE ON / OFF CONTROL
- REMOTE SENSING DESIGN
- BALANCE LOAD SHARING DESIGN
- HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION
- ISOLATION : BUILT-IN THE POWER MODULE
- FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL
- DIMENSION : 185mm (D) x 150mm (W) x 86mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



DC MINI REDUNDANT

HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DMRW-5500V4V     | 500W    | 25A    | 41A   | 25A   | X   | 0.8A  | 3.5A  |
| DMRW-5600V4V     | 600W    | 25A    | 45A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 170W

DMRW-5500V4V  
DMRW-5600V4V

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~50°C , STORAGE -20°C ~80°C

HOLD UP TIME : WHEN POWER SHUTDOWN DC OUTPUT 5V MUST BE MAINTAIN 1mS IN -48V

EFFICIENCY : TYPICAL >80% AT -48VDC, 25%~100% MAX LOAD

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

WARNING METHOD : LED, BUZZER, TTL SIGNAL

DIMENSION : 185mm (D) x 150mm (W) x 86mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

INPUT CHARACTERISTICS

VOLTAGE :

-36 ~ -72 VDC

INPUT CURRENT :

13A / 16A @ -48VDC

INRUSH CURRENT :

70A AT -48VDC AT 25 DEGREES AMBIENT COLD START

EMI :


FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE


SAFETY :

TO MEET UL, CUL, TUV, CCC





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### BM1U2-5500V4V BM1U2-5501V4V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

19 ~ 36VDC

##### STEADY-STATE CURRENT :

30 / 18A MAXIMUM AT ANY LOW/HIGH RANGE INPUT

##### VOLTAGE

##### INRUSH CURRENT :

10AMPS MAX.@28VDC INPUT (AT 25 DEGREES AMBIENT COLD START)

##### START UP CURRENT :

24AMPS MAX.@28VDC INPUT (AT 25 DEGREES AMBIENT COLD START)

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| BM1U2-5500V4V    | 500W    | 22A    | 41A   | 22A   | X   | 0.5A  | 3A    |
| BM1U2-5501V4V    | 500W    | 36A    | 41A   | 31A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARK :

TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED 150W. (BM1U2-5500V4V)

TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED 210W. (BM1U2-5501V4V)

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STOREAGE -20°C ~80°C

EFFICIENCY : TYPICAL 80% AT 28VDCin, FULL LOAD (PER SET)

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

REMOTE ON / OFF CONTROL

BALANCE LOAD SHARING DESIGN


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

FAULTY ALARM METHODS : BUZZER, TTL SIGNAL


DIMENSION : 400mm (D) x 54.5mm (W) x 84.6mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DM1U2-5650V4V    | 650W    | 22A    | 54A   | 22A   | X   | 0.5A  | 3A    |
| DM1U2-5750V4V    | 750W    | 22A    | 62A   | 22A   | X   | 0.5A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 150W.  
POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 650W / 750W

## DM1U2-5650V4V DM1U2-5750V4V

DC 2U REDUNDANT

### INPUT CHARACTERISTICS

#### VOLTAGE :

-40 ~ -72VDC

#### FREQUENCY :

0HZ (DC)

#### STEADY-STATE CURRENT :

| WATTAGE | LOW | HIGH |
|---------|-----|------|
| 650W    | 20A | 10A  |
| 750W    | 24A | 14A  |

#### INRUSH CURRENT :

10A MAX. @ -48VDC INPUT(AT 25DEGREES  
AMBIENT COLD START)

#### START UP CURRENT :

20 AMPS MAX. @ -48VDC INPUT(AT 25DEGREES  
AMBIENT COLD START)

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

#### SAFETY :

TO MEET UL, CUL, TUV

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STOREAGE -20°C ~80°C

EFFICIENCY(PER SET) : TYPICAL 85% AT -48V, FULL LOAD

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON / OFF CONTROL

REMOTE SENSING DESIGN

BALANCE LOAD SHARING DESIGN


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

DIMENSION : 400mm (D) x 54.5mm (W) x 84.6mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### DPSS2-5A00V3V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

DC -36 V ~ -72 V

##### INRUSH CURRENT :

10A MAXIMUM @ -48VDC

##### START UP CURRENT :

LESS THAN 30A FOR EACH MODULE

##### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL&CUL, TUV



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DPSS2-5A00V3V    | 1000W   | 22A    | 83A   | 22A   | X   | 0.5A  | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

POWER MODULE TOTAL OUTPUT POWER OF +5V & +3.3V NOT EXCEED 150W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING : 0°C ~ 40°C ; STORAGE : -20°C ~ 80°C

EFFICIENCY : TYPICAL 83% AT -48VDC FULL LOAD (PER SET)

POWER GOOD SIGNAL : ON DELAY 100 mS TO 550 mS

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

REMOTE SENSING DESIGN

DIMENSION : 385mm (D) x 65mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



DR1S2-5300V4V  
DR1S2-5380V4V

OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DR1S2-5300V4V    | 300W    | 20A    | 24A   | 20A   | X   | 0.5A  | 2.5A  |
| DR1S2-5380V4V    | 380W    | 20A    | 30A   | 20A   | X   | 0.5A  | 2.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |


REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 140W; TOTAL OUTPUT MAX : 300W/380W

INPUT CHARACTERISTICS

- VOLTAGE :  
-36 ~ -72VDC, NORMAL : -48VDC
- STEADY-STATE CURRENT :
- | WATTAGE | -36~-72VDC                  |
|---------|-----------------------------|
| 300W    | 12~6 AMP (9 AMP AT -48VDC)  |
| 380W    | 15~7 AMP (11 AMP AT -48VDC) |
- INRUSH CURRENT :  
70 AMPS @-48VDC (AT 25 DEGREES AMBIENT COLD START)
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV, CCC

- SPECIFICATION :
- TEMPERATURE RANGE : OPERATING 0°C ~ 50°C , STORAGE -20°C ~80°C
- EFFICIENCY : >80% AT -48V · FULL LOAD
- OUTPUT PROTECTION : OPP / OVP / SCP
- REMOTE ON/OFF CONTROL
- BALANCE LOAD SHARING DESIGN
- HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION
- ISOLATION : BUILT-IN THE POWER MODULE
- DIMENSION : 207mm (D) x 85mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| BM1P2-5250V4V    | 250W    | 32A    | 20A   | 25A   | X   | 0.5A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARK :  
TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED 170W.


BM1P2-5250V4V

INPUT CHARACTERISTICS

- VOLTAGE :  
19 ~ 36VDC
- STEADY-STATE CURRENT :  
18~9 AMP (14A@24VDC)
- INRUSH CURRENT :  
50A MAX. @24VDC INPUT (AT 25DEGREES AMBIENT COLD START)
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV, CCC

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STOREAGE -20°C ~80°C
- EFFICIENCY(PER SET) : POWER SUPPLY EFFICIENCY TYPICAL 80% AT 24VDCin, FULL LOAD
- OUTPUT PROTECTION : OPP / OVP / SCP / OCP
- REMOTE ON / OFF CONTROL
- BALANCE LOAD SHARING DESIGN
- HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION
- ISOLATION : BUILT-IN THE POWER MODULE
- FAULTY ALARM METHODS : BUZZER, TTL SIGNAL
- DIMENSION : 217mm (D) x 85mm (W) x 84mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



DC 2U REDUNDANT

DC INPUT TO DC OUTPUT

HIGH EFFICIENCY



DM1P2-5500V4V

INPUT CHARACTERISTICS

- VOLTAGE :  
-36 ~ -72 VDC, NORMAL -48VDC
- INPUT CURRENT :  
-36 ~ -72VDC/19~9AMP ( 14AMP AT -48 VDC )
- INRUSH CURRENT :  
40A AT -48VDC (AT 25 DEGREES AMBIEND COLD START)
- EMI :  
FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL&CUL, TUV




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DM1P2-5500V4V    | 500W    | 32A    | 41A   | 25A   | X   | 0.5A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED170W.

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 40°C · STORAGE -20°C ~ 80°C
- EFFICIENCY : POWER SUPPLY EFFICIENCY TYPICAL 80% AT 48VDCin, FULL LOAD
- OUTPUT PROTECTION : OPP / OVP / SCP /OCP
- BALANCE LOAD SHARING DESIGN
- REMOTE ON/OFF CONTROL
- HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION
- DIMENSION : 217mm (D) x 85mm (W) x 84mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





DC INPUT TO DC OUTPUT

HIGH EFFICIENCY



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DM1X2-5700V0V    | 700W    | 32A    | 57A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPU NOT EXCEED 170W

DM1X2-5700V0V

INPUT CHARACTERISTICS

VOLTAGE :

-36 ~ -72 VDC, NORMAL -48VDC

INPUT CURRENT :

25~13A @ -48VDC

INRUSH CURRENT :

32A AT -48VDC (AT 25 DEGREES AMBIEND COLD START)

START UP CURRENT 45A MAX. @-36VDC INPUT  
CAT 25 DEGREES AMBIENT COLD START

EMI :

FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

SAFETY :

TO MEET UL, CUL, TUV, CCC

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C · STORAGE -20°C ~ 80°C

EFFICIENCY : 86% MAX · AT INPUT -48V FULL LOAD

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

BALANCE LOAD SHARING DESIGN


REMOTE ON/OFF CONTROL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

DIMENSION : 240mm (D) x 101mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE  
OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH  
CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| BM1Z2-5360V3V    | 360W    | 24A    | 28A   | 24A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

## BM1Z2-5360V3V

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

EFFICIENCY : TYPICAL >80% AT 24VDC, FULL LOAD

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

BALANCE LOAD SHARING DESIGN

REMOTE ON/OFF CONTROL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

DIMENSION : 265mm (D) x 101mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

### INPUT CHARACTERISTICS

#### VOLTAGE :

18 ~ 36 VDC, NORMAL 24VDC

#### INRUSH CURRENT :

60A @24VDC

#### STEADY-STATE CURRENT :

29AMPS MAXIMUM AT 18 TO 36V DC

#### EMI :


FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### DM1Z2-5500V3V DM1Z2-5550V3V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

-36 ~ -72 VDC, NORMAL -48VDC

##### INPUT CURRENT :

20A MAX. AT -36~72VDC

##### INRUSH CURRENT :

30A AT -48VDC (AT 25 DEGREES AMBIEND COLD START)

##### EMI :

FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL&CUL, TUV, CCC

#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DM1Z2-5500V3V    | 500W    | 24A    | 40A   | 24A   | X   | 0.8A  | 3A    |
| DM1Z2-5550V3V    | 550W    | 24A    | 45A   | 24A   | X   | 0.8A  | 3A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

EFFICIENCY : 80% TYPICAL · AT INPUT -48V FULL LOAD

OUTPUT PROTECTION : OPP / OVP / SCP / OCP


BALANCE LOAD SHARING DESIGN

REMOTE ON/OFF CONTROL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

DIMENSION : 265(D) X 101(W) X 84(H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



BR2G-5420V4V  
BR2G-5460V4V

INPUT CHARACTERISTICS

- VOLTAGE :**
- 18 ~ 36 VDC, NORMAL 24VDC
- STEADY-STATE CURRENT :**
- 18~36VDC / 35-16AMP (22/24AMP @ 24VDC)
- INRUSH CURRENT :**
- 30A @ 24VDC (AT 25 DEGREES AMBIEND COLD START)
- EMI :**
- FCC, CISPR 22(EN 55022)
- EMS :**
- EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :**
- TO MEET UL&CUL, TUV

OUTPUT CHARACTERISTICS


| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| BR2G-5420V4V     | 420W    | 25A    | 33A   | 25A   | X   | 0.8A  | 3.5A  |
| BR2G-5460V4V     | 460W    | 25A    | 37A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :

+5V AND +3.3V TOTAL OUTPUT MAX : 170W

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 40°C · STORAGE -20°C ~ 80°C
- EFFICIENCY : >80% TYPICAL AT 24VDC FULL LOAD
- OUTPUT PROTECTION : OPP / OVP / SCP /OCP
- BALANCE LOAD SHARING DESIGN
- REMOTE ON/OFF CONTROL
- HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION
- DIMENSION : 276mm (D) x 101mm (W) x 82mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



DR2G-5500V4V  
DR2G-5600V4V

INPUT CHARACTERISTICS

VOLTAGE :  
-36 ~ -72 VDC, NORMAL -48VDC  
INPUT CURRENT :

| WATTAGE | -48VDC ( -36 ~ -72VDC )    |
|---------|----------------------------|
| 500W    | 25~10AMP (13AMP AT -48VDC) |
| 600W    | 25~10AMP (15AMP AT -48VDC) |

INRUSH CURRENT :  
35A @ -48VDC (AT 25 DEGREES AMBIEND COLD START)  
EMI :  
FCC, CISPR 22(EN 55022)  
EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE  
SAFETY :  
TO MEET UL&CUL, TUV




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DR2G-5500V4V     | 500W    | 25A    | 40A   | 25A   | X   | 0.8A  | 3.5A  |
| DR2G-5600V4V     | 600W    | 25A    | 48A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 170W

SPECIFICATION :  
TEMPERATURE RANGE : OPERATING : 0°C ~40°C , STORAGE : -20°C ~80°C ,  
EFFICIENCY : >80% TYPICAL AT -48VDC FULL LOAD  
OUTPUT PROTECTION : OPP / OVP / SCP / OCP  
BALANCE LOAD SHARING DESIGN  
REMOTE ON/OFF CONTROL  
HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION  
WARNING METHOD : LED, BUZZER, TTL SIGNAL  
DIMENSION : 276mm (D) x 101mm (W) x 82mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



DR2G-5800V

OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DR2G-5800V       | 800W    | 32A    | 65A   | 32A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |


REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 190W

INPUT CHARACTERISTICS

- VOLTAGE :  
-39 ~ -72 VDC
- STEADY-STATE CURRENT :  
-39 ~ -72VDC / 26-14 AMP(21 AMP @ -48VDC)
- INRUSH CURRENT :  
70A @ -48VDC (AT 25 DEGREES AMBIEND COLD START)
- EMI :  
FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV, GOST

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING : 0°C ~50°C , STORAGE : -20°C ~80
- EFFICIENCY : >80% TYPICAL AT -48VDC FULL LOAD
- OUTPUT PROTECTION : OPP / OVP / SCP / OCP
- BALANCE LOAD SHARING DESIGN
- REMOTE ON/OFF CONTROL
- HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION
- ISOLATION BUILT-IN THE POWER MODULE
- WAWARNING METHOD : LED, BUZZER, TTL SIGNAL
- DIMENSION : 340mm (D) x 101mm (W) x 82mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## DC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| BMTW2-5600V3V    | 600W    | 32A    | 50A   | 36A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 60mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

#### REMARKS :

\* +5V AND +3.3V TOTAL OUTPUT MAX : 200W

\* TOTAL OUTPUT MAX : 600W (AT 18V ONLY 550W)

## BMTW2-5600V3V

### INPUT CHARACTERISTICS

#### VOLTAGE :

19 ~ 36VDC

#### STEADY-STATE CURRENT :

19~36VDC/45~21 AMP

#### INRUSH CURRENT :

50A MAX. @24VDC INPUT (AT 25DEGREES AMBIENT COLD START)

#### EMI :

IEC61000-3-2, FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV, CCC

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 40°C ,STORAGE -20°C ~ 80°C

EFFICIENCY : TYPICAL >80% @ 24VDC, 30~100% MAX LOAD

OUTPUT PROTECTION : OPP / OVP / SCP / OCP

BALANCE LOAD SHARING DESIGN

REMOTE ON/OFF CONTROL


HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

WARNING METHOD : LED, BUZZER, TTL SIGNAL

DIMENSION : 300mm (D) x 101mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### DM1W2-5600V3V DM1W2-5650V3V DM1W2-5700V3V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

-36 ~ -72 VDC, NORMAL -48VDC

##### INPUT CURRENT :

16/17/17A @ -48VDC

##### INRUSH CURRENT :

30A AT -48VDC (AT 25 DEGREES AMBIENT COLD START)

##### EMI :

FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC



#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DM1W2-5600V3V    | 600W    | 32A    | 45A   | 36A   | X   | 0.8A  | 3.5A  |
| DM1W2-5650V3V    | 650W    | 32A    | 50A   | 36A   | X   | 0.8A  | 3.5A  |
| DM1W2-5700V3V    | 700W    | 32A    | 55A   | 36A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

+5V AND +3.3V TOTAL OUTPUT NOT EXCEED 200W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

EFFICIENCY : 80% TYPICAL · AT INPUT -48V FULL LOAD

OUTPUT PROTECTION : OPP / OVP / SCP / OCP


BALANCE LOAD SHARING DESIGN

REMOTE ON/OFF CONTROL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

DIMENSION : 300mm (D) x 101mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| BG1W2-5600V3V    | 600W    | 25A    | 50A   | 25A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |


REMARKS :  
POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 190W;  
TOTAL OUTPUT MAX 600W (AT 18V ONLY 550W)

BG1W2-5600V3V

INPUT CHARACTERISTICS

- VOLTAGE :  
19 ~ 36 VDC
- STEADY-STATE CURRENT :  
19-36VDC/44-21AMP(32AMP AT 24VDC)
- INRUSH CURRENT :  
50A @24VDC AT 25 DEGREES AMBIENT COLD START
- EMI :  
FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV

- SPECIFICATION :
- TEMPERATURE RANGE : OPERATING 0°C ~ 40°C , STORAGE -20°C ~ 80°C
- EFFICIENCY : TYPICAL >80% AT 24VDC, FULL LOAD
- OUTPUT PROTECTION : OPP / OVP / OCP / SCP
- REMOTE ON / OFF CONTROL
- REMOTE SENSING DESIGN
- BALANCE LOAD SHARING DESIGN
- HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION
- ISOLATION : BUILT-IN THE POWER MODULE
- FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL
- DIMENSION : 300mm (D) x 101.2mm (W) x 84mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



DC 2U REDUNDANT

DC INPUT TO DC OUTPUT



DG1W2-5660V3V  
DG1W2-5760V3V  
DG1W2-5860V3V  
DG1W2-5960V3V  
DG1W2-5A10V3V

INPUT CHARACTERISTICS

VOLTAGE :  
-36 ~ -72 VDC  
STEADY-STATE CURRENT :

| WATTAGE | -48VDC ( -36 ~ -72VDC )    |
|---------|----------------------------|
| 660W    | 24~12AMP (21AMP AT -48VDC) |
| 760W    | 28~14AMP (21AMP AT -48VDC) |
| 860W    | 31~15AMP (23AMP AT -48VDC) |
| 960W    | 35~16AMP (26AMP AT -48VDC) |
| 1010W   | 36~17AMP (26AMP AT -48VDC) |

INRUSH CURRENT :  
80AMPS @ -48VDC  
EMI :  
FCC, CISPR 22(EN 55022)  
EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE  
SAFETY :  
TO MEET UL, CUL, TUV, CCC




OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DG1W2-5660V3V    | 660W    | 25A    | 55A   | 25A   | X   | 0.8A  | 3.5A  |
| DG1W2-5760V3V    | 760W    | 32A    | 62A   | 32A   | X   | 0.8A  | 3.5A  |
| DG1W2-5860V3V    | 860W    | 32A    | 70A   | 32A   | X   | 0.8A  | 3.5A  |
| DG1W2-5960V3V    | 960W    | 32A    | 78A   | 32A   | X   | 0.8A  | 3.5A  |
| DG1W2-5A10V3V    | 1010W   | 32A    | 83A   | 32A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
+5V AND +3.3V TOTAL OUTPUT MAX : 190W

SPECIFICATION :  
TEMPERATURE RANGE : OPERATING 0°C ~40°C ,STORAGE -20°C ~80°C  
EFFICIENCY : TYPICAL >80% @ DC-48 INPUT, FULL LOAD  
OUTPUT PROTECTION : OPP / OVP / SCP / OCP  
BALANCE LOAD SHARING DESIGN  
REMOTE ON/OFF CONTROL  
HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION  
ISOLATION BUILT-IN THE POWER MODULE  
DIMENSION : 300mm (D) x 101.2mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





DMTW2-5660V3V  
DMTW2-5820V3V

INPUT CHARACTERISTICS

- VOLTAGE :  
-36 ~ -72 VDC
- STEADY-STATE CURRENT :  
25/13 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT  
VOLTAGE (660W)  
30/15 AMPS MAXIMUM AT ANY LOW/HIGH RANGE INPUT  
VOLTAGE (820W)
- INRUSH CURRENT :  
35A MAX. @-48VDC INPUT(AT 25DEGREES AMBIENT COLD START FOR EACH POWER UNIT)
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV, CCC



OUTPUT CHARACTERISTICS


| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DMTW2-5660V3V    | 660W    | 32A    | 50A   | 36A   | X   | 0.8A  | 3.5A  |
| DMTW2-5820V3V    | 820W    | 32A    | 67A   | 36A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARKS :  
POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 200W.  
POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 660W / 820W

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING 0°C ~ 45°C , STOREAGE -20°C ~80°C
- EFFICIENCY(PER SET) : TYPICAL >80% AT 48VDC, 30~100% MAX LOAD
- OUTPUT PROTECTION : OPP / OVP / OCP / SCP
- REMOTE ON / OFF CONTROL
- BALANCE LOAD SHARING DESIGN
- HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION
- ISOLATION : BUILT-IN THE POWER MODULE
- FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL
- DIMENSION : 300mm (D) x 101.2mm (W) x 84mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.







## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### DM1L2-5600V3V DM1L2-5650V3V DM1L2-5700V3V

#### INPUT CHARACTERISTICS

##### VOLTAGE :

-36 ~ -72 VDC, NORMAL -48VDC

##### STEADY-STATE CURRENT :

16/17/19 AMP @ -48VDC

##### INRUSH CURRENT :

30A AMP @ -48VDC

##### EMI :

FCC, CISPR 22(EN 55022)

##### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

##### SAFETY :

TO MEET UL, CUL, TUV, CCC

#### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DM1L2-5600V3V    | 600W    | 32A    | 45A   | 36A   | X   | 0.8A  | 3.5A  |
| DM1L2-5650V3V    | 650W    | 32A    | 50A   | 36A   | X   | 0.8A  | 3.5A  |
| DM1L2-5700V3V    | 700W    | 32A    | 55A   | 36A   | X   | 0.8A  | 3.5A  |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±10%  | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

##### REMARKS :

+5V AND +3.3V TOTAL OUTPUT NOT EXCEED 200W

#### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 50°C · STORAGE -20°C ~ 80°C

EFFICIENCY : 80% TYPICAL · AT INPUT -48V FULL LOAD

OUTPUT PROTECTION : OPP / OVP / SCP / OCP


BALANCE LOAD SHARING DESIGN

REMOTE ON/OFF CONTROL

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

DIMENSION : 330(D) X 101.2(W) X 84(H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.





## HIGH EFFICIENCY DC INPUT TO DC OUTPUT



### OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DPSS2-5A00V3H    | 1000W   | 22A    | 83A   | 22A   | X   | 0.5A  | 4A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 70mV  |

REMARKS :  
TOTAL MAX OUTPUT OF +5V AND +3.3V NOT EXCEED 150W

## DPSS2-5A00V3H

### INPUT CHARACTERISTICS

#### VOLTAGE :

-36 ~ -72 VDC, NORMAL -48VDC

#### INPUT CURRENT :

30A @ -48VDC

#### INRUSH CURRENT :

10AMPS MAX @ -48VDC INPUT

#### EMI :

FCC, CISPR 22(EN 55022)

#### EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5 SURGE

#### SAFETY :

TO MEET UL, CUL, TUV

### SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~40°C , STORAGE -20°C ~80°C

EFFICIENCY : TYPICAL 83% AT DC-48 INPUT, FULL LOAD (PER SET)

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON/OFF CONTROL


BALANCE LOAD SHARING DESIGN

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION BUILT-IN THE POWER MODULE

DIMENSION : 360mm (D) x 127mm (W) x 44mm (H)

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT

OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DMTW4-5M10V3H    | 2210W   | 86A    | 180A  | 97A   | X   | 1.6A  | 7A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARK :  
POWER MODULE TOTAL OUTPUT POWER OF +5V AND +3.3V NOT EXCEED 540W.  
POWER MODULE TOTAL OUTPUT POWER NOT EXCEED 2210W



DMTW4-5M10V3H

SPECIFICATION :

TEMPERATURE RANGE : OPERATING 0°C ~ 45°C , STOREAGE -20°C ~80°C

EFFICIENCY : TYPICAL >80% AT 48VDC, 50~100% MAX LOAD

OUTPUT PROTECTION : OPP / OVP / OCP / SCP

REMOTE ON / OFF CONTROL

BALANCE LOAD SHARING DESIGN

HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION

ISOLATION : BUILT-IN THE POWER MODULE

FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL

DIMENSION : 340(D) \* 422(W) \* 43 (H) mm

THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.

INPUT CHARACTERISTICS

VOLTAGE :

-36 ~ -72VDC

STEADY-STATE CURRENT :

30/15 AMPS MAXIMUM AT ANY LOW/HIGH RANGE  
INPUT VOLTAGE

INRUSH CURRENT :

35A MAX. @-48VDC INPUT(AT 25DEGREES  
AMBIENT COLD START FOR EACH POWER UNIT)

EMI :


IEC61000-3-2, FCC, CISPR 22(EN 55022)

EMS :

EN 61000-4-2 ESD, EN61000-4-4 EFT, EN61000-4-5  
SURGE

SAFETY :

TO MEET UL, CUL, TUV, CCC



HIGH EFFICIENCY  
DC INPUT TO DC OUTPUT



OUTPUT CHARACTERISTICS

| MODEL            | WATTAGE | OUTPUT |       |       |     |       |       |
|------------------|---------|--------|-------|-------|-----|-------|-------|
|                  |         | +5V    | +12V  | +3.3V | -5V | -12V  | +5VSB |
| DG1W4-5BG0V0H    | 2700W   | 32A    | 225A  | 32A   | X   | 1A    | 6A    |
| REGULATION LOAD  |         | ±5%    | ±5%   | ±5%   | X   | ±5%   | ±5%   |
| RIPPLE AND NOISE |         | 50mV   | 120mV | 50mV  | X   | 120mV | 50mV  |

REMARK :  
THE OUTPUT CURRENT OF +5V AND +3.3V NOT EXCEED 190W  
TOTAL POWER:2700W (MAX)


DG1W4-5BG0V0H

INPUT CHARACTERISTICS

- VOLTAGE :  
-36 ~ -72VDC
- STEADY-STATE CURRENT :  
-36 ~ -72VDC / 97~46A
- INRUSH CURRENT :  
80AMP AT -48VDC
- EMI :  
IEC61000-3-2, FCC, CISPR 22(EN 55022)
- EMS :  
EN 61000-4-2 ESD, EN6100-4-4 EFT, EN61000-4-5 SURGE
- SAFETY :  
TO MEET UL, CUL, TUV, CCC

SPECIFICATION :

- TEMPERATURE RANGE : OPERATING : 0°C ~ 40°C , STORAGE : -20°C --- 80°C
- HOLD UP TIME : 16 ms MINIMUM AT FULL LOAD & NORMAL INPUT VOLTAGE
- EFFICIENCY : >80% TYPICAL AT -48VDC FULL LOAD
- POWER GOOD SIGNAL : ON DELAY 100 ms TO 500 ms, OFF DELAY 1 ms
- OUTPUT PROTECTION : OPP / OVP / OCP / SCP
- FAULTY ALARM METHODS : LED, BUZZER, TTL SIGNAL
- HOT-SWAPPABLE/HOT PLUGGABLE REDUNDANCY FUNCTION
- ISOLATION : BUILT-IN THE POWER MODULE
- REMOTE SENSING DESIGN
- LEAKAGE CURRENT : INPUT LEAKAGE CURRENT FROM LINE TO GROUND WILL BE LESS THAN 3.5MA RMS. MEASUREMENT WILL BE MADE AT 240 VAC AND 60HZ.
- DIMENSION : 340mm (D) x 422mm (W) x 43mm (H)
- THE POWER-SUPPLY IS FOR CHASSIS-ASSEMBLY ONLY AND IS NOT ALLOWED TO BE OPERATED AS STAND-ALONE COMPONENT. FINAL ASSEMBLY HAS TO COMPLY WITH CORRESPONDING EMC- AND SAFETY-REGULATIONS.



DC N+1 REDUNDANT

[More product details](#)

| FORM FACTOR | MODEL NAME | WATTAGE | INPUT | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) |
|-------------|------------|---------|-------|----------------|----------------|----------------|
| EASYSWAP    | P1Z-6350P  | 350W    | PFC   | 265/10.43      | 100.8/3.97     | 41.8/1.65      |
| EASYSWAP    | P1Z-6400P  | 400W    | PFC   | 265/10.43      | 100.8/3.97     | 41.8/1.65      |
| EASYSWAP    | P1W-6520P  | 520W    | PFC   | 300/11.81      | 100.8/3.97     | 41.8/1.65      |
| 1U          | H1U-6150P  | 150W    | PFC   | 155/6.1        | 100/3.94       | 40/1.57        |
| 1U          | H1U-6200P  | 200W    | PFC   | 155/6.1        | 100/3.94       | 40/1.57        |
| 1U          | H1U-6250P  | 250W    | PFC   | 155/6.1        | 100/3.94       | 40/1.57        |
| 1U          | P1A-6200P  | 200W    | PFC   | 190/7.48       | 100/3.94       | 40.5/1.59      |
| 1U          | P1A-6250P  | 250W    | PFC   | 190/7.48       | 100/3.94       | 40.5/1.59      |
| 1U          | P1A-6300P  | 300W    | PFC   | 205/8.07       | 100/3.94       | 40.5/1.59      |
| 1U          | P1A-6201P  | 200W    | PFC   | 190/7.48       | 100/3.94       | 40.5/1.59      |
| 1U          | P1A-6221P  | 220W    | PFC   | 190/7.48       | 100/3.94       | 40.5/1.59      |
| 1U          | P1A-6301P  | 300W    | PFC   | 190/7.48       | 100/3.94       | 40.5/1.59      |
| 1U          | P1X-6200P  | 200W    | PFC   | 190/7.48       | 100/3.94       | 40.5/1.59      |
| 1U          | P1X-6250P  | 250W    | PFC   | 190/7.48       | 100/3.94       | 40.5/1.59      |
| 1U          | P1X-6300P  | 300W    | PFC   | 190/7.48       | 100/3.94       | 40.5/1.59      |
| 1U          | P1U-6150P  | 150W    | PFC   | 190/7.48       | 100/3.94       | 40/1.57        |
| 1U          | P1U-6180P  | 180W    | PFC   | 190/7.48       | 100/3.94       | 40/1.57        |
| 1U          | P1U-6200P  | 200W    | PFC   | 190/7.48       | 100/3.94       | 40/1.57        |
| 1U          | P1G-6250P  | 250W    | PFC   | 205/8.07       | 100/3.94       | 40.5/1.59      |
| 1U          | P1G-6300P  | 300W    | PFC   | 205/8.07       | 100/3.94       | 40.5/1.59      |
| 1U          | P1G-6305P  | 300W    | PFC   | 205/8.07       | 100/3.94       | 40.5/1.59      |
| 1U          | P1H-6350P  | 350W    | PFC   | 225/8.86       | 100/3.94       | 40.5/1.59      |
| 1U          | P1H-6400P  | 400W    | PFC   | 225/8.86       | 100/3.94       | 40.5/1.59      |
| 1U          | H1M-6550P  | 550W    | PFC   | 225/8.86       | 100/3.94       | 40.5/1.59      |
| 1U          | H1M-6600P  | 600W    | PFC   | 225/8.86       | 100/3.94       | 40.5/1.59      |
| 1U          | H1M-6557P  | 550W    | PFC   | 275/10.83      | 100/3.94       | 40.5/1.59      |
| 1U          | H1M-6607P  | 600W    | PFC   | 275/10.83      | 100/3.94       | 40.5/1.59      |
| 2U          | P2U-6300P  | 300W    | PFC   | 200/7.87       | 100/3.94       | 70/2.76        |
| 2U          | P2U-6320P  | 320W    | PFC   | 200/7.87       | 100/3.94       | 70/2.76        |
| 2U          | P2H-6350P  | 350W    | PFC   | 240/9.45       | 100/3.94       | 70/2.76        |
| 2U          | P2H-6400P  | 400W    | PFC   | 240/9.45       | 100/3.94       | 70/2.76        |
| 2U          | P2G-6400P  | 400W    | PFC   | 240/9.45       | 100/3.94       | 70/2.76        |
| 2U          | P2G-6435P  | 435W    | PFC   | 240/9.45       | 100/3.94       | 70/2.76        |
| 2U          | P2G-6460P  | 460W    | PFC   | 240/9.45       | 100/3.94       | 70/2.76        |

| CCC | BSMI | +5V | +12V | +3.3V | -5V | -12V | +5VSB | +5.3VA.VB | +5V2 | +12V2 | +3.3V2 |
|-----|------|-----|------|-------|-----|------|-------|-----------|------|-------|--------|
| V   |      | 25  | 28   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 25  | 28   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 30  | 32   | 24    | 0.7 | 0.7  | 3     | X         | X    | X     | X      |
| V   |      | 16  | 9    | 10    | 0.2 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 20  | 12   | 14    | 0.2 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 23  | 16   | 14    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 25  | 8    | 14    | 0.5 | 0.5  | 1.5   | X         | X    | X     | X      |
| V   |      | 24  | 12   | 20    | 0.5 | 0.5  | 1.5   | X         | X    | X     | X      |
| V   |      | 24  | 20   | 20    | 0.5 | 1    | 1.5   | X         | X    | X     | X      |
| V   |      | 24  | 12   | 20    | 0.5 | 0.5  | 1.5   | X         | X    | X     | X      |
| V   |      | 24  | 12   | 20    | 0.5 | 0.5  | 1.5   | X         | X    | X     | X      |
| V   |      | 24  | 20   | 20    | 0.5 | 0.5  | 1.5   | X         | X    | X     | X      |
| V   |      | 23  | 12   | 14    | 0.2 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 23  | 16   | 14    | 0.2 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 23  | 20   | 14    | 0.2 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 14  | 7    | 10    | 0.1 | 0.7  | 1.5   | X         | X    | X     | X      |
| V   |      | 16  | 7    | 14    | 0.1 | 0.7  | 1.5   | X         | X    | X     | X      |
| V   |      | 16  | 7    | 14    | 0.2 | 0.7  | 1.5   | X         | X    | X     | X      |
| V   |      | 25  | 12   | 14    | 0.5 | 1    | 1.5   | X         | X    | X     | X      |
| V   |      | 25  | 16   | 14    | 0.5 | 1    | 1.5   | X         | X    | X     | X      |
| V   |      | 30  | 16   | 14    | 0.5 | 1    | 1.5   | X         | X    | X     | X      |
| V   |      | 25  | 22   | 20    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 25  | 28   | 20    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 30  | 48   | 24    | 0.5 | 0.5  | 4     | X         | X    | X     | X      |
| V   |      | 30  | 48   | 24    | 0.5 | 0.5  | 4     | X         | X    | X     | X      |
| V   |      | 30  | 48   | 24    | 0.5 | 0.5  | 4     | X         | X    | X     | X      |
| V   |      | 30  | 48   | 24    | 0.5 | 0.5  | 4     | X         | X    | X     | X      |
| V   |      | 35  | 16   | 20    | 0.5 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 35  | 16   | 20    | 0.5 | 1    | 2     | X         | X    | X     | X      |
| V   | V    | 25  | 28   | 20    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 25  | 28   | 20    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 33  | 25   | 28    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 33  | 25   | 28    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 33  | 27   | 28    | 0.8 | 1    | 2     | X         | X    | X     | X      |

| FORM FACTOR  | MODEL NAME   | WATTAGE | INPUT | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) |
|--------------|--------------|---------|-------|----------------|----------------|----------------|
| 2U           | P2G-6510P    | 510W    | PFC   | 240/9.45       | 100/3.94       | 70/2.76        |
| 2U           | P2G-6510PE   | 510W    | PFC   | 240/9.45       | 100/3.94       | 70/2.76        |
| 2U           | P2M-6550P    | 550W    | PFC   | 270/10.63      | 100/3.94       | 70/2.76        |
| 2U           | P2M-6600P    | 600W    | PFC   | 270/10.63      | 100/3.94       | 70/2.76        |
| 2U           | P2P-5650P    | 650W    | PFC   | 280/11.02      | 100/3.94       | 82.5/3.25      |
| 2U           | P2P-5700P    | 700W    | PFC   | 280/11.02      | 100/3.94       | 82.5/3.25      |
| 3U           | H3M-6500P    | 500W    | PFC   | 265/10.43      | 100/3.94       | 120/4.72       |
| 3U           | H3M-6600P    | 600W    | PFC   | 265/10.43      | 100/3.94       | 120/4.72       |
| PS2          | HG2-6300P    | 300W    | PFC   | 140/5.51       | 150/5.91       | 86/3.39        |
| PS2          | HG2-6350P    | 350W    | PFC   | 140/5.51       | 150/5.91       | 86/3.39        |
| PS2          | HG2-6400P    | 400W    | PFC   | 140/5.51       | 150/5.91       | 86/3.39        |
| PS2          | HP2-6400P    | 400W    | PFC   | 140/5.51       | 150/5.91       | 86/3.39        |
| PS2          | HP2-6460P    | 460W    | PFC   | 140/5.51       | 150/5.91       | 86/3.39        |
| PS2          | HP2-6500P    | 500W    | PFC   | 140/5.51       | 150/5.91       | 86/3.39        |
| PS2+         | PSM-6550P    | 550W    | PFC   | 160/6.3        | 150/5.91       | 86/3.39        |
| PS2+         | PSM-6600P    | 600W    | PFC   | 160/6.3        | 150/5.91       | 86/3.39        |
| PS2+         | PSA-6600P    | 600W    | PFC   | 220/8.66       | 150/5.91       | 86/3.39        |
| PS2+         | PSA-6650P    | 650W    | PFC   | 220/8.66       | 150/5.91       | 86/3.39        |
| PS2+         | PSA-6700P    | 700W    | PFC   | 220/8.66       | 150/5.91       | 86/3.39        |
| PS2+         | PSL-6600P    | 600W    | PFC   | 220/8.66       | 150/5.91       | 86/3.39        |
| PS2+         | PSL-6700P    | 700W    | PFC   | 220/8.66       | 150/5.91       | 86/3.39        |
| PS2+         | PSL-6701P    | 700W    | PFC   | 220/8.66       | 150/5.91       | 86/3.39        |
| 1U Redundant | R1M-6251P    | 250W    | PFC   | 260/10.24      | 180/7.09       | 40.6/1.6       |
| 1U Redundant | R1Z-6350P    | 350W    | PFC   | 265/10.43      | 206/8.11       | 41.5/1.63      |
| 1U Redundant | R1Z-6400P    | 400W    | PFC   | 265/10.43      | 206/8.11       | 41.5/1.63      |
| 2U Redundant | MIN2-6251P   | 250W    | PFC   | 230/9.06       | 82/3.23        | 85/3.35        |
| 2U Redundant | M1L2-5650P3V | 650W    | PFC   | 330/12.99      | 101.2/3.98     | 84/3.31        |
| 2U Redundant | M1L2-5700P3V | 700W    | PFC   | 330/12.99      | 101.2/3.98     | 84/3.31        |
| 2U Redundant | R2Z-6350P    | 350W    | PFC   | 265/10.43      | 101.2/3.98     | 84/3.31        |
| 2U Redundant | R2Z-6400P    | 400W    | PFC   | 265/10.43      | 101.2/3.98     | 84/3.31        |
| 2U Redundant | R2G-5420P4V  | 420W    | PFC   | 276/10.87      | 101/3.98       | 82/3.23        |
| 2U Redundant | R2G-6300P    | 300W    | PFC   | 300/11.81      | 101/3.98       | 82/3.23        |
| 2U Redundant | R2G-6350P    | 350W    | PFC   | 300/11.81      | 101/3.98       | 82/3.23        |
| 2U Redundant | R2W-5600P3V  | 600W    | PFC   | 300/11.81      | 101/3.98       | 84/3.31        |

| CCC | BSMI | +5V | +12V | +3.3V | -5V | -12V | +5VSB | +5.3VA.VB | +5V2 | +12V2 | +3.3V2 |
|-----|------|-----|------|-------|-----|------|-------|-----------|------|-------|--------|
| V   |      | 33  | 32   | 28    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 33  | 36   | 28    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 35  | 42   | 30    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 35  | 42   | 30    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 30  | 50   | 25    | X   | 0.8  | 3     | X         | X    | X     | X      |
| V   |      | 30  | 50   | 25    | X   | 0.8  | 3     | X         | X    | X     | X      |
| V   |      | 30  | 40   | 24    | 0.5 | 0.5  | 4     | X         | X    | X     | X      |
| V   |      | 30  | 48   | 24    | 0.5 | 0.5  | 4     | X         | X    | X     | X      |
| V   |      | 35  | 22   | 25    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 35  | 26   | 25    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 35  | 30   | 25    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 35  | 20   | 28    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 40  | 27   | 30    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 40  | 32   | 30    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 30  | 26   | 30    | 0.8 | 0.8  | 2     | X         | X    | 20    | X      |
| V   |      | 30  | 26   | 30    | 0.8 | 0.8  | 2     | X         | X    | 20    | X      |
| V   |      | 50  | 36   | 45    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 50  | 36   | 45    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 50  | 36   | 45    | 0.8 | 10   | 2     | X         | X    | X     | X      |
| V   |      | 50  | 36   | 45    | 0.8 | 10   | 2     | X         | X    | X     | X      |
| V   |      | 35  | 45   | 30    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 25  | 16   | 15    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 25  | 28   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 25  | 28   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 25  | 16   | 15    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   | V    | 32  | 45   | 25    | X   | 0-1  | 0.1-3 | X         | X    | X     | X      |
| V   |      | 32  | 45   | 25    | X   | 0-1  | 0.1-3 | X         | X    | X     | X      |
| V   |      | 25  | 28   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 25  | 28   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 24  | 26   | 20    | X   | 0.8  | 3     | X         | X    | X     | X      |
| V   |      | 32  | 16   | 20    | 0.5 | 0.8  | 1.5   | X         | X    | X     | X      |
| V   |      | 35  | 22   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 32  | 42   | 24    | X   | 1    | 2     | X         | X    | X     | X      |



| FORM FACTOR     | MODEL NAME  | WATTAGE | INPUT | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) |
|-----------------|-------------|---------|-------|----------------|----------------|----------------|
| 2U Redundant    | R2W-6400P   | 400W    | PFC   | 300/11.81      | 101/3.98       | 84/3.31        |
| 2U Redundant    | R2W-6460P   | 460W    | PFC   | 300/11.81      | 101/3.98       | 84/3.31        |
| 2U Redundant    | R2W-6500P   | 500W    | PFC   | 300/11.81      | 101/3.98       | 84/3.31        |
| 2U Redundant    | M2W-6460P   | 460W    | PFC   | 300/11.81      | 101/3.98       | 84/3.31        |
| 2U Redundant    | M2W-6500P   | 500W    | PFC   | 300/11.81      | 101/3.98       | 84/3.31        |
| 2U Redundant    | M2W-6550P   | 550W    | PFC   | 300/11.81      | 101/3.98       | 84/3.31        |
| 2U Redundant    | R2A-5350P   | 350W    | PFC   | 220/8.66       | 120/4.72       | 85/3.35        |
| 2U Redundant    | R2A-6300P   | 300W    | PFC   | 220/8.66       | 120/4.72       | 85/3.35        |
| 2U Redundant    | R2A-6320P   | 320W    | PFC   | 220/8.66       | 120/4.72       | 85/3.35        |
| Mini Redundant  | MRT-6300P   | 300W    | PFC   | 185/7.28       | 150/5.91       | 86/3.39        |
| Mini Redundant  | MRT-6320P   | 320W    | PFC   | 185/7.28       | 150/5.91       | 86/3.39        |
| Mini Redundant  | MRW-6350P   | 350W    | PFC   | 185/7.28       | 150/5.91       | 86/3.39        |
| Mini Redundant  | MRW-6400P   | 400W    | PFC   | 185/7.28       | 150/5.91       | 86/3.39        |
| Mini Redundant  | MRW-6420P   | 420W    | PFC   | 185/7.28       | 150/5.91       | 86/3.39        |
| Mini Redundant  | MRG-6460P   | 460W    | PFC   | 200/7.87       | 150/5.91       | 86/3.39        |
| Mini Redundant  | MRG-6500P   | 500W    | PFC   | 200/7.87       | 150/5.91       | 86/3.39        |
| Mini Redundant  | MX3-6550P   | 550W    | PFC   | 254/10         | 150/5.91       | 82/3.23        |
| Mini Redundant  | MX3-6600P   | 600W    | PFC   | 254/10         | 150/5.91       | 82/3.23        |
| Mini Redundant  | MX3-5700P   | 700W    | PFC   | 265/10.43      | 150/5.91       | 84/3.31        |
| Mini Redundant  | MX3-5750P   | 750W    | PFC   | 265/10.43      | 150/5.91       | 84/3.31        |
| Mini Redundant  | MRM-6550P   | 550W    | PFC   | 254/10         | 150/5.91       | 84/3.31        |
| Mini Redundant  | MRM-6600P   | 600W    | PFC   | 254/10         | 150/5.91       | 84/3.31        |
| Mini Redundant  | MRM-6650P   | 650W    | PFC   | 254/10         | 150/5.91       | 84/3.31        |
| PS2*2 Redundant | RHD-6400P   | 400W    | PFC   | 183/7.2        | 153.4/6.04     | 213.2/8.39     |
| PS2*2 Redundant | RHD-6460P   | 460W    | PFC   | 183/7.2        | 153.4/6.04     | 213.2/8.39     |
| PS2*2 Redundant | RHI-6400P   | 400W    | PFC   | 183/7.2        | 167/6.57       | 187.8/7.39     |
| PS2*2 Redundant | RHI-6460P   | 460W    | PFC   | 183/7.2        | 167/6.57       | 187.8/7.39     |
| PS2*2 Redundant | RHH-6400P   | 400W    | PFC   | 194.2/7.65     | 354/13.94      | 106/4.17       |
| PS2*2 Redundant | RHH-6460P   | 460W    | PFC   | 194.2/7.65     | 354/13.94      | 106/4.17       |
| N + 1 Redundant | M3W-6950P   | 950W    | PFC   | 300/11.81      | 101/3.98       | 125/4.92       |
| N + 1 Redundant | R3U-6460P   | 460W    | PFC   | 254/10         | 127/5          | 82/3.23        |
| N + 1 Redundant | R3G-5800P4V | 800W    | PFC   | 276/10.87      | 127/5          | 83/3.27        |
| N + 1 Redundant | R3G-6650P   | 650W    | PFC   | 300/11.81      | 127/5          | 82/3.23        |
| N + 1 Redundant | MR3-6460P   | 460W    | PFC   | 254/10         | 150/5.91       | 82/3.23        |

| CCC | BSMI | +5V | +12V | +3.3V | -5V | -12V | +5VSB | +5.3VA.VB | +5V2 | +12V2 | +3.3V2 |
|-----|------|-----|------|-------|-----|------|-------|-----------|------|-------|--------|
| V   |      | 26  | 28   | 24    | 0.7 | 0.7  | 2     | X         | X    | X     | X      |
| V   |      | 30  | 32   | 24    | 0.7 | 0.7  | 2     | X         | X    | X     | X      |
| V   |      | 30  | 32   | 24    | 0.7 | 0.7  | 2     | X         | X    | X     | X      |
| V   | V    | 30  | 32   | 24    | 0.7 | 0.7  | 2     | X         | X    | X     | X      |
| V   | V    | 30  | 32   | 24    | 0.7 | 0.7  | 2     | X         | X    | X     | X      |
| V   |      | 30  | 36   | 24    | 0.7 | 0.7  | 2     | X         | X    | X     | X      |
| V   |      | 35  | 8    | 35    | X   | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 32  | 16   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 32  | 16   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 25  | 16   | 18    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 25  | 16   | 18    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 35  | 22   | 25    | 0.5 | 1.2  | 2     | X         | X    | X     | X      |
| V   |      | 35  | 28   | 25    | 0.5 | 1.2  | 2     | X         | X    | X     | X      |
| V   |      | 35  | 28   | 25    | 0.5 | 1.2  | 2     | X         | X    | X     | X      |
| V   |      | 35  | 32   | 25    | 0.8 | 1    | 2.5   | X         | X    | X     | X      |
| V   |      | 35  | 32   | 25    | 0.8 | 1    | 2.5   | X         | X    | X     | X      |
| V   |      | 60  | 40   | 36    | 1   | 1    | 2.5   | X         | X    | X     | X      |
| V   |      | 60  | 40   | 36    | 1   | 1    | 2.5   | X         | X    | X     | X      |
| V   |      | 50  | 52   | 38    | X   | 1    | 3.5   | X         | X    | X     | X      |
| V   |      | 52  | 56   | 40    | X   | 1    | 3.5   | X         | X    | X     | X      |
| V   |      | 28  | 41   | 28    | 0.8 | 1    | 3.5   | X         | X    | X     | X      |
| V   |      | 30  | 45   | 28    | 0.8 | 1    | 3.5   | X         | X    | X     | X      |
| V   |      | 30  | 48   | 28    | 0.8 | 1    | 3.5   | X         | X    | X     | X      |
| V   |      | 35  | 20   | 28    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 40  | 32   | 30    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 35  | 20   | 28    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 40  | 32   | 30    | 0.8 | 1    | 2     | X         | X    | X     | X      |
| V   |      | 56  | 60   | 44    | 1.2 | 1.2  | 3.5   | X         | X    | X     | X      |
| V   |      | 50  | 32   | 28    | 1   | 1    | 1     | X         | X    | X     | X      |
| V   |      | 45  | 49   | 38    | 0   | 1    | 4     | X         | X    | X     | X      |
| V   |      | 60  | 40   | 40    | 1   | 1    | 2.5   | X         | X    | X     | X      |
| V   |      | 50  | 32   | 28    | 1   | 1    | 3     | X         | X    | X     | X      |

| FORM FACTOR        | MODEL NAME  | WATTAGE | INPUT   | D<br>(mm/inch) | W<br>(mm/inch) | H<br>(mm/inch) |
|--------------------|-------------|---------|---------|----------------|----------------|----------------|
| N + 1 Redundant    | MR3-6480P   | 480W    | PFC     | 254/10         | 150/5.91       | 82/3.23        |
| N + 1 Redundant    | M1G3-6930P  | 930W    | PFC     | 335/13.19      | 369/14.53      | 42/1.65        |
| N + 1 Redundant    | M1W4-6D50P  | 1350W   | PFC     | 340/13.39      | 422/16.61      | 43/1.69        |
| DC 1U              | B1U-6150F   | 150W    | DC 24V  | 190/7.48       | 100/3.94       | 40.5/1.59      |
| DC 1U              | BP1H-6300F  | 300W    | DC 24V  | 225/8.86       | 100/3.94       | 40.5/1.59      |
| DC 1U              | DP1A-6250F  | 250W    | DC -48V | 205/8.07       | 100/3.94       | 40.5/1.59      |
| DC 1U              | DP1A-6300F  | 300W    | DC -48V | 205/8.07       | 100/3.94       | 40.5/1.59      |
| DC 1U              | DP1H-6350F  | 350W    | DC -48V | 225/8.86       | 100/3.94       | 40.5/1.59      |
| DC 1U              | DP1H-6400F  | 400W    | DC -48V | 225/8.86       | 100/3.94       | 40.5/1.59      |
| DC 2U              | DP2H-6350F  | 350W    | DC -48V | 215/8.46       | 100/3.94       | 70/2.76        |
| DC 2U              | DP2H-6400F  | 400W    | DC -48V | 215/8.46       | 100/3.94       | 70/2.76        |
| DC PS2+            | DPSM-6500F  | 500W    | DC -48V | 160/6.3        | 150/5.91       | 86/3.39        |
| DC PS2+            | DPSM-6550F  | 550W    | DC -48V | 160/6.3        | 150/5.91       | 86/3.39        |
| DC 1U Redundant    | DR1M-6221F  | 220W    | DC -48V | 260/10.24      | 180/7.09       | 40.5/1.59      |
| DC 1U Redundant    | DR1Z-6400F  | 400W    | DC -48V | 265/10.43      | 206/8.11       | 41.5/1.63      |
| DC Mini Redundant  | DMRW-6300F  | 300W    | DC -48V | 185/7.28       | 150/5.91       | 86/3.39        |
| DC Mini Redundant  | DMRW-6350F  | 350W    | DC -48V | 185/7.28       | 150/5.91       | 86/3.39        |
| DC Mini Redundant  | DMRW-6375F  | 375W    | DC -48V | 185/7.28       | 150/5.91       | 86/3.39        |
| DC Mini Redundant  | DMRW-6400F  | 400W    | DC -48V | 185/7.28       | 150/5.91       | 86/3.39        |
| DC 2U Redundant    | DMIN2-6221F | 220W    | DC -48V | 230/9.06       | 82/3.23        | 85/3.35        |
| DC 2U Redundant    | DR2Z-6400F  | 400W    | DC -48V | 265/10.43      | 101/3.98       | 84/3.31        |
| DC 2U Redundant    | DM2W-6460F  | 460W    | DC -48V | 300/11.81      | 101/3.98       | 84/3.31        |
| DC 2U Redundant    | DM2W-6500F  | 500W    | DC -48V | 300/11.81      | 101/3.98       | 84/3.31        |
| DC 2U Redundant    | DR2G-6350F  | 350W    | DC -48V | 300/11.81      | 101/3.98       | 82/3.23        |
| DC N + 1 Redundant | DM3W-6950F  | 950W    | DC -48V | 300/11.81      | 101/3.98       | 125/4.92       |
| DC N + 1 Redundant | DM4W-6D50F  | 1350W   | DC -48V | 300/11.81      | 101/3.98       | 166/6.54       |
| DC N + 1 Redundant | DR3G-6650F  | 650W    | DC -48V | 300/11.81      | 127/5          | 82/3.23        |
| DC N + 1 Redundant | DGIH3-6650F | 650W    | DC -48V | 330/12.99      | 290/11.42      | 42/1.65        |
| DC N + 1 Redundant | DGIH4-6950F | 950W    | DC -48V | 330/12.99      | 383/15.08      | 42/1.65        |
| DC N + 1 Redundant | DM1W3-6950F | 950W    | DC -48V | 330/12.99      | 383/15.08      | 42/1.65        |
| DC N + 1 Redundant | DM1W4-6D50F | 1350W   | DC -48V | 340/13.39      | 422/16.61      | 43/1.69        |

| CCC | BSMI | +5V  | +12V | +3.3V | -5V | -12V | +5VSB | +5.3VA.VB | +5V2 | +12V2 | +3.3V2 |
|-----|------|------|------|-------|-----|------|-------|-----------|------|-------|--------|
| V   |      | 50   | 32   | 28    | 1   | 1    | 3     | X         | X    | X     | X      |
| V   |      | 44   | 30   | 50    | 44  | 1.2  | 50    | X         | 3.5  | X     | X      |
| V   |      | 84.5 | 90   | 67.5  | 1.2 | 1.2  | 3.5   | X         | X    | X     | X      |
| V   |      | 18   | 6    | 10    | 0.5 | 18   | 6     | X         | X    | X     | X      |
| V   |      | 35   | 22   | 20    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 24   | 16   | 20    | 0.5 | 0.5  | 2.5   | X         | X    | X     | X      |
| V   |      | 24   | 20   | 20    | 0.5 | 0.5  | 2.5   | X         | X    | X     | X      |
| V   |      | 35   | 22   | 20    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 35   | 28   | 20    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 35   | 22   | 20    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 35   | 22   | 20    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
|     |      | 30   | 40   | 30    | 0.8 | 0.8  | 2     | X         | X    | X     | X      |
|     | V    | 30   | 45   | 30    | 0.8 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 25   | 16   | 15    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 25   | 28   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 30   | 20   | 20    | 0.5 | 1.2  | 2     | X         | X    | X     | X      |
| V   |      | 32   | 25   | 25    | 0.5 | 1.2  | 2     | X         | X    | X     | X      |
| V   |      | 32   | 25   | 25    | 0.5 | 1.2  | 2     | X         | X    | X     | X      |
| V   |      | 32   | 25   | 25    | 0.5 | 1.2  | 2     | X         | X    | X     | X      |
| V   |      | 25   | 16   | 15    | 0.5 | 0.5  | 2     | X         | X    | X     | X      |
| V   |      | 25   | 28   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 27   | 32   | 24    | 0.7 | 0.7  | 2     | X         | X    | X     | X      |
| V   |      | 27   | 32   | 24    | 0.7 | 0.7  | 2     | X         | X    | X     | X      |
| V   |      | 35   | 22   | 20    | 0.5 | 0.8  | 2     | X         | X    | X     | X      |
| V   |      | 50   | 60   | 44    | 1.2 | 1.2  | 3.5   | X         | X    | X     | X      |
| V   |      | 75   | 90   | 67.5  | 1.2 | 1.2  | 3.5   | X         | X    | X     | X      |
| V   |      | 60   | 40   | 40    | 1   | 1    | 2.5   | X         | X    | X     | X      |
| V   |      | 60   | 40   | 40    | 1   | 1    | 2.5   | X         | X    | X     | X      |
| V   |      | 90   | 60   | 54    | 1.2 | 2    | 5     | X         | X    | X     | X      |
| V   |      | 50   | 60   | 44    | 1.2 | 1.2  | 3.5   | X         | X    | X     | X      |
| V   |      | 75   | 90   | 67.5  | 1.2 | 1.2  | 3.5   | X         | X    | X     | X      |



| NEW | FORM FACTOR | MODEL NAME | WATTAGE | INPUT   | D<br>(mm/inch) | W<br>(mm/inch) |
|-----|-------------|------------|---------|---------|----------------|----------------|
|     | AC N + 1    | R1T-1120V  | 120W    | PFC     | 167 / 6.57     | 50.5 / 1.99    |
| New | AC N + 1    | R1T-1127V  | 120W    | PFC     | 167 / 6.57     | 50.5 / 1.99    |
|     | AC N + 1    | R1S-1120V  | 120W    | PFC     | 100 / 3.94     | 81.5 / 3.21    |
|     | AC N + 1    | R1U-2220V  | 220W    | PFC     | 223 / 8.78     | 50.5 / 1.99    |
|     | AC N + 1    | R1U-2200V  | 200W    | PFC     | 223 / 8.78     | 50.5 / 1.99    |
| New | AC N + 1    | M1Y-2302G  | 300W    | PFC     | 236 / 9.29     | 50.5 / 1.99    |
| New | AC N + 1    | M1Y-2302K  | 300W    | PFC     | 236 / 9.29     | 50.5 / 1.99    |
| New | AC N + 1    | M1Y-2152V  | 150W    | PFC     | 236 / 9.29     | 50.5 / 1.99    |
|     | AC 1 + 1    | R1V-2275V  | 275W    | PFC     | 236 / 9.29     | 50.5 / 1.99    |
|     | AC N + 1    | M1S-3400V  | 400W    | PFC     | 300 / 11.81    | 50.5 / 1.99    |
|     | AC N + 1    | M1S-3401V  | 400W    | PFC     | 300 / 11.81    | 50.5 / 1.99    |
|     | AC N + 1    | M1S-3500V  | 500W    | PFC     | 300 / 11.81    | 50.5 / 1.99    |
|     | AC N + 1    | M1S-3501V  | 500W    | PFC     | 300 / 11.81    | 50.5 / 1.99    |
|     | AC N + 1    | M1S-3551V  | 550W    | PFC     | 300 / 11.81    | 50.5 / 1.99    |
|     | AC N + 1    | M1S-3600G  | 600W    | PFC     | 300 / 11.81    | 50.5 / 1.99    |
| New | AC N + 1    | M1S-3602G  | 600W    | PFC     | 300 / 11.81    | 50.5 / 1.99    |
|     | AC N + 1    | M1U-2650V  | 650W    | PFC     | 300 / 11.81    | 50.5 / 1.99    |
|     | AC N + 1    | M1U-2750V  | 750W    | PFC     | 300 / 11.81    | 50.5 / 1.99    |
|     | AC N + 1    | M1U-2800V  | 800W    | PFC     | 300 / 11.81    | 50.5 / 1.99    |
|     | AC N + 1    | M1V-2800V  | 800W    | PFC     | 300 / 11.81    | 50.5 / 1.99    |
|     | AC N + 1    | M1K-2A00V  | 1000W   | PFC     | 350 / 13.78    | 50.5 / 1.99    |
| New | AC N + 1    | M1K-2A10V  | 1010W   | PFC     | 330 / 12.99    | 50.5 / 1.99    |
|     | AC N + 1    | M1K-2C00V  | 1200W   | PFC     | 350 / 13.78    | 50.5 / 1.99    |
| New | AC N + 1    | M1H-2AD0V  | 1400W   | PFC     | 373 / 14.69    | 50.5 / 1.99    |
| New | AC N + 1    | M1H-2A00V  | 1000W   | DC -48V | 350 / 13.78    | 50.5 / 1.99    |
| New | AC N + 1    | M1H-2C00V  | 1200W   | PFC     | 350 / 13.78    | 50.5 / 1.99    |
|     | AC 1 + 1    | SPH-2A00V  | 1000W   | PFC     | 335 / 13.19    | 61 / 2.4       |
|     | AC 1 + 1    | SPH-2C00V  | 1200W   | PFC     | 335 / 13.19    | 61 / 2.4       |
|     | AC N + 1    | PSS-2A00V  | 1000W   | PFC     | 310 / 12.2     | 61 / 2.4       |
|     | AC N + 1    | PSS-2C00V  | 1200W   | PFC     | 310 / 12.2     | 61 / 2.4       |
|     | AC N + 1    | PSS-2E00V  | 1400W   | PFC     | 310 / 12.2     | 61 / 2.4       |
| New | AC 1 + 1    | MRH-2930V  | 930W    | PFC     | 220 / 8.66     | 72.5 / 2.85    |
|     | AC 1 + 1    | MRH-2AD0V  | 1400W   | PFC     | 220 / 8.66     | 72.5 / 2.85    |
|     | AC N + 1    | MIN-6251P  | 250W    | PFC     | 200 / 7.87     | 79 / 3.11      |
|     | AC N + 1    | G1M-5300P  | 300W    | PFC     | 215 / 8.46     | 79 / 3.11      |
|     | AC N + 1    | GTM-5400V  | 400W    | PFC     | 215 / 8.46     | 79 / 3.11      |
|     | AC N + 1    | GHM-5400V  | 400W    | PFC     | 215 / 8.46     | 79 / 3.11      |
|     | AC N + 1    | MX1-6300P  | 300W    | PFC     | 224 / 8.82     | 79 / 3.11      |
|     | AC N + 1    | MX1-6325P  | 325W    | PFC     | 224 / 8.82     | 79 / 3.11      |
|     | AC N + 1    | GIN-5420P  | 420W    | PFC     | 250 / 9.84     | 79 / 3.11      |
|     | AC N + 1    | GIN-6350P  | 350W    | PFC     | 242 / 9.53     | 79 / 3.11      |
|     | AC N + 1    | GIN-3420V  | 420W    | PFC     | 250 / 9.84     | 79 / 3.11      |

| H<br>(mm/inch) | +5V | +12V | +3.3V | -5V | -12V | +5VSB | +5V2 |
|----------------|-----|------|-------|-----|------|-------|------|
| 40 / 1.57      | X   | 10   | X     | X   | X    | X     | X    |
| 40 / 1.57      | X   | 10   | X     | X   | X    | X     | X    |
| 40.3 / 1.59    | X   | 10   | X     | X   | X    | X     | X    |
| 40 / 1.57      | X   | 17.5 | X     | X   | X    | X     | X    |
| 40 / 1.57      | X   | 16   | X     | X   | X    | X     | X    |
| 40 / 1.57      | X   | 24   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 25   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 12   | X     | X   | X    | 2     | X    |
| 40 / 1.57      | X   | 22   | X     | X   | X    | 2.5   | X    |
| 40 / 1.57      | X   | 33   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 33   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 41   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 41   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 45   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 45   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 45   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 54   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 62   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 66   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 66   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 83   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 84   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 100  | X     | X   | X    | 4     | X    |
| 40 / 1.57      | X   | 116  | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 83   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 100  | X     | X   | X    | 3     | X    |
| 45 / 1.77      | X   | 83   | X     | X   | X    | 4     | X    |
| 45 / 1.77      | X   | 100  | X     | X   | X    | 4     | X    |
| 40.5 / 1.59    | X   | 83   | X     | X   | X    | 4     | X    |
| 40.5 / 1.59    | X   | 100  | X     | X   | X    | 4     | X    |
| 40.5 / 1.59    | X   | 125  | X     | X   | X    | 4     | X    |
| 82 / 3.23      | X   | 77.5 | X     | X   | X    | 3     | X    |
| 82 / 3.23      | X   | 116  | X     | X   | X    | 3     | X    |
| 40 / 1.57      | 25  | 16   | 15    | 0.5 | 0.5  | 2     | X    |
| 40 / 1.57      | 20  | 22   | 20    | X   | 0.8  | 3     | X    |
| 40 / 1.57      | 30  | 25   | 20    | X   | 0.8  | 3     | X    |
| 40 / 1.57      | 30  | 25   | X     | X   | 0.8  | 3     | 30   |
| 48.6 / 1.91    | 30  | 20   | 18    | 0.5 | 0.8  | 2     | X    |
| 48.6 / 1.91    | 30  | 20   | 18    | 0.5 | 0.8  | 2     | X    |
| 40.5 / 1.59    | 24  | 26   | 20    | X   | 0.8  | 3     | X    |
| 40.5 / 1.59    | 35  | 22   | 20    | 0.5 | 0.8  | 2     | X    |
| 40.5 / 1.59    | X   | 33   | X     | X   | 0.8  | 3.5   | X    |

| NEW | FORM FACTOR | MODEL NAME  | WATTAGE | INPUT | D<br>(mm/inch) | W<br>(mm/inch) |
|-----|-------------|-------------|---------|-------|----------------|----------------|
|     | AC N + 1    | GIN-3500V   | 500W    | PFC   | 250 / 9.84     | 79 / 3.11      |
|     | AC N + 1    | GIN-3600V   | 600W    | PFC   | 250 / 9.84     | 79 / 3.11      |
|     | AC N + 1    | GIN-3800V   | 800W    | PFC   | 305 / 12.01    | 79 / 3.11      |
|     | AC N + 1    | GIN-3602G   | 600W    | PFC   | 250 / 9.84     | 79 / 3.11      |
|     | AC N + 1    | GIN-2650G2  | 650W    | PFC   | 250 / 9.84     | 79 / 3.11      |
|     | AC N + 1    | ATN-5400V   | 400W    | PFC   | 265 / 10.43    | 79 / 3.11      |
|     | AC N + 1    | ATN-5500V   | 500W    | PFC   | 265 / 10.43    | 79 / 3.11      |
|     | AC N + 1    | ATN-5600V   | 600W    | PFC   | 265 / 10.43    | 79 / 3.11      |
| New | AC N + 1    | KIN-2AD2V   | 1400W   | PFC   | 305 / 12.01    | 79 / 3.11      |
|     | AC N + 1    | KIN-2800V   | 800W    | PFC   | 305 / 12.01    | 79 / 3.11      |
|     | AC N + 1    | KIN-2A00V   | 1000W   | PFC   | 305 / 12.01    | 79 / 3.11      |
|     | AC N + 1    | KIN-2C00V   | 1200W   | PFC   | 305 / 12.01    | 79 / 3.11      |
|     | AC N + 1    | KIN-2802V   | 800W    | PFC   | 305 / 12.01    | 79 / 3.11      |
|     | AC N + 1    | KIN-2A02V   | 1000W   | PFC   | 305 / 12.01    | 79 / 3.11      |
| New | AC N + 1    | KIN-2AB0K2  | 1200W   | PFC   | 305 / 12.01    | 79 / 3.11      |
| New | AC N + 1    | KIN-2AB0G2  | 1200W   | PFC   | 305 / 12.01    | 79 / 3.11      |
|     | AC N + 1    | MX1-5350P   | 350W    | PFC   | 224 / 8.82     | 81 / 3.19      |
|     | AC N + 1    | MX1-5375P   | 375W    | PFC   | 224 / 8.82     | 81 / 3.19      |
|     | AC 1 + 1    | P1S-2300V-R | 300W    | PFC   | 170 / 6.69     | 81.5 / 3.21    |
|     | AC 1 + 1    | P1S-2400V-R | 400W    | PFC   | 170 / 6.69     | 81.5 / 3.21    |
| New | AC 1 + 1    | P1S-2407V-R | 400W    | PFC   | 210 / 8.27     | 81.5 / 3.21    |
| New | AC 1 + 1    | P1S-2500V-R | 500W    | PFC   | 170 / 6.69     | 81.5 / 3.21    |
| New | AC 1 + 1    | P1S-2507V-R | 500W    | PFC   | 190 / 7.48     | 81.5 / 3.21    |
|     | AC 1 + 1    | P1S-3180V-R | 180W    | PFC   | 170 / 6.69     | 81.5 / 3.21    |
| New | AC N + 1    | M1P-2300V   | 300W    | PFC   | 180 / 7.09     | 81.5 / 3.21    |
|     | AC N + 1    | M1P-2420V   | 420W    | PFC   | 180 / 7.09     | 81.5 / 3.21    |
|     | AC N + 1    | M1P-2500V   | 500W    | PFC   | 180 / 7.09     | 81.5 / 3.21    |
| New | AC N + 1    | M1D-2500G   | 500W    | PFC   | 138.5 / 5.45   | 98.4 / 3.87    |
| New | AC N + 1    | M1D-2300V   | 300W    | PFC   | 138.5 / 5.45   | 98.4 / 3.87    |
| New | AC N + 1    | M1D-2400V   | 400W    | PFC   | 138.5 / 5.45   | 98.4 / 3.87    |
| New | AC N + 1    | M1D-2500V   | 500W    | PFC   | 138.5 / 5.45   | 98.4 / 3.87    |
| New | AC N + 1    | M1D-2600V   | 600W    | PFC   | 169 / 6.65     | 98.4 / 3.87    |
| New | AC N + 1    | M1D-2700V   | 700W    | PFC   | 169 / 6.65     | 98.4 / 3.87    |
| New | AC N + 1    | M1D-2800V   | 800W    | PFC   | 169 / 6.65     | 98.4 / 3.87    |
|     | AC 1 + 1    | R2Z-6350P-R | 350W    | PFC   | 230.3 / 9.07   | 98.4 / 3.87    |
|     | AC 1 + 1    | R2Z-6400P-R | 400W    | PFC   | 230.3 / 9.07   | 98.4 / 3.87    |
|     | AC N + 1    | M1Z-5400V   | 400W    | PFC   | 230.3 / 9.07   | 98.4 / 3.87    |
|     | AC N + 1    | M1Z-5460V   | 460W    | PFC   | 230.3 / 9.07   | 98.4 / 3.87    |
|     | AC N + 1    | M1Z-5500V   | 500W    | PFC   | 230.3 / 9.07   | 98.4 / 3.87    |
|     | AC N + 1    | M1Z-5550V   | 550W    | PFC   | 230.3 / 9.07   | 98.4 / 3.87    |
|     | AC 1 + 1    | R2W-5600P-R | 600W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC 1 + 1    | R2W-6460P-R | 460W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |

| H<br>(mm/inch) | +5V | +12V | +3.3V | -5V | -12V | +5VSB | +5V2 |
|----------------|-----|------|-------|-----|------|-------|------|
| 40.5 / 1.59    | X   | 40   | X     | X   | 0.8  | 3.5   | X    |
| 40.5 / 1.59    | X   | 48   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 65   | X     | X   | 0.8  | 3.5   | X    |
| 40.5 / 1.59    | X   | 48   | X     | X   | 0.8  | 3.5   | X    |
| 40.5 / 1.59    | X   | 54   | X     | X   | X    | 3     | X    |
| 40.5 / 1.59    | 32  | 33   | 25    | X   | 0.5  | 3.5   | X    |
| 40.5 / 1.59    | 32  | 41   | 25    | X   | 0.5  | 3.5   | X    |
| 40.5 / 1.59    | 32  | 49   | 25    | X   | 0.5  | 3.5   | X    |
| 40 / 1.57      | X   | 116  | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 65   | X     | X   | X    | 3.5   | X    |
| 40 / 1.57      | X   | 83   | X     | X   | X    | 3.5   | X    |
| 40 / 1.57      | X   | 100  | X     | X   | X    | 3.5   | X    |
| 40 / 1.57      | X   | 65   | X     | X   | X    | 3.5   | X    |
| 40 / 1.57      | X   | 83   | X     | X   | X    | 3.5   | X    |
| 40 / 1.57      | X   | 100  | X     | X   | X    | 3.5   | X    |
| 40 / 1.57      | X   | 100  | X     | X   | X    | 3.5   | X    |
| 48.6 / 1.91    | 25  | 26   | 19    | X   | 0.8  | 2.5   | X    |
| 48.6 / 1.91    | 26  | 28   | 20    | X   | 0.8  | 2.5   | X    |
| 40.3 / 1.59    | X   | 24   | X     | X   | X    | 2.5   | X    |
| 40.3 / 1.59    | X   | 33   | X     | X   | X    | 2.5   | X    |
| 40.3 / 1.59    | X   | 33   | X     | X   | X    | 2.5   | X    |
| 40.3 / 1.59    | X   | 41   | X     | X   | X    | 2.5   | X    |
| 40.3 / 1.59    | X   | 41   | X     | X   | X    | 2.5   | X    |
| 40.3 / 1.59    | X   | 14   | X     | X   | 0.3  | 2.5   | X    |
| 40.3 / 1.59    | X   | 25   | X     | X   | X    | 3.5   | X    |
| 40.3 / 1.59    | X   | 35   | X     | X   | X    | 3.5   | X    |
| 40.3 / 1.59    | X   | 41   | X     | X   | X    | 3.5   | X    |
| 40 / 1.57      | X   | 41   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 25   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 33   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 41   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 50   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 58   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 66   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | 25  | 28   | 20    | 0.5 | 0.8  | 2     | X    |
| 40 / 1.57      | 25  | 28   | 20    | 0.5 | 0.8  | 2     | X    |
| 40 / 1.57      | 24  | 32   | 24    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 24  | 36   | 24    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 24  | 40   | 24    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 24  | 45   | 24    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 32  | 42   | 24    | X   | 0.7  | 2     | X    |
| 40 / 1.57      | 30  | 32   | 24    | 0.7 | 0.7  | 2     | X    |

| NEW | FORM FACTOR | MODEL NAME  | WATTAGE | INPUT | D<br>(mm/inch) | W<br>(mm/inch) |
|-----|-------------|-------------|---------|-------|----------------|----------------|
|     | AC 1 + 1    | R2W-6500P-R | 500W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | MTW-5660V   | 660W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | MTW-5760V   | 760W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | MTW-5820V   | 820W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | MTW-5900V   | 900W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | MTW-5962V   | 960W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | MTW-5AD0V   | 1400W   | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | MTW-5AD0B2  | 1400W   | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | MHW-5960V   | 960W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | MHW-5962V   | 960W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | G1W-3660V   | 660W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | G1W-3760V   | 760W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | G1W-3762V   | 760W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | G1W-3860V   | 860W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | G1W-3862V   | 860W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | G1W-3960V   | 960W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | G1W-3962V   | 960W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | G1W-3A10V   | 1010W   | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | G1W-3A12V   | 1010W   | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | G1W-3C00V   | 1200W   | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | G1W-3C02V   | 1200W   | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | G1W-3AE2G   | 1500W   | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | T1W-3A12V   | 1010W   | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-6460P   | 460W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-6500P   | 500W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-6550P   | 550W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-3500V   | 500W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-3600V   | 600W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | G2W-3662V-R | 660W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-2600G   | 600W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | M1W-2650G   | 650W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | M1W-2700G   | 700W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-2700K   | 700W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-2810V   | 810W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-2910V   | 910W    | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-2A10V   | 1010W   | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-2C00V   | 1200W   | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
|     | AC N + 1    | M1W-2E00V   | 1400W   | PFC   | 265.3 / 10.44  | 98.4 / 3.87    |
| New | AC N + 1    | M1W-2AG0V   | 1700W   | PFC   | 285.3 / 11.23  | 98.4 / 3.87    |
|     | AC N + 1    | S1L-2C00V   | 1200W   | PFC   | 279.4 / 11     | 98.4 / 3.87    |
|     | AC N + 1    | S1M-5350P   | 350W    | PFC   | 247.9 / 9.76   | 106 / 4.17     |
|     | AC N + 1    | S1M-5460P   | 460W    | PFC   | 247.9 / 9.76   | 106 / 4.17     |

| H<br>(mm/inch) | +5V | +12V | +3.3V | -5V | -12V | +5VSB | +5V2 |
|----------------|-----|------|-------|-----|------|-------|------|
| 40 / 1.57      | 30  | 32   | 24    | 0.7 | 0.7  | 2     | X    |
| 40 / 1.57      | 32  | 50   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 32  | 62   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 32  | 67   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 32  | 72   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 32  | 77   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 50  | 100  | 12    | X   | 0.8  | 3     | X    |
| 40 / 1.57      | 50  | 100  | 12    | X   | 0.5  | 3     | X    |
| 40 / 1.57      | 32  | 77   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 32  | 77   | X     | X   | 0.8  | 3.5   | 32   |
| 40 / 1.57      | X   | 55   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 62   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 62   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 70   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 70   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 78   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 78   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 83   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 83   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 98   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 98   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 125  | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 83   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 30  | 32   | 24    | 0.7 | 0.7  | 20    | X    |
| 40 / 1.57      | 30  | 32   | 24    | 0.7 | 0.7  | 20    | X    |
| 40 / 1.57      | 30  | 36   | 24    | 0.7 | 0.7  | 20    | X    |
| 40.5 / 1.59    | X   | 40   | X     | X   | 0.8  | 3.5   | X    |
| 40.5 / 1.59    | X   | 48   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 55   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 50   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 54   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 58   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 58   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 66   | X     | X   | X    | 4     | X    |
| 40 / 1.57      | X   | 75   | X     | X   | X    | 4     | X    |
| 40 / 1.57      | X   | 83   | X     | X   | X    | 4     | X    |
| 40 / 1.57      | X   | 100  | X     | X   | X    | 4     | X    |
| 40 / 1.57      | X   | 116  | X     | X   | X    | 4     | X    |
| 40 / 1.57      | X   | 141  | X     | X   | X    | 4     | X    |
| 40 / 1.57      | X   | 100  | X     | X   | X    | 4     | X    |
| 40 / 1.57      | 32  | 28   | 30    | X   | 1    | 2     | X    |
| 40 / 1.57      | 32  | 32   | 30    | X   | 1    | 2     | X    |



| NEW | FORM FACTOR | MODEL NAME  | WATTAGE | INPUT   | D<br>(mm/inch) | W<br>(mm/inch) |
|-----|-------------|-------------|---------|---------|----------------|----------------|
|     | AC N + 1    | S1M-5500P   | 500W    | PFC     | 247.9 / 9.76   | 106 / 4.17     |
|     | AC N + 1    | S1M-5500V   | 500W    | PFC     | 247.9 / 9.76   | 106 / 4.17     |
|     | AC N + 1    | S1M-5550V   | 550W    | PFC     | 247.9 / 9.76   | 106 / 4.17     |
| New | AC N + 1    | M1R-2300V   | 300W    | PFC     | 256.5 / 10.1   | 50.5 / 1.99    |
| New | AC N + 1    | M1R-2400V   | 400W    | PFC     | 256.5 / 10.1   | 50.5 / 1.99    |
| New | AC N + 1    | M1R-2500G   | 500W    | PFC     | 256.5 / 10.1   | 50.5 / 1.99    |
| New | AC N + 1    | M1X-3552V   | 500W    | PFC     | 205.3 / 8.08   | 98.4 / 3.87    |
|     | AC 1 + 1    | MRT-6300P-R | 300W    | PFC     | 153 / 6.02     | 120 / 4.72     |
|     | AC 1 + 1    | MRT-6320P-R | 320W    | PFC     | 153 / 6.02     | 120 / 4.72     |
|     | AC 1 + 1    | R2A-5350P-R | 350W    | PFC     | 190 / 7.48     | 117 / 4.61     |
|     | AC 1 + 1    | R2A-6300P-R | 300W    | PFC     | 190 / 7.48     | 117 / 4.61     |
|     | AC 1 + 1    | R2A-6320P-R | 550W    | PFC     | 190 / 7.48     | 117 / 4.61     |
|     | AC 1 + 1    | MRM-6550P-R | 550W    | PFC     | 220 / 8.66     | 137 / 5.39     |
|     | AC 1 + 1    | MRM-6600P-R | 600W    | PFC     | 220 / 8.66     | 137 / 5.39     |
|     | AC 1 + 1    | MRM-6650P-R | 650W    | PFC     | 220 / 8.66     | 137 / 5.39     |
|     | AC 1 + 1    | MRW-6350P-R | 350W    | PFC     | 161 / 6.34     | 143 / 5.63     |
|     | AC 1 + 1    | MRW-6400P-R | 400W    | PFC     | 161 / 6.34     | 143 / 5.63     |
|     | AC 1 + 1    | MRW-6420P-R | 420W    | PFC     | 161 / 6.34     | 143 / 5.63     |
|     | AC 1 + 1    | MRW-3450V-R | 450W    | PFC     | 161 / 6.34     | 143 / 5.63     |
|     | AC 1 + 1    | MRW-3500V-R | 500W    | PFC     | 161 / 6.34     | 143 / 5.63     |
|     | AC 1 + 1    | MRW-3600V-R | 600W    | PFC     | 161 / 6.34     | 143 / 5.63     |
|     | AC 1 + 1    | MRT-2320G-R | 320W    | PFC     | 161 / 6.34     | 143 / 5.63     |
| New | AC 1 + 1    | MRT-2450G-R | 450W    | PFC     | 161 / 6.34     | 143 / 5.63     |
|     | AC 1 + 1    | MRG-6460P-R | 460W    | PFC     | 176 / 6.93     | 143 / 5.63     |
|     | AC 1 + 1    | MRG-6500P-R | 500W    | PFC     | 176 / 6.93     | 143 / 5.63     |
|     | AC N + 1    | MPN1-5350P  | 350W    | PFC     | 160 / 6.3      | 142 / 5.59     |
|     | AC N + 1    | MPN1-5420P  | 420W    | PFC     | 160 / 6.3      | 142 / 5.59     |
|     | AC 1 + 1    | MRG-3700V-R | 700W    | PFC     | 176 / 6.93     | 143 / 5.63     |
|     | AC 1 + 1    | MRG-3800V-R | 800W    | PFC     | 176 / 6.93     | 143 / 5.63     |
|     | DC N + 1    | DR1U-2200V  | 200W    | DC -48V | 224 / 8.82     | 50.5 / 1.99    |
|     | DC N + 1    | DR1V-2250V  | 250W    | DC -48V | 236 / 9.29     | 50.5 / 1.99    |
| New | DC N + 1    | DM1R-2500V  | 500W    | DC -48V | 256.5 / 10.1   | 50.5 / 1.99    |
| New | DC N + 1    | DM1Y-2152V  | 150W    | DC -48V | 236 / 9.29     | 50.5 / 1.99    |
| New | DC N + 1    | DM1Y-2300V  | 300W    | DC -48V | 236 / 9.29     | 50.5 / 1.99    |
| New | DC N + 1    | DM1Y-2302V  | 300W    | DC -48V | 236 / 9.29     | 50.5 / 1.99    |
|     | DC N + 1    | BM1U-2500V  | 500W    | DC 28V  | 300 / 11.81    | 50.5 / 1.99    |
|     | DC N + 1    | DM1S-3400V  | 400W    | DC -48V | 300 / 11.81    | 50.5 / 1.99    |
|     | DC N + 1    | DM1S-3500V  | 500W    | DC -48V | 300 / 11.81    | 50.5 / 1.99    |
|     | DC N + 1    | DM1S-3401V  | 400W    | DC -48V | 300 / 11.81    | 50.5 / 1.99    |
|     | DC N + 1    | DM1S-3501V  | 500W    | DC -48V | 300 / 11.81    | 50.5 / 1.99    |
|     | DC N + 1    | DM1S-3551V  | 550W    | DC -48V | 300 / 11.81    | 50.5 / 1.99    |
|     | DC N + 1    | DM1U-2650V  | 650W    | DC -48V | 300 / 11.81    | 50.5 / 1.99    |

| H<br>(mm/inch) | +5V | +12V | +3.3V | -5V | -12V | +5VSB | +5V2 |
|----------------|-----|------|-------|-----|------|-------|------|
| 40 / 1.57      | 32  | 32   | 30    | X   | 1    | 2     | X    |
| 40 / 1.57      | 32  | 40   | 25    | X   | 1    | 3.5   | X    |
| 40 / 1.57      | 32  | 45   | 25    | X   | 1    | 3.5   | X    |
| 40 / 1.57      | X   | 25   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 33   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 41   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 45   | X     | X   | 0.8  | 3.5   | X    |
| 41.4 / 1.63    | 25  | 16   | 18    | 0.5 | 0.5  | 2     | X    |
| 41.4 / 1.63    | 25  | 16   | 18    | 0.5 | 0.5  | 2     | X    |
| 40.5 / 1.59    | 35  | 8    | 35    | X   | 0.8  | 2     | X    |
| 40.5 / 1.59    | 32  | 16   | 20    | 0.5 | 0.8  | 1.5   | X    |
| 40.5 / 1.59    | 32  | 16   | 20    | 0.5 | 0.8  | 1.5   | X    |
| 40 / 1.57      | 28  | 41   | 28    | 0.8 | 1    | 2.5   | X    |
| 40 / 1.57      | 28  | 45   | 28    | 0.8 | 1    | 3.5   | X    |
| 40 / 1.57      | 30  | 48   | 28    | 0.8 | 1    | 3.5   | X    |
| 41.4 / 1.63    | 35  | 22   | 25    | 0.5 | 1.2  | 2     | X    |
| 41.4 / 1.63    | 35  | 28   | 25    | 0.5 | 1.2  | 2     | X    |
| 41.4 / 1.63    | 35  | 28   | 25    | 0.5 | 1.2  | 2     | X    |
| 41.4 / 1.63    | X   | 37   | X     | X   | 0.8  | 3.5   | X    |
| 41.4 / 1.63    | X   | 41   | X     | X   | 0.8  | 3.5   | X    |
| 41.4 / 1.63    | X   | 49   | X     | X   | 0.8  | 3.5   | X    |
| 41.4 / 1.63    | X   | 26   | X     | X   | X    | 3     | X    |
| 41.4 / 1.63    | X   | 37   | X     | X   | X    | 3     | X    |
| 41.4 / 1.63    | 35  | 32   | 25    | 0.8 | 1    | 2.5   | X    |
| 41.4 / 1.63    | 35  | 32   | 25    | 0.8 | 1    | 2.5   | X    |
| 42 / 1.65      | 25  | 26   | 22    | X   | 0.8  | 3     | X    |
| 42 / 1.65      | 25  | 26   | 22    | X   | 0.8  | 3     | X    |
| 41.4 / 1.63    | X   | 57   | X     | X   | 0.8  | 3.5   | X    |
| 41.4 / 1.63    | X   | 65   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 16   | X     | X   | X    | 2     | X    |
| 40 / 1.57      | X   | 20   | X     | X   | X    | 2.5   | X    |
| 40 / 1.57      | X   | 41   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 12   | X     | X   | X    | 2     | X    |
| 40 / 1.57      | X   | 25   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 24   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 41   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 33   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 41   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 33   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 41   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 45   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 54   | X     | X   | X    | 3     | X    |



| NEW | FORM FACTOR       | MODEL NAME   | WATTAGE | INPUT   | D<br>(mm/inch) | W<br>(mm/inch) |
|-----|-------------------|--------------|---------|---------|----------------|----------------|
|     | DC N + 1          | DM1U-2750V   | 750W    | DC -48V | 300 / 11.81    | 50.5 / 1.99    |
| New | DC N + 1          | DM1H-2A00V   | 1000W   | DC -48V | 350 / 13.78    | 50.5 / 1.99    |
|     | DC N + 1          | DPSS-2A00V   | 1000W   | DC -48V | 310 / 12.2     | 61 / 2.4       |
|     | DC N + 1          | BGIN-3420V   | 420W    | DC 24V  | 250 / 9.84     | 79 / 3.11      |
|     | DC N + 1          | BGIN-3460V   | 460W    | DC 24V  | 250 / 9.84     | 79 / 3.11      |
|     | DC N + 1          | DMIN-6221F   | 220W    | DC -48V | 200 / 7.87     | 79 / 3.11      |
|     | DC N + 1          | DGIN-6350F   | 350W    | DC -48V | 250 / 9.84     | 79 / 3.11      |
|     | DC N + 1          | DGIN-3500V   | 500W    | DC 24V  | 250 / 9.84     | 79 / 3.11      |
|     | DC N + 1          | DGIN-3600V   | 600W    | DC 24V  | 250 / 9.84     | 79 / 3.11      |
|     | DC N + 1          | DGIN-3800V   | 800W    | DC -48V | 305 / 12.01    | 79 / 3.11      |
|     | DC N + 1          | DP1S-2300V-R | 300W    | DC -48V | 170 / 6.69     | 81.5 / 3.21    |
|     | DC N + 1          | DP1S-2400V-R | 400W    | DC -48V | 170 / 6.69     | 81.5 / 3.21    |
|     | DC N + 1          | BM1P-2250V   | 250W    | DC 24V  | 180 / 7.09     | 81.5 / 3.21    |
|     | DC N + 1          | DM1P-2500V   | 500W    | DC -48V | 180 / 7.09     | 81.5 / 3.21    |
|     | DC N + 1          | BM1Z-5360V   | 360W    | DC 24V  | 230 / 9.06     | 98.4 / 3.87    |
|     | DC N + 1          | DM1Z-5500V   | 500W    | DC -48V | 230 / 9.06     | 98.4 / 3.87    |
|     | DC N + 1          | DM1Z-5550V   | 550W    | DC -48V | 230 / 9.06     | 98.4 / 3.87    |
|     | DC N + 1          | BG1W-3600V   | 600W    | DC 24V  | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DG1W-3660V   | 660W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DG1W-3760V   | 760W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DG1W-3860V   | 860W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DG1W-3960V   | 960W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DG1W-3A10V   | 860W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DM1W-6460F   | 460W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DM1W-6500F   | 500W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DM1W-5600V   | 600W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DM1W-5650V   | 650W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DM1W-5700V   | 700W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DMTW-5660V   | 660W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DMTW-5820V   | 820W    | DC -48V | 265.3 / 10.44  | 98.4 / 3.87    |
|     | DC N + 1          | DM1L-5600V   | 600W    | DC -48V | 295.3 / 11.63  | 98.4 / 3.87    |
|     | DC N + 1          | DM1L-5650V   | 650W    | DC -48V | 295.3 / 11.63  | 98.4 / 3.87    |
|     | DC N + 1          | DM1L-5700V   | 700W    | DC -48V | 295.3 / 11.63  | 98.4 / 3.87    |
|     | DC 1+1            | DR2Z-6400F-R | 400W    | DC -48V | 230.3 / 9.07   | 98.4 / 3.87    |
|     | DC Mini Redundant | BMRW-3360V-R | 360W    | DC 24V  | 161 / 6.34     | 143 / 5.63     |
|     | DC 1+1            | DMRW-6350F-R | 350W    | DC -48V | 161 / 6.34     | 143 / 5.63     |
|     | DC 1+1            | DMRW-6375F-R | 375W    | DC -48V | 161 / 6.34     | 143 / 5.63     |
|     | DC 1+1            | DMRW-6400F-R | 400W    | DC -48V | 161 / 6.34     | 143 / 5.63     |
|     | DC 1+1            | DMRW-3500V-R | 500W    | DC -48V | 161 / 6.34     | 143 / 5.63     |
|     | DC 1+1            | DMRW-3600V-R | 600W    | DC -48V | 161 / 6.34     | 143 / 5.63     |

| H<br>(mm/inch) | +5V | +12V | +3.3V | -5V | -12V | +5VSB | +5V2 |
|----------------|-----|------|-------|-----|------|-------|------|
| 40 / 1.57      | X   | 62   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 83   | X     | X   | X    | 3     | X    |
| 40 / 1.57      | X   | 83   | X     | X   | X    | 3     | X    |
| 40.5 / 1.59    | X   | 33   | X     | X   | 0.8  | 3.5   | X    |
| 40.5 / 1.59    | X   | 37   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 25  | 16   | 15    | 0.5 | 0.5  | 2     | X    |
| 40.5 / 1.59    | 35  | 22   | 20    | 0.5 | 0.8  | 2     | X    |
| 40.5 / 1.59    | X   | 40   | X     | X   | 0.8  | 3.5   | X    |
| 40.5 / 1.59    | X   | 48   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 65   | X     | X   | 0.8  | 3.5   | X    |
| 40.3 / 1.59    | X   | 24   | X     | X   | X    | 2.5   | X    |
| 40.3 / 1.59    | X   | 33   | X     | X   | X    | 2.5   | X    |
| 40.3 / 1.59    | X   | 20   | X     | X   | X    | 3.5   | X    |
| 40.3 / 1.59    | X   | 41   | X     | X   | X    | 3.5   | X    |
| 40 / 1.57      | 24  | 28   | 24    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 24  | 40   | 24    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 24  | 45   | 24    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 50   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 55   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 62   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 70   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 78   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | X   | 83   | X     | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 27  | 32   | 24    | 0.7 | 0.7  | 2     | X    |
| 40 / 1.57      | 27  | 32   | 24    | 0.7 | 0.7  | 2     | X    |
| 40 / 1.57      | 32  | 45   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 32  | 50   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 32  | 55   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 32  | 50   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 32  | 50   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 32  | 67   | 36    | X   | 0.8  | 3.5   | X    |
| 40.5 / 1.59    | 32  | 45   | 36    | X   | 0.8  | 3.5   | X    |
| 40.5 / 1.59    | 32  | 50   | 36    | X   | 0.8  | 3.5   | X    |
| 40.5 / 1.59    | 32  | 55   | 36    | X   | 0.8  | 3.5   | X    |
| 40 / 1.57      | 25  | 28   | 20    | 0.5 | 0.8  | 2     | X    |
| 41.4 / 1.63    | X   | 28   | X     | X   | 0.8  | 3.5   | X    |
| 41.4 / 1.63    | 32  | 25   | 25    | 0.5 | 1.2  | 2     | X    |
| 41.4 / 1.63    | 32  | 25   | 25    | 0.5 | 1.2  | 2     | X    |
| 41.4 / 1.63    | 32  | 25   | 25    | 0.5 | 1.2  | 2     | X    |
| 41.4 / 1.63    | X   | 41   | X     | X   | 0.8  | 3.5   | X    |
| 41.4 / 1.63    | X   | 45   | X     | X   | 0.8  | 3.5   | X    |

MEMO

MEMO

MEMO

MEMO

MEMO